C53

14K733

K36
Low beam relay



F04018

Pin	Circuit	Circuit Function
1	29S-LE19 (OG/BU)	Voltage supplied at all times (overload protected), switched
2	31-LE19 (BK)	Ground
3	30-LE20 (RD)	Voltage supplied at all times (not overload protected)
5	30S-LE20 (RD/OG)	Voltage supplied at all times (not overload protected), switched

C54

14K733

K37
High beam relay



F04018

Pin	Circuit	Circuit Function
1	29S-LE12 (OG/YE)	Voltage supplied at all times (overload protected), switched
2	31-LE12 (BK) + 31-LE19 (BK)	Ground
3	30-LE13 (RD)	Voltage supplied at all times (not overload protected)
5	30S-LE13 (RD/BU)	Voltage supplied at all times (not overload protected), switched

C56

K1
Rear window defrost relay



F05018

C57

K47
Courtesy lamp relay



F04018