


Jawaban Tugas Normalisasi:

1. $R(A, B, C)$

$AB \rightarrow C$

$C \rightarrow A$

FD Diagram:



Key: AB, BC

NKA: -

$\therefore$ 3NF


2. $R(A, B, C, D)$

$A \rightarrow C$

$C \rightarrow A$

$AB \rightarrow D$

FD Diagram:



Key: AB, BC

NKA: D
FFD


$\therefore$ 3NF

3. $R(A, B, C, D, E)$

$BD \rightarrow AE$

$AB \rightarrow C$

FD Diagram:



Key: BD

NKA: A, C, E
FFD FFD FFD
tdk lgsg

$\therefore$ 2NF


4. $R(S, T, U, V, W)$

$SU \rightarrow T$

$ST \rightarrow UV$

$UV \rightarrow W$

FD Diagram:



Key: SU, ST

NKA: V, W
FFD, FFD
tdk lgsg

$\therefore$ 2NF

5. $R(A, B, C, D, E, F, G)$


$ABC \rightarrow DE$

$DE \rightarrow CF$

$F \rightarrow EG$

$G \rightarrow F$

FD Diagram:



Key: ABC, ABDE, ABDF,

ABDE

NKA: -

$\therefore$ 3NF

6. $R(A, B, C, D, S, T, U, V)$

$S \rightarrow T$

$DT \rightarrow V$

$T \rightarrow S$

$V \rightarrow U$


$D \rightarrow B$

$U \rightarrow V$

$B \rightarrow A$

$A \rightarrow C$

FD Diagram:



Key: DS, DT

NKA: A, B, C, U, V
FFD FFD

$\therefore$ 1NF