

Boolean Algebra Reference

Axioms of Boolean Algebra*

- 1a. $0 \cdot 0 = 0$
 1b. $1 + 1 = 1$
 2a. $1 \cdot 1 = 1$
 2b. $0 + 0 = 0$
 3a. $0 \cdot 1 = 1 \cdot 0 = 0$
 3b. $1 + 0 = 0 + 1 = 1$
 4a. If $x = 0$, then $\bar{x} = 1$
 4b. If $x = 1$, then $\bar{x} = 0$

Single-Variable Theorems

- 5a. $x \cdot 0 = 0$
 5b. $x + 1 = 1$
 6a. $x \cdot 1 = x$
 6b. $x + 0 = x$
 7a. $x \cdot x = x$
 7b. $x + x = x$
 8a. $x \cdot \bar{x} = 0$
 8b. $x + \bar{x} = 1$
 9. $\bar{\bar{x}} = x$

Two- and Three-Variable Properties

- 10a. $x \cdot y = y \cdot x$ *Commutative*
 10b. $x + y = y + x$
 11a. $x \cdot (y \cdot z) = (x \cdot y) \cdot z$ *Associative*
 11b. $x + (y + z) = (x + y) + z$
 12a. $x \cdot (y + z) = x \cdot y + x \cdot z$ *Distributive*
 12b. $x + y \cdot z = (x + y) \cdot (x + z)$
 13a. $x + x \cdot y = x$ *Absorption*
 13b. $x \cdot (x + y) = x$
 14a. $x \cdot y + x \cdot \bar{y} = x$ *Combining*
 14b. $(x + y) \cdot (x + \bar{y}) = x$
 15a. $\overline{x \cdot y} = \bar{x} + \bar{y}$ *DeMorgan's theorem*
 15b. $\overline{x + y} = \bar{x} \cdot \bar{y}$
 16a. $x + \bar{x} \cdot y = x + y$
 16b. $x \cdot (\bar{x} + y) = x \cdot y$
 17a. $x \cdot y + y \cdot z + \bar{x} \cdot z = x \cdot y + \bar{x} \cdot z$ *Consensus*
 17b. $(x + y) \cdot (y + z) \cdot (\bar{x} + z) = (x + y) \cdot (\bar{x} + z)$

* Information copied from Brown, S. & Vranesic, Z. (2008). *Fundamentals of Digital Logic with Verilog Design*, 2nd ed. Boston: McGraw-Hill, pp. 29-31.