

1) $BE = X + Y'$

X	Y	Y'	BE
0	0	1	1
0	1	0	0
1	0	1	1
1	1	0	1

2) $BE = X Y + Z$

X	Y	Z	X Y	BE
0	0	0	0	0
0	0	1	0	1
0	1	0	0	0
0	1	1	0	1
1	0	0	0	0
1	0	1	0	1
1	1	0	1	1
1	1	1	1	1

3) $BE = X Y Z + X Y Z'$

X	Y	Z	Z'	X Y Z	X Y Z'	BE
0	0	0	1	0	0	0
0	0	1	0	0	0	0
0	1	0	1	0	0	0
0	1	1	0	0	0	0
1	0	0	1	0	0	0
1	0	1	0	0	0	0
1	1	0	1	0	1	1
1	1	1	0	1	0	1