


## **Interface Description**



DC 5V-12V power input 5V power output 3.3V power output (multiple modules can be cascaded for power supply)

nterface type	Pin name	Pin description	Interface type	Pin name	Pin description
MCU/host interface	E1A	Motor 1 Hall signal A	Motor port	AO1	Motor 1 power supply+
	E1B	Motor 1 Hall signal B		AO2	Motor 1 power supply-
	E2A	Motor 2 Hall signal A		GND	GND
	E2B	Motor 2 Hall signal B		3V3	Motor 1 Hall power supply
	ADC	Collect VM input voltage		E1B	Motor 1 Hall signal B
	5V	Output 5V3A power supply		E1A	Motor 1 Hall signal A
	GND	GND		B01	Motor 2 power supply+
	3V3	Output 3.3V voltage		BO2	Motor 2 power supply-
	AIN1	Motor 1 drive signal 1		GND	GND
	AIN2	Motor 1 drive signal 2		3V3	Motor 2 Hall power supply
	BIN1	Motor 2 drive signal 1		E2B	Motor 2 Hall signal B
	BIN2	Motor 2 drive signal 2		E2A	Motor 2 Hall signal A

