ZX48essentials - Bill of Materials

Reference	Quantity	Value	Type/Description
Resistors			
R24,R37,R73	3	1K	0.25W, P=12.7mm
R25	1	180R	0.25W, P=12.7mm
R26,R27	2	470R	0.25W, P=12.7mm
R28,R29,R30,R35	4	10K	0.25W, P=12.7mm
R31	1	220K	0.25W, P=12.7mm
R32	1	100R	0.25W, P=12.7mm
R33,R36	2	680R	0.25W, P=12.7mm
R41	1	15R	0.5W or more, P=20.3mm
R201	1	220R	0.25W, P=12.7mm
R202,R203	2	620R	0.25W, P=12.7mm
Resistor networks			
R1-R8	2	4 x 470R	8-pin, parallel topology
R9-R16	1	8 x 8K2	9-pin, star topology
R17-R23	2	4 x 330R	8-pin, parallel topology
R65-R69	1	5 x 10K	6-pin, star topology
Capacitors			
C26,C29,C30,C41	4	47nF	ceramic, axial or disc, P=12.7mm
C27	1	1uF	electrolytic, axial P=20mm or radial P=2.0mm
C28	1	22uF	electrolytic, axial P=20mm or radial P=2.0mm
C31,C32,C75	3	100nF	ceramic, axial or disc, P=12.7mm
C35	1	10nF	ceramic, axial or disc, P=12.7mm
C67	1	100pF	ceramic, axial or disc, P=12.7mm
C73	1	16pF	ceramic, axial or disc, P=12.7mm
C201,C202,C203,C204	4	100nF	ceramic, P=2.5mm, unmarked near U201-U204
Diodes			
D1-D8,D9-10	10	1N4148	
D201	1	DF02M	rectifier brigde
Transistors			
TR3,TR6	2	ZTX313	
TR7	1	ZTX450	
Integrated circuits			
IC1	1	vLA82S+	vRetroDesign
IC2	1	Z80 CPU	
IC3,IC4	2	74LS157	
IC5	1	W27C512	EEPROM
IC23	1	74LS32	
U201,U202	2	HM62256	
U203	1	74LS574	
U204	1	74LS04	
Connectors			
J1	1	DC 5.5/2.1	power jack
J2	1	5-pin FFC/FPC	keyboard KB1
J3	1	8-pin FFC/FPC	keyboard KB2
J4,J5	2	PJ-307	MIC,EAR
J201	1	Mini-DIN-8	socket
J202	1	8-pin JST-SH1.0	socket horizontal
Other components			
Speaker	1	40R	ZX Spectrum speaker
Quartz	1	14.00MHz	HC-49-S
Regulator	1	2450	Traco TSR-1 or similar