USAF ACADEMY
DEPARTMENT OF ELECTRICAL AND COMPUTER ENGINEERING
LESSON 14 LAB - HD RADIO
Lab Packet
Spring 2027

Name: _____ **Section:** _____ **Date:** _____

Learning Objective 6.3: I can describe how HD Radio works and demodulate an HD Radio signal.

This packet is the L14 Lab, in three parts, and you turn it in once, complete, before Lesson 15. Do **Part 1** on your own before the lab period: run the sideband finder and make the predictions you will use at the bench. **Part 2** is your own measurements, recorded in class on your own laptop with your RTL-SDR. Do **Part 3** on your own after the lab: compare the measurements with the rules and answer the analysis questions.

Grading. One submission, graded against Objective 6.3 on the course's 1 / 0 scale, with revision allowed under course policy. Paste screenshots where a question asks for one.

Transmitting. Nothing in this lab transmits. The RTL-SDR receives only, and both captures came from GNU Radio flowgraphs, not from an antenna.

The flowgraphs are on the L14 lesson page, `L14-hd-test-tx.grc` and `L14-hd-find.grc`, and the capture `L14-lab-capture.cu8` will be posted on the L14 Lab page before the lab. Both captures are simulated: unsigned 8-bit I and Q at 1,488,375 samples per second, the format the RTL-SDR and nrsc5 record. Every number below uses the hybrid values from the lesson: subcarrier spacing $\Delta f = 1{,}488{,}375/4096 = 363.37$ Hz, sidebands from subcarrier 356 to 546 on each side, partitions of 19 subcarriers, and an extended hybrid station adding one, two, or four partitions inside subcarrier 356 on each side.

Part 1: Pre-Lab (individual, before the lab period)

1. **Run the sideband finder.** Put both L14 flowgraphs in one folder. Run `L14-hd-test-tx.grc` once, then open and run `L14-hd-find.grc`.

   (a) After about 5 s, record the two meter readings.

   upper [ ]

   lower [ ]

   (b) Paste a screenshot of the running flowgraph's window.

2. Block settings. You will use each of these at the bench.

(a) The sideband meter takes its band from the Variables `inner` and `outer`, in subcarrier numbers. A station adds one, two, or four partitions of 19 subcarriers inside subcarrier 356 on each side. What value of `inner` covers each?

Added partitions	1	2	4
`inner`			

(b) nrsc5 also records complex float files at 744,187.5 samples per second. What FFT size in the frequency sink makes each bin exactly one 363.4 Hz subcarrier at that rate?

Part 2: Measurements (in class)

3. **Build the sideband meter.** Start GRC with an empty canvas. Do not open `L14-hd-find.grc`: build the meter yourself as the lab page lists.

   (a) Paste a screenshot of your flowgraph on the GRC canvas. Every connection must be black, not red.

   (b) Run it on `L14-hd-test.cu8` and record both readings. Paste a screenshot of the running window.

   upper

   lower

4. Identify the lab capture. Run your meter on `L14-lab-capture.cu8`, as the lab page lists. Treat the center as 100.3 MHz.

(a) Zoom in on each sideband's edges with an FFT of 8192 points, read them, convert each to a subcarrier number, and name the configuration.

	Lower outer	Lower inner	Upper inner	Upper outer
Edge (MHz)				
Subcarrier				

(b) Record both meter readings with `inner` at 356 and with `inner` set to the inner edge you found.

`inner`	Upper (dBc)	Lower (dBc)
356		
your inner edge		

(c) Which sideband is stronger, and by how many dB? What does that tell you about the station?

difference

(d) Find the other station in the capture, give its offset from the center, and say whether it carries HD Radio. How can you tell?

5. A live station. Add the RTL-SDR Source to your meter and find a local station with HD Radio, as the lab page lists.

(a) Paste a screenshot with the shelves visible, and record the station, the RF gain, and the height of the shelves above the floor.

(b) Record the inner and outer edges, the subcarrier numbers, and the configuration.

(c) Record both meter readings. Then lower the gain in steps and record what happens to the shelves and the readings as the floor rises toward them.

upper

lower

6. Decode it. Decode the same station with nrsc5, as the lab page lists. These steps are documented usage from the nrsc5 README; we have not yet tested them in this course.

(a) Record the station name, the title and artist of what is playing, and the programs the station carries.

(b) Lower the gain until the audio stops. At what gain does it stop, and how high do the shelves stand above the floor at that gain in your meter?

(c) Record 10 s with `nrsc5 -w`, open the recording in your meter, and record both readings. Do they match Question 5(c)?

upper

lower

Part 3: Writeup (individual, after the lab)

7. Analysis.

(a) Compare the live station with the lesson's test file: where its shelves sit, how high they stand, and whether the two sides match. What does each difference tell you about how the station runs its HD Radio signal?

(b) Explain how the lab capture's edges and meter readings identified its configuration, and give one reason a station would choose each feature you found.

(c) nrsc5 cannot decode `L14-hd-test.cu8`, although its sidebands have the right subcarriers, spacing, and guard. Name two things nrsc5 needs from a signal that the test file does not provide.

Documentation: _____