Learning Objective 6.3: I can describe how HD Radio works and demodulate an HD Radio signal.

Show your work. Write a **Documentation** line at the end (**None** if you did not collaborate). From the lesson: a hybrid station's sidebands run from 129.4 to 198.4 kHz on each side of its center, subcarriers 356 to 546, spaced 363.4 Hz apart.

1. **Reading the display.** You tune `L14-hd-find.grc` to a station at 98.5 MHz.

   (a) Between which two frequencies, in MHz, should the upper sideband appear on the frequency sink? The lower sideband?

   Upper: $98.5 + 0.1294 = 98.6294$ MHz to $98.5 + 0.1984 = 98.6984$ MHz. Lower: 98.3016 to 98.3706 MHz.

   upper: 98.6294 to 98.6984

   lower: 98.3016 to 98.3706

   (b) On the waterfall, the station at 98.5 MHz shows a rounded band whose width changes from moment to moment, and two straight bands of constant width on either side. Which is the analog host, and which are the HD Radio sidebands? What makes each look the way it does?

   The rounded band of changing width is the analog FM host: its width follows the audio, because louder audio swings the frequency farther. The straight bands are the sidebands: every subcarrier carries the same power all the time and the subcarriers stop at fixed numbers, so the shelves are flat, sharp-edged, and constant in width.

   (c) A second station shows shelves that start much closer to its host, about 102 kHz out, and end at 198.4 kHz. A third shows a rounded host and nothing beside it. Name the mode of each.

   The second is extended hybrid: it has added partitions on the inside edge of each sideband. The third is an analog-only station with no HD Radio.

2. **Setting the OFDM blocks.** You adapt `L14-hd-test-tx.grc`, which runs at 1,488,375 samples per second with `fft_len` = 4096 and `cp_len` = 224, to a different sample rate.

   (a) At 2,976,750 samples per second, what `fft_len` keeps each FFT bin one 363.4 Hz subcarrier, and what `cp_len` keeps the guard the same length in time?

   The rate doubles, so both double:

   $$\texttt{fft_len} = 2{,}976{,}750/363.4 = 8192$$
   $$\texttt{cp_len} = 2 \times 224 = 448$$

`fft_len`	8192
`cp_len`	448

   (b) The OFDM Carrier Allocator's occupied carriers for the upper sideband are `list(range(356, 547))`. To build an extended hybrid station, which number do you change, in which direction, and what changes on the frequency sink?

   Lower the first number, 356, by 19 for each added partition, and change the lower sideband's list to match. On the frequency sink each shelf grows toward the host, while its outer edge stays at 198.4 kHz.

   (c) You set the OFDM Cyclic Prefixer's rolloff from 112 to 0. What do you expect to see at the edges of the shelves, and why does it matter to a neighboring station?

   The rolloff smooths the change from one symbol to the next. Without it, each symbol starts and stops abruptly, which spreads power outside the sideband, so the shelves' edges slope down slowly instead of dropping sharply. That spread power lands in the neighboring channel.

3. **Setting the meter.** The sideband meter in `L14-hd-find.grc` uses a Frequency Xlating FFT Filter, Complex to Mag^2, a Moving Average of `avg_len` samples (0.2 s), Keep 1 in N, and Log10 for each band.

   (a) You shorten the Moving Average to 0.02 s. What changes in the readings, and what stays the same?

   The readings jump around more from one update to the next, because each one averages fewer samples of a noise-like signal. Their average value stays the same.

   (b) You type `sb_center` into the lower sideband's filter instead of `-sb_center`. What do the two readings show?

   Both meters then measure the upper sideband, so both read the upper sideband's level, and the lower sideband is not measured at all.

   (c) On an extended hybrid station, you leave `inner` at 356. Does the meter read high or low, and what setting fixes it?

   Low: the filter leaves out the added partitions inside 356. Setting `inner` to the inner edge you see on the display includes them.

4. **What noise does.** In `L14-hd-test-tx.grc` you raise the Variable `noise_amp`, run it again, and play the new file in the sideband finder.

   (a) Describe what happens to the floor, the shelves, and the host on the frequency sink as `noise_amp` goes up.

   The floor rises. The host stays well above it, but the shelves, which are much weaker, sink toward the floor; their edges blur, and eventually the shelves disappear into it.

   (b) What happens to the two meter readings, and why?

   They read higher than the level the sidebands were built with. Each meter measures all the power in its band, and the noise in that band adds to the sideband's power, so the reading rises as the floor comes up to the shelves.

   (c) On a real station, what would you expect nrsc5, and a car radio, to do as the shelves sink into the floor?

   nrsc5 would report errors and then lose the digital audio, which stops abruptly rather than getting gradually noisier. A car radio would blend back to the analog program, which is still well above the noise.