**Learning Objective 3.3:** I can implement an FM receiver in GNU Radio, demodulate a live broadcast FM signal, and decode its RDS data.

**Learning Objective 3.4:** I can explain and demonstrate the trade-off between bandwidth and noise performance for AM vs. FM.

Show your work. Write a **Documentation** line at the end (**None** if you did not collaborate).

1. **FM bandwidth.** Carson's rule, a rule of thumb for setting a channel filter, puts the width of an FM signal with peak deviation $\Delta f$ and audio bandwidth $W$ at about

$$B \approx 2(\Delta f + W)$$

(a) Fill in the table. For the AM row, the station sends the same audio as DSB-AM.

| Service | $\Delta f$ (kHz) | $W$ (kHz) | Bandwidth (kHz) |
|---|---|---|---|
| Broadcast FM, mono | 75 | 15 | |
| Two-way radio, NBFM | 5 | 3 | |
| AM, broadcast audio | – | 15 | |

Broadcast FM: $2(75 + 15) = 180$ kHz. NBFM: $2(5 + 3) = 16$ kHz. AM: $2W = 30$ kHz. Broadcast FM is six times as wide as AM carrying the same audio.

(b) Open the FM Explorer on the Lesson 7 page and choose the broadcast preset, 75 kHz of deviation with a 15 kHz tone. Lower the deviation to 25 kHz and describe what happens to the spectrum. Then explain in words why the broadcast signal is wider than $2\Delta f$ = 150 kHz.

At 25 kHz the lines crowd in toward the carrier and the shaded band shrinks to 80 kHz. At 75 kHz the explorer draws lines every 15 kHz out past $\pm 75$ kHz: the frequency swings at the tone's rate, and that swing adds lines beyond the peak deviation, about one tone frequency on each side.

2. **The WBFM receiver.** An RTL-SDR records 2.4 MS/s centered on 98.8 MHz, and the station we want is at 99.1 MHz. The receiver is `L07-wbfm-rx.grc`.

   (a) Find the center frequency of the Frequency Xlating FIR Filter, and the sample rate after it decimates by 10.

   $$99.1 - 98.8 = 0.3 \text{ MHz} = 300 \text{ kHz}$$

   $$\frac{2.4 \text{ MS/s}}{10} = 240 \text{ kS/s}$$

   shift = 300 kHz

   rate = 240 kS/s

   (b) A classmate decimates by 20 instead. Explain what goes wrong, using the channel filter's ±90 kHz passband and the 57 kHz RDS subcarrier.

   At 120 kS/s the flowgraph can hold only $-60$ to $+60$ kHz. The station's ±90 kHz no longer fits, so its outer parts alias into the band, and after demodulation the RDS signal, which reaches 59.4 kHz, sits at the edge of the Nyquist frequency with no room for a filter.

   (c) Find the Quadrature Demod gain that makes 75 kHz of deviation produce an output of 1, and the output when the carrier sits 30 kHz above center.

   $$\frac{240 \text{ kHz}}{2\pi \times 75 \text{ kHz}} = 0.509$$

   $$\frac{30}{75} = 0.40$$

   gain = $0.509$

   output = $0.40$

   (d) Find the decimation from the demodulator to a 48 kHz sound card, and the time constant to type into FM Deemphasis for a US station.

   $$\frac{240}{48} = 5$$

   75 $\mu$s in the US; Europe uses 50 $\mu$s.

   decimation = 5

   $\tau$ = 75 $\mu$s

   (e) Explain why the flowgraph needs no Throttle, whether it plays a file or receives from the RTL-SDR.

   The Audio Sink takes exactly 48,000 samples per second, so it paces a File Source. With the RTL-SDR, the radio's clock and the sound card's already set the pace, and a Throttle would add yet another clock and cause dropouts.

3. **RDS.** RDS sends 1187.5 bits per second on a 57 kHz subcarrier.

   (a) The RDS branch resamples to 19 kHz before Symbol Sync. Find the samples per bit that Symbol Sync is set for.

   $$\frac{19000}{1187.5} = 16$$

   16 samples

   (b) The RDS signal is BPSK, a DSB-SC signal. Name the block in `L07-rds-rx.grc` that recovers its carrier, and explain why a recovered carrier $180^\circ$ off does no harm, given the differential coding.

   The Constellation Receiver locks to the subcarrier's phase. A BPSK loop can lock at either of two phases $180^\circ$ apart, which inverts every bit. The data is differentially coded, so the Differential Decoder reads only whether each bit changed from the last, and inverting every bit leaves those changes the same.

   (c) A station's audio is clear, but the station name never appears. Explain why RDS needs a stronger signal than the audio does.

   The noise at the FM demodulator's output rises with frequency, so the 57 kHz subcarrier sees much more noise than the audio below 15 kHz, which de-emphasis also cleans up.

4. **AM and FM in the same noise.** `L07-am-vs-fm.grc` sends a 1 kHz tone as AM at $m = 1$ in a 10 kHz channel and as FM in a wider channel, with the same transmitted power and the same noise. Its Input SNR slider sets the noise, and two meters show each receiver's output SNR.

   (a) At 30 dB Input SNR and 25 kHz deviation, the meters read 29.5 dB for AM and 48.4 dB for FM. Say which output is cleaner and by about how much, and explain in words how FM wins although its wider channel lets in more noise.

   FM, by about 19 dB. The demodulator's output follows how far the frequency swings, and a 25 kHz swing is large next to the small jitter that the noise adds to a strong carrier. FM trades bandwidth for a cleaner output.

   (b) With the speaker on FM, you drag Input SNR from 30 down to 10 dB. Describe what you expect to hear, and what the FM meter does compared with the AM meter.

   The tone stays clean at first. Below about 15 dB, clicks start and get more frequent, and the FM meter falls quickly; near 10 dB it reads about the same as AM's, about 9 dB. That collapse is the point where FM breaks into clicks. AM only hisses more as the slider comes down.

   (c) You raise the deviation from 25 to 50 kHz. Say what happens to the FM meter at 30 dB, and to the Input SNR at which the clicks begin. Explain the trade in words.

   The meter at 30 dB rises, to about 53 dB. The clicks start sooner as the noise goes up, near 20 dB instead of near 15. The wider deviation needs a wider channel, which lets in more noise, so the cleaner output lasts only while the signal is strong.

   (d) Set Input SNR to 10 dB and listen to the FM output at 5, 25, and 50 kHz deviation. Say which sounds cleanest and why, in words. Then say which you would choose for a weak link to a distant receiver.

   5 kHz sounds cleanest: a steady tone under some hiss, while 25 kHz crackles with clicks and 50 kHz is mostly clicks. The narrow channel lets in the least noise, so at 5 kHz FM has not yet broken up. The wider deviations would sound cleaner on a strong link, but on a weak one the narrow deviation is the better choice.

5. **An AM receiver for ATIS.** An airport broadcasts its ATIS on 119.25 MHz. The RTL-SDR runs at 2.4 MS/s centered on 119.0 MHz, and the receiver is `L07-am-rx.grc`.

   (a) Find the Frequency Xlating FIR Filter's center frequency, and the decimation that takes it straight to a 48 kHz sound card.

   shift = 250 kHz

   $$119.25 - 119.0 = 0.25\,\text{MHz} = 250\,\text{kHz}$$

   decimation = 50

   $$\frac{2.4\,\text{MS/s}}{48\,\text{kS/s}} = 50$$

   (b) Lesson 6 detected the envelope with Abs, a low-pass filter, and a gain of $\pi/2$. Explain why Complex to Mag replaces Abs and the $\pi/2$ gain.

   After the Frequency Xlating FIR Filter, the station's carrier sits at 0 Hz, and each complex sample is the envelope times a phase factor. Its magnitude is the envelope itself, with no carrier to rectify or average away, so the receiver needs no $\pi/2$ correction. The low-pass filter stays, but it now serves only as the audio filter.

   (c) Explain why the AM receiver needs an AGC and the FM receiver does not.

   An envelope detector's output is proportional to the received amplitude, which changes with an aircraft's distance, so the AGC holds the audio level steady. The Quadrature Demod measures only how fast the phase turns, so the FM receiver's output does not depend on the signal's strength.

**Documentation:** _____