Learning Objective 3.1: I can describe DSB-AM, DSB-SC, and SSB and identify each on a spectrum.
Learning Objective 3.2: I can implement an AM modulator and demodulator in GNU Radio and verify demodulated audio against the source.

Show your work. Write a **Documentation** line at the end (**None** if you did not collaborate).

1. **Reading a spectrum.** A 1 kHz tone modulates a 100 kHz carrier.

   (a) List the frequencies of the spectral lines for DSB-AM, DSB-SC, USB, and LSB.

Signal	Lines (kHz)	Bandwidth (kHz)
DSB-AM		
DSB-SC		
USB		
LSB		

   DSB-AM: 99, 100, and 101 kHz, 2 kHz wide. DSB-SC: 99 and 101 kHz, 2 kHz wide. USB: 101 kHz only, 1 kHz of message bandwidth. LSB: 99 kHz only, 1 kHz of message bandwidth.

   (b) A spectrum display shows two lines of equal height at 14.997 and 15.003 MHz and nothing between them. Name the modulation, the carrier frequency, and the message tone.

   DSB-SC: the lines are symmetric about 15.000 MHz, so that is the carrier, and there is no carrier line. The tone is $15.003 - 15.000 = 3$ kHz.

   (c) A waterfall shows a voice signal from 7.1970 to 7.1997 MHz that comes and goes with speech, with no steady line beside it. Voice runs from 300 Hz to 3 kHz. Name the modulation and the frequency a receiver must tune to.

   SSB, because it is about 2.7 kHz wide, one-sided, and carrierless. The audio from 300 Hz to 3 kHz lies *below* the carrier, so it is LSB with the carrier at

$$7.1970 + 0.0030 = 7.1997 + 0.0003 = 7.2000 \text{ MHz}$$

   LSB below 10 MHz is the amateur convention.

2. **DSB-AM.** A transmitter sends $s(t) = [1 + m\cos(2\pi f_m t)]\cos(2\pi f_c t)$ with $m = 0.8$.

   (a) Find the amplitude of each sideband line, and its level in dB relative to the carrier.

   $$\frac{m}{2} = 0.4, \qquad 20\log_{10}(0.4) = -8.0 \text{ dB}$$

   amplitude = 0.4

   level = -8.0 dB

   (b) Find the fraction of the transmitted power in the sidebands.

   A tone has $P_x = 1/2$, so

   $$\eta = \frac{m^2/2}{1 + m^2/2} = \frac{0.32}{1.32} = 24\%$$

   24%

   (c) A station carries audio up to 5 kHz. Find its bandwidth.

   $$2W = 2 \times 5 = 10 \text{ kHz}$$

   10 kHz

   (d) The operator raises m to 1.2. Explain in words what an envelope detector now outputs, and why it no longer matches the message.

   At the message's troughs, $1 + 1.2\cos(2\pi f_m t)$ goes as low as -0.2. The carrier's amplitude cannot be negative, so the envelope is the absolute value, and the detector outputs $|1 + m\cos(2\pi f_m t)|$: the troughs fold back up. The audio distorts, and the new frequencies spread the signal outside its channel.

3. **The envelope detector flowgraph.** The receiver in `L06-dsb-am.grc` is Abs, then a low-pass filter, then Multiply Const. The flowgraph runs at 48 kHz with a 10 kHz carrier and a message up to 2.5 kHz.

   (a) The low-pass filter has a 3 kHz cutoff and a 1 kHz transition. Explain why that works: what must it pass, and what must it stop?

   It must pass the envelope, which holds the message up to 2.5 kHz, and stop the rectified carrier, whose lowest component is at $2f_c = 20$ kHz. A 3 kHz cutoff with a 1 kHz transition passes everything below about 2.5 kHz and stops everything above about 3.5 kHz.

   (b) Explain the Multiply Const of $\pi/2$ after the filter.

   The average of a rectified cosine is $2/\pi$ of its peak, so the filter outputs $(2/\pi)\,[1 + m\,x(t)]$. Multiplying by $\pi/2$ restores the envelope's level so we can compare it with $1 + m\,x(t)$.

   (c) The time sink shows the detector output lagging the envelope by 57 samples. Find the lag in milliseconds, and name the block that causes it.

   1.19 ms

   $$\frac{57}{48000} = 1.19\,\text{ms}$$

   The low-pass filter delays its output by half its length. The flowgraph's Delay block delays the reference by the same 57 samples so the traces line up.

   (d) The flowgraph has an Audio Sink and no Throttle. Explain why.

   The sound card takes exactly 48,000 samples per second, so the Audio Sink paces the flowgraph the way an SDR does. A Throttle would add a second clock competing with the sound card's and cause audio dropouts.

4. **Coherent and product detectors.**

(a) A DSB-SC receiver's LO is 60° out of phase with the transmitter's carrier. Find the output's amplitude relative to a matched LO, in dB.

-6.0 dB

$$\cos 60^\circ = 0.5, \qquad 20\log_{10}(0.5) = -6.0 \text{ dB}$$

(b) Explain why a DSB-SC receiver on the air needs carrier recovery, and how FM stereo provides it for its DSB-SC subcarrier.

The receiver's LO must match the carrier in frequency and phase, and DSB-SC transmits no carrier to lock to; at 90° the output vanishes. FM stereo sends a 19 kHz pilot tone, and the receiver doubles it to rebuild the 38 kHz LO in the right phase.

(c) A USB signal carries a 1 kHz tone. The product detector's LO sits 150 Hz above the carrier. Find the output tone. Repeat for LSB.

The USB tone is at $f_c + 1000$; mixing with $f_c + 150$ leaves $1000 - 150 = 850$ Hz. The LSB tone is at $f_c - 1000$, which leaves $1000 + 150 = 1150$ Hz.

USB: 850 Hz

LSB: 1150 Hz

(d) The SSB flowgraph's Delay block holds the message back $(129 - 1)/2 + 57$ samples before comparing it with the receiver's output. Find the delay and explain each term.

121 samples

$$64 + 57 = 121 \text{ samples}$$

The 129-tap Hilbert filter delays the message by 64 samples, half its length, and the receiver's low-pass filter adds 57 more.

Documentation: _____