Learning Objective 2.1: I can describe what a Software Defined Radio is, contrast it with a traditional hardware radio, and identify the SDR platforms used in this course (RTL-SDR, HackRF, PlutoSDR, ADALM-PHASER).

Learning Objective 2.2: I can identify the roles of the RF frontend, ADC/DAC, and host in an SDR signal chain and describe sample-rate, bandwidth, and dynamic-range trade-offs.

Use the course SDR table from the lesson page. Show your work. Write a **Documentation** line at the end (**None** if you did not collaborate).

1. **Choosing a radio.** The course SDRs are the RTL-SDR Blog V4 (0.5 to 1766 MHz, 2.56 MS/s, 8 bits, receive only), the HackRF One (1 to 6000 MHz, 20 MS/s, 8 bits, half duplex), the PlutoSDR (325 to 3800 MHz, 20 MHz analog bandwidth, 12 bits, full duplex), and the ADALM-PHASER (10.0 to 10.5 GHz, digitized by a PlutoSDR).

    (a) For each task, name a course SDR that can do it, and give the specification that rules out each of the others.

    (i) Receive ship AIS at 162 MHz.

    (ii) Display the whole FM broadcast band, 88 to 108 MHz, at once.

    (iii) Transmit a 915 MHz test signal into a cable and receive it at the same time.

    (iv) Find the direction of a 10.3 GHz beacon.

    (b) Explain how an SDR differs from a hardware FM radio, and why the same RTL-SDR can decode both broadcast FM and aircraft ADS-B.

2. **The mixer and I and Q.** An RTL-SDR's center frequency, its LO, is set to 433.0 MHz, and a key fob transmits at 433.92 MHz.

   (a) Find the two frequencies at the mixer output, and say which one the low-pass filter keeps.

   kept:

   removed:

   (b) With a single real mixer, a second transmitter would also come out at 0.92 MHz. Find its frequency, and explain how the SDR's I and Q outputs tell the two apart.

   (c) A superheterodyne receiver, like the ADALM-PHASER, mixes a 10.25 GHz signal to an IF of 2.2 GHz with an LO above the signal. Find the LO frequency, and the other input frequency that also mixes to 2.2 GHz.

   LO:

   other:

3. **Sample rate and data rate.** A team captures one 20 MHz Wi-Fi channel centered on 2437 MHz with a HackRF.

   (a) Find the lowest sample rate that shows the whole channel, and the band the window covers.

   rate: ____

   band: ____

   (b) GNU Radio stores each complex sample in 8 bytes. Find the data rate through the flowgraph and the size of a 10 s File Sink capture.

   rate: ____

   file: ____

   (c) The HackRF sends 8-bit I and 8-bit Q over USB. Find the USB data rate at 20 MS/s, and how many times larger the flowgraph's rate is.

   USB: ____

   ratio: ____

   (d) A teammate suggests the RTL-SDR instead. Give two separate reasons it cannot make this capture.

4. **Bits and dynamic range.** Each ADC bit adds about 6 dB of dynamic range. A strong local station reaches the ADC at -10 dBFS, and a weak station of interest is 55 dB below it.

   (a) Estimate the dynamic range of an 8-bit and a 12-bit converter, and the level of the weak station in dBFS.

   8 / 12 bits: ____

   weak: ____

   (b) The converter's own floor sits about one dynamic range below full scale. Which converter shows the weak station, and by how many dB does it clear that converter's floor?

   (c) On the 8-bit radio, how much can the gain rise before the strong station clips, and does that rise make the weak station visible? Explain.

   (d) In the L4 flowgraph, name two things on the plots that show the ADC is clipping.

Documentation: _____