Learning Objective 1.1: I can define noise figure and cascade it through a receiver chain to predict system noise performance.

Learning Objective 1.2: I can compute a link budget and predict received SNR for a specified geometry, transmitter, and antenna configuration.

Show your work. Write a **Documentation** line at the end (**None** if you did not collaborate).

1. **Decibels and the ISM bands.** A small 915 MHz telemetry radio puts out 100 mW. It connects to a 9 dBi antenna through a cable and connectors with 2 dB of loss.

   (a) Express 5 W and 0.1 μW in dBm.

   5 W = ____

   0.1 μW = ____

   (b) Find the radio's EIRP in dBm and in milliwatts.

   EIRP = ____

   EIRP = ____

   (c) Which of the course SDRs (RTL-SDR, PlutoSDR, HackRF One) can receive the 2.4 GHz ISM band, and which can transmit in it?

   (d) Explain in one or two sentences why Wi-Fi, Bluetooth, and most hobby drones all operate in the same few bands.

2. **Free-space path loss.** The 915 MHz radio of Question 1 talks to a ground station 10 km away. Both antennas have 6 dBi of gain, and the transmitter delivers 1 W to its antenna.

   (a) Find the free-space path loss at 915 MHz and 10 km.

   L_p =

   (b) Find the received power in dBm.

   P_r =

   (c) The same system moves to 2.45 GHz with the same antenna gains and twice the distance. Find the new path loss using the rules of thumb, then check it with the full expression.

   L_p =

   (d) Path loss is not absorption, yet it grows with frequency. Explain why in one or two sentences.

3. **The noise floor.** An RTL-SDR with a 6 dB noise figure receives a broadcast FM station. One FM channel occupies about 200 kHz.

   (a) Find the receiver's noise floor in one 200 kHz channel.

   N =

   (b) The station arrives at -80 dBm. Find the SNR in the channel.

   SNR =

   (c) A student leaves the receiver filter open to the full 2.4 MHz sample rate and measures the station's power against all of that noise. Find the noise floor and the SNR the student would compute.

   N =

   SNR =

   (d) Explain why the answers to (b) and (c) differ, and which one the FM demodulator experiences.

4. **Cascaded noise figure.** A ground station has a 2 dB cable run, an LNA with NF 0.8 dB and 18 dB of gain, and an SDR with NF 7 dB.

   (a) Convert each stage to a linear noise factor and gain.

   F_{cable} =

   F_{LNA} =

   (b) The cable runs from the antenna to the LNA, which sits next to the SDR. Find the system noise figure.

   NF =

   (c) The LNA moves to the antenna, ahead of the cable. Find the new system noise figure.

   NF =

   (d) Moving the LNA lowered the noise figure by 1.8 dB. Explain why the cable's loss matters so much more in front of the LNA than behind it.

5. **A GPS link budget.** A GPS satellite transmits the L1 signal at 1575.42 MHz with an EIRP of 27 dBW. A receiver on the ground sees the satellite directly overhead at 20,200 km through a 0 dBi antenna. Polarization and atmospheric losses total 2 dB. The receiver has a 2 dB noise figure and a 2 MHz bandwidth.

   (a) Find the free-space path loss and the received power in dBm.

   L_p =

   P_r =

   (b) Find the noise floor and the SNR at the receiver.

   N =

   SNR =

   (c) The receiver correlates the signal against the satellite's known 1023-chip code, which raises the SNR by $10\log_{10}(1023)$. Find the SNR after correlation.

   SNR =

   (d) A car's GPS antenna sits on the roof with 5 m of cable to the dashboard receiver. Where should the LNA go, and why? Use your answer to (b) to explain what is at stake.

Documentation: _____