

PHYSICAL ROM SOCKET LAYOUT



WIZARD OF WOR MEMORY MAP

Unmapped / Open Bus Sockets X12, X13 (Empty)	\$FFFF 8 KB \$E000
Empty RAM Sockets Sockets X23-X28 (Unused)	\$DFFF 3 KB \$D400
Static Work RAM Sockets X21, X22	\$D3FF 960 B \$D040
Protected RAM Sockets X21, X22 (Audits)	\$D03F 64 B \$D000
Foreign Language ROM Socket X11 (Empty)	\$CFFF 4 KB \$C000
Unmapped ROM Socket X8 (Empty)	\$BFFF 4 KB \$B000
High ROM Sockets X5, X6, X7	\$AFFF 12 KB \$8000
Hardware Stack Stack Area	\$7FFF 64 B \$7FC0
Viewable Screen RAM Framebuffer (\$50 stride)	\$7FBF ~16 KB \$4000
Low ROM / Magic Write Sockets X1-X4 Read: ROM Write: Magic	\$3FFF 16 KB \$0000

ROM ADDRESS MAP

Sockets X12 & X13 Unpopulated / Open Bus High Expansion	\$FFFF 8 KB \$E000
Socket X11 Unpopulated Socket Foreign Language ROM	\$CFFF 4 KB \$C000
Socket X8 Unpopulated Socket System Expansion	\$BFFF 4 KB \$B000
Sockets X5, X6 & X7 Active High ROMs (3x 2732) Logic, Speech & Sprites	\$AFFF 12 KB \$8000
Sockets X1, X2, X3 & X4 Active Low ROMs (4x 2732) Engine (R) / Magic (W)	\$3FFF 16 KB \$0000