

1.

What will be the output of the following C code?

```
#include <stdio.h>
typedef int num;
int main()
{
    num x = 15, y = 25;

    num result = 0;

    if (y % 5 != 0)
        continue;
    else
        result -= y;

    printf("%d\n", result);

    return 0;
}
```

- A. -10
- B. 0
- C. -40
- D. Compile time error

Answer:D

2.

What will be the output of the following C code?

```
#include <stdio.h>
typedef enum { OFF, ON } State;
int main()
{
    State s = ON;

    switch (s)
    {
        case 0:
            printf("Off ");
            break;
        case 1:
            printf("On ");
            break;
        default:
            printf("Unknown ");
    }
    return 0;
}
```

- A. Off
- B. On
- C. Unknown
- D. Compilation error

Answer: B

3. What will be the output of the following C code?

```
#include <stdio.h>
enum Boolean { FALSE, TRUE=0 };
int main()
{
    enum Boolean b1 = TRUE;
    enum Boolean b2 = FALSE;

    if (b1 == b2)
    {
        printf("Equal\n");
    }
    else
    {
        printf("Not Equal\n");
    }
    return 0;
}
```

- A. Equal
- B. Not Equal
- C. 0
- D. 1

Answer:A

4
What will be the output of the following C code?

```
#include <stdio.h>
int main()
{
    int x = 4;
    switch (x * 2, x/2)
    {
        case 2:
            printf("Sunbeam ");
        case 4:
            printf("Karad ");
            break;
        case 8:
            printf("Hinjewadi ");
            break;
        default:
            printf("Market Yard");
            break;
    }
    return 0;
}
```

- A. Sunbeam Karad
- B. Market Yard
- C. Sunbeam Hinjewadi
- D. Compile time Error
- E. Run time Error

Answer: A.

5. What will be the output of the following C code?

```
#include <stdio.h>
int main()
{
    int x = 0;
    switch (x)
    {
        case 0:
            printf("PG-DAC ");
        case 1:
            printf("PG-DBDA ");
        case 2:
            printf("PG-DITISS ");
        default:
            break;
            printf("PG-DMC ");
            break;
    }
    return 0;
}
```

- A. PG-DAC
- B. PG-DAC PG-DBDA
- C. PG-DAC PG-DBDA PG-DITISS
- D. PG-DAC PG-DBDA PG-DITISS PG-DMC
- E. Error

Answer:C