

ENGR 102 Summer Bridge

Day 12 Student Workbook

For Loops, Range, Counters, and Accumulators

Tuesday, July 21, 2026 • 50 points

Name		UIN		Section	
------	--	-----	--	---------	--

Boolean-operator convention. Python operators appear as **and**, **or**, and **not**. Their lowercase spelling is required in code.

Daily target

increasing independence

Build fixed-count programs that preserve loop state and exact bounds.

Allowed tools	Day 10 tools plus for, range, counters, and accumulators
Support supplied	Required inputs, required outputs, and one sample run are supplied.
You must decide	Initialization, range bounds, accumulator updates, and the placement of the threshold decision.
Scaffold level	State inventory prompted once; loop body is student-authored.

Scoring and completion standard

50 points

Evidence	Points	Secure work shows
Integrated trace	10	intermediate state, condition results, and exact output
Diagnosis and repair	10	actual, intended, cause, repair, and a boundary test when requested
Full program and tests	30	coherent executable logic, required output, and defended tests

Independence standard. You may use the supplied requirements and examples, but you must produce one connected solution. A collection of disconnected correct lines is not yet a complete program.

Begin with the trace, then use its evidence habits when you construct.

Task 1. Integrated trace**10 points**

Trace the range, the conditional counter, and the accumulator after every pass.

```
total = 0
multiple_count = 0

for number in range(2, 11, 2):
    if number % 4 == 0:
        multiple_count = multiple_count + 1
    total = total + number - multiple_count
    print(number, total, multiple_count)
```

Your task

1. List the values produced by range(2, 11, 2).
2. Create one pass ledger containing number, multiple_count after the if, and total after the update.
3. Write all printed lines in exact order.

A final answer without the requested state evidence cannot earn full trace credit.

Task 2. Diagnose and repair**10 points**

The intended program must add the integers from 1 through limit, inclusive.

```
limit = int(input())
total = 0

for number in range(1, limit):
    total = total + number

print(total)
```

Your task

1. For limit = 4, state the actual and intended totals and identify the exact cause.
2. Write the minimal repair and a boundary test that would expose the original bug.

Debugging evidence is complete only when the repair is tied to the stated defect and an expected result.

Task 3. Construct a complete program**30 points across Pages 4-5****Program specification**

- Read `sample_count` as an integer and `threshold` as a float.
- If `sample_count` is not positive, print `Invalid count` and do not ask for readings.
- Otherwise read exactly `sample_count` floating-point readings.
- Compute the total, average, and number of readings at or above threshold.
- Print total, average, and `at_or_above` on separate lines in that order.

Required planning evidence

1. Name the state that must exist before the loop and give each initial value.

Program workspace – begin the connected solution here.

Task 3 continued. Test and defend the program**included in 30 points**

Continue code if needed.

Required tests, expected results, and brief defense

--

VIP Lab Alignment

Bridge Day 12 • Contract c821cfcf7189

This page adds a current lab handoff while preserving the workbook’s independence-ramp tasks.

Why this page is here

VIP Lab Day(s): 5

Activities: 18.18, 18.20

Use deliberate range bounds and comparison state to collect multiples and preserve the smallest value.

Open these current notebook cells

Activity / stable cells	Notebook work	Evidence to carry forward
18.18 18-18-work / 18-18-transfer	Multiples In Range	Choose inclusive range bounds.
18.20 18-20-work / 18-20-transfer	Smallest Value	Initialize comparison state from real data.

Readiness check before you code

1. Write the first value, final included value, and excluded stop value for the range used in Activity 18.18. _____
- _____
2. Explain why Activity 18.20 initializes from real data instead of from zero. _____
- _____

Notebook and submission procedure

1. Work in the provided sample and transfer cells; do not delete or recreate them.
2. Run each cell and compare fresh output with the notebook’s stated result before revising.
3. Save or download the completed notebook as one .ipynb file.
4. Upload that one notebook to the matching Gradescope assignment. Do not export a .py file or create a ZIP.