

ENGR 102 Summer Bridge

Bridge Day 10 Instructor Key

Lectures 1-5 Recap, Direct Input, and Repetition Launch

Friday, July 17, 2026 • 50 points • tagged v5 successor

Name		UIN		Section	
------	--	-----	--	---------	--

Daily target and independence boundary

Connect input, state, Boolean decisions, and testing to a first complete while-loop program.

Allowed tools	input, int, float, arithmetic, comparisons, Boolean operators [[and]], [[or]], and [[not]], if/elif/else, assignment, print, and a first while loop after the quiz
Support supplied	Variable names, a floor-validity rule, the movement goal, and named boundary tests are supplied.
Student decides	The conversion, validation branch order, continuation condition, direction decision, and one-floor update.
Scaffold level	Planning frame supplied; the complete elevator loop is student-authored.

Evidence and scoring

Evidence	Points	Secure work shows
Integrated trace	14	intermediate state, condition results, exact output, and meaning
Diagnosis and repair	12	actual, intended, cause, repair, and a discriminating test
Complete program and tests	24	coherent executable logic, required output, assumptions, and defended tests

Task 1. Integrated trace - 14 points

Trace types, Boolean subexpressions, and branch order. Do not jump directly to the final line.

```
sample = "14"
offset = 5
value = int(sample) * 2 + offset
stable = 20 <= value <= 35 and value % 3 == 0

if not stable:
    status = "review"
elif value >= 30:
    status = "high"
else:
    status = "normal"

print(value, stable, status)
```

Your task

1. Compute value and identify its type. Then evaluate each side of the `[[and]]` expression used to compute stable.
2. State which branch assigns status and explain why the earlier branch does not execute.
3. Write the exact printed output, including the Boolean capitalization.

Model response:

1. `int(sample)` is 14, so value is $14 * 2 + 5 = 33$, an integer. The range check $20 \leq 33 \leq 35$ is True, and $33 \% 3 == 0$ is True; therefore stable is True.
- [not] stable is False, so the first branch is skipped. `value >= 30` is True, so the `elif` branch assigns `status = high`. The `else` branch is not considered after that match.
2. Exact output: 33 True high

Task 2. Diagnose and repair - 12 points

The requirement is: approval requires training, and it also requires either a temperature from 15 through 30 inclusive or a supervisor override.

```
trained = False
temperature = 20
supervisor = False

approved = trained and temperature >= 15 or temperature <= 30 or supervisor
print(approved)
```

Your task

1. Show the actual Boolean result for the supplied values and explain why it violates the requirement.
2. Write one corrected Boolean assignment and defend its grouping with a test in which trained is False.

Model response:

1. Python evaluates `[[and]]` before `[[or]]`. `trained [[and]] temperature >= 15` is False, but `temperature <= 30` is True, so the entire expression becomes True. That incorrectly approves an untrained person.
2. Correct assignment: `approved = trained [[and]] (15 <= temperature <= 30 [[or]] supervisor)`. With `trained = False`, the left side of the outer `[[and]]` is False, so approval is False regardless of temperature or supervisor. This matches the stated requirement that training is always required.

Task 3. Construct a complete program - 24 points

Program specification

- Read `current_floor` and `desired_floor` as integers.
- Valid floors are 1 through 10 inclusive. Print invalid if either input is outside that interval.
- If the valid floors are equal, print already there.
- Otherwise, use a while loop that changes `current_floor` by exactly one floor per pass until it equals `desired_floor`.
- Print each newly reached floor inside the loop. Do not jump directly to the destination.

Required planning evidence

1. Write the invalid-input Boolean expression and the branch order that protects the loop.
2. Write the continuation condition and both possible one-floor updates before coding.

Model program

```
current_floor = int(input())
desired_floor = int(input())

invalid = (current_floor < 1 or current_floor > 10 or
           desired_floor < 1 or desired_floor > 10)

if invalid:
    print("invalid")
elif current_floor == desired_floor:
    print("already there")
else:
    while current_floor != desired_floor:
        if current_floor < desired_floor:
            current_floor = current_floor + 1
        else:
            current_floor = current_floor - 1
        print(current_floor)
```

Model response: Validation and the equal-floor case occur before the loop, so every loop pass begins with two valid unequal floors. **Model response:** The continuation condition describes unfinished movement. Exactly one branch changes `current_floor` by one, which guarantees progress toward `desired_floor` from either direction.

Task 3 continued. Test and defend - included in 24 points

Expected tests and results

1. Inputs 2 and 5 print 3, 4, and 5 on separate lines.
2. Inputs 5 and 2 print 4, 3, and 2 on separate lines. This protects the downward update.
3. Inputs 4 and 4 print already there. Inputs 0 and 4 print invalid.

Scoring guidance 4 points planning; 4 input/validation; 4 equal-floor branch; 4 while condition; 4 directional one-floor update; 2 output placement; 2 tests. Equivalent coherent code earns full credit.

Bridge Day 10 VIP Evidence Handoff

INSTRUCTOR KEY • Contract 07a04826c975 • Accessible v5 successor

Why engineers use this page

Begin with the notebook's required read-convert-compute-format-print reconnect, then transfer the elevator loop's continuation, update, and termination evidence into three while-loop activities.

Decision boundary: Code is useful only when its stored state, visible result, assumptions, units, limits, and tests support a defensible engineering interpretation.

Construct readiness before independent work

New authoring tools: for loop, while loop, range call, loop state update, termination condition, list literal as collector, append call

Carried authoring tools: assignment, print call, arithmetic expression, modulo, input call, int conversion, f string, comparison expression, if elif else

Supplied-code exposure only: list index read

An exposure-only construct may be traced in complete supplied code, but the independent task will not require students to invent it before its authoring day.

Notebook cells and task constructs

Activity	Work	Stable cells	Required authoring constructs
18.19	Countdown To Multiple	18-19-work / 18-19-transfer / 18-19-cold	arithmetic expression, while loop
18.21	Cooldown Sequence	18-21-work / 18-21-transfer / 18-21-cold	append call, arithmetic expression, while loop
18.22	Rounds To Clear Queue	18-22-work / 18-22-transfer / 18-22-cold	arithmetic expression, f string, input call, int conversion, while loop

Readiness evidence

1. Write the five-part program shell, then for each mapped activity identify the input conversion, changing state, and continuation condition.

Model response: The shell is input, numeric conversion, current-day computation, f-string formatting, and print. Numeric text becomes int or float before arithmetic. Activity 18.19 changes the current number until divisibility is reached; 18.21 changes the cooldown value while storing each state; 18.22 reduces backlog while counting rounds.

2. Explain in one sentence why the update moves the state toward termination.

Model response: A complete explanation connects the direction and size of the update to the condition becoming false; merely saying that the loop eventually stops is insufficient.

Timing and help trigger

Record a first prediction before running. If you still lack an executable plan after about 8 focused minutes, use the linked ThinkCSPy refresher or the supplied model. If two attempts fail for the same named requirement, write the exact mismatch and ask a peer mentor or instructor a targeted question. Timing is diagnostic evidence, not a speed grade. **Start or elapsed minutes:** _____ **My help trigger:**

Engineering Evidence Record

Complete one record from a model, transfer, or Independent Program Studio build. Generic statements are not sufficient; use actual values, a real revision, and one concrete next test.

Evidence field	Record
Prediction	A specific expected state or output before execution.
Observed Result	The actual state or output, including a value or exact text.
Revision Reason	The defect or mismatch and the change that addresses it.
Engineering Meaning	How the evidence changes or supports the engineering decision.
Units Or Not Applicable	The physical unit, or the evidence type when no unit applies.
Assumption	One condition accepted as true for this model or rule.
Model Limit	One situation the result does not justify or predict.
Next Test	A concrete boundary, invalid, or alternate case with an expected result.
Help Trigger	The exact unresolved point that would trigger a targeted question.
Minutes Used	Approximate minutes from first prediction through revision.

Notebook and submission procedure

1. Attempt, predict, run, inspect, and revise before opening a reveal.
2. Complete the end-of-notebook Independent Program Studio without a reveal or copied solution. Only those visibly labeled Studio cells are scored for independent mastery.
3. Save or download the completed notebook as one `.ipynb` file.
4. Upload that one notebook to the matching Gradescope assignment. Do not export a `.py` file or create a ZIP.