

PHYSICS • UPPER SIXTH

UPPER SIXTH — PHYSICS

CHAPTER 8

ELECTROMAGNETIC INDUCTION

SUGGESTED TIME: 2 PERIODS

IN THIS CHAPTER

This chapter introduces electromagnetic induction: how a changing magnetic flux produces an induced e.m.f. (Faraday's and Lenz's laws), and how this principle powers AC and DC generators. It then develops self- and mutual inductance, the growth and decay of current in an L-R circuit, and the energy stored in an inductor.

- By the end of this chapter I can define magnetic flux and calculate the flux through a coil of N turns in a uniform field.
- By the end of this chapter I can state and apply Faraday's law $\mathcal{E} = -N \frac{d\Phi}{dt}$ to compute an induced e.m.f.
- By the end of this chapter I can use Lenz's law (and Fleming's right-hand rule) to predict the direction of an induced current.
- By the end of this chapter I can derive and apply $\mathcal{E} = Blv$ for a conductor moving through a uniform magnetic field.
- By the end of this chapter I can explain the working principles of simple AC and DC generators and sketch their output e.m.f. against time.
- By the end of this chapter I can define self-inductance L and mutual inductance M through $N\Phi = LI$ and $N\Phi_2 = MI_1$, and compute them in simple cases.



DOWNLOAD ON- BUCH

Free • Google Play
AI tutor, past papers,
results



GO ONBUCH+

All signed courses, unlimited AI
tutor, PDF sheets — OnBuch+
tab in the app

THIS SIGNED COURSE CONTAINS

COURSE

complete, illustrated,
step by step

METHODS

and worked examples

EXERCISES

exam style + solutions

SUMMARY SHEET

the essentials to
remember



Signed • OnBuch+

ONBUCH+ TEACHING TEAM
FOLLOWS THE OFFICIAL MINESEC SYLLABUS

OnBuch+

CONTENTS

- | | |
|---|--------------------------------|
| 1. Magnetic Flux and Faraday's Law of Induction | 5. Integration activity |
| 2. Lenz's Law and the Motional E.M.F. ($e = Blv$) | 6. Methods and worked examples |
| 3. Simple AC and DC Generators | 7. Exercises |
| 4. Self- and Mutual Inductance; the L-R Circuit and Stored Energy | 8. Solutions to the exercises |
| | 9. Summary sheet |

CHAPTER OBJECTIVES

- By the end of this chapter I can define magnetic flux and calculate the flux through a coil of N turns in a uniform field.
- By the end of this chapter I can state and apply Faraday's law $e = -N d\Phi/dt$ to compute an induced e.m.f.
- By the end of this chapter I can use Lenz's law (and Fleming's right-hand rule) to predict the direction of an induced current.
- By the end of this chapter I can derive and apply $e = Blv$ for a conductor moving through a uniform magnetic field.
- By the end of this chapter I can explain the working principles of simple AC and DC generators and sketch their output e.m.f. against time.
- By the end of this chapter I can define self-inductance L and mutual inductance M through $N\Phi = LI$ and $N\Phi_2 = MI_1$, and compute them in simple cases.
- By the end of this chapter I can write and solve the differential equation of an L-R circuit for the growth and decay of current.
- By the end of this chapter I can calculate the energy stored in an inductor, $E = \frac{1}{2}LI^2$.
- By the end of this chapter I can interpret time constants and exponential curves in induction problems, as required in GCE structured questions.

PREREQUISITES

- Magnetic field B , force on a current-carrying conductor $F = BIl$, and Fleming's left-hand rule (Lower Sixth, magnetic fields chapter)
- Magnetic flux $\Phi = BA \cos \theta$ and flux linkage $N\Phi$
- Electric current, e.m.f., resistance and Ohm's law; Kirchhoff's laws
- Exponential functions and simple first-order differential equations (Further/Pure Mathematics)
- Alternating current basics: sinusoidal variation, peak and r.m.s. values (Lower Sixth)

1 MAGNETIC FLUX AND FARADAY'S LAW OF INDUCTION

During the long rainy-season blackouts in Douala and Bamenda, many families switch on a small petrol generator — yet few realise that this machine works by spinning a coil in a magnetic field, exactly like the alternator of a motorcycle. Even more surprising: you can light a bulb by simply waving a magnet near a coil of wire, with no battery at all. How does a changing magnetic field ‘push’ charges around a circuit? Why does the induced current always fight the change that creates it? And why does a big coil in a DC circuit make the current rise slowly instead of instantly? This chapter answers these questions and explains the physics behind generators, transformers and the ENEO grid itself.

We begin with the central discovery, made by Michael Faraday in 1831: a changing magnetic flux through a circuit generates an electromotive force (e.m.f.) in that circuit. This phenomenon is called **electromagnetic induction**. Before we can state the law quantitatively, we need a precise way of measuring “how much magnetic field passes through a circuit”. That quantity is the magnetic flux.

1.1 Magnetic Flux and Flux Linkage

DEFINITION Magnetic flux

The **magnetic flux** Φ through a plane surface of area A placed in a uniform magnetic field of magnitude B is

$$\Phi = BA \cos \theta$$

where θ is the angle between the field vector $\vec{B}$ and the normal (perpendicular) to the surface. The SI unit of flux is the **weber** (Wb): $1 \text{ Wb} = 1 \text{ T m}^2$.

Think of magnetic field lines as rain falling vertically and the coil as a hoop you hold in the rain. The amount of rain caught by the hoop depends on three things: how hard it rains (B), how big the hoop is (A), and how you tilt it (θ). Hold the hoop horizontally (normal vertical, $\theta = 0$) and you catch the maximum, $\Phi = BA$; hold it edge-on ($\theta = 90^\circ$) and you catch nothing, $\Phi = 0$. Flux is exactly this “amount of field threading the loop”.

DEFINITION Flux linkage

For a coil of N turns, each turn of area A threading the same flux Φ , the **flux linkage** is

$$N\Phi = NBA \cos \theta$$

Its unit is the weber-turn (Wb-turns), dimensionally identical to the weber.

WARNING Angle with the normal, not with the plane

The angle θ in $\Phi = BA \cos \theta$ is measured between $\vec{B}$ and the normal to the plane of the coil, not between $\vec{B}$ and the plane itself. If a question gives the angle between the field and the plane of the coil, you must use $\Phi = BA \sin \theta$ instead. This is one of the most frequent slips at the GCE.

EXAMPLE Computing a flux linkage

A circular coil of 200 turns and radius 5.0 cm is placed with its plane perpendicular to a uniform field $B = 0.30 \text{ T}$. Then $\theta = 0$ and

$$N\Phi = NBA = 200 \times 0.30 \times \pi(0.050)^2 = 0.47 \text{ Wb-turns.}$$


1.2 Experimental Evidence of Electromagnetic Induction

Faraday's conclusions rest on simple experiments that you can perform in the school laboratory with a bar magnet, a coil of insulated copper wire and a centre-zero galvanometer (a sensitive current detector whose needle can swing left or right).

EXPERIMENT Inducing a current with a magnet and a coil

Connect the two ends of a coil of many turns to a centre-zero galvanometer. There is no battery anywhere in the circuit.

1. Magnet pushed into the coil: while the north pole of the magnet is moving towards and into the coil, the needle kicks to one side (say, to the right). The faster the magnet moves, the larger the kick.
2. Magnet held at rest inside the coil: the needle sits exactly at zero, even though the field through the coil is now at its strongest.
3. Magnet pulled out: the needle kicks to the opposite side (to the left).
4. Coil moved instead of magnet: the same deflections occur — only the relative motion matters.
5. Neighbouring circuit switched on/off: replace the magnet by a second coil carrying a current from a battery. Nothing happens while the current is steady, but at the instant the switch is closed or opened, the galvanometer kicks — in opposite directions for closing and opening.



A bar magnet pushed into a coil connected to a centre-zero galvanometer. The needle deflects only while the magnet is moving; reversing the motion reverses the deflection.

The crucial observation is this:

KEY POINTS What the experiments show

- An e.m.f. (and hence a current) is induced only while the flux linkage through the circuit is changing.
- The magnitude of the induced e.m.f. increases with the speed of the change.
- The direction of the induced current depends on the sense of the change (flux increasing or decreasing).
- A steady flux, however large, induces nothing.

1.3 Faraday's Law of Electromagnetic Induction

Faraday turned these observations into a quantitative law: the induced e.m.f. equals the rate of change of flux linkage.

PROPERTY Faraday's law of electromagnetic induction

When the flux linkage through a circuit of N turns changes, an e.m.f. is induced given by

$$e = -N \frac{d\Phi}{dt} = -\frac{d(N\Phi)}{dt}$$

The magnitude of the induced e.m.f. equals the rate of change of flux linkage; the minus sign expresses the direction of the e.m.f. (Lenz's law, studied in the next section). SI check: weber per second = volt, since $1\text{ V} = 1\text{ Wb s}^{-1}$.

The law contains everything the experiments showed. If $N\Phi$ is constant, $d(N\Phi)/dt = 0$ and $e = 0$: no change, no e.m.f. If the change is twice as fast, the e.m.f. is twice as big. If the flux decreases instead of increasing, the sign of the derivative flips, and so does the direction of the e.m.f.

WARNING A change of flux, not a large flux

The most common misconception is to believe that a strong field or a large flux induces a large e.m.f. It does not. A coil sitting motionless in the strongest steady magnet in the laboratory has zero induced e.m.f., because $d\Phi/dt = 0$. Only the rate of change of flux linkage matters. Always ask yourself first: what is changing — B , A , or θ ?

Since $\Phi = BA \cos \theta$, there are exactly three independent ways to change the flux through a circuit:

- **Change B :** move a magnet, switch an electromagnet on or off, or vary the current in a neighbouring coil.
- **Change A :** deform the loop, slide one rail of a rectangular circuit, or withdraw the coil from the field region (the effective area threading the field changes).
- **Change θ :** rotate the coil in the field — this is the principle of the alternator and of every generator in the ENEO grid.

METHOD Three-step recipe for induced-e.m.f. problems

1. Write the flux linkage $N\Phi$ as a function of the quantity that is changing ($B(t)$, $A(t)$ or $\theta(t)$).
2. Differentiate with respect to time to get $e = -d(N\Phi)/dt$.
3. Take the magnitude $|e|$ for the size of the e.m.f., and determine the direction separately (Lenz's law, next section). Never try to read the direction off the algebra alone.

1.4 Induced Current and Induced Charge

If the circuit is closed with total resistance R , the induced e.m.f. drives an induced current

$$I = \frac{|e|}{R} = \frac{N}{R} \left| \frac{d\Phi}{dt} \right|.$$

The charge that flows during a change lasting from t_1 to t_2 is obtained by integrating:

$$Q = \int_{t_1}^{t_2} I dt = \frac{N}{R} \int_{t_1}^{t_2} \left| \frac{d\Phi}{dt} \right| dt = \frac{N |\Delta\Phi|}{R}.$$

PROPERTY Induced charge


The total charge circulated while the flux linkage changes by $\Delta(N\Phi)$ is

$$Q = \frac{N |\Delta\Phi|}{R}$$

where R is the total resistance of the circuit. Remarkably, Q depends only on the total change of flux linkage, not on how fast the change occurs: a slow withdrawal and a quick withdrawal of the coil pass the same total charge (the quick one gives a larger current for a shorter time). This result is frequently examined at the GCE and is the working principle of the fluxmeter and of the ballistic galvanometer used to measure magnetic fields.

1.5 Graphical View: from $N\Phi(t)$ to $e(t)$

Because $e = -d(N\Phi)/dt$, the induced e.m.f. at each instant is minus the slope of the flux-linkage-time graph. Where $N\Phi$ is flat, $e = 0$; where $N\Phi$ falls steeply, e is large and positive.



Top: flux linkage $N\Phi(t)$. Bottom: induced e.m.f. $e = -d(N\Phi)/dt$, which is minus the slope of the upper graph. A steady flux (flat portions) gives zero e.m.f.; a decreasing flux gives a positive e.m.f. and an increasing flux a negative one.

1.6 Worked Examples**WORKED EXAMPLE 1 Coil withdrawn from a magnetic field**

A rectangular coil of $N = 50$ turns and area $A = 2.0 \times 10^{-3} \text{ m}^2$ lies perpendicular to a uniform field $B = 0.40 \text{ T}$. It is pulled completely out of the field in 0.25 s . The coil has resistance

$R = 10\ \Omega$. Find (a) the average induced e.m.f., (b) the average induced current, (c) the total charge that flows.

SOLUTION

Solution. The changing quantity is the effective area in the field; the flux goes from its full value to zero.

(a) Initial flux linkage: $N\Phi_1 = NBA = 50 \times 0.40 \times 2.0 \times 10^{-3} = 4.0 \times 10^{-2}$ Wb-turns. Final flux linkage: $N\Phi_2 = 0$. By Faraday's law,

$$|e| = \left| \frac{\Delta(N\Phi)}{\Delta t} \right| = \frac{4.0 \times 10^{-2}}{0.25} = 0.16\text{ V}.$$

(b) Induced current:

$$I = \frac{|e|}{R} = \frac{0.16}{10} = 1.6 \times 10^{-2}\text{ A} = 16\text{ mA}.$$

(c) Induced charge (note that the time cancels):

$$Q = \frac{N|\Delta\Phi|}{R} = \frac{4.0 \times 10^{-2}}{10} = 4.0 \times 10^{-3}\text{ C} = 4.0\text{ mC}.$$

Check: $Q = I\Delta t = 0.016 \times 0.25 = 4.0 \times 10^{-3}\text{ C}$. ✓

WORKED EXAMPLE 2 Field switched off inside a solenoid

A small search coil of 500 turns and cross-sectional area 1.0 cm^2 sits inside a long solenoid, coaxial with it, where the field is $B = 0.080\text{ T}$. The solenoid current is switched off and the field falls to zero uniformly in 40 ms. Calculate the average e.m.f. induced in the search coil.

SOLUTION

Solution. Here it is B that changes; N , A and $\theta = 0$ are fixed.

$$|e| = NA \left| \frac{\Delta B}{\Delta t} \right| = 500 \times 1.0 \times 10^{-4} \times \frac{0.080}{0.040} = 0.10\text{ V}.$$

This is exactly how the field inside a solenoid is measured in the laboratory: the search coil is connected to a fluxmeter, and the induced charge $Q = N\Delta\Phi/R$ gives B .

WORKED EXAMPLE 3 Rotating coil — a taste of the alternator

A flat coil of $N = 100$ turns and area $A = 5.0 \times 10^{-3}\text{ m}^2$ rotates at constant angular speed $\omega = 20\text{ rad s}^{-1}$ about an axis in its plane, perpendicular to a uniform field $B = 0.25\text{ T}$. (a) Write the flux linkage as a function of time. (b) Find the maximum induced e.m.f.

SOLUTION

Solution. (a) If $\theta = 0$ when the plane of the coil is perpendicular to $\vec{B}$, then $\theta = \omega t$ and

$$N\Phi(t) = NBA \cos \omega t = 100 \times 0.25 \times 5.0 \times 10^{-3} \cos(20t) = 0.125 \cos(20t) \text{ Wb-turns.}$$

(b) Differentiating (step 2 of the method):

$$e = -\frac{d(N\Phi)}{dt} = 0.125 \times 20 \sin(20t) = 2.5 \sin(20t) \text{ V.}$$

The maximum e.m.f. is $e_{\max} = NBA\omega = 2.5 \text{ V}$. The e.m.f. is alternating: this is precisely the principle of the AC generator, developed in Section 3. Note that the e.m.f. is greatest when the flux is zero (coil edge-on to the field), because that is where the flux changes fastest.

WARNING Pitfalls to avoid at the GCE

- Do not write $e = N\Phi/t$ with the total flux: the law involves the change $\Delta(N\Phi)$.
- Do not forget the factor N : examiners routinely give the number of turns and many candidates drop it.
- In $Q = N\Delta\Phi/R$, R is the total resistance of the whole circuit, including the coil itself.
- Keep units in SI: areas in m^2 , times in seconds; convert cm^2 ($1 \text{ cm}^2 = 10^{-4} \text{ m}^2$) and milliseconds before substituting.

EXERCISE 1

A coil of 300 turns, each of area $4.0 \times 10^{-4} \text{ m}^2$, is placed with its plane perpendicular to a field that increases uniformly from 0.10 T to 0.50 T in 0.10 s. The circuit resistance is 6.0Ω . Calculate (a) the induced e.m.f., (b) the induced current, (c) the charge that circulates. (d) What would the charge be if the same change took 1.0 s instead?

SOLUTION Exercise 1

(a) $|e| = NA\Delta B/\Delta t = 300 \times 4.0 \times 10^{-4} \times 0.40/0.10 = 0.48 \text{ V}$. (b) $I = 0.48/6.0 = 0.080 \text{ A}$. (c) $Q = NA\Delta B/R = 300 \times 4.0 \times 10^{-4} \times 0.40/6.0 = 8.0 \times 10^{-3} \text{ C}$. (d) The charge is unchanged, $Q = 8.0 \text{ mC}$, because $Q = N\Delta\Phi/R$ does not depend on the duration; only the current (8.0 mA) and e.m.f. (48 mV) would be ten times smaller.

KEY POINTS Key points of this section

- Magnetic flux: $\Phi = BA \cos \theta$ (weber); flux linkage $N\Phi$ for N turns.
- An e.m.f. is induced only while the flux linkage is changing.
- Faraday's law: $e = -N d\Phi/dt$; magnitude = rate of change of flux linkage.
- Three ways to change the flux: change B , change A , change θ .
- Induced current $I = |e|/R$; induced charge $Q = N|\Delta\Phi|/R$, independent of the speed of the change.
- The minus sign in Faraday's law encodes the direction of the e.m.f. — this is Lenz's law, the subject of the next section.

2 LENZ'S LAW AND THE MOTIONAL E.M.F. ($E = BLv$)

In the previous section we discovered Faraday's law: whenever the magnetic flux Φ linking a circuit changes, an e.m.f. is induced, of magnitude $|e| = \left| \frac{d\Phi}{dt} \right|$. But a magnitude alone is not enough. To predict the behaviour of a circuit we must also know the direction of the induced e.m.f. and of the induced current. This is the question answered by the Russian physicist Heinrich Lenz, and it will lead us to one of the most useful results of this chapter: the motional e.m.f. $e = Blv$.

2.1 Lenz's Law

A simple observation.

Take a bar magnet and push its North pole towards a coil connected to a sensitive galvanometer. The pointer deflects: a current is induced. Now pull the magnet away: the pointer deflects the other way. Push the South pole in instead: the deflection reverses again. The induced current always seems to “fight” whatever you are doing. This is not a coincidence — it is a fundamental law of nature.

PROPERTY Lenz's Law (law)


The direction of the induced e.m.f. (and hence of the induced current) is always such that it **opposes the change** that produces it.

Let us make this concrete with the magnet and the coil:

- A North pole approaching the coil increases the flux through it. The induced current flows so that the near face of the coil becomes a North pole. Since like poles repel, the coil pushes

back against the incoming magnet — it opposes the approach.

- A North pole receding decreases the flux. The induced current reverses, so the near face becomes a South pole, attracting the magnet back — it opposes the retreat.



A North pole approaching a coil: the induced current makes the near face a North pole, opposing the approach.

The pole rule. A quick way to remember the result:

KEY POINTS Pole rule for a magnet and a coil

An approaching pole induces the same pole on the near face of the coil (repulsion); a receding pole induces the opposite pole (attraction). Approaching North $\Rightarrow$ near face becomes North.

The minus sign in Faraday's law.

We can now write Faraday's law in its complete form:

$$e = -\frac{d\Phi}{dt} = -N \frac{d\Phi_B}{dt}$$

where $\Phi = N\Phi_B$ is the total flux linkage of a coil of N turns, each turn carrying flux Φ_B . The **minus sign** is the mathematical expression of Lenz's law. If we choose a positive sense of circulation around the coil and define the flux Φ as positive when it passes in the corresponding direction (right-hand grip rule), then the induced e.m.f. e is negative when the flux is increasing ($d\Phi/dt > 0$): the induced e.m.f. drives current in the negative sense, creating a flux that cancels the increase. The minus sign is not a decoration — it is Lenz's law written in algebra.

WARNING Common mistake

Do not say “the induced current opposes the magnetic field”. It opposes the change of flux, not the field itself. If the flux is decreasing, the induced current actually reinforces the existing field to slow the decrease.

2.2 Lenz's Law and the Conservation of Energy

Why must nature behave this way? Suppose, for a moment, that the induced current helped the change instead of opposing it. Then an approaching North pole would induce a South pole on the near face, attracting the magnet, accelerating it further, inducing more current, attracting it more strongly... We would obtain an ever-growing current and an ever-faster magnet for free. This is impossible: it violates the **conservation of energy**.

PROPERTY Energy conservation in induction (property)

Lenz's law is a direct consequence of the conservation of energy. To change the flux through a circuit, an external agent must do **mechanical work** against the electromagnetic opposition; this work is converted into **electrical energy** in the circuit (and ultimately into heat in the resistance):

$$\text{mechanical work done} = \text{electrical energy produced (+ heat)}.$$

When you push the magnet into the coil, you feel the repulsion: you must push harder, and the work you supply is exactly what lights the lamp connected to the coil. Every dynamo, every alternator at the Song Loulou or Memve'ele hydroelectric stations, obeys this principle: the turbines supply mechanical work, and Lenz's law guarantees that this work — and no less — is needed to generate the electrical energy.

2.3 Fleming's Right-Hand Rule

For a straight conductor moving through a magnetic field, there is a practical tool for finding the direction of the induced current: **Fleming's right-hand (dynamo) rule**.

METHOD Using Fleming's right-hand rule

Hold the thumb, first finger and second finger of the right hand mutually at right angles:


1. First finger → Field (direction of $\vec{B}$, North to South);
2. thuMb → Motion (direction of the velocity $\vec{v}$ of the conductor);
3. seCond finger → Current (direction of the induced conventional current).

WARNING Right hand or left hand?

A classic GCE trap! Use the right hand for induction (generators, dynamos: motion → current). Use the left hand for the motor effect (force on a current-carrying conductor: current + field → force). Memory aid: Right = Induction; Left = motor ($\vec{F} = I\vec{l} \wedge \vec{B}$).

2.4 The Motional E.M.F.: Derivation of $e = Blv$

Consider a straight conducting rod PQ of length l sliding with constant velocity $\vec{v}$ on two parallel conducting rails, in a uniform magnetic field $\vec{B}$ directed into the page. The rails are joined at one end, so the rod and rails form a closed rectangular circuit.



Rod sliding on U-shaped rails in a field into the page. The induced current I flows round the loop; the magnetic force $\vec{F}$ on the rod opposes its motion (Lenz's law).

Derivation from Faraday's law.

Let x be the distance of the rod from the closed end of the rails. The area of the circuit is $A = lx$, so the flux linking the circuit is

$$\Phi = BA = Blx.$$

As the rod moves, x changes at the rate $\frac{dx}{dt} = v$. Applying Faraday's law:

$$|e| = \frac{d\Phi}{dt} = Bl \frac{dx}{dt} = Blv.$$

PROPERTY Motional e.m.f. (formula)

A straight conductor of length l moving with velocity v perpendicular to a uniform magnetic field B (conductor, field and velocity mutually perpendicular) has an induced e.m.f.

$$e = Blv$$

with B in tesla (T), l in metres (m), v in m s^{-1} , e in volts (V). If the velocity makes an angle θ with the field, only the component of $\vec{v}$ perpendicular to $\vec{B}$ counts:

$$e = Blv \sin \theta.$$

Microscopic origin. The free electrons in the rod are carried along at velocity $\vec{v}$ through the field, so each electron experiences a magnetic force $e\vec{v} \times \vec{B}$ along the rod. Electrons accumulate at one end, leaving the other end positive: the rod becomes a battery of e.m.f. Blv . Fleming's right-hand rule gives the direction of the conventional current this "battery" drives.

2.5 Force on the Induced Current and the Power Balance

Once the induced current I flows in the rod, the rod is a current-carrying conductor sitting in a

magnetic field: it experiences the Laplace force

$$F = BIl.$$

By Fleming's left-hand rule, this force points opposite to $\vec{v}$ — exactly as Lenz's law demands. To keep the rod moving at constant velocity, an external agent must pull with an equal force $F = BIl$.

Now check the energy balance. The mechanical power supplied by the agent is

$$P_{\text{mech}} = Fv = BIl \times v = (Blv)I = eI = P_{\text{elec}}.$$

The mechanical power is converted entirely into electrical power eI (which then appears as heat RI^2 in the circuit resistance). The equations $e = Blv$ and $F = BIl$ are two faces of the same energy conversion.

WORKED EXAMPLE 4 Rod sliding on conducting rails

A rod of length $l = 0.50 \text{ m}$ slides at constant speed $v = 4.0 \text{ m s}^{-1}$ on frictionless horizontal rails, in a uniform vertical field $B = 0.20 \text{ T}$. The total resistance of the circuit is $R = 0.10 \Omega$. Find (a) the induced e.m.f., (b) the induced current, (c) the force needed to keep the rod moving, (d) the mechanical power and the electrical power dissipated.

SOLUTION

Solution.

(a) Motional e.m.f.: $e = Blv = 0.20 \times 0.50 \times 4.0 = 0.40 \text{ V}$.

(b) Induced current: $I = \frac{e}{R} = \frac{0.40}{0.10} = 4.0 \text{ A}$.

(c) Opposing force: $F = BIl = 0.20 \times 4.0 \times 0.50 = 0.40 \text{ N}$. The agent must pull with 0.40 N .

(d) Mechanical power: $P = Fv = 0.40 \times 4.0 = 1.6 \text{ W}$. Electrical power: $P = eI = 0.40 \times 4.0 = 1.6 \text{ W}$ (equivalently $RI^2 = 0.10 \times 16 = 1.6 \text{ W}$). The two are equal: energy is conserved.

WORKED EXAMPLE 5 Aeroplane wing cutting the Earth's field

An aeroplane with wingspan $l = 30 \text{ m}$ flies horizontally at $v = 250 \text{ m s}^{-1}$ over a region where the vertical component of the Earth's magnetic field is $B = 4.0 \times 10^{-5} \text{ T}$. Calculate the e.m.f. induced between the wing tips.

SOLUTION

Solution. The wings, the velocity and the vertical field component are mutually perpendicular, so

$$e = Blv = 4.0 \times 10^{-5} \times 30 \times 250 = 0.30 \text{ V}.$$

A small but measurable e.m.f. of 0.30 V appears between the wing tips. (No current flows, because the circuit is not closed.)

2.6 Eddy Currents and Electromagnetic Braking

Induction does not only occur in wires. When the flux through a block of metal changes, currents are induced in closed loops inside the material: these are called **eddy currents**. By Lenz's law, they always oppose the change producing them.

EXPERIMENT The falling magnet in a copper tube

Drop a small strong magnet down a vertical copper tube. Astonishingly, it falls in slow motion, far slower than a non-magnetic object of the same mass. As the magnet falls, the flux through each ring-shaped slice of the tube changes, inducing eddy currents. By Lenz's law, the eddy currents below the magnet repel the approaching pole, while those above the magnet attract the receding pole: the net effect is an upward force opposing the fall. The magnet quickly reaches a small terminal velocity when this force balances its weight. The gravitational potential energy is converted, via the eddy currents, into heat in the copper.

DID YOU KNOW? Electromagnetic braking

The same principle brakes some trains, lorries and roller-coasters: a strong electromagnet induces eddy currents in a metal disc or rail attached to the wheel, and the opposing force slows the vehicle without any contact or wear. The kinetic energy is dissipated as heat. Eddy currents are a nuisance in transformer cores (they waste energy), which is why cores are made of thin insulated laminations that break the current loops.

EXERCISE 2 Checking your understanding

1. A South pole is withdrawn from a coil. State the polarity induced on the near face and justify using Lenz's law.
2. A rectangular coil is pulled horizontally out of a uniform field directed into the page. In which sense does the induced current flow?
3. A metal rod 0.80 m long moves at 15 m s^{-1} at 60° to a field of 0.50 T, the rod being perpendicular to both. Calculate the induced e.m.f.

SOLUTION Exercise

1. Withdrawing a South pole decreases the flux; the coil opposes the retreat by attracting the magnet, so the near face becomes a North pole.

2. The flux directed into the page decreases, so the induced current creates its own field into the page: by the right-hand grip rule it flows clockwise.
3. $e = Blv \sin \theta = 0.50 \times 0.80 \times 15 \times \sin 60^\circ = 6.0 \times 0.866 = 5.2 \text{ V}.$

KEY POINTS Key points of this section

- Lenz's law: the induced e.m.f. opposes the change producing it; this is the meaning of the minus sign in $e = -\frac{d\Phi}{dt}$.
- Approaching North $\Rightarrow$ near face of the coil becomes North (repulsion); receding North $\Rightarrow$ near face becomes South (attraction).
- Fleming's right-hand rule (induction): First finger Field, seCond finger Current, thuMb Motion. Right hand = generator; left hand = motor.
- Motional e.m.f.: $e = Blv$ (mutually perpendicular), or $e = Blv \sin \theta$ in general.
- The induced current feels a force $F = BIl$ opposing the motion; mechanical power Fv equals electrical power el : energy is conserved.
- Changing flux in bulk metal produces eddy currents, used in electromagnetic braking and responsible for the slow fall of a magnet in a copper tube.

3 SIMPLE AC AND DC GENERATORS

In the previous section we established that a conductor moving through a magnetic field experiences a motional e.m.f. $e = Blv$, and that Lenz's law fixes its direction. A natural question follows: how can we make a conductor move continuously through a magnetic field so as to produce a continuous supply of electrical energy? The answer is one of the most consequential inventions in human history: the **generator**. Instead of pushing a straight rod along rails, we rotate a coil in a magnetic field. Rotation is easy to sustain — a waterfall, steam from a boiler, or a petrol engine can all spin a shaft — and, as we shall now show, a rotating coil automatically produces an alternating e.m.f. This section builds the simple AC generator from Faraday's law, then shows how a single clever modification — the split-ring commutator — turns it into a DC generator.


3.1 The Simple AC Generator: Construction

DEFINITION Simple AC generator

A **simple AC generator** (or **alternator**) consists of a rectangular coil of N turns, each of area A , mounted on an axle and rotated at constant angular velocity ω in a uniform magnetic field $\vec{B}$. The ends of the coil are connected to two **slip rings** which rotate with the coil; stationary carbon **brushes** press against the slip rings and connect the coil to the external circuit.

Each component has a precise role:

- The **coil** (N turns, area A): this is where the e.m.f. is induced. Using many turns multiplies the flux linkage and hence the e.m.f.
- The **magnet** (permanent magnet or electromagnet): provides the uniform field $\vec{B}$ across the coil.
- The **axle**: driven by an external mechanical agent (turbine, engine, hand crank); it supplies the mechanical work that will be converted into electrical energy.
- The **slip rings**: two complete copper rings, each permanently connected to one end of the coil. They rotate with the coil, so each end of the coil always remains connected to the same terminal of the external circuit.
- The **brushes**: small blocks of carbon held by springs against the slip rings. They rub on the rotating rings and carry the current to the stationary external circuit without twisting the wires.



The simple AC generator: a coil rotating in a uniform field, connected to the external circuit through two slip rings and two brushes.

3.2 Derivation of the Induced E.M.F.: $e = NBA\omega \sin(\omega t)$

This derivation is **examinable** and follows directly from Faraday's law.

Setting up. Let the coil rotate with constant angular velocity ω about an axis perpendicular to

$\vec{B}$. Choose the origin of time so that at $t = 0$ the plane of the coil is perpendicular to $\vec{B}$, i.e. the normal $\vec{n}$ to the coil is parallel to $\vec{B}$. After a time t , the normal makes an angle

$$\theta = \omega t$$

with the field direction.

Step 1: flux linkage. The flux through one turn is $\Phi = BA \cos \theta$, so the total flux linkage is

$$N\Phi = NBA \cos(\omega t).$$

Step 2: Faraday's law. The induced e.m.f. is the negative rate of change of flux linkage:

$$\begin{aligned} e &= -\frac{d(N\Phi)}{dt} = -\frac{d}{dt}[NBA \cos(\omega t)] \\ &= -NBA(-\omega \sin(\omega t)) = NBA\omega \sin(\omega t). \end{aligned}$$

PROPERTY E.M.F. of a rotating coil

A coil of N turns and area A rotating at angular frequency ω in a uniform field B develops a sinusoidal e.m.f.

$$e = NBA\omega \sin(\omega t) = e_0 \sin(\omega t), \quad \text{with peak e.m.f. } e_0 = NBA\omega.$$


(Here $t = 0$ is taken when the coil plane is perpendicular to $\vec{B}$.) The frequency of the output is $f = \omega/(2\pi)$ and the r.m.s. value is $E_{\text{rms}} = e_0/\sqrt{2}$. The derivation from Faraday's law is examinable.

Note that $e_0 = NBA\omega$ shows exactly how to build a bigger e.m.f.: stronger field B , larger area A , more turns N , faster rotation ω . This is the design recipe for every real alternator.

WARNING The origin of time matters

A very common mistake is to write $e = NBA\omega \cos(\omega t)$ "because flux is a cosine". Whether the e.m.f. is a sine or a cosine depends entirely on where you take $t = 0$. With $t = 0$ at the perpendicular position (normal parallel to $\vec{B}$), $N\Phi = NBA \cos(\omega t)$ and $e = NBA\omega \sin(\omega t)$. If instead $t = 0$ is taken with the coil plane parallel to $\vec{B}$, then $N\Phi = NBA \sin(\omega t)$ and $e = NBA\omega \cos(\omega t)$. Always state the position of the coil at $t = 0$ before writing the equation. The peak value $e_0 = NBA\omega$ is unaffected.

3.3 Interpreting the Graph: Where is the E.M.F. Maximum?



Output e.m.f. of the simple AC generator (sinusoid) and of the simple DC generator (rectified, pulsating) on the same axes.

The graph raises a subtle point that examiners love. There are two remarkable positions of the coil:

- **Coil plane perpendicular to $\vec{B}$** ($\omega t = 0, \pi, \dots$): the flux linkage $N\Phi$ is maximum, but at that instant it is passing through its peak, so its rate of change is zero: $e = 0$.
- **Coil plane parallel to $\vec{B}$** ($\omega t = \pi/2, 3\pi/2, \dots$): the flux through the coil is zero, but it is changing fastest (the long sides of the coil are then cutting field lines at the greatest rate): $|e| = e_0$, maximum.

METHOD Locating maxima and zeros of the e.m.f.

1. Sketch or picture the coil at the instant considered and ask: “is the flux itself large, or is the flux changing fast?”
2. The e.m.f. depends only on the rate of change of flux linkage (Faraday), never on the flux itself.
3. Conclusion: e is maximum when the coil plane is parallel to $\vec{B}$ (flux zero, rate of change maximum); e is zero when the coil plane is perpendicular to $\vec{B}$ (flux maximum, rate of change zero).
4. Check with the motional picture: the e.m.f. is greatest when the long sides of the coil move perpendicularly across the field lines ($e = Blv$ per side, all N turns adding up).

WARNING Flux maximum does not mean e.m.f. maximum

Students frequently write “the e.m.f. is maximum when the flux through the coil is maximum”. This is wrong and costs marks. The induced e.m.f. is $e = -d(N\Phi)/dt$: it is propor-

tional to the slope of the flux–time graph, not to the flux. When the flux is at its peak, its slope is zero, so $e = 0$.

3.4 Energy Conservation in the Generator

Why must the turbine keep pushing? When the coil delivers current to the external circuit, that current flows through the coil inside the magnetic field, so each side of the coil experiences a force $\vec{F} = I\vec{L} \wedge \vec{B}$. By Lenz's law, the direction of the induced current is always such that these forces create a **torque opposing the rotation**. The external agent must therefore work continuously against this braking torque: the mechanical work done per second against the opposing torque is exactly the electrical power delivered (plus small losses). A generator is thus an energy converter: mechanical energy $\rightarrow$ electrical energy. If the external circuit is opened (no current), the opposing torque vanishes and the coil spins freely — a fact anyone who has pedalled a bicycle dynamo with the lamp switched off will recognise.

3.5 The Simple DC Generator: the Split-Ring Commutator

The AC generator delivers a current that reverses direction every half-turn. For some applications (charging batteries, electrolysis, older DC motors) we want a current that keeps one direction in the external circuit, even if its magnitude varies. The solution is beautifully simple.

DEFINITION Simple DC generator


A **simple DC generator** is an AC generator in which the two slip rings are replaced by a **split-ring commutator**: a single copper ring cut into two insulated half-rings, each connected to one end of the coil. The brushes are placed so that each brush changes from one half-ring to the other exactly at the instant when the e.m.f. passes through zero.

PROPERTY Action of the commutator

Every half-turn, the connections between the coil ends and the external terminals are swapped by the split-ring commutator, at precisely the moment the induced e.m.f. reverses. The two reversals cancel each other: although the e.m.f. inside the coil is still alternating, the e.m.f. delivered to the external circuit is

$$e_{\text{out}} = |e_0 \sin(\omega t)|,$$

a rectified, pulsating e.m.f. that never changes sign. The external current therefore keeps one direction.



The split-ring commutator at the moment of reversal: the brushes pass over the insulating gap and swap half-rings exactly when $e = 0$.

The output is shown as the dashed orange curve in the graph above: the negative half-cycles are “folded up”, giving $|e_0 \sin(\omega t)|$. The current is unidirectional but far from smooth — real DC generators use many coils at different angles to smooth it out.

3.6 Comparing the Two Generators; Practical Improvements

Feature	Simple AC generator	Simple DC generator
Rotating part	Coil of N turns, area A	Coil of N turns, area A
Connection to coil	Two slip rings	Split-ring commutator (two half-rings)
Brushes	One per slip ring	One per half-ring pair, swapping every half-turn
E.M.F. in the coil	$e = e_0 \sin(\omega t)$	$e = e_0 \sin(\omega t)$ (same)
Output e.m.f.	$e_0 \sin(\omega t)$ (alternating)	$ e_0 \sin(\omega t) $ (pulsating, one sign)
Current in external circuit	Reverses each half-cycle	Keeps one direction
Peak e.m.f.	$e_0 = NBA\omega$	$e_0 = NBA\omega$

Real generators improve on the simple model in several standard ways:

- **Many turns** of insulated copper wire: $e_0 \propto N$.
- A **soft-iron core** inside the coil: it concentrates and guides the field lines, greatly increasing the effective B through the coil (and is laminated to reduce eddy-current losses).
- **Electromagnets** instead of permanent magnets: they provide a much stronger and adjustable field B .
- **Several coils** at angles to one another (and several commutator segments): the outputs add to give a smoother, nearly steady DC, or three-phase AC in power-station alternators.

DID YOU KNOW? Generators and Cameroon

Nearly all of Cameroon’s electricity comes from alternators working on exactly this principle. At the hydroelectric stations of Songloulou on the Sanaga river and Edéa further down-

stream on the same river, falling water spins turbines coupled to huge alternators; the rotating magnetic field induces three-phase alternating e.m.f. in stationary coils at $f = 50$ Hz. Thermal stations (gas or heavy-fuel-oil plants near Douala and Kribi) use steam or gas turbines to the same end. On a much smaller scale, the alternator of a motorcycle or the dynamo of a bicycle lamp is a miniature rotating-coil (or rotating-magnet) generator: the faster the engine turns, the larger ω , and the brighter the lamp — a direct, everyday illustration of $e_0 = NBA\omega$.

3.7 Worked Examples

WORKED EXAMPLE 6 Peak e.m.f. of a rotating coil

A rectangular coil of $N = 200$ turns has dimensions $10\text{ cm} \times 8.0\text{ cm}$. It rotates at 3000 revolutions per minute about an axis perpendicular to a uniform magnetic field of flux density $B = 0.40\text{ T}$. (a) Calculate the peak e.m.f. induced in the coil. (b) Write the equation of the e.m.f., taking $t = 0$ when the plane of the coil is perpendicular to the field. (c) State the frequency and the r.m.s. value of the e.m.f.

SOLUTION

(a) Convert all data to SI units:

$$A = 0.10 \times 0.080 = 8.0 \times 10^{-3}\text{ m}^2, \quad \omega = \frac{3000 \times 2\pi}{60} = 100\pi\text{ rad s}^{-1} \approx 314\text{ rad s}^{-1}.$$

Peak e.m.f.:

$$e_0 = NBA\omega = 200 \times 0.40 \times 8.0 \times 10^{-3} \times 314 \approx 2.0 \times 10^2\text{ V}.$$

(b) With $t = 0$ at the perpendicular position, $N\Phi = NBA \cos(\omega t)$, so

$$e = e_0 \sin(\omega t) = 201 \sin(314 t)\text{ V}.$$

(c) Frequency: $f = \frac{\omega}{2\pi} = \frac{3000}{60} = 50\text{ Hz}$. R.m.s. value:

$$E_{\text{rms}} = \frac{e_0}{\sqrt{2}} = \frac{201}{\sqrt{2}} \approx 142\text{ V}.$$

Note the pleasing result: 3000 rpm gives exactly the mains frequency of 50 Hz used in Cameroon.

WORKED EXAMPLE 7 Designing for a target e.m.f.

A simple AC generator must produce a peak e.m.f. of 170 V at 50 Hz. The available magnet

provides $B = 0.25 \text{ T}$ and the coil has area $A = 2.0 \times 10^{-2} \text{ m}^2$. How many turns are required?

SOLUTION

Angular frequency: $\omega = 2\pi f = 2\pi \times 50 = 100\pi \approx 314 \text{ rad s}^{-1}$. From $e_0 = NBA\omega$:

$$N = \frac{e_0}{BA\omega} = \frac{170}{0.25 \times 2.0 \times 10^{-2} \times 314} = \frac{170}{1.57} \approx 108.$$

So about **108** turns (in practice one would wind 110 turns to allow for losses). Check the units: $\text{T m}^2 \text{ s}^{-1} = \text{Wb s}^{-1} = \text{V}$, as required.

EXERCISE 3 From AC to DC

A coil of 150 turns and area $5.0 \times 10^{-3} \text{ m}^2$ rotates at 1200 rpm in a field of 0.60 T, first with slip rings, then with a split-ring commutator. (a) Calculate the peak e.m.f. and the frequency. (b) Sketch the output e.m.f. in both cases over one full period. (c) Explain why the average value of the DC output is $\frac{2e_0}{\pi}$ and compute it.

SOLUTION Exercise 1

(a) $\omega = \frac{1200 \times 2\pi}{60} = 40\pi \approx 126 \text{ rad s}^{-1}$; $e_0 = NBA\omega = 150 \times 0.60 \times 5.0 \times 10^{-3} \times 126 \approx 57 \text{ V}$; $f = 20 \text{ Hz}$. (b) With slip rings: sinusoid $57 \sin(126 t)$. With commutator: the same curve with negative half-cycles reflected upwards, i.e. $|57 \sin(126 t)|$. (c) Averaging over a half-period: $\langle e \rangle = \frac{1}{\pi} \int_0^\pi e_0 \sin \theta d\theta = \frac{e_0}{\pi} [-\cos \theta]_0^\pi = \frac{2e_0}{\pi} \approx 36 \text{ V}$.

KEY POINTS Key points

- A coil rotating at angular frequency ω in a field B produces $e = NBA\omega \sin(\omega t)$, with peak e.m.f. $e_0 = NBA\omega$ (taking $t = 0$ with the coil plane perpendicular to $\vec{B}$).
- The e.m.f. is maximum when the coil plane is parallel to $\vec{B}$ (flux zero, rate of change of flux maximum) and zero when the coil plane is perpendicular to $\vec{B}$.
- Slip rings + brushes give an AC output; a split-ring commutator swaps the connections every half-turn and gives a pulsating DC output $|e_0 \sin(\omega t)|$.
- The induced current creates a torque opposing the rotation (Lenz's law): the mechanical work done against it is the source of the electrical energy.

- Practical generators use many turns, a laminated soft-iron core, electromagnets and several coils; alternators of this type power Cameroon from Songloulou and Edéa.

4 SELF- AND MUTUAL INDUCTANCE; THE L-R CIRCUIT AND STORED ENERGY

In the previous section we saw how a generator converts mechanical work into electrical energy by forcing a flux change through a coil. But a coil does not need an external moving magnet to experience induction: its own changing current changes the flux through itself, and two neighbouring coils can induce e.m.f.s in each other. These two ideas — **self-inductance** and **mutual inductance** — explain why the current in a circuit containing a coil cannot switch on instantly, why a spark jumps when you open a switch, and how much energy a current-carrying coil stores. They are also the working principle of transformers, which you will meet later.

4.1 Self-Inductance

Observation. Connect a coil in series with a lamp and a battery. When the switch is closed, the lamp brightens gradually over a fraction of a second; with a plain resistor instead of the coil, it lights instantly. The coil is opposing the growth of its own current. Where does this opposition come from? When the current I in the coil changes, the magnetic field it produces changes, so the flux through the coil itself changes. By Faraday's law, an e.m.f. is induced in the same coil, and by Lenz's law it opposes the change: it is called a **back e.m.f.**.

DEFINITION Self-inductance

The **self-inductance** L of a coil is the constant of proportionality between the flux linkage through the coil and the current producing it:

$$N\Phi = LI$$

where N is the number of turns and Φ the flux through one turn. The SI unit of L is the **henry** (H): a coil has an inductance of 1 H if a current of 1 A produces a flux linkage of 1 Wb turn. Equivalently, $1 \text{ H} = 1 \text{ V s A}^{-1}$. By Faraday's and Lenz's laws, the induced (back) e.m.f. is

$$e = -\frac{d(N\Phi)}{dt} = -L \frac{dI}{dt}.$$

The minus sign is Lenz's law: if I is increasing, e opposes the battery; if I is decreasing, e tries to maintain it. Note that L depends only on the geometry of the coil (number of turns, length, cross-section) and the core material — an iron core multiplies L enormously because of its large relative permeability.

PROPERTY Self-inductance of a long solenoid

For a long solenoid of length ℓ , cross-sectional area A , with N turns ($n = N/\ell$ turns per unit length), in air (or vacuum):

$$L = \mu_0 n^2 A \ell = \frac{\mu_0 N^2 A}{\ell}.$$

Derivation (examinable). A current I in a long solenoid gives a uniform internal field $B = \mu_0 nI$. The flux through one turn is $\Phi = BA = \mu_0 nIA$, so the flux linkage is

$$N\Phi = N\mu_0 nIA = \mu_0 n^2 A \ell I \quad (\text{since } N = n\ell).$$

Comparing with $N\Phi = LI$ gives $L = \mu_0 n^2 A \ell$. This shows explicitly that L grows with N^2 , with A , and decreases with ℓ .

4.2 Mutual Inductance

Observation. Wind two coils on the same soft-iron core (or place them coaxially close together). Pass a varying current I_1 through the first (the primary): a galvanometer connected to the second (the secondary) deflects, although the two coils are not electrically connected. Part of the flux produced by the primary links the secondary, and its variation induces an e.m.f. there. This is **mutual induction**.


DEFINITION Mutual inductance

The **mutual inductance** M between two coils is the constant of proportionality between the flux linkage in one coil and the current in the other:

$$N_2 \Phi_2 = M I_1 \quad \text{and} \quad N_1 \Phi_1 = M I_2,$$

where Φ_2 is the flux through one turn of coil 2 due to the current I_1 in coil 1 (and vice versa). It can be shown (reciprocity theorem) that the same constant M appears in both relations. The unit of M is the **henry** (H). The e.m.f. induced in the secondary is

$$e_2 = -M \frac{dI_1}{dt}.$$




Mutual inductance: the varying current I_1 in the primary creates a flux Φ_2 linking the secondary; the galvanometer G detects the induced e.m.f. $e_2 = -M dI_1/dt$.

KEY POINTS Meaning of L and M

L and M are constants of proportionality between flux linkage and current. They depend only on geometry (turns, sizes, separation) and on the core material — never on the actual value of the current. A shared iron core concentrates the flux and makes M large; moving the coils apart reduces M .

4.3 The L–R Circuit: Growth of Current



Series L–R circuit: battery E , switch K , resistor R , inductor L . The ammeter records $I(t)$; the voltmeter monitors the supply voltage.

Setting up the equation. Close the switch K at $t = 0$. At each instant, Kirchhoff's voltage law around the loop gives

$$E = RI + L \frac{dI}{dt},$$

since the inductor presents a back e.m.f. $L dI/dt$ opposing the battery. This is a first-order linear differential equation. Separating variables:

$$\frac{dI}{E - RI} = \frac{dt}{L} \implies -\frac{1}{R} \ln(E - RI) = \frac{t}{L} + C.$$

With the initial condition $I(0) = 0$ (the current through an inductor cannot jump discontinuously),

we find $C = -\frac{1}{R} \ln E$. Solving for I :

PROPERTY Growth of current in an L–R circuit


$$I(t) = I_0 (1 - e^{-t/\tau}), \quad I_0 = \frac{E}{R}, \quad \tau = \frac{L}{R}.$$

I_0 is the final steady current (when $dI/dt = 0$, the inductor behaves like a plain wire) and τ is the **time constant** of the circuit.

Physical meaning of τ . After a time $t = \tau$, $I = I_0(1 - e^{-1}) \approx 0.63 I_0$: the current has reached 63% of its final value. After $t = 5\tau$, $I \approx 0.993 I_0$ — the growth is practically complete. A large L or a small R makes the growth slow.

4.4 Decay of Current

Suppose the current has reached I_0 and the battery is then removed from the circuit (the switch connects the coil and resistor in a closed loop without the source).




Decay circuit: the battery is replaced by a short circuit; the inductor discharges through the resistor.

Kirchhoff's law now gives

$$L \frac{dI}{dt} + RI = 0 \implies \frac{dI}{I} = -\frac{R}{L} dt \implies I(t) = I_0 e^{-t/\tau}.$$

The inductor opposes the decrease: it releases its stored energy to keep the current flowing, and the current dies away exponentially. After one time constant, $I = I_0 e^{-1} \approx 0.37 I_0$.



Growth and decay of current in an L - R circuit. At $t = \tau$ the growing current reaches $0.63 I_0$ and the decaying current has fallen to $0.37 I_0$.

WARNING The spark at switch opening

If you simply open a switch in a highly inductive circuit, di/dt becomes enormous and the back e.m.f. $e = -L di/dt$ can reach thousands of volts: a spark jumps across the switch contacts. This is why engineers place a protective diode (flyback diode) in parallel with the coil of a relay: when the switch opens, the coil's current circulates through the diode and decays gently instead of sparking.

4.5 Energy Stored in an Inductor

While the current grows, the inductor absorbs energy from the source and stores it in its magnetic field. The instantaneous power absorbed by the inductor is

$$P = e_{\text{absorbed}} I = L \frac{dI}{dt} I.$$

The total energy stored as the current rises from 0 to I is

$$E = \int_0^I LI' dI' = \frac{1}{2} LI^2.$$

PROPERTY Energy stored in an inductor

$$E = \frac{1}{2} LI^2 \quad (\text{joules, with } L \text{ in H and } I \text{ in A}).$$

This is the magnetic analogue of the energy $\frac{1}{2} CV^2$ stored in a capacitor's electric field. The

proof by integration of power, as above, is examinable.

METHOD Solving L–R problems

1. Write Kirchhoff's equation for the loop: $E = RI + L \, di/dt$ (growth) or $RI + L \, di/dt = 0$ (decay).
2. Identify the steady current $I_0 = E/R$ and the time constant $\tau = L/R$.
3. Use the exponential solution: $I = I_0(1 - e^{-t/\tau})$ for growth, $I = I_0 e^{-t/\tau}$ for decay; differentiate if the back e.m.f. is asked.
4. Check the limits: at $t = 0$ the growth current is 0; as $t \rightarrow \infty$ it tends to I_0 . If your formula violates these, it is wrong.

WORKED EXAMPLE 8 Growth, time constant and stored energy

A coil of inductance $L = 0.40 \text{ H}$ and negligible resistance is connected in series with a resistor $R = 20 \, \Omega$, a switch and a battery of e.m.f. $E = 12 \text{ V}$. The switch is closed at $t = 0$.

- (a) Find the time constant and the final steady current.
- (b) Find the current at $t = 30 \text{ ms}$ and the back e.m.f. at that instant.
- (c) Find the energy stored in the coil when the current is steady.

SOLUTION

Solution.

$$(a) \tau = \frac{L}{R} = \frac{0.40}{20} = 0.020 \text{ s} = 20 \text{ ms}; \quad I_0 = \frac{E}{R} = \frac{12}{20} = 0.60 \text{ A}.$$

$$(b) I = I_0(1 - e^{-t/\tau}) = 0.60(1 - e^{-30/20}) = 0.60(1 - e^{-1.5}) = 0.60(1 - 0.223) \approx 0.47 \text{ A}.$$

$$\text{Back e.m.f.: } e = L \frac{dI}{dt} = E - RI = 12 - 20 \times 0.47 \approx 2.7 \text{ V}.$$

$$(c) E_{\text{stored}} = \frac{1}{2} L I_0^2 = \frac{1}{2} \times 0.40 \times (0.60)^2 = 0.072 \text{ J}.$$

WARNING Common mistakes

- The current through an inductor cannot change instantaneously: at $t = 0$ during growth, $I = 0$, not E/R . Writing $I = E/R$ at $t = 0$ is the classic GCE error.
- Do not confuse $\tau = L/R$ (inductor) with $\tau = RC$ (capacitor).
- In $e = -L \, di/dt$, the back e.m.f. is largest at $t = 0$ (equal to E) and falls to zero as the

current stabilises — not the other way round.

- Energy is $\frac{1}{2}LI^2$: forgetting the factor $\frac{1}{2}$ or squaring L instead of I are frequent slips.

EXERCISE 4 Decay and graph reading

A coil of inductance 0.10 H carries a steady current of 2.0 A in series with a $5.0\ \Omega$ resistor. The source is suddenly replaced by a short circuit, so the current decays through the resistor.

- Write the expression for $I(t)$ and give the time constant.
- Calculate the current at $t = 40\text{ ms}$.
- Calculate the energy stored initially, and state what becomes of it.

SOLUTION Exercise 1

- $I(t) = I_0 e^{-t/\tau}$ with $I_0 = 2.0\text{ A}$ and $\tau = L/R = 0.10/5.0 = 0.020\text{ s}$.
- $I = 2.0 e^{-40/20} = 2.0 e^{-2} = 2.0 \times 0.135 \approx 0.27\text{ A}$.
- $E = \frac{1}{2}LI_0^2 = \frac{1}{2} \times 0.10 \times (2.0)^2 = 0.20\text{ J}$. This magnetic energy is dissipated as heat in the resistor as the current decays.

DID YOU KNOW? Inductors in everyday Cameroon

The fluorescent lamp chokes used in many classrooms and homes are simply large inductors: they limit the current through the tube once it is lit, and they provide the high voltage spike (via $e = -L di/dt$) needed to start the discharge. The same principle, mutual inductance this time, is at work in the transformers that step down ENEO's high-voltage lines to the 220 V supplied to your house.

5 INTEGRATION ACTIVITY

5.1 Aims of the activity

This integration activity closes the chapter on electromagnetic induction by placing you in the role of a young engineer. Working in groups, you will design a simple bicycle dynamo capable of charging mobile phones in a village without grid electricity. By the end of the activity you should be able to:

- apply **Faraday's law** and the rotating-coil formula $E_0 = NBA\omega$ to a concrete design problem;
- interpret the sinusoidal output of a simple **AC generator** and relate its frequency to the rotation speed;
- use **Lenz's law** to explain the back-torque that a loaded generator exerts on the cyclist;
- compute the **time constant** $\tau = L/R$ of an L - R circuit and the **energy stored in an inductor** $W = \frac{1}{2}LI^2$;
- argue, quantify, justify and communicate a technical solution on a poster, as expected at the GCE Advanced Level.

5.2 Situation

EXPERIMENT The Nkongsamba phone-charging project

The village of Bakassa, near Nkongsamba in the Littoral Region, is not yet connected to the national grid. The nearest charging point is a commercial generator 8 km away, and villagers pay for each phone charge. The science club of the local secondary school decides to build a bicycle-powered charging station: a cyclist pedals, the wheel drives a small coil which spins between the poles of a permanent magnet, and the induced e.m.f. charges phones through a simple regulating circuit.

The club has salvaged the following components:

- a permanent magnet giving an approximately uniform field $B = 0.20 \text{ T}$ between its poles;
- copper wire, to be wound into a flat rectangular coil of area $A = 20 \text{ cm}^2 = 2.0 \times 10^{-3} \text{ m}^2$;
- a belt drive allowing a fit cyclist to spin the coil at up to 300 revolutions per minute;
- a rectifier and regulating circuit whose total resistance, together with the coil, is $R = 10 \Omega$; the coil itself has a self-inductance $L = 50 \text{ mH}$.

The phone battery requires a rectified supply whose peak e.m.f. should be about 6 V. The club must decide how many turns N to wind, predict the output waveform, understand why pedalling “bites back” when a phone is connected, and check the behaviour of the coil in the DC part of the circuit. You are the consulting physicists: produce the calcula-

tions and a poster justifying every step.

5.3 Tasks

1. **Choosing the number of turns.** Convert the rotation speed into angular velocity ω in rad s^{-1} . Using the peak e.m.f. of a rotating coil, $E_0 = NBA\omega$, determine the number of turns N needed for $E_0 \approx 6 \text{ V}$. Round to a realistic whole number of turns.
2. **Output waveform.** Write the instantaneous e.m.f. $E(t)$, sketch E against time for two full cycles, and state the frequency f and period T of the output. Mark the instants when the coil plane is parallel to the field.
3. **Lenz's law and the cyclist.** When no phone is connected, the coil circuit is open and pedalling is easy. When a phone draws current, pedalling becomes noticeably harder. Using Lenz's law, explain the origin of the extra resistive torque, and state where the extra energy goes.
4. **The coil as an inductor.** In the DC (rectified) part of the circuit, the coil of inductance $L = 50 \text{ mH}$ is in series with the total resistance $R = 10 \Omega$.
 - (a) Compute the time constant τ of this L - R circuit and interpret its meaning for the growth of the current.
 - (b) Compute the magnetic energy stored in the coil when the steady current is $I = 0.5 \text{ A}$.
5. **Improving the design.** Propose one modification that would increase the peak e.m.f., and justify it using the formula $E_0 = NBA\omega$. Discuss briefly one practical drawback of your proposal.
6. **Poster.** Assemble your results (calculations, graph, explanations) on a poster and present them to the class in five minutes.

5.4 Model answer

Task 1 — Number of turns.

The angular velocity corresponding to 300 revolutions per minute is

$$\omega = \frac{300 \times 2\pi}{60} = 10\pi \approx 31.4 \text{ rad s}^{-1}.$$

From $E_0 = NBA\omega$,

$$N = \frac{E_0}{BA\omega} = \frac{6}{0.20 \times 2.0 \times 10^{-3} \times 31.4} \approx 4.8 \times 10^2.$$

KEY POINTS Design choice

Wind about $N \approx 480$ turns (say 500 turns to allow for losses). Fewer turns would leave the peak e.m.f. below the 6 V target.

Task 2 — Output waveform.


Take $t = 0$ when the coil plane is perpendicular to $\vec{B}$, so that the flux through one turn is $\Phi = BA \cos \omega t$ and the **flux linkage** is $N\Phi = NBA \cos \omega t$. Faraday's law then gives

$$E(t) = -\frac{d(N\Phi)}{dt} = NBA\omega \sin \omega t = E_0 \sin \omega t, \quad E_0 \approx 6 \text{ V}.$$

The frequency is

$$f = \frac{\omega}{2\pi} = \frac{300}{60} = 5.0 \text{ Hz}, \quad T = \frac{1}{f} = 0.20 \text{ s}.$$

The e.m.f. is zero when the coil plane is perpendicular to $\vec{B}$ (flux maximum, but momentarily not changing) and maximum when the coil plane is parallel to $\vec{B}$ (flux zero but changing fastest). On the graph below, the instants $t = 0.05 \text{ s}$, 0.15 s , 0.25 s and 0.35 s (peaks and troughs) correspond to the coil plane being parallel to $\vec{B}$.



Sinusoidal output of the dynamo: $E(t) = 6 \sin(10\pi t)$, frequency 5.0 Hz, period 0.20 s. The orange dots mark the instants when the coil plane is parallel to the field.

Task 3 — Lenz's law and the back-torque.

With the circuit open, no current flows: the coil experiences only friction, so pedalling is easy. When a phone is connected, the induced e.m.f. drives a current I around the coil. By **Lenz's law**, this induced current must oppose the change that produces it: the magnetic forces on the current-carrying sides of the coil create a **braking torque** opposing the rotation. The cyclist must therefore work against this torque. Energy is conserved: the extra muscular work done by the cyclist is transferred to the phone battery (and partly dissipated as heat in R). The harder the phone charges (larger I), the larger the braking torque — the dynamo never gives energy for free.

Task 4 — The coil as an inductor.

(a) The time constant of the L - R circuit is

$$\tau = \frac{L}{R} = \frac{50 \times 10^{-3}}{10} = 5.0 \times 10^{-3} \text{ s} = 5.0 \text{ ms}.$$

When the rectified supply is switched on, the current grows according to $i(t) = I_0(1 - e^{-t/\tau})$: it reaches about 63 % of its final value after 5 ms, and is practically steady after $5\tau \approx 25 \text{ ms}$. The inductor smooths the charging current — a useful side-effect for the phone.

(b) At $I = 0.5 \text{ A}$, the magnetic energy stored in the coil is

$$W = \frac{1}{2}LI^2 = \frac{1}{2} \times 50 \times 10^{-3} \times (0.5)^2 = 6.25 \times 10^{-3} \text{ J} \approx 6.3 \text{ mJ}.$$

Task 5 — Improving the design.

Since $E_0 = NBA\omega$, the peak e.m.f. can be raised by increasing any one of N , B , A or ω . A practical suggestion: **fit a stronger neodymium magnet** (from an old loudspeaker or hard-disk drive), raising B from 0.20 T to about 0.40 T , which would double E_0 to about 12 V without adding turns. Drawback: stronger magnets are costlier, and the larger back-torque (Lenz's law) makes pedalling harder when the phone is connected — the energy must always come from the cyclist. (Equally acceptable: doubling N to about 1000 turns, at the cost of a heavier coil and a larger resistance.)

WARNING Common mistakes to avoid on the poster

- Forgetting to convert revolutions per minute into rad s^{-1} : $\omega = 2\pi f$ with f in hertz, not 300 rad s^{-1} !
- Mixing up cm^2 and m^2 : $20 \text{ cm}^2 = 2.0 \times 10^{-3} \text{ m}^2$.
- Writing $\tau = R/L$ instead of $\tau = L/R$ — check with units: henry per ohm gives seconds.
- Believing the dynamo “creates” energy: Lenz's law guarantees that every joule delivered to the phone is paid for by the cyclist's muscles.

METHOD Assessment guide for the poster

1. Correct use of $E_0 = NBA\omega$ with unit conversions (2 marks).
2. Correct sinusoidal sketch with labelled amplitude, period and frequency (2 marks).
3. Lenz's-law explanation of the braking torque, linked to energy conservation (2 marks).
4. Correct $\tau = L/R = 5.0 \text{ ms}$ and $W = \frac{1}{2}LI^2 = 6.3 \text{ mJ}$ with units (2 marks).
5. A justified, realistic improvement and its drawback; clarity of presentation (2 marks).

DID YOU KNOW? Did you know?

Bicycle dynamos of this kind have powered lamps in Cameroonian towns and villages for decades, and hand-cranked or pedal chargers remain vital in off-grid areas of the Far North and East Regions. The same physics — a coil spinning in a magnetic field — is scaled up enormously at the Song Loulou and Edea hydroelectric stations on the Sanaga river, where

turbines spin huge rotors to supply the national grid. From a bicycle in Bakassa to a dam on the Sanaga, it is always Faraday's law at work.

6 METHODS AND WORKED EXAMPLES

6.1 Methods and Worked Examples

METHOD Calculating Magnetic Flux and Applying Faraday's Law

1. Identify the surface and its orientation. Define the area vector $\vec{A}$ (magnitude A , direction normal to the plane). Determine the angle θ between $\vec{B}$ and $\vec{A}$.
2. Write the magnetic flux. For a uniform field: $\Phi = BA \cos \theta$. For a coil of N turns: $\Phi_{\text{total}} = N\Phi = NBA \cos \theta$.
3. Determine the rate of change. Identify what varies with time: B , A , or θ (or a combination). Compute $\frac{d\Phi}{dt}$ or $\frac{\Delta\Phi}{\Delta t}$ for average values.
4. Apply Faraday's Law. The magnitude of the induced e.m.f. is $E = \left| \frac{d\Phi_{\text{total}}}{dt} \right| = \left| N \frac{d\Phi}{dt} \right|$.
5. Check units. $1 \text{ Wb} = 1 \text{ T m}^2$, $1 \text{ V} = 1 \text{ Wb s}^{-1}$.

WORKED EXAMPLE 9 Magnetic Flux through a Rotating Coil

A circular coil of 200 turns has a radius of 5.0 cm. It is placed in a uniform magnetic field of flux density 0.80 T. Calculate the magnetic flux linkage through the coil when: (a) the plane of the coil is perpendicular to the field; (b) the plane of the coil is at 30° to the field; (c) the plane of the coil is parallel to the field. If the coil is rotated from position (a) to position (c) in 0.25 s, calculate the average e.m.f. induced in the coil.

SOLUTION

Solution.

- Data: $N = 200$, $r = 5.0 \text{ cm} = 0.050 \text{ m}$, $B = 0.80 \text{ T}$, $\Delta t = 0.25 \text{ s}$.
- Area: $A = \pi r^2 = \pi(0.050)^2 = 7.854 \times 10^{-3} \text{ m}^2$.
- Angle definition: θ is the angle between $\vec{B}$ and the normal to the plane (area vector $\vec{A}$).

(a) Plane $\perp$ field $\Rightarrow$ Normal $\parallel$ field $\Rightarrow \theta = 0^\circ$.

$$\Phi = BA \cos 0^\circ = (0.80)(7.854 \times 10^{-3})(1) = 6.283 \times 10^{-3} \text{ Wb}$$

$$\text{Flux linkage} = N\Phi = 200 \times 6.283 \times 10^{-3} = \boxed{1.26 \text{ Wb (or Vs)}}$$

(b) Plane at 30° to field $\Rightarrow$ Normal at 60° to field $\Rightarrow \theta = 60^\circ$.

$$\Phi = BA \cos 60^\circ = (0.80)(7.854 \times 10^{-3})(0.5) = 3.142 \times 10^{-3} \text{ Wb}$$

$$\text{Flux linkage} = 200 \times 3.142 \times 10^{-3} = \boxed{0.628 \text{ Wb}}.$$

(c) Plane $\parallel$ field $\Rightarrow$ Normal $\perp$ field $\Rightarrow \theta = 90^\circ$.

$$\Phi = BA \cos 90^\circ = 0 \quad \Rightarrow \quad \text{Flux linkage} = \boxed{0 \text{ Wb}}.$$

Average e.m.f. from (a) to (c):

$$E_{\text{avg}} = \left| N \frac{\Delta\Phi}{\Delta t} \right| = \left| 200 \times \frac{0 - 6.283 \times 10^{-3}}{0.25} \right| = \frac{1.2566}{0.25} = \boxed{5.03 \text{ V}}.$$

METHOD Applying Lenz's Law and Motional E.M.F. ($E = Blv$)

1. Draw the situation. Show $\vec{B}$, the conductor (length l), velocity $\vec{v}$, and the circuit loop (real or imaginary).
2. Determine the change in flux. Is the area of the loop increasing or decreasing? Is the flux entering or leaving the page?
3. Apply Lenz's Law: The induced current flows in a direction such that its magnetic field opposes the change in flux that produced it.
4. Find current direction. Use the Right-Hand Grip Rule: thumb along the induced $\vec{B}_{\text{ind}}$ (opposing the change), fingers curl in direction of I_{ind} .
5. Calculate magnitude. For a straight rod moving perpendicular to $\vec{B}$: $E = Blv$. If $\vec{v}$ is at angle θ to $\vec{B}$: $E = Blv \sin \theta$ (component of $v \perp B$). If rod is at angle ϕ to $\vec{v}$: $E = Blv \sin \phi$ (effective length $\perp v$). General: $E = (\vec{v} \times \vec{B}) \cdot \vec{l}$.
6. Polarity. The end of the rod where positive charge accumulates is at higher potential. Use $\vec{F}_q = q(\vec{v} \times \vec{B})$ on free electrons ($q = -e$) to find which end becomes negative.

WORKED EXAMPLE 10 Motional E.M.F. in a Moving Rod on Rails

A horizontal rod PQ of length 0.40 m and resistance 2.0Ω slides at a constant speed of 5.0 m s^{-1} along two parallel vertical rails separated by 0.40 m . The rails are connected at the bottom by a resistor $R = 3.0 \Omega$. The whole apparatus is in a uniform vertical magnetic field of flux density 0.50 T directed downwards. (a) Calculate the induced e.m.f. in the rod. (b) Find the magnitude and direction of the induced current. (c) Calculate the magnetic force acting on the rod due to this current. (d) What external force is required to keep the rod moving at constant speed? (e) Calculate the power dissipated in the circuit and the rate of work done by the external force.

SOLUTION

Solution.

- Setup: Rod moves horizontally (say to the right). $\vec{B}$ downwards. Rails vertical $\Rightarrow$ loop area increases horizontally.

(a) Induced e.m.f.: $\vec{v} \perp \vec{B}$, rod $\perp \vec{v}$ and $\perp \vec{B}$.

$$E = Blv = (0.50)(0.40)(5.0) = \boxed{1.0 \text{ V}}.$$

(b) Current magnitude and direction. Total resistance $R_{\text{tot}} = 2.0 + 3.0 = 5.0 \Omega$.

$$I = \frac{E}{R_{\text{tot}}} = \frac{1.0}{5.0} = \boxed{0.20 \text{ A}}.$$

Direction (Lenz's Law): Rod moves right $\Rightarrow$ Area increases $\Rightarrow$ Flux downwards increases. Induced $\vec{B}_{\text{ind}}$ must be upwards to oppose. Right-hand grip rule: Thumb up $\Rightarrow$ fingers curl anticlockwise (viewed from above). Current flows $P \rightarrow Q$ along the rod (if P is left, Q right), down the right rail, through R , up the left rail.

Polarity (Lorentz force on electrons): $\vec{F} = -e(\vec{v} \times \vec{B})$. Take coordinates: x right, y up, z out of page. $\vec{v} = v\hat{i}$, $\vec{B} = -B\hat{j}$, so $\vec{v} \times \vec{B} = -vB(\hat{i} \times \hat{j}) = -vB\hat{k}$ (into page). The force on electrons ($q = -e$) is $+evB\hat{k}$ (out of page): electrons accumulate at the end facing out of the page, which becomes negative; the opposite end is positive. Conventional current inside the rod flows from the negative end to the positive end, i.e. in the direction of $\vec{v} \times \vec{B}$.

(c) Magnetic force on rod: $\vec{F}_B = I\vec{l} \times \vec{B}$. $I = 0.20 \text{ A}$, $\vec{l}$ along the rod, $\vec{B}$ down. The cross product gives a force directed opposite to the velocity (as Lenz's law requires). Magnitude: $F_B = Bil = (0.50)(0.20)(0.40) = \boxed{0.040 \text{ N}}$ opposing the motion.

(d) External force: Constant velocity $\Rightarrow$ Net force = 0. $\vec{F}_{\text{ext}} + \vec{F}_B = 0 \Rightarrow \vec{F}_{\text{ext}} = -\vec{F}_B$.

$$F_{\text{ext}} = \boxed{0.040 \text{ N}} \text{ in the direction of motion.}$$

(e) Power balance. Power dissipated (Joule heating): $P_{\text{diss}} = I^2 R_{\text{tot}} = (0.20)^2(5.0) = \boxed{0.20 \text{ W}}$. Rate of work by external force: $P_{\text{ext}} = F_{\text{ext}} v = (0.040)(5.0) = \boxed{0.20 \text{ W}}$. Check: $P_{\text{ext}} = P_{\text{diss}}$. Mechanical work is converted to electrical energy then heat. Energy conserved.

METHOD Analysing AC and DC Generators

1. Visualise the rotation. A coil of N turns, area A , rotates at constant angular velocity ω in uniform $\vec{B}$.
2. Flux linkage: $\Phi_N = NBA \cos \theta = NBA \cos(\omega t)$ (assuming $\theta = 0$ at $t = 0$, flux max).
3. Induced e.m.f. (Faraday): $E = -\frac{d\Phi_N}{dt} = NBA\omega \sin(\omega t) = E_0 \sin(\omega t)$.

4. Peak e.m.f.: $E_0 = NBA\omega = 2\pi fNBA$.
5. RMS values: $E_{\text{rms}} = E_0/\sqrt{2}$, $I_{\text{rms}} = I_0/\sqrt{2}$ (for purely resistive load).
6. DC Generator (Commutator): Split-ring commutator reverses connections every half-turn. Output is $|E_0 \sin(\omega t)|$ (pulsating DC). Brushes contact when coil plane $\parallel \vec{B}$ (flux zero, rate of change max).
7. AC Generator (Slip rings): Continuous rings $\Rightarrow$ sinusoidal AC output.

WORKED EXAMPLE 11 Design Parameters of an AC Generator

An AC generator consists of a rectangular coil of 500 turns, each of area $2.5 \times 10^{-2} \text{ m}^2$, rotating at 50 rev s^{-1} in a uniform magnetic field of flux density 0.40 T . The coil has a total resistance of 10Ω and is connected to a purely resistive load of 40Ω . (a) Calculate the peak e.m.f. and the r.m.s. e.m.f. generated. (b) Write the equation for the instantaneous e.m.f. assuming $E = 0$ at $t = 0$ and increasing positively. (c) Calculate the r.m.s. current in the circuit. (d) Determine the average power dissipated in the load resistor. (e) If the generator runs at the same speed but the magnetic field is doubled, what happens to the peak e.m.f. and the r.m.s. current?

SOLUTION

Solution. Data: $N = 500$, $A = 2.5 \times 10^{-2} \text{ m}^2$, $f = 50 \text{ Hz}$, $B = 0.40 \text{ T}$, $R_{\text{coil}} = 10 \Omega$, $R_{\text{load}} = 40 \Omega$.
 $\omega = 2\pi f = 100\pi \text{ rad s}^{-1}$.

(a) Peak and RMS e.m.f.:

$$E_0 = NBA\omega = 500 \times 0.40 \times (2.5 \times 10^{-2}) \times (100\pi) = 500\pi \approx \boxed{1570 \text{ V}}.$$

$$E_{\text{rms}} = \frac{E_0}{\sqrt{2}} = \frac{1570}{\sqrt{2}} \approx \boxed{1110 \text{ V}}.$$

(b) Instantaneous e.m.f.: $E = 0$ at $t = 0$, increasing $\Rightarrow$ sine function.

$$E(t) = E_0 \sin(\omega t) = \boxed{1570 \sin(100\pi t) \text{ V}}.$$

(c) RMS current: Total resistance $R_T = 10 + 40 = 50 \Omega$.

$$I_{\text{rms}} = \frac{E_{\text{rms}}}{R_T} = \frac{1110}{50} = \boxed{22.2 \text{ A}}.$$

(d) Average power in load: $P_{\text{avg}} = I_{\text{rms}}^2 R_{\text{load}} = (22.2)^2 \times 40 = 492.8 \times 40 \approx \boxed{19.7 \text{ kW}}$.

(e) Effect of doubling B : $E_0 \propto B \Rightarrow E'_0 = 2E_0 = \boxed{3140 \text{ V}}$. $I_{\text{rms}} \propto E_{\text{rms}} \propto B \Rightarrow I'_{\text{rms}} = 2I_{\text{rms}} = \boxed{44.4 \text{ A}}$.

METHOD Self-Inductance and the L-R Circuit (Growth/Decay)

1. Define Self-Inductance L . $\Phi_N = LI$ (flux linkage proportional to current). Unit: Henry (H) = Vs A^{-1} . For a long solenoid: $L = \mu_0 n^2 Al = \mu_0 N^2 A / l$.
2. Back e.m.f.: $E_L = -L \frac{dI}{dt}$. Opposes the change in current (Lenz's law applied to own field).
3. L-R Circuit Equation (Growth): Switch closed at $t = 0$. $E = IR + L \frac{dI}{dt}$.
4. Solution (Growth): $I(t) = \frac{E}{R} (1 - e^{-t/\tau})$ where $\tau = \frac{L}{R}$ (time constant).
5. Key instants: $t = 0$: $I = 0$, $V_L = E$, $V_R = 0$. $t \rightarrow \infty$: $I = E/R$, $V_L = 0$, $V_R = E$. $t = \tau$: $I = 0.632(E/R)$.
6. Decay: Switch opened (or source shorted). $0 = IR + L \frac{dI}{dt} \Rightarrow I(t) = I_0 e^{-t/\tau}$. $t = \tau$: $I = 0.368 I_0$.
7. Energy Stored: $U = \frac{1}{2} LI^2$. Derived from $P = E_L I = LI \frac{dI}{dt} = \frac{d}{dt} (\frac{1}{2} LI^2)$.

WORKED EXAMPLE 12 Transient Analysis of an L-R Circuit

A coil of inductance $L = 2.0 \text{ H}$ and resistance $R = 10 \Omega$ is connected to a battery of e.m.f. $E = 12 \text{ V}$ and negligible internal resistance. (a) Calculate the time constant of the circuit. (b) Determine the initial rate of increase of current ($\frac{dI}{dt}$ at $t = 0$). (c) Find the current and the potential difference across the inductor at $t = 0.10 \text{ s}$. (d) Calculate the energy stored in the magnetic field of the inductor when the current reaches its steady-state value. (e) The battery is suddenly disconnected and the coil is short-circuited (connected across a wire of zero resistance). Write the equation for the decaying current and find the time for the current to fall to 1.0 A .

SOLUTION

Solution. Data: $L = 2.0 \text{ H}$, $R = 10 \Omega$, $E = 12 \text{ V}$.

(a) Time constant:

$$\tau = \frac{L}{R} = \frac{2.0}{10} = \boxed{0.20 \text{ s}}.$$

(b) Initial rate of increase: At $t = 0$, $I = 0$, so $V_R = 0$. Loop rule: $E = V_L = L \frac{dI}{dt}$.

$$\left. \frac{dI}{dt} \right|_{t=0} = \frac{E}{L} = \frac{12}{2.0} = \boxed{6.0 \text{ A s}^{-1}}.$$

(c) At $t = 0.10 \text{ s}$ ($t = 0.5\tau$): Steady current $I_0 = E/R = 12/10 = 1.2 \text{ A}$.

$$I(t) = I_0 (1 - e^{-t/\tau}) = 1.2(1 - e^{-0.5}) = 1.2(1 - 0.6065) = \boxed{0.472 \text{ A}}.$$

P.D. across inductor: $V_L = L \frac{dI}{dt} = E - IR = 12 - (0.472 \times 10) = 12 - 4.72 = \boxed{7.28 \text{ V}}$. (Check: $V_L = E e^{-t/\tau} = 12 e^{-0.5} = 7.28 \text{ V}$).

(d) Energy stored at steady state ($I = I_0 = 1.2 \text{ A}$):

$$U = \frac{1}{2} L I_0^2 = \frac{1}{2} \times 2.0 \times (1.2)^2 = 1.0 \times 1.44 = \boxed{1.44 \text{ J}}.$$

(e) Decay (short-circuited): Initial current $I_0 = 1.2 \text{ A}$. Equation: $I(t) = I_0 e^{-t/\tau}$. Find t when $I = 1.0 \text{ A}$.

$$1.0 = 1.2 e^{-t/0.20} \Rightarrow e^{-t/0.20} = \frac{1.0}{1.2} = \frac{5}{6} \approx 0.8333.$$

$$-\frac{t}{0.20} = \ln(0.8333) \approx -0.1823 \Rightarrow t = 0.20 \times 0.1823 = \boxed{0.0365 \text{ s}} \text{ (36.5 ms)}.$$

METHOD Mutual Inductance and Transformer Principles

1. Define Mutual Inductance M . Coil 1 (primary) carries I_1 , creates flux Φ_{21} linking coil 2 (secondary). $\Phi_{21} \propto I_1 \Rightarrow N_2 \Phi_{21} = M I_1$. Unit: Henry (H). M depends on geometry, distance, orientation, and core material (μ_r).
2. Reciprocity Theorem: $M_{12} = M_{21} = M$. $N_1 \Phi_{12} = M I_2$.
3. Induced e.m.f. in secondary: $E_2 = -M \frac{dI_1}{dt}$. Magnitude: $|E_2| = M \left| \frac{dI_1}{dt} \right|$.
4. Coupling Coefficient k : $M = k \sqrt{L_1 L_2}$, where $0 \leq k \leq 1$. $k = 1$ for perfect coupling (ideal transformer).
5. Ideal Transformer (No losses, $k = 1$, infinite L): $\frac{V_s}{V_p} = \frac{N_s}{N_p} = \frac{I_p}{I_s}$. Power in = Power out:
 $V_p I_p = V_s I_s$.
6. Step-up/Step-down: $N_s > N_p \Rightarrow$ Step-up (Voltage increases, Current decreases).
 $N_s < N_p \Rightarrow$ Step-down.

WORKED EXAMPLE 13 Mutual Inductance and Transformer Calculations

Two coils are wound on a common ferromagnetic core. The primary coil has $N_p = 2000$ turns and inductance $L_p = 4.0 \text{ H}$. The secondary coil has $N_s = 500$ turns. The coupling coefficient is $k = 0.95$. (a) Calculate the self-inductance of the secondary coil L_s . (b) Calculate the mutual inductance M . (c) An alternating current $I_p = 2.0 \sin(100\pi t) \text{ A}$ flows in the primary. Determine the amplitude of the e.m.f. induced in the secondary. (d) If the secondary is connected to a resistive load of 10Ω , calculate the r.m.s. current in the sec-

ondary, assuming the induced e.m.f. of part (c) acts as the source for the secondary circuit. (e) Explain why the primary current would increase if the secondary load resistance is decreased.

SOLUTION

Solution. (a) Self-inductance L_s : For coils on the same core, $L \propto N^2$ (assuming same geometry, length, area, μ).

$$\frac{L_s}{L_p} = \left(\frac{N_s}{N_p}\right)^2 \Rightarrow L_s = L_p \left(\frac{N_s}{N_p}\right)^2 = 4.0 \times \left(\frac{500}{2000}\right)^2 = 4.0 \times \frac{1}{16} = \boxed{0.25 \text{ H}}.$$

(b) Mutual Inductance M :

$$M = k\sqrt{L_p L_s} = 0.95 \times \sqrt{4.0 \times 0.25} = 0.95 \times \sqrt{1.0} = \boxed{0.95 \text{ H}}.$$

(Note: For perfect coupling $k = 1$, $M = \sqrt{L_p L_s} = 1.0 \text{ H}$. Also $M = k \frac{N_s}{N_p} L_p = 0.95 \times \frac{1}{4} \times 4.0 = 0.95 \text{ H}$. Consistent.)

(c) Induced e.m.f. amplitude in secondary: $I_p = I_0 \sin(\omega t)$ with $I_0 = 2.0 \text{ A}$, $\omega = 100\pi \text{ rad s}^{-1}$.
 $\frac{dI_p}{dt} = I_0 \omega \cos(\omega t)$. Max magnitude = $I_0 \omega$.

$$E_{s0} = M \left| \frac{dI_p}{dt} \right|_{\max} = M I_0 \omega = 0.95 \times 2.0 \times 100\pi = 190\pi \approx \boxed{597 \text{ V}}.$$

(d) Secondary RMS current: The induced e.m.f. of part (c) acts as the AC source for the secondary loop (standard GCE simplification: leakage and coil resistance neglected).

$$V_{s,\text{rms}} = E_{s,\text{rms}} = \frac{E_{s0}}{\sqrt{2}} = \frac{597}{\sqrt{2}} \approx 422 \text{ V}.$$

Load $R_L = 10 \Omega$.

$$I_{s,\text{rms}} = \frac{V_{s,\text{rms}}}{R_L} = \frac{422}{10} = \boxed{42.2 \text{ A}}.$$

(e) Primary current increase with load: When secondary load R_L decreases, I_s increases. The secondary current creates a magnetic flux opposing the primary flux (Lenz's Law). This reduces the net flux in the core, which reduces the back e.m.f. in the primary. With reduced back e.m.f., the primary current I_p increases (drawn from the source) to restore the flux balance. The primary current has two components: a magnetizing component (lagging 90°) and a load component (in phase with V_p , reflected from the secondary).

METHOD**Energy Stored in an Inductor and Magnetic Energy Density**

1. Work done against back e.m.f.: To establish current I in an inductor L , the source does work against $E_L = -LdI/dt$. Power $P = E_L I = LI \frac{dI}{dt}$.
2. Total Energy: $U = \int_0^I P dt = \int_0^I LI dI = \frac{1}{2} LI^2$.
3. Magnetic Energy Density: For a solenoid, $U = \frac{1}{2}(\mu_0 n^2 Al)I^2$. Volume $V = Al$. Magnetic field $B = \mu_0 nI$.

$$u = \frac{U}{V} = \frac{\frac{1}{2}\mu_0 n^2 Al I^2}{Al} = \frac{1}{2}\mu_0 n^2 I^2 = \frac{1}{2} \frac{B^2}{\mu_0} \quad (\text{in vacuum/air}).$$

In a material with permeability $\mu = \mu_0 \mu_r$: $u = \frac{1}{2} \frac{B^2}{\mu} = \frac{1}{2} BH$.

4. Application: Energy stored in the magnetic field of a transformer core, or in the stray inductance of cables (surge protection).

WORKED EXAMPLE 14 Energy in a Solenoid and Magnetic Energy Density

A long air-cored solenoid has length $l = 0.50$ m, cross-sectional area $A = 4.0 \times 10^{-4}$ m², and $N = 1000$ turns. It carries a current $I = 2.0$ A. (a) Calculate the self-inductance L of the solenoid. (b) Calculate the magnetic flux density B inside the solenoid. (c) Determine the total energy stored in the magnetic field using both $U = \frac{1}{2} LI^2$ and the energy density formula $u = \frac{B^2}{2\mu_0}$. (d) If the current is reduced to zero uniformly in 1.0 ms, calculate the average magnitude of the induced e.m.f. across the solenoid.

SOLUTION

Solution. Constants: $\mu_0 = 4\pi \times 10^{-7}$ H m⁻¹. Data: $l = 0.50$ m, $A = 4.0 \times 10^{-4}$ m², $N = 1000$, $I = 2.0$ A.

(a) Self-inductance L :

$$L = \frac{\mu_0 N^2 A}{l} = \frac{(4\pi \times 10^{-7}) \times (1000)^2 \times (4.0 \times 10^{-4})}{0.50}$$

$$L = \frac{4\pi \times 10^{-7} \times 10^6 \times 4.0 \times 10^{-4}}{0.5} = 32\pi \times 10^{-5} = \boxed{1.01 \times 10^{-3} \text{ H}} \quad (1.01 \text{ mH}).$$

(b) Magnetic Flux Density B : $n = N/l = 1000/0.50 = 2000$ turns/m.

$$B = \mu_0 nI = (4\pi \times 10^{-7}) \times 2000 \times 2.0 = 16\pi \times 10^{-4} = \boxed{5.03 \times 10^{-3} \text{ T}} \quad (5.03 \text{ mT}).$$

(c) Energy Stored: Method 1: $U = \frac{1}{2} LI^2 = 0.5 \times (1.005 \times 10^{-3}) \times (2.0)^2 = \boxed{2.01 \times 10^{-3} \text{ J}} \quad (2.01 \text{ mJ}).$

Method 2: Energy density $u = \frac{B^2}{2\mu_0} = \frac{(5.027 \times 10^{-3})^2}{2 \times 4\pi \times 10^{-7}} = \frac{25.27 \times 10^{-6}}{8\pi \times 10^{-7}} \approx 10.05 \text{ J m}^{-3}$. Volume $V = Al = (4.0 \times 10^{-4}) \times 0.50 = 2.0 \times 10^{-4} \text{ m}^3$. $U = uV = 10.05 \times 2.0 \times 10^{-4} = \boxed{2.01 \times 10^{-3} \text{ J}}$. Results agree.

(d) Average induced e.m.f. during switch-off: $\Delta I = 0 - 2.0 = -2.0 \text{ A}$, $\Delta t = 1.0 \text{ ms} = 1.0 \times 10^{-3} \text{ s}$.

$$|E_{\text{avg}}| = L \left| \frac{\Delta I}{\Delta t} \right| = (1.005 \times 10^{-3}) \times \frac{2.0}{1.0 \times 10^{-3}} = \boxed{2.01 \text{ V}}.$$

Note: This voltage spike is why inductive loads need flyback diodes/snubbers.

METHOD Solving Complex Induction Problems: Combined Motion and Field Change

1. General Faraday's Law: $E = -\frac{d\Phi}{dt} = -\frac{d}{dt} \int \vec{B} \cdot d\vec{A}$.
2. Two contributions: a transformer e.m.f. from the time-varying $\vec{B}$ through a fixed loop, and a motional e.m.f. from conductors moving in $\vec{B}$: $E_{\text{mot}} = \oint (\vec{v} \times \vec{B}) \cdot d\vec{l}$.
3. Strategy:
 - (a) Define the loop (closed circuit) clearly at instant t .
 - (b) Compute total flux $\Phi(t)$ through that loop.
 - (c) Differentiate $\Phi(t)$ w.r.t. time. This automatically accounts for both changing B and changing area/orientation.
 - (d) Alternatively, compute motional emf on moving parts (Blv) and transformer emf on stationary parts separately, then sum them (Kirchhoff's loop rule).
4. Sign convention: Use Lenz's law / Right-hand rule to assign polarity to the calculated magnitude.

WORKED EXAMPLE 15 Rod Moving in a Time-Varying Magnetic Field

A conducting rod of length $l = 0.20 \text{ m}$ slides on two parallel horizontal rails separated by l . The rails are connected at one end by a resistor $R = 5.0 \Omega$. The rod moves with constant velocity $v = 3.0 \text{ m s}^{-1}$ away from the resistor, increasing the loop area. The magnetic field is vertical, directed downwards, and its magnitude varies with time as $B(t) = (0.10 + 0.050t) \text{ T}$, where t is in seconds. At $t = 0$, the rod is at a distance $x_0 = 0.10 \text{ m}$ from the resistor. (a) Derive an expression for the magnetic flux through the loop as a function of time. (b) Calculate the induced e.m.f. at $t = 2.0 \text{ s}$. (c) Determine the magnitude and direction of the induced current at $t = 2.0 \text{ s}$. (d) Calculate the magnetic force on the rod at this instant and the mechanical power required to maintain constant velocity.

SOLUTION

Solution. Setup: Loop area $A(t) = l \times x(t)$ with $x(t) = x_0 + vt = 0.10 + 3.0t$. $\vec{B}(t) = (0.10 + 0.050t) \text{ T}$

downwards. Define positive flux downwards, so $\Phi(t) = B(t)A(t)$; Lenz's law will give the direction.

(a) Flux $\Phi(t)$:

$$\Phi(t) = B(t) \cdot A(t) = (0.10 + 0.050t) \times [0.20 \times (0.10 + 3.0t)]$$

Expand the product:

$$(0.10 + 0.05t)(0.10 + 3t) = 0.01 + 0.30t + 0.005t + 0.15t^2 = 0.01 + 0.305t + 0.15t^2$$

$$\Phi(t) = 0.20(0.01 + 0.305t + 0.15t^2) = \boxed{0.002 + 0.061t + 0.030t^2 \text{ Wb}}.$$

(b) Induced e.m.f. at $t = 2.0$ s:

$$E = -\frac{d\Phi}{dt} = -(0.061 + 0.060t)$$

At $t = 2.0$ s:

$$E = -(0.061 + 0.120) = -0.181 \text{ V}.$$

Magnitude $\boxed{0.181 \text{ V}}$. The negative sign means the induced current produces flux opposing the increase. Since Φ (downwards) is increasing, the induced flux is upwards, so the current is anticlockwise (viewed from above).

(c) Induced Current:

$$I = \frac{|E|}{R} = \frac{0.181}{5.0} = \boxed{0.0362 \text{ A}} \quad (36.2 \text{ mA}).$$

Direction: anticlockwise viewed from above. With the resistor at the near end and the rod moving away, the current in the rod flows towards the resistor side of the loop (from the far rail to the near rail along the rod).

(d) Magnetic Force and Power: Force on rod: $\vec{F}_B = I\vec{l} \times \vec{B}$. With $\vec{l}$ along the current in the rod and $\vec{B}$ downwards, the cross product gives a horizontal force opposing the motion (as Lenz's law requires). Magnitude: $F_B = BIl$. At $t = 2.0$ s: $B = 0.10 + 0.050(2) = 0.20 \text{ T}$, $I = 0.0362 \text{ A}$, $l = 0.20 \text{ m}$.

$$F_B = 0.20 \times 0.0362 \times 0.20 = \boxed{1.45 \times 10^{-3} \text{ N}} \quad (\text{opposing motion}).$$

External force: $F_{\text{ext}} = \boxed{1.45 \times 10^{-3} \text{ N}}$ in the direction of motion. Mechanical Power: $P_{\text{mech}} = F_{\text{ext}}v = (1.448 \times 10^{-3}) \times 3.0 = \boxed{4.34 \times 10^{-3} \text{ W}} \quad (4.34 \text{ mW})$.

Energy check. Electrical power dissipated: $P_{\text{elec}} = I^2 R = (0.0362)^2 \times 5.0 = 6.55 \times 10^{-3} \text{ W}$, which is larger than P_{mech} . There is no contradiction: the magnetic field is also changing with time, so the external agent driving $B(t)$ supplies the difference. Splitting the e.m.f.:

$$\frac{d\Phi}{dt} = B \frac{dA}{dt} + A \frac{dB}{dt}, \quad \frac{dA}{dt} = lv = 0.60 \text{ m}^2 \text{ s}^{-1}.$$

At $t = 2.0$ s: $A = lx = 0.20 \times (0.10 + 6.0) = 1.22 \text{ m}^2$, $dB/dt = 0.050 \text{ T s}^{-1}$. Motional part: $E_{\text{mot}} = B \frac{dA}{dt} = 0.20 \times 0.60 = 0.12 \text{ V}$. Transformer part: $E_{\text{trans}} = A \frac{dB}{dt} = 1.22 \times 0.050 = 0.061 \text{ V}$. Total: $0.12 + 0.061 = 0.181 \text{ V}$, matching (b). Power balance: $P_{\text{mech}} = E_{\text{mot}} I = 0.12 \times 0.0362 = 4.34 \text{ mW}$; field source supplies $E_{\text{trans}} I = 0.061 \times 0.0362 = 2.21 \text{ mW}$; sum = $6.55 \text{ mW} = P_{\text{elec}}$. Energy is conserved.

METHOD Exam Technique: Graphs and Quantitative Analysis

1. Flux vs Time Graph: Slope = $d\Phi/dt$. Induced e.m.f. $E = -\text{slope}$. Steepest slope $\Rightarrow \max E$. Zero slope $\Rightarrow E = 0$.
2. Current vs Time (L-R Growth): Exponential rise $I = I_0(1 - e^{-t/\tau})$. Tangent at $t = 0$ has slope $I_0/\tau = E/L$. Intercept of tangent at $I = I_0$ gives τ .
3. Current vs Time (L-R Decay): Exponential fall $I = I_0 e^{-t/\tau}$. Tangent at $t = 0$ slope $-I_0/\tau$. Time to halve $t_{1/2} = \tau \ln 2 \approx 0.693\tau$.
4. AC Generator Output: Sinusoidal $E = E_0 \sin(\omega t)$. Peak $E_0 = NBA\omega$. Period $T = 2\pi/\omega$. RMS $E_{\text{rms}} = E_0/\sqrt{2}$.
5. DC Generator Output (Commutator): Rectified sine $|E_0 \sin(\omega t)|$. Average (DC) value $E_{\text{avg}} = \frac{2}{\pi} E_0 \approx 0.637 E_0$.
6. Units Check: Always write units in final answer. Wb, T, H, V, A, s, J.
7. Direction Language: "Clockwise viewed from...", "From X to Y", "End A is positive relative to End B".

EXAMPLE Reading an L-R Growth Graph

A graph of current I against time t for an L-R circuit rises from 0 and levels off at $I_0 = 1.2 \text{ A}$. The tangent at the origin reaches the line $I = I_0$ at $t = 0.20 \text{ s}$. We read directly: time constant $\tau = 0.20 \text{ s}$, initial slope = $I_0/\tau = 6.0 \text{ A s}^{-1}$, and since $E = 12 \text{ V}$, $R = E/I_0 = 10 \Omega$ and $L = E/(\text{initial slope}) = 2.0 \text{ H}$. A single graph therefore yields all the circuit parameters.

7 EXERCISES

7.1 I check my knowledge

EXERCISE 5 Multiple choice questions

For each question, choose the single correct answer and justify your choice briefly.

- The magnetic flux through a plane coil of N turns, area A , whose normal makes an angle θ with a uniform field B is:
 - $\Phi = NBA \sin \theta$
 - $\Phi = NBA \cos \theta$
 - $\Phi = BA \cos \theta$
 - $\Phi = NBA \tan \theta$
- The magnitude of the e.m.f. induced in a circuit equals:
 - the magnetic flux through the circuit;
 - the rate of change of flux linkage with time;
 - the flux linkage divided by the resistance;
 - the product of the flux and the time.
- The current in an L – R circuit connected to a DC supply grows according to:
 - $I = I_0 e^{-t/\tau}$
 - $I = I_0 (1 - e^{-t/\tau})$
 - $I = I_0 t/\tau$
 - $I = I_0 (1 + e^{-t/\tau})$
- The energy stored in an inductor carrying a current I is:
 - $W = \frac{1}{2}LI^2$
 - $W = LI^2$
 - $W = \frac{1}{2}L^2I$
 - $W = \frac{1}{2}LI$

EXERCISE 6 True or false?

State whether each statement is true or false, and justify your answer in one or two sentences.

1. An e.m.f. is induced in a coil whenever a magnetic field exists near it, even if the field is constant.
2. According to Lenz's law, the induced current always flows so as to oppose the change of flux that produces it.
3. A split-ring commutator is fitted to a simple AC generator.
4. The self-inductance L of a coil is defined by the flux-linkage equation $N\Phi = LI$.
5. In the steady state, an ideal inductor connected to a DC supply behaves like a simple connecting wire.

EXERCISE 7 Definitions and statements

1. Define the **weber** in terms of the tesla and state the SI unit of flux linkage.
2. State Faraday's law of electromagnetic induction and write its mathematical form, explaining every symbol.
3. State Lenz's law and explain how it follows from the principle of conservation of energy.
4. Define the **mutual inductance** M of two coils from the equation $N_2\Phi_2 = MI_1$, and state its SI unit.

EXERCISE 8 Quick calculations

1. A flat coil of area 25 cm^2 lies perpendicular to a uniform field of 0.30 T . Calculate the flux through the coil.
2. A conductor of length 0.50 m moves at 8.0 m s^{-1} perpendicular to a field of 0.12 T . Calculate the e.m.f. induced between its ends.
3. An inductor of $L = 0.50 \text{ H}$ carries a steady current of 2.0 A . Calculate the energy stored in its magnetic field.
4. The current in a coil of self-inductance 80 mH changes at the rate of 150 A s^{-1} . Calculate the magnitude of the self-induced e.m.f.

7.2 I practise

EXERCISE 9 E.M.F. and induced charge in a coil

A coil of 200 turns and area 15 cm^2 is placed with its plane perpendicular to a uniform magnetic field which falls uniformly from 0.40 T to zero in 0.050 s .

1. Calculate the change of flux linkage of the coil.
2. Calculate the magnitude of the e.m.f. induced in the coil.
3. The coil forms part of a closed circuit of total resistance 5.0Ω . Calculate the induced current and the total charge that flows round the circuit while the field is falling.

EXERCISE 10 Motional e.m.f. in the Earth's field

A metal rod of length 0.80 m is moved horizontally at 12 m s^{-1} in a direction perpendicular both to its length and to the horizontal component of the Earth's magnetic field, of magnitude $2.0 \times 10^{-5} \text{ T}$.

1. Calculate the e.m.f. induced between the ends of the rod.
2. Using Fleming's right-hand rule (or the force on positive charges, $\vec{F} = q\vec{v} \times \vec{B}$), explain how you decide which end of the rod becomes positive.
3. Explain why no current flows unless the rod forms part of a closed circuit, although the e.m.f. still exists.

EXERCISE 11 Growth of current in an L–R circuit

An inductor of inductance $L = 0.20 \text{ H}$ and negligible resistance is connected in series with a resistor $R = 40 \Omega$ across a 12 V DC supply.

1. Write down the equation giving the growth of the current $I(t)$ after the switch is closed, defining all symbols.
2. Calculate the time constant τ of the circuit.
3. Calculate the steady-state current I_0 .
4. Calculate the current 2.0 ms after the switch is closed.
5. Calculate the energy stored in the inductor in the steady state.

EXERCISE 12 Mutual induction between two coils

Two neighbouring coils have mutual inductance $M = 15 \text{ mH}$. The current in the primary coil changes uniformly from 3.0 A to zero in 10 ms . The secondary coil has 800 turns.

1. Define the mutual inductance M from the flux-linkage equation $N_2\Phi_2 = MI_1$.
2. Calculate the average e.m.f. induced in the secondary coil.
3. Calculate the average change of flux through each turn of the secondary coil during the 10 ms interval.
4. State two practical ways of increasing the mutual inductance of the pair of coils.

7.3 I prepare for the GCE**EXERCISE 13 Structured question: the rotating-coil generator**

A rectangular coil of $N = 500$ turns and area $A = 100 \text{ cm}^2$ rotates at a steady frequency of 50 Hz about an axis perpendicular to a uniform magnetic field of flux density $B = 0.15 \text{ T}$.

- (a) Write down the expression for the flux linkage of the coil at time t , taking $t = 0$ when the plane of the coil is perpendicular to the field. (2 marks)
- (b) Hence show that the induced e.m.f. is $e(t) = E_0 \sin(\omega t)$ and calculate the peak e.m.f. E_0 . (4 marks)
- (c) Calculate the r.m.s. value of the e.m.f. (2 marks)
- (d) Sketch, on the same time axis, two complete cycles of the output e.m.f. when the coil is connected to an external circuit through:
 - (i) two slip rings;
 - (ii) a split-ring commutator.

Label the axes with numerical values. (4 marks)
- (e) State and explain the effect on the peak e.m.f. and on the frequency of doubling the speed of rotation. (3 marks)

(Total: 15 marks)

EXERCISE 14 Essay question: the magnet falling through a copper tube

A small but strong bar magnet is dropped through a long vertical copper tube. It is observed to fall much more slowly than an identical unmagnetised object falling through the

same tube.

- Explain, with the help of Lenz's law and a clear description of the induced currents in the tube, why the magnet experiences an upward force opposing its fall. (5 marks)
 - Show, using the principle of conservation of energy, that the gravitational potential energy lost by the magnet reappears as thermal energy in the tube. (3 marks)
 - Explain why the magnet eventually reaches a constant terminal velocity. (3 marks)
 - State and explain what changes, and why, if the tube is replaced by an identical tube having a narrow vertical slit along its whole length. (3 marks)
 - Suggest one practical application of this phenomenon in engineering. (1 mark)
- (Total: 15 marks)

EXERCISE 15 Data analysis: decay of current in an L–R circuit

The steady current through a coil of inductance L in series with a resistor of resistance $R = 20\ \Omega$ is suddenly allowed to decay by short-circuiting the supply. The current I is measured at successive times t :

t / ms	0	2.0	4.0	6.0	8.0	10.0
I / A	0.60	0.40	0.27	0.18	0.12	0.080

- Starting from Kirchhoff's voltage law applied to the L – R loop, show that the decaying current obeys $I = I_0 e^{-Rt/L}$. (4 marks)
- Copy and complete the table with values of $\ln(I/A)$. (2 marks)
- Plot a graph of $\ln(I/A)$ against t , choosing suitable scales. (3 marks)
- Explain the shape of the graph and determine its gradient. (3 marks)
- Hence determine the time constant τ of the circuit and deduce the inductance L of the coil. (3 marks)

(Total: 15 marks)

8 SOLUTIONS TO THE EXERCISES

8.1 I check my knowledge

SOLUTION Exercise 1 — Multiple choice questions

1. (b) $\Phi = NBA \cos \theta$. Only the component of $\vec{B}$ along the normal to the coil contributes to the flux; multiplying by the N turns gives the flux linkage $N\Phi = NBA \cos \theta$. Option (c) forgets the number of turns, and (a) would be correct only if θ were measured from the plane of the coil.
2. (b). Faraday's law: $e = -\frac{d(N\Phi)}{dt}$; the magnitude of the induced e.m.f. equals the rate of change of flux linkage with time. Flux itself (a) induces nothing if it is constant.
3. (b) $I = I_0(1 - e^{-t/\tau})$ with $\tau = L/R$: the current starts at zero (an inductor opposes any sudden change of current) and rises asymptotically towards $I_0 = E/R$. Option (a) describes the decay of current.
4. (a) $W = \frac{1}{2}LI^2$, obtained by integrating the power $p = LI \frac{dI}{dt}$ supplied to the inductor; it is the magnetic analogue of $\frac{1}{2}CV^2$ for a capacitor.

SOLUTION Exercise 2 — True or false?

1. False. An e.m.f. is induced only when the flux linkage changes; a constant field produces a constant flux and hence no induced e.m.f., however strong the field may be.
2. True. This is exactly the statement of Lenz's law; it is a direct consequence of the conservation of energy (the induced current can never aid the change that creates it).
3. False. A simple AC generator uses two **slip rings**, one connected to each end of the coil; the **split-ring commutator** is fitted to a simple DC generator to reverse the connections every half-turn and rectify the output.
4. True. L is the constant of proportionality in $N\Phi = LI$, i.e. the flux linkage per unit current; it is measured in henry (H), with $1 \text{ H} = 1 \text{ Wb A}^{-1}$.
5. True. In the steady state $\frac{dI}{dt} = 0$, so the back e.m.f. $L \frac{dI}{dt} = 0$; an ideal (resistance-free) inductor then offers no opposition at all and behaves like a plain connecting wire.

SOLUTION Exercise 3 — Definitions and statements

1. One weber is the magnetic flux through an area of 1 m^2 placed perpendicular to a uniform magnetic field of flux density 1 T :

$$1 \text{ Wb} = 1 \text{ T m}^2.$$

The flux linkage $N\Phi$ is measured in weber-turns (Wb-turns), usually written simply Wb.

2. Faraday's law: whenever the magnetic flux linkage of a circuit changes, an e.m.f. is induced in the circuit whose magnitude is equal to the rate of change of flux linkage:

$$e = -\frac{d(N\Phi)}{dt},$$

where e is the induced e.m.f. (V), N the number of turns of the coil, Φ the magnetic flux through one turn (Wb) and t the time (s). The minus sign expresses Lenz's law: the induced e.m.f. opposes the change producing it.

3. Lenz's law: the direction of the induced current is always such that its magnetic effect opposes the change of flux producing it. Suppose the opposite were true: the induced current would reinforce the change of flux, which would induce a still larger current, and so on — energy would be created from nothing, contradicting the conservation of energy. In reality, external work must be done against the opposing (Lenz) force, and this work is exactly the electrical energy that appears in the circuit.
4. M is the constant of proportionality between the flux linkage $N_2\Phi_2$ of the secondary coil and the current I_1 in the primary coil that produces it:

$$M = \frac{N_2\Phi_2}{I_1} \quad (\text{equivalently } N_1\Phi_1 = MI_2).$$

Its SI unit is the henry (H).

SOLUTION Exercise 4 — Quick calculations

1. Convert the area: $A = 25 \text{ cm}^2 = 2.5 \times 10^{-3} \text{ m}^2$. The field is normal to the plane of the coil, so

$$\Phi = BA = 0.30 \times 2.5 \times 10^{-3} = 7.5 \times 10^{-4} \text{ Wb}.$$

2. Motional e.m.f.:

$$e = Blv = 0.12 \times 0.50 \times 8.0 = 0.48 \text{ V}.$$

3. Energy stored:

$$W = \frac{1}{2}LI^2 = \frac{1}{2} \times 0.50 \times (2.0)^2 = 1.0 \text{ J}.$$

4. Self-induced e.m.f.:

$$|e| = L \frac{dI}{dt} = 0.080 \times 150 = 12 \text{ V.}$$

WARNING Units first!

Always convert cm^2 to m^2 ($1 \text{ cm}^2 = 10^{-4} \text{ m}^2$) and mH to H before substituting; most lost marks in these questions come from unit errors, not from physics.

8.2 I practise

SOLUTION Exercise 5 — E.M.F. and induced charge in a coil

1. The field is normal to the plane of the coil, so the flux through one turn is $\Phi = BA$. The change of flux linkage is

$$\Delta(N\Phi) = NA \Delta B = 200 \times 15 \times 10^{-4} \times (0.40 - 0) = 0.12 \text{ Wb-turns.}$$

2. Faraday's law, using the uniform (average) rate of change:

$$|e| = \frac{\Delta(N\Phi)}{\Delta t} = \frac{0.12}{0.050} = 2.4 \text{ V.}$$

3. Induced current:

$$I = \frac{|e|}{R} = \frac{2.4}{5.0} = 0.48 \text{ A.}$$

Total charge circulated:

$$Q = I \Delta t = 0.48 \times 0.050 = 2.4 \times 10^{-2} \text{ C.}$$

Check with the general result $Q = \frac{\Delta(N\Phi)}{R} = \frac{0.12}{5.0} = 0.024 \text{ C}$: the charge depends only on the total change of flux linkage and the resistance, not on how quickly the change occurs.

SOLUTION Exercise 6 — Motional e.m.f. in the Earth's field

1. The rod, its velocity and the field are mutually perpendicular, so

$$e = Blv = 2.0 \times 10^{-5} \times 0.80 \times 12 = 1.9 \times 10^{-4} \text{ V} \approx 0.19 \text{ mV.}$$

2. The free charge carriers in the rod are carried along with velocity $\vec{v}$ and each experi-

ences the magnetic force $\vec{F} = q\vec{v} \times \vec{B}$, directed along the rod. Fleming's right-hand rule (First finger = Field, thumb = Motion, second finger = induced Current) gives the same direction. Positive charges are pushed towards one end of the rod, which becomes positive, while the other end, depleted of positive charge, becomes negative. Charge accumulates until the electric field it creates inside the rod exactly balances the magnetic force ($qE = qvB$, giving $e = El = Blv$).

3. The separation of charge is the e.m.f.: it exists whenever the rod moves through the field, whether or not the circuit is closed. But a current requires a complete conducting path; with the rod open-ended, charges merely pile up at the ends and no continuous flow is possible. Closing the circuit allows the e.m.f. to drive a current $I = e/R$.

SOLUTION Exercise 7 — Growth of current in an L–R circuit

1. Kirchhoff's voltage law around the loop gives $E = RI + L \frac{dI}{dt}$. Solving this differential equation with the initial condition $I(0) = 0$:

$$I(t) = I_0 (1 - e^{-t/\tau}), \quad I_0 = \frac{E}{R}, \quad \tau = \frac{L}{R},$$

where E is the supply e.m.f., I_0 the steady-state (final) current and τ the time constant of the circuit.

2. Time constant:

$$\tau = \frac{L}{R} = \frac{0.20}{40} = 5.0 \times 10^{-3} \text{ s} = 5.0 \text{ ms}.$$

3. Steady-state current (the inductor then behaves like a wire):

$$I_0 = \frac{E}{R} = \frac{12}{40} = 0.30 \text{ A}.$$

4. At $t = 2.0 \text{ ms}$:

$$I = 0.30 (1 - e^{-2.0/5.0}) = 0.30 (1 - e^{-0.40}) = 0.30 \times 0.330 = 9.9 \times 10^{-2} \text{ A}.$$

5. Energy stored in the steady state:

$$W = \frac{1}{2} LI_0^2 = \frac{1}{2} \times 0.20 \times (0.30)^2 = 9.0 \times 10^{-3} \text{ J}.$$

SOLUTION Exercise 8 — Mutual induction between two coils

1. M is the flux linkage of the secondary coil per unit current in the primary coil:

$$M = \frac{N_2 \Phi_2}{I_1},$$

where Φ_2 is the flux through one turn of the secondary produced by the primary current I_1 ; M is measured in henry.

2. The current changes uniformly, so $\left| \frac{dI_1}{dt} \right| = \frac{3.0}{10 \times 10^{-3}} = 300 \text{ A s}^{-1}$, and

$$|e_2| = M \left| \frac{dI_1}{dt} \right| = 15 \times 10^{-3} \times 300 = 4.5 \text{ V}.$$

3. From $N_2 \Delta \Phi_2 = M \Delta I_1$:

$$\Delta \Phi_2 = \frac{M \Delta I_1}{N_2} = \frac{15 \times 10^{-3} \times 3.0}{800} = 5.6 \times 10^{-5} \text{ Wb}.$$

4. Any two of: wind both coils on a common soft-iron core, which concentrates and guides the flux from one coil to the other; bring the coils closer together or wind one directly on top of the other; increase the number of turns of either coil; orient the coils coaxially so that maximum flux links them.

8.3 I prepare for the GCE

SOLUTION Exercise 9 — Structured question: the rotating-coil generator

- (a) At $t = 0$ the plane of the coil is perpendicular to $\vec{B}$, so the normal to the coil is parallel to $\vec{B}$; after time t the normal makes the angle $\theta = \omega t$ with $\vec{B}$. Hence

$$N\Phi = NBA \cos(\omega t), \quad \omega = 2\pi f = 2\pi \times 50 = 314 \text{ rad s}^{-1}.$$

Mark scheme (2): 1 mark for $\theta = \omega t$ (or $\cos$ dependence consistent with the stated initial condition); 1 mark for the complete expression including N .

- (b) Faraday's law:

$$e = -\frac{d(N\Phi)}{dt} = -\frac{d}{dt} [NBA \cos(\omega t)] = NBA\omega \sin(\omega t) = E_0 \sin(\omega t),$$

with peak value

$$E_0 = NBA\omega = 500 \times 0.15 \times 100 \times 10^{-4} \times 314 = 2.4 \times 10^2 \text{ V} (\approx 236 \text{ V}).$$

Mark scheme (4): 1 mark for quoting Faraday's law; 1 mark for correct differentiation ($\frac{d}{dt} \cos \omega t = -\omega \sin \omega t$); 1 mark for identifying $E_0 = NBA\omega$; 1 mark for the numerical value


with unit (accept 235–236 V). Examiner's expectation: the area must be converted to m^2 ($100 \text{ cm}^2 = 1.0 \times 10^{-2} \text{ m}^2$).

(c) For a sinusoidal e.m.f.:

$$E_{\text{rms}} = \frac{E_0}{\sqrt{2}} = \frac{236}{\sqrt{2}} = 1.7 \times 10^2 \text{ V } (\approx 167 \text{ V}).$$

Mark scheme (2): 1 mark for the relation $E_{\text{rms}} = E_0/\sqrt{2}$; 1 mark for the value with unit.

(d) Period $T = \frac{1}{f} = 20 \text{ ms}$.



(i) Slip rings: sinusoidal AC output, $e = 236 \sin(314t)$. (ii) Split-ring commutator: the negative half-cycles are reversed, giving a pulsating unidirectional output of the same peak value and the same period.

Mark scheme (4): 1 mark for a correct sine wave through the origin (slip rings); 1 mark for the rectified shape with all half-cycles on the same side and the same peak (split ring); 1 mark for labelled axes with units; 1 mark for correct numerical scales ($T = 20 \text{ ms}$, $E_0 = 236 \text{ V}$).

(e) Since $E_0 = NBA\omega = 2\pi fNBA$, both the frequency and the peak e.m.f. are directly proportional to the speed of rotation. Doubling the speed doubles the frequency ($50 \text{ Hz} \rightarrow 100 \text{ Hz}$) and doubles the peak e.m.f. ($236 \text{ V} \rightarrow 471 \text{ V}$). Mark scheme (3): 1 mark for f doubles; 1 mark for E_0 doubles; 1 mark for justification via $E_0 = 2\pi fNBA$.

SOLUTION

Exercise 10 — Essay question: the magnet falling through a copper tube

(a) As the magnet falls, the magnetic flux through each section of the tube changes: it

increases in the region below the magnet (which the magnet approaches) and decreases in the region above it (which the magnet leaves). Copper is a good conductor, so these flux changes drive induced (**eddy**) currents in closed loops around the tube wall. By Lenz's law, the currents below the magnet flow in such a direction as to repel the approaching pole, while the currents above flow so as to attract the receding pole. Both effects produce an upward force on the magnet opposing its fall, so it descends far more slowly than a non-magnetic object.

Mark scheme (5): 1 mark for identifying the changing flux; 1 mark for induced currents in the tube wall (copper a conductor); 1 mark for correct use of Lenz's law below the magnet (repulsion); 1 mark for attraction above; 1 mark for the conclusion (net upward braking force).

- (b) The induced currents flow through the resistance of the copper and dissipate electrical energy as heat (Joule heating, $P = I^2 R$). The only source of this energy is the work done by gravity. As the magnet descends through a height h , it loses gravitational potential energy mgh . Once the magnet moves at constant (terminal) velocity its kinetic energy no longer changes, so the whole of mgh is converted into thermal energy in the tube: energy is conserved, merely transferred from gravitational potential energy to internal energy of the copper.

Mark scheme (3): 1 mark for Joule heating of the tube; 1 mark for identifying gravity as the energy source; 1 mark for the balance $mgh \rightarrow \text{heat}$ at constant speed.

- (c) The faster the magnet falls, the greater the rate of change of flux $\frac{d\Phi}{dt}$, hence the larger the induced e.m.f.s, the induced currents and therefore the braking force. The upward electromagnetic force thus grows with speed until it exactly balances the weight mg (air resistance being negligible). The resultant force is then zero and, by Newton's first law, the magnet continues at a constant **terminal velocity**.

Mark scheme (3): 1 mark for braking force increasing with speed (via rate of change of flux); 1 mark for force balance $F = mg$; 1 mark for zero acceleration $\Rightarrow$ constant velocity.

- (d) The slit cuts the closed conducting loops around the circumference of the tube, so the eddy currents can no longer circulate around it. The induced currents, and therefore the braking force, become very small; the magnet then falls almost freely, nearly like the unmagnetised object.

Mark scheme (3): 1 mark for recognising that the current loops are interrupted; 1 mark for the consequent near-absence of eddy currents/braking; 1 mark for the conclusion (near-free fall).

- (e) Electromagnetic (eddy-current) braking, e.g. on trains or roller-coasters; electromagnetic damping of moving-coil meters; induction furnaces; electromagnetic sorting of metals. (Any one, 1 mark.)

SOLUTION Exercise 11 — Data analysis: decay of current in an L–R circuit

- (a) With the supply short-circuited, the loop contains only L and R . Kirchhoff's voltage law gives

$$L \frac{dI}{dt} + RI = 0 \quad \Rightarrow \quad \frac{dI}{I} = -\frac{R}{L} dt.$$

Integrating between $(0, I_0)$ and (t, I) :

$$\int_{I_0}^I \frac{dI'}{I'} = -\frac{R}{L} \int_0^t dt' \quad \Rightarrow \quad \ln I - \ln I_0 = -\frac{R}{L} t,$$

so


$$I = I_0 e^{-Rt/L} = I_0 e^{-t/\tau}, \quad \tau = \frac{L}{R}.$$

Mark scheme (4): 1 mark for the Kirchhoff equation; 1 mark for correct separation of variables; 1 mark for correct integration with limits; 1 mark for the final exponential form.

- (b) Completed table:

t / ms	0	2.0	4.0	6.0	8.0	10.0
I / A	0.60	0.40	0.27	0.18	0.12	0.080
$\ln(I/\text{A})$	-0.51	-0.92	-1.31	-1.71	-2.12	-2.53

Mark scheme (2): all six values correct to 2 d.p. (2 marks); one error (1 mark).



Graph of $\ln(I/\text{A})$ against t : a straight line of negative gradient passing through the experimental points.

Mark scheme (3): 1 mark for sensible scales using more than half of each axis; 1 mark for all points plotted correctly; 1 mark for labelled axes with units and a best-fit straight line.

(d) Taking logarithms of $I = I_0 e^{-Rt/L}$:

$$\ln I = \ln I_0 - \frac{R}{L} t,$$

which is the equation of a straight line of gradient $-\frac{R}{L}$ and intercept $\ln I_0$ — exactly what the graph shows. Using two well-separated points on the best-fit line:

$$\text{gradient} = \frac{-2.53 - (-0.51)}{(10.0 - 0) \times 10^{-3}} = \frac{-2.02}{1.0 \times 10^{-2}} = -2.0 \times 10^2 \text{ s}^{-1}.$$

Mark scheme (3): 1 mark for deriving $\ln I = \ln I_0 - Rt/L$; 1 mark for identifying the gradient with $-R/L$; 1 mark for a gradient read from a large triangle, value in the range $(1.9-2.1) \times 10^2 \text{ s}^{-1}$.

(e) Time constant:

$$\tau = -\frac{1}{\text{gradient}} = \frac{1}{2.0 \times 10^2} = 5.0 \times 10^{-3} \text{ s} = 5.0 \text{ ms}.$$

Inductance, from $\tau = L/R$:


$$L = R\tau = 20 \times 5.0 \times 10^{-3} = 0.10 \text{ H}.$$

Mark scheme (3): 1 mark for $\tau = -1/\text{gradient}$; 1 mark for $\tau = 5.0 \text{ ms}$; 1 mark for $L = R\tau = 0.10 \text{ H}$ with unit.

WARNING Examiner's advice

In graphical questions, always draw the gradient triangle using more than half of the drawn line, quote the gradient with its unit (here s^{-1}), and carry the unit through to the final answer. A value of L without "H" loses the last mark.

9 SUMMARY SHEET



9.1 Key Definitions

- **Magnetic flux** (Φ): $\Phi = \vec{B} \cdot \vec{A} = BA \cos \theta$, where θ is the angle between $\vec{B}$ and the normal to the surface. Scalar quantity; SI unit the weber ($1 \text{ Wb} = 1 \text{ T m}^2$).
- **Flux linkage**: for a coil of N turns, flux linkage = $N\Phi$ (unit: Wb-turns).
- **Induced e.m.f.** (E): the e.m.f. produced by a changing flux linkage; work done per unit charge; unit volt (V).
- **Self-inductance** (L): the constant in $N\Phi = LI$, i.e. the flux linkage per unit current in the same coil: $L = N\Phi/I$; unit the henry (H).
- **Mutual inductance** (M): the constant in $N_2\Phi_2 = MI_1$ (flux linkage of coil 2 per unit current in coil 1); symmetrically $N_1\Phi_1 = MI_2$; unit the henry (H).
- **Time constant** (τ) of an L-R circuit: $\tau = L/R$; the time for the current to reach about 63% of its final value during growth, or to fall to about 37% of its initial value during decay.

9.2 Fundamental Laws and Formulas

- **Faraday's law**: $E = -\frac{d(N\Phi)}{dt}$. The magnitude of the induced e.m.f. equals the rate of change of flux linkage: $|E| = N \left| \frac{d\Phi}{dt} \right|$.
- **Lenz's law**: the induced current flows in such a direction that its own magnetic effect opposes the change of flux producing it. This is the meaning of the minus sign in Faraday's law and is a direct consequence of the conservation of energy.

- **Motional e.m.f.:** for a straight conductor of length l moving with velocity v perpendicular to a uniform field $\vec{B}$ (with $\vec{v}$, $\vec{B}$, $\vec{l}$ mutually perpendicular):

$$E = Blv.$$

If $\vec{v}$ makes an angle θ with $\vec{B}$, only the perpendicular component counts: $E = Blv \sin \theta$.

- **AC generator** (coil of N turns, area A , rotating at angular speed ω in uniform $\vec{B}$):

$$E = E_0 \sin(\omega t), \quad E_0 = NBA\omega.$$

- **Inductor (back) e.m.f.:** $E_L = -L \frac{dI}{dt}$.

- **L-R circuit** (d.c. source of e.m.f. E_0 , total resistance R):

$$\text{Growth: } I(t) = \frac{E_0}{R} (1 - e^{-t/\tau}), \quad \tau = \frac{L}{R},$$

$$\text{Decay: } I(t) = I_0 e^{-t/\tau}, \quad I_0 = \frac{E_0}{R}.$$

- **Energy stored in an inductor:** $U = \frac{1}{2} LI^2$. During growth, at time t :

$$U(t) = \frac{1}{2} L I(t)^2 = \frac{1}{2} L \left(\frac{E_0}{R} \right)^2 (1 - e^{-t/\tau})^2.$$

- **Mutual induction:** $E_2 = -M \frac{dI_1}{dt}$ and $E_1 = -M \frac{dI_2}{dt}$.

9.3 Standard Methods

1. **Flux calculation:** identify $\vec{B}$, the area A , and the angle θ between $\vec{B}$ and the normal to the surface. Then $\Phi = BA \cos \theta$; multiply by N for flux linkage.
2. **Direction of the induced current (Lenz's law):**
 - (a) State the direction of the external field $\vec{B}$ through the circuit.
 - (b) Decide whether the flux is increasing or decreasing.
 - (c) The induced field $\vec{B}_{\text{ind}}$ opposes the change: if the flux increases, $\vec{B}_{\text{ind}}$ is opposite to $\vec{B}$; if it decreases, $\vec{B}_{\text{ind}}$ is in the same direction as $\vec{B}$.
 - (d) Apply the right-hand grip rule to deduce the current direction from $\vec{B}_{\text{ind}}$.
3. **Polarity of a motional e.m.f.:** apply the magnetic force $\vec{F} = q(\vec{v} \times \vec{B})$ to the free electrons (negative charges); the end where electrons accumulate becomes the negative terminal.
4. **L-R circuit analysis:** write Kirchhoff's loop rule, $E_0 - IR - L \frac{dI}{dt} = 0$; separate variables and integrate with the initial condition $I(0) = 0$ (growth) or set $E_0 = 0$ with $I(0) = I_0$ (decay).

5. **Energy balance in an L–R circuit:** power supplied by the source $P = E_0 I$; power dissipated in the resistor $P_R = I^2 R$; rate of storage in the inductor $P_L = LI \frac{dI}{dt}$. Energy conservation gives $E_0 I = I^2 R + LI \frac{dI}{dt}$, which is the loop equation multiplied by I .

9.4 Common Mistakes and Traps

- **Sign errors:** forgetting the minus sign in Faraday's law when only the magnitude is required; confusing Lenz's law with opposing the field itself instead of the change of flux.
- **The angle θ :** using the angle between $\vec{B}$ and the plane of the coil instead of the angle between $\vec{B}$ and the normal to the plane in $\Phi = BA \cos \theta$.
- **Motional e.m.f.:** applying $E = Blv$ when $\vec{v}$, $\vec{B}$ and $\vec{l}$ are not mutually perpendicular; the correct form is then $E = Blv \sin \theta$.
- **Inductance formulas:** confusing the definition $N\Phi = LI$ with the induced e.m.f. $E = -L dI/dt$. L is a geometric property of the coil and does not depend on I .
- **Time constant:** writing $\tau = R/L$ instead of $\tau = L/R$. Check physically: a larger L opposes changes more strongly, so the current changes more slowly and τ must be larger.
- **Energy:** believing the energy is stored in the resistor; it is stored in the magnetic field of the inductor. The correct expression is $U = \frac{1}{2} LI^2$, not LI^2 .
- **Generators:** confusing slip rings (AC output) with the split-ring commutator (DC output). The DC output is pulsating (rectified), not steady; the peak e.m.f. $NBA\omega$ is the same in both cases.

9.5 GCE Examination Tips

- **Derivations:** be ready to derive $E = Blv$ from the magnetic force on the free electrons of the moving rod, and to derive the growth and decay equations of the L–R circuit. Show the steps clearly: loop rule $\rightarrow$ differential equation $\rightarrow$ separation of variables $\rightarrow$ integration $\rightarrow$ application of the initial condition.
- **Graph sketching:** be able to sketch I against t for growth and decay (exponential curves, with τ marked), E against t for an AC generator (sinusoid, peak $E_0 = NBA\omega$), and E against t for a DC generator (rectified half-waves). Always label axes and peak values.
- **Units:** always quote SI units: Φ in Wb, L and M in H, E in V, τ in s. Check dimensional consistency: $[L] = [\Phi]/[I] = \text{Wb A}^{-1} = \text{H}$, and $[L/R] = \text{s}$.
- **Quantitative problems:** typical values are $B \sim 0.1\text{--}1\text{ T}$, $A \sim 10^{-3}\text{--}10^{-2}\text{ m}^2$, $N \sim 100\text{--}500$ turns, $\omega = 2\pi f$ with $f = 50\text{ Hz}$, $L \sim \text{mH--H}$, $R \sim \Omega\text{--k}\Omega$. Give final answers to 2–3 significant figures with units.
- **Mutual inductance:** frequently examined with two coaxial coils; remember that the same constant M appears in both $N_2\Phi_2 = MI_1$ and $N_1\Phi_1 = MI_2$, and that $E_2 = -M dI_1/dt$.
- **Language of definitions:** “State Faraday's law” $\rightarrow$ give the equation and a sentence in words. “Explain Lenz's law” $\rightarrow$ mention opposition to the change of flux and conservation of en-

ergy. “Define self-inductance” → write $N\Phi = LI$ and state “the flux linkage per unit current in the coil”.



Signed • OnBuch+

ONBUCH+ TEACHING TEAM
FOLLOWS THE OFFICIAL MINESEC SYLLABUS

OnBuch+