OnBuch+

SIGNED COURSE • PREMIUM

FURTHER MATHEMATICS • UPPER SIXTH

UPPER SIXTH — FURTHER MATHEMATICS

CHAPTER 6

DIFFERENTIAL EQUATIONS

SUGGESTED TIME: 8 PERIODS

IN THIS CHAPTER

This chapter introduces the theory and solution techniques for first- and second-order differential equations, from separable variables to linear equations with constant coefficients and reducible forms. Mastery of these tools enables students to model and solve a wide range of scientific and engineering problems encountered in the GCE Advanced Level examination.

- Identify the order, degree and type of a given differential equation.
- Sketch direction fields and interpret integral curves geometrically.
- Solve first-order equations by separation of variables and by the integrating factor method.
- Recognise and solve homogeneous, Bernoulli and Riccati equations using appropriate substitutions.
- Solve linear second-order differential equations with constant coefficients (homogeneous and non-homogeneous).
- Apply reduction of order and other techniques to equations missing the dependent or independent variable.

DOWNLOAD ONBUCH

Free • Google Play
AI tutor, past papers, results

GO ONBUCH+

All signed courses, unlimited AI tutor, PDF sheets — OnBuch+ tab in the app

THIS SIGNED COURSE CONTAINS

COURSE
complete, illustrated, step by step

METHODS
and worked examples

EXERCISES
exam style + solutions

SUMMARY SHEET
the essentials to remember

Signed • OnBuch+
ONBUCH+ TEACHING TEAM
FOLLOWS THE OFFICIAL MINESEC SYLLABUS

OnBuch+

CONTENTS

1. First-Order Differential Equations – Foundations and Geometry
2. Separable Variables and Linear First-Order Non-Homogeneous Equations
3. Homogeneous, Bernoulli and Riccati Equations
4. Linear Second-Order Differential Equations with Constant Coefficients
5. Reducible Equations, Reduction of Order and Modelling Applications
6. Integration activity
7. Methods and worked examples
8. Exercises
9. Solutions to the exercises
10. Summary sheet

CHAPTER OBJECTIVES

- Identify the order, degree and type of a given differential equation.
- Sketch direction fields and interpret integral curves geometrically.
- Solve first-order equations by separation of variables and by the integrating factor method.
- Recognise and solve homogeneous, Bernoulli and Riccati equations using appropriate substitutions.
- Solve linear second-order differential equations with constant coefficients (homogeneous and non-homogeneous).
- Apply reduction of order and other techniques to equations missing the dependent or independent variable.
- Formulate and solve simple mathematical models from physics, biology or economics.
- Check solutions and avoid common algebraic pitfalls in the solution process.

PREREQUISITES

- Differentiation rules (product, quotient, chain) from Lower Sixth.
- Integration techniques: substitution, partial fractions, integration by parts.

- Basic algebra of complex numbers (for complex roots of characteristic equations).
- Elementary knowledge of exponential, logarithmic and trigonometric functions.

1 FIRST-ORDER DIFFERENTIAL EQUATIONS – FOUNDATIONS AND GEOMETRY

Imagine a cocoa farmer in the South-West region of Cameroon who wants to predict how the humidity inside his drying shed changes during the day, so that he can optimise his drying schedule and avoid mould on his beans. The rate at which the humidity changes depends on the current humidity, on the outside temperature, and on how much he opens the ventilation. In other words, he does not know the humidity function $H(t)$ directly; what nature gives him is a relationship between $H(t)$ and its rate of change $\frac{dH}{dt}$. A relationship of this kind is called a **differential equation**, and solving it means recovering the unknown function from information about its derivative. This is one of the most powerful ideas in all of mathematics: the laws of physics, biology, economics and engineering are almost always written in the language of differential equations.

1.1 What is a Differential Equation?

DEFINITION **Differential equation, order, degree**

A **differential equation** (DE) is an equation involving an unknown function and one or more of its derivatives. If the unknown function depends on a single variable, the equation is called an **ordinary differential equation** (ODE).

- The **order** of a differential equation is the order of the highest derivative appearing in it.
- The **degree** of a differential equation is the power to which the highest derivative is raised, after the equation has been cleared of fractions and radicals in the derivatives (when such a power is defined).

A first-order differential equation has the general form

$$F\left(x,\, y,\, \frac{dy}{dx}\right) = 0, \qquad \text{often written } \frac{dy}{dx} = f(x, y).$$

EXEMPLE **Identifying order and degree**

- $\frac{dy}{dx} = 3x^2$: order 1, degree 1.
- $\frac{d^2y}{dx^2} + 4\frac{dy}{dx} + y = 0$: order 2, degree 1.
- $\left(\frac{dy}{dx}\right)^3 + y = x$: order 1, degree 3.

- $\frac{d^2y}{dx^2} = \sqrt{1 + \frac{dy}{dx}}$: order 2; squaring gives $\left(\frac{d^2y}{dx^2}\right)^2 = 1 + \frac{dy}{dx}$, so the degree is 2.

WARNING **Order is not degree**

The **order** counts how many times we differentiate; the **degree** is the power of that highest derivative. In $\left(\frac{d^2y}{dx^2}\right)^5 + \frac{dy}{dx} = 0$, the order is 2 (second derivative is the highest) and the degree is 5 (it is raised to the fifth power). Examiners frequently test this distinction.

DEFINITION **Solution, general solution, particular solution**

A **solution** of a differential equation on an interval I is a function $y = \varphi(x)$ which, together with its derivatives, satisfies the equation identically on I.

- The **general solution** of an n-th order equation contains n independent arbitrary constants.
- A **particular solution** is obtained by assigning specific values to the constants, usually from given conditions.

EXEMPLE **Verifying a solution**

Show that $y = Ce^{2x}$ is the general solution of $\frac{dy}{dx} = 2y$, and find the particular solution with $y(0) = 5$.

Solution. If $y = Ce^{2x}$ then $\frac{dy}{dx} = 2Ce^{2x} = 2y$, so the equation is satisfied for every constant C. The condition $y(0) = 5$ gives $Ce^0 = 5$, so $C = 5$ and the particular solution is $y = 5e^{2x}$.

WARNING **Always verify by substitution**

To check that a function is a solution, substitute it into the equation; do not try to "solve backwards". Also remember: the general solution of a first-order equation contains exactly one arbitrary constant. If your answer has two constants for a first-order equation, something is wrong.

1.2 Initial Value Problems

In applications we rarely want all solutions; we want the solution that matches the state of the system at a starting moment. The farmer knows the humidity at 6 a.m.; he wants the humidity at noon.

DEFINITION **Initial value problem**

An **initial value problem** (IVP) for a first-order equation consists of the equation together with one initial condition:

$$\frac{dy}{dx} = f(x, y), \qquad y(x_0) = y_0.$$

Geometrically, we seek the integral curve passing through the point (x_0, y_0). The condition fixes the constant of integration.

WORKED EXAMPLE 1 **A simple initial value problem**

Solve the initial value problem $\frac{dy}{dx} = 3x^2$, with $y(1) = 4$.

SOLUTION

Solution. Integrate directly:

$$y = \int 3x^2\,dx = x^3 + C.$$

This is the general solution. Apply the initial condition: $y(1) = 1 + C = 4$, so $C = 3$. The particular solution is

$$y = x^3 + 3.$$

Check: $\frac{dy}{dx} = 3x^2$ ✓ and $y(1) = 1 + 3 = 4$ ✓.

1.3 Geometric Interpretation: Direction Fields and Integral Curves

Here is the key geometric idea. The equation $\frac{dy}{dx} = f(x, y)$ tells us something remarkable: if a solution curve passes through the point (x, y), then its tangent there has slope $f(x, y)$. So even **before solving anything**, we can draw at each point of the plane a small segment with slope $f(x, y)$. The resulting picture is called a **direction field** (or slope field). A solution curve, called an **integral curve**, is simply a curve that is tangent to the little segments everywhere it goes – like a leaf drifting along a river, always following the local current.


DEFINITION **Direction field, integral curve, isocline**

Let $\frac{dy}{dx} = f(x, y)$.

- The **direction field** is the family of short line segments drawn at points (x, y) with slope $f(x, y)$.
- An **integral curve** is a curve tangent to the direction field at every point; it is the graph of a solution.
- An **isocline** is a curve along which the slope is constant: $f(x, y) = k$ for a fixed value k. Isoclines help us draw direction fields efficiently.

EXEMPLE **Direction field of $\frac{dy}{dx} = x - y$**


Along the line $y = x$ the slope is 0 (horizontal segments); along $y = x - 1$ the slope is 1; along $y = x + 1$ the slope is -1. The isoclines are the parallel lines $x - y = k$. Sketching segments along these lines and threading curves through them gives the picture below. Notice how all solutions are attracted towards the line $y = x - 1$ (indeed $y = x - 1$ is itself a solution, and the general solution is $y = x - 1 + Ce^{-x}$).



Direction field for $\frac{dy}{dx} = x - y$ (grey segments), the isocline $y = x$ of zero slope (dashed), and four integral curves $y = x - 1 + Ce^{-x}$.

EXEMPLE **Isoclines of $\frac{dy}{dx} = y^2 - x$**

Here the isoclines are the parabolas $x = y^2 - k$. On the parabola $x = y^2$ the slope is 0; on $x = y^2 - 1$ the slope is 1; on $x = y^2 + 1$ the slope is -1. Drawing segments of the appropriate slope along each parabola builds up the field. This equation cannot be solved by elementary methods (it is a Riccati equation), yet the direction field still shows us exactly how its solutions behave – a powerful reminder that geometry can succeed where algebra fails.



Direction field for $\frac{dy}{dx} = y^2 - x$ with isoclines $x = y^2 - k$ (parabolas). Along each parabola all segments have the same slope k.

METHOD **Sketching a direction field by hand**

1. Choose a few convenient slope values k (e.g. -2, -1, 0, 1, 2).
2. For each k, draw the isocline $f(x, y) = k$ and mark on it several short segments of slope k.
3. Fill in extra segments at grid points if needed.
4. Starting from a given point (x_0, y_0), draw a smooth curve that stays tangent to the segments: this is the integral curve through that point.
5. With software: in GeoGebra, type `SlopeField(x - y)` to obtain the field of $\frac{dy}{dx} = x - y$, then `SolveODE(x - y, 0, 1)` to plot the solution through $(0, 1)$.

1.4 Existence and Uniqueness: the Picard–Lindelöf Theorem

Before rushing to solve $\frac{dy}{dx} = f(x, y)$ with $y(x_0) = y_0$, a careful mathematician asks two questions:

- **Existence:** is there any solution at all?
- **Uniqueness:** is there only one solution through (x_0, y_0), or could two different curves pass through the same point?

The answers matter practically: if the farmer's humidity model had no solution, his prediction would be impossible; if it had several, his prediction would be ambiguous.

PROPERTY **Picard–Lindelöf existence and uniqueness theorem**

Let $f(x, y)$ be continuous in a rectangle R containing (x_0, y_0), and suppose f satisfies a **Lipschitz condition** in y on R: there exists a constant $L > 0$ such that for all $(x, y_1), (x, y_2) \in R$,

$$|f(x, y_1) - f(x, y_2)| \le L\,|y_1 - y_2|.$$

(A sufficient condition, easy to check in practice: $\frac{\partial f}{\partial y}$ exists and is continuous, hence bounded, on R.) Then the initial value problem

$$\frac{dy}{dx} = f(x, y), \qquad y(x_0) = y_0,$$

has a unique solution $y = \varphi(x)$, defined on some interval $|x - x_0| \le h$ around x_0. (Statement examinable; proof not required.)

EXEMPLE **Applying the theorem**

For $\frac{dy}{dx} = x - y$, we have $f(x, y) = x - y$, and $\frac{\partial f}{\partial y} = -1$ is continuous everywhere. Hence through every point of the plane there passes exactly one integral curve – which is exactly what the direction field picture suggests: the curves $y = x - 1 + Ce^{-x}$ fill the plane without ever crossing.

WARNING **When uniqueness fails**

The conditions of the theorem are essential. Consider $\frac{dy}{dx} = y^{2/3}$ with $y(0) = 0$. Here $f(x, y) = y^{2/3}$ is continuous, but $\frac{\partial f}{\partial y} = \frac{2}{3}y^{-1/3}$ blows up at $y = 0$: the Lipschitz condition fails. And indeed both $y \equiv 0$ and $y = \frac{x^3}{27}$ are solutions through $(0, 0)$ – uniqueness is lost. Moral: always check the hypotheses before claiming "the" solution.

DID YOU KNOW? **Picard's successive approximations**

Émile Picard's proof constructs the solution as the limit of the sequence

$$\varphi_{n+1}(x) = y_0 + \int_{x_0}^{x} f\big(t, \varphi_n(t)\big)\,dt, \qquad \varphi_0(x) = y_0.$$

This iteration idea – start with a guess, feed it back into the equation, repeat – is the ancestor of many numerical methods used today in weather forecasting and in the simulation software used by engineers, including those modelling river flow and rainfall patterns in Cameroon.

1.5 A First Classification of First-Order Equations

First-order equations come in several families, each with its own method of solution. Recognising the family is the first skill; the methods themselves are developed in the next sections.

Family	Standard form	Example
Separable	$\dfrac{dy}{dx} = g(x)\,h(y)$	$\dfrac{dy}{dx} = \dfrac{x}{y}$
Linear	$\dfrac{dy}{dx} + P(x)\,y = Q(x)$	$\dfrac{dy}{dx} + y = e^{x}$
Homogeneous	$\dfrac{dy}{dx} = F\!\left(\dfrac{y}{x}\right)$	$\dfrac{dy}{dx} = \dfrac{x^2 + y^2}{xy}$
Bernoulli	$\dfrac{dy}{dx} + P(x)\,y = Q(x)\,y^{n}$	$\dfrac{dy}{dx} + y = xy^{2}$
Riccati	$\dfrac{dy}{dx} = q_0(x) + q_1(x)\,y + q_2(x)\,y^{2}$	$\dfrac{dy}{dx} = y^{2} - x$

WARNING **Classify before you solve**

The single most common error at this stage is applying the wrong method – for instance trying to separate variables in $\dfrac{dy}{dx} = x - y$ (impossible: $x - y$ is not a product $g(x)h(y)$). Train yourself to ask, before any computation: is it separable? linear? homogeneous? Bernoulli? Riccati? The example $\dfrac{dy}{dx} = x - y$ is linear; $\dfrac{dy}{dx} = y^{2} - x$ is Riccati.

WORKED EXAMPLE 2 **Classifying equations**

Classify each equation and state its order and degree:

1. $\dfrac{dy}{dx} = \dfrac{x^2}{1 + y^2}$ (b) $x\dfrac{dy}{dx} + y = x^{3}y^{3}$ (c) $\dfrac{dy}{dx} = \dfrac{y}{x} + \dfrac{x}{y}$

SOLUTION

Solution.

1. $\frac{dy}{dx} = x^2 \cdot \frac{1}{1+y^2}$ is a product $g(x)h(y)$: separable; order 1, degree 1.
2. Dividing by x: $\frac{dy}{dx} + \frac{1}{x}y = x^2y^3$. This matches $\frac{dy}{dx} + P(x)y = Q(x)y^n$ with $n = 3$: Bernoulli; order 1, degree 1.
3. $\frac{y}{x} + \frac{x}{y} = \frac{y}{x} + \left(\frac{y}{x}\right)^{-1}$ is a function of $\frac{y}{x}$ alone: homogeneous; order 1, degree 1.

KEY POINTS **Key points of this section**

- A differential equation relates an unknown function to its derivatives; the **order** is the highest derivative present, the **degree** its power.
- The general solution of a first-order equation contains one arbitrary constant; an initial condition $y(x_0) = y_0$ fixes it and selects one particular solution.
- $\frac{dy}{dx} = f(x, y)$ assigns a slope to every point: the **direction field**. Solutions are the **integral curves** tangent to it; **isoclines** ($f(x, y) = k$) organise the sketching.
- Picard–Lindelöf: if f is continuous and Lipschitz in y (e.g. $\frac{\partial f}{\partial y}$ continuous), the IVP has exactly one solution near x_0.
- First-order equations are classified as separable, linear, homogeneous, Bernoulli or Riccati – identify the family before choosing a method.

EXERCISE 1 **Practice**

1. State the order and degree of: (a) $\left(\frac{dy}{dx}\right)^2 + xy = \sin x$; (b) $\frac{d^2y}{dx^2} = \left(1 + \left(\frac{dy}{dx}\right)^2\right)^{3/2}$.
2. Verify that $y = x - 1 + Ce^{-x}$ solves $\frac{dy}{dx} = x - y$, and find the solution through $(0, 2)$.
3. Show that the IVP $\frac{dy}{dx} = 1 + y^2$, $y(0) = 0$, has a unique solution near $x = 0$. (It is $y = \tan x$; check!)
4. Sketch by hand the direction field of $\frac{dy}{dx} = -\frac{x}{y}$ using the isoclines, and guess the shape

of the integral curves.

SOLUTION **Exercise 1**

1. (a) Order 1, degree 2. (b) Squaring: $\left(\frac{d^2y}{dx^2}\right)^2 = \left(1+\left(\frac{dy}{dx}\right)^2\right)^3$: order 2, degree 2.

2. $\frac{dy}{dx} = 1 - Ce^{-x}$ and $x - y = x - (x - 1 + Ce^{-x}) = 1 - Ce^{-x}$: equal ✓. Through $(0, 2)$: $2 = -1 + C$, so $C = 3$ and $y = x - 1 + 3e^{-x}$.

3. $f(x, y) = 1+y^2$ is continuous and $\frac{\partial f}{\partial y} = 2y$ is continuous, hence bounded on any rectangle about $(0, 0)$: Picard–Lindelöf applies, so a unique solution exists near 0. Check: $y = \tan x$ gives $\frac{dy}{dx} = \sec^2 x = 1 + \tan^2 x = 1 + y^2$ and $y(0) = 0$ ✓.

4. Isoclines $-\frac{x}{y} = k$ are the lines $y = -\frac{x}{k}$ through the origin. Segments along them suggest curves everywhere perpendicular to radial lines: the integral curves are the circles $x^2 + y^2 = C$ centred at the origin.

2 SEPARABLE VARIABLES AND LINEAR FIRST-ORDER NON-HOMOGENEOUS EQUATIONS

In the previous section we learned what a first-order differential equation is, how it arises from physical and geometric situations, and how its solutions form a family of curves filling the plane. We also saw that there is no universal formula for solving every first-order equation: each type requires its own technique. In this section we master the two most important techniques of the whole chapter: **separation of variables**, which works whenever the variables can be untangled, and the **integrating factor** method, which solves every linear first-order equation. These two methods, together, settle a large proportion of the differential equations you will meet at the GCE Advanced Level and in applied science.

2.1 Equations with Separable Variables

Intuition.

Suppose the rate of change of a quantity y can be written as a product of a piece that depends only on x and a piece that depends only on y:

$$\frac{dy}{dx} = g(x)\,h(y).$$

For example, $\frac{dy}{dx} = xy$ says: the slope is the product of the position x and the height y. The key idea is to separate the two variables: push everything involving y (including dy) to one side, and everything involving x (including dx) to the other, then integrate both sides. It is as if the equation were a knot that we untie before pulling.

DEFINITION **Separable equation**

A first-order differential equation is called **separable** (or with separable variables) if it can be written in the form

$$\frac{dy}{dx} = g(x)\,h(y),$$

where g is a function of x alone and h is a function of y alone. If $h(y) \neq 0$ on the interval considered, we may divide by $h(y)$ and write

$$\frac{dy}{h(y)} = g(x)\,dx, \qquad \text{hence} \qquad \int \frac{dy}{h(y)} = \int g(x)\,dx + C.$$

PROPERTY **Justification of separation of variables**

Let y be a differentiable function of x satisfying $\frac{dy}{dx} = g(x)h(y)$ with $h(y) \neq 0$. Then $\frac{1}{h(y)}\frac{dy}{dx} = g(x)$. If H is an antiderivative of $1/h$ and G an antiderivative of g, the chain rule gives

$$\frac{d}{dx}\big[H(y(x))\big] = H'(y)\,\frac{dy}{dx} = \frac{1}{h(y)}\frac{dy}{dx} = g(x) = \frac{d}{dx}G(x),$$

so $H(y) = G(x) + C$, which is exactly what the formal rule "$\int dy/h(y) = \int g(x)\,dx + C$" produces. The method is therefore rigorous, not merely symbolic. (This justification is instructive; the method itself is examinable.)

METHOD **Separation of variables – step-by-step algorithm**

1. Factorise: write the equation as $\frac{dy}{dx} = g(x)\,h(y)$. If this is impossible, the equation is not separable – try another method.
2. Check for lost solutions: solve $h(y) = 0$. Each constant root $y = y_0$ is a singular (equilibrium) solution; note it down before dividing.
3. Separate: write $\frac{dy}{h(y)} = g(x)\,dx$.
4. Integrate both sides, adding one constant C (on either side).
5. Solve for y if possible (explicit solution); otherwise leave the answer in implicit form

$H(y) = G(x) + C$.

6. Apply the initial condition if one is given, to fix C.
7. Verify by substituting your answer into the original equation.

WARNING **Forgetting the constant of integration**

After integrating both sides you must add a constant of integration. One constant suffices: $\int \frac{dy}{h(y)} + C_1 = \int g(x)\,dx + C_2$ reduces to $\int \frac{dy}{h(y)} = \int g(x)\,dx + (C_2 - C_1)$, and $C_2 - C_1$ is just an arbitrary constant C. But omitting the constant altogether loses the entire family of solutions and makes it impossible to satisfy an initial condition. In the GCE examination this error costs most of the marks of the question.

WORKED EXAMPLE 3 **Solving $\frac{dy}{dx} = xy$**

Find the general solution of $\frac{dy}{dx} = xy$, then the particular solution with $y(0) = 3$.

SOLUTION


Solution. The equation is separable with $g(x) = x$ and $h(y) = y$.
Step 2 – lost solutions: $h(y) = y = 0$ gives the constant solution $y = 0$.
Steps 3–4: for $y \neq 0$,

$$\frac{dy}{y} = x\,dx \implies \int \frac{dy}{y} = \int x\,dx \implies \ln|y| = \frac{x^2}{2} + C.$$

Step 5: exponentiating, $|y| = e^C e^{x^2/2}$, so $y = Ae^{x^2/2}$ where $A = \pm e^C$ is any non-zero constant. Allowing $A = 0$ recovers the lost solution $y = 0$, so the general solution is

$$y = Ae^{x^2/2}, \qquad A \in \mathbb{R}.$$

Step 6: $y(0) = Ae^0 = A = 3$, hence $y = 3e^{x^2/2}$.
Step 7 – verification: $\frac{dy}{dx} = 3 \cdot xe^{x^2/2} = x\left(3e^{x^2/2}\right) = xy$. ✓



Family of solution curves $y = Ae^{x^2/2}$ of the separable equation $\frac{dy}{dx} = xy$. Through each point of the plane passes exactly one curve; the x-axis ($A = 0$) is the singular solution recovered by allowing $A = 0$.

WARNING **Dividing by $h(y)$: loss of solutions**

When you divide by $h(y)$ you silently assume $h(y) \neq 0$. Constant solutions of $h(y) = 0$ may be lost. In the example above, dividing by y discarded $y = 0$; we recovered it only by allowing $A = 0$. This is not always possible: for $\frac{dy}{dx} = y^{2/3}$, separation gives $y = \left(\frac{x+C}{3}\right)^3$, and the solution $y = 0$ is not obtained for any value of C – it is a genuine singular solution. Always list the roots of $h(y) = 0$ separately.

WORKED EXAMPLE 4 **Implicit solution and singular solutions**

Solve $\frac{dy}{dx} = \frac{x}{y}$ with $y(0) = 2$.

SOLUTION

Solution. Here $h(y) = 1/y$, which never vanishes, so no constant solution is lost. Separating:

$$y\,dy = x\,dx \implies \int y\,dy = \int x\,dx \implies \frac{y^2}{2} = \frac{x^2}{2} + C \implies y^2 - x^2 = 2C.$$

The solution curves are hyperbolas. The initial condition $y(0) = 2$ gives $4 = 2C$, so $y^2 - x^2 = 4$, and since $y(0) = 2 > 0$ we take the positive branch: $y = \sqrt{x^2 + 4}$.

Verification: $\frac{dy}{dx} = \frac{x}{\sqrt{x^2+4}} = \frac{x}{y}$. ✓

WARNING **Watch the sign when removing logarithms**

From $\ln|y| = F(x) + C$ you obtain $|y| = e^{C}e^{F(x)}$, hence $y = \pm e^{C}e^{F(x)}$. Writing simply $y = e^{C}e^{F(x)}$ silently discards all negative solutions. The clean habit is to rename $\pm e^{C}$ as a single arbitrary non-zero constant A, then check whether $A = 0$ is also allowed.

2.2 Linear First-Order Non-Homogeneous Equations: the Integrating Factor

Intuition.

Many equations are not separable, for instance $\frac{dy}{dx} + 2y = e^{-x}$: the right-hand side mixes x and y in a sum, not a product. But such an equation is linear in y. The brilliant idea, going back to Leibniz, is to multiply the whole equation by a cleverly chosen function $\mu(x)$ so that the left-hand side becomes the derivative of a single product, $\frac{d}{dx}[\mu(x)y]$. Integration then finishes the job immediately.

DEFINITION **Linear first-order equation**

A **linear first-order differential equation** is one that can be written in standard form

$$\frac{dy}{dx} + P(x)\,y = Q(x),$$

where P and Q are continuous functions of x on some interval. If $Q(x) \equiv 0$ the equation is homogeneous (and separable); otherwise it is non-homogeneous. The function

$$\mu(x) = e^{\int P(x)\,dx}$$

is called the **integrating factor** of the equation.

PROPERTY **The integrating factor works**

Let $\mu(x) = e^{\int P\,dx}$. Then $\mu'(x) = P(x)\,\mu(x)$ by the chain rule. Multiplying the standard equation by μ:

$$\mu\frac{dy}{dx} + \mu P\,y = \mu Q \iff \mu\frac{dy}{dx} + \frac{d\mu}{dx}\,y = \mu Q \iff \frac{d}{dx}\big[\mu(x)\,y\big] = \mu(x)Q(x).$$

Integrating and dividing by μ (which is always positive, hence never zero):

$$\boxed{y\,\mu(x) = \int \mu(x)Q(x)\,dx + C} \qquad \text{i.e.} \qquad y = \frac{1}{\mu(x)}\left(\int \mu(x)Q(x)\,dx + C\right).$$

(This derivation is examinable and frequently asked.)

METHOD **Integrating factor for linear first-order equations**

1. Standard form: divide through by the coefficient of $\frac{dy}{dx}$ so that the equation reads $\frac{dy}{dx} + P(x)y = Q(x)$.
2. Identify $P(x)$ and compute $\int P(x)\,dx$ (take the constant of integration to be zero here – any one antiderivative works).
3. Compute the integrating factor $\mu(x) = e^{\int P\,dx}$. Simplify: $e^{k\ln|x|} = |x|^k$, and the absolute value may be dropped since μ may be taken positive.
4. Multiply through by μ and recognise the left side as $\frac{d}{dx}[\mu y]$.
5. Integrate: $\mu y = \int \mu Q\,dx + C$, then divide by μ to obtain y.
6. Apply any initial condition and verify by substitution.

WORKED EXAMPLE 5 **Solving $\frac{dy}{dx} + 2y = e^{-x}$**

Find the general solution of $\frac{dy}{dx} + 2y = e^{-x}$, then the solution with $y(0) = 2$.

SOLUTION


Solution. The equation is already in standard form with $P(x) = 2$, $Q(x) = e^{-x}$.
Steps 2–3: $\int P\,dx = 2x$, so $\mu(x) = e^{2x}$.
Step 4: multiplying by e^{2x}:

$$e^{2x}\frac{dy}{dx} + 2e^{2x}y = e^{x} \iff \frac{d}{dx}\left[e^{2x}y\right] = e^{x}.$$

Step 5: integrate: $e^{2x}y = e^{x} + C$, hence

$$y = e^{-x} + Ce^{-2x}.$$

Step 6: $y(0) = 1 + C = 2$ gives $C = 1$, so $y = e^{-x} + e^{-2x}$.
Verification: $\frac{dy}{dx} = -e^{-x} - 2e^{-2x}$, and $\frac{dy}{dx} + 2y = -e^{-x} - 2e^{-2x} + 2e^{-x} + 2e^{-2x} = e^{-x}$. ✓



The integrating factor $\mu(x) = e^{\int P\,dx}$ for three sample equations. A constant P gives an exponential factor; when $P = 0$ the factor is 1 and the equation is solved by direct integration.

WORKED EXAMPLE 6 **A variable coefficient**

Solve $x\dfrac{dy}{dx} - y = x^2$ for $x > 0$.

SOLUTION

Solution. Step 1 – standard form: divide by x:

$$\frac{dy}{dx} - \frac{1}{x}y = x, \qquad P(x) = -\frac{1}{x}, \quad Q(x) = x.$$

Steps 2–3: $\int P\,dx = -\ln x$ (since $x > 0$), so $\mu = e^{-\ln x} = \dfrac{1}{x}$.

Step 4: multiplying by $\dfrac{1}{x}$: $\dfrac{1}{x}\dfrac{dy}{dx} - \dfrac{y}{x^2} = 1$, i.e. $\dfrac{d}{dx}\left(\dfrac{y}{x}\right) = 1$.

Step 5: $\dfrac{y}{x} = x + C$, hence $y = x^2 + Cx$.

Verification: $\dfrac{dy}{dx} = 2x + C$, and $x\dfrac{dy}{dx} - y = 2x^2 + Cx - x^2 - Cx = x^2$. ✓

WARNING **Standard form first!**

The most common error is to read off $P(x)$ before dividing by the coefficient of $\dfrac{dy}{dx}$. In $x\dfrac{dy}{dx} - y = x^2$, students who take $P = -1$ instead of $P = -1/x$ get the wrong integrating factor and a wrong answer. Also remember: the integrating factor is $e^{\int P\,dx}$, not $e^{P(x)}$.

PROPERTY **Superposition fails for non-homogeneous equations**

For the homogeneous linear equation $y' + P(x)y = 0$, any linear combination of solutions is again a solution (superposition holds). This is false for the non-homogeneous equation $y' + P(x)y = Q(x)$ with $Q \not\equiv 0$: if y_1 and y_2 are two solutions, then $y_1 + y_2$ satisfies

$$(y_1 + y_2)' + P(y_1 + y_2) = Q + Q = 2Q \neq Q,$$

so $y_1 + y_2$ is not a solution. What is true: the difference $y_1 - y_2$ solves the homogeneous equation, and the general solution is

$$y = y_p + y_h,$$

where y_p is any one particular solution and $y_h = Ce^{-\int P\,dx}$ is the general solution of the associated homogeneous equation. (Examinable as a structural remark.)

2.3 Modelling Applications

Exponential growth and decay.

When the rate of change of a quantity is proportional to the quantity itself – a bacterial culture in a laboratory in Bamenda, the decay of a radioactive sample, a sum of money at continuous compound interest – we obtain $\dfrac{dy}{dt} = ky$, a separable equation:

$$\frac{dy}{y} = k\,dt \implies \ln|y| = kt + C \implies y = y_0 e^{kt},$$

where $y_0 = y(0)$. Growth corresponds to $k > 0$, decay to $k < 0$.

Newton's law of cooling.

A body at temperature T placed in an environment at constant temperature T_a cools (or warms) at a rate proportional to the difference $T - T_a$:

$$\frac{dT}{dt} = -k(T - T_a), \qquad k > 0.$$

This is linear with $P = k$, $Q = kT_a$; the integrating factor e^{kt} gives $\frac{d}{dt}\left[e^{kt}T\right] = kT_a e^{kt}$, hence

$$T(t) = T_a + \left(T_0 - T_a\right)e^{-kt}.$$

The temperature approaches the ambient temperature T_a exponentially.

WORKED EXAMPLE 7 **Newton's law of cooling**

A bottle of water at 90 °C is placed in a room at 30 °C. After 10 minutes its temperature is 60 °C. Find its temperature after 20 minutes.

SOLUTION

Solution. With $T_a = 30$ and $T_0 = 90$: $T(t) = 30 + 60e^{-kt}$.
At $t = 10$: $60 = 30 + 60e^{-10k}$, so $e^{-10k} = \frac{1}{2}$, giving $k = \frac{\ln 2}{10}$.
At $t = 20$: $e^{-20k} = \left(e^{-10k}\right)^2 = \frac{1}{4}$, so

$$T(20) = 30 + 60 \times \tfrac{1}{4} = 45\,^{\circ}\mathrm{C}.$$

Check: the temperature decreases from 90 towards 30; 45 lies between 60 and 30, as expected. ✓

Mixing problems.

A tank contains a solution; liquid flows in and out at known rates with known concentrations. If $y(t)$ is the amount of dissolved substance (salt, for example) at time t, then

$$\frac{dy}{dt} = (\text{rate in}) - (\text{rate out}),$$

which typically produces a linear first-order equation.

WORKED EXAMPLE 8 **A mixing problem**

A tank contains 100 L of brine with 10 kg of dissolved salt. Fresh water enters at 5 L min^{-1} and the well-stirred mixture leaves at the same rate. Find the amount of salt after 20 minutes.

SOLUTION

Solution. The volume stays constant at 100 L, so the concentration at time t is $\frac{y}{100}$ kg L^{-1}.
Salt enters at rate 0 and leaves at rate $5 \times \frac{y}{100} = \frac{y}{20}$ kg min^{-1}:

$$\frac{dy}{dt} = -\frac{y}{20}.$$

Separating: $\frac{dy}{y} = -\frac{dt}{20}$, so $\ln|y| = -\frac{t}{20} + C$, i.e. $y = y_0 e^{-t/20} = 10e^{-t/20}$.
At $t = 20$: $y = 10e^{-1} \approx 3.68$ kg.
Verification: $\frac{dy}{dt} = -\frac{1}{20} \cdot 10e^{-t/20} = -\frac{y}{20}$. ✓

KEY POINTS **Key points of this section**

- A **separable** equation $\frac{dy}{dx} = g(x)h(y)$ is solved by $\int \frac{dy}{h(y)} = \int g(x)\,dx + C$; check the roots

of $h(y) = 0$ for **singular solutions** before dividing.

- Add one constant of integration after integrating; never forget it.
- A **linear** first-order equation $\frac{dy}{dx} + P(x)y = Q(x)$ is solved with the **integrating factor** $\mu = e^{\int P\,dx}$: then $\frac{d}{dx}[\mu y] = \mu Q$ and $y = \frac{1}{\mu}\left(\int \mu Q\,dx + C\right)$.
- Put the equation in standard form before identifying $P(x)$.
- Superposition fails for non-homogeneous equations; the general solution is $y = y_p + y_h$.
- Growth/decay, Newton's cooling and mixing problems all lead to these two types; always verify your final answer by substitution.

EXERCISE 2 **Practice**

1. Solve $\frac{dy}{dx} = \frac{y}{x}$ for $x > 0$, and identify any solution lost when separating.
2. Solve $\frac{dy}{dx} + y = x$ with $y(0) = 1$.
3. Solve $\frac{dy}{dx} = e^{x-y}$.
4. A radioactive substance decays according to $\frac{dm}{dt} = -km$. If half the mass remains after 5 days, what fraction remains after 15 days?
5. Solve $x\frac{dy}{dx} + 2y = x^3$ for $x > 0$.

SOLUTION **Exercise 1**

1. $\frac{dy}{y} = \frac{dx}{x}$ gives $\ln|y| = \ln x + C$, so $y = Ax$ $(A \in \mathbb{R})$. The solution $y = 0$, lost when dividing by y, is recovered with $A = 0$.
2. $\mu = e^x$: $\frac{d}{dx}[e^x y] = xe^x$, so $e^x y = (x-1)e^x + C$, i.e. $y = x - 1 + Ce^{-x}$. With $y(0) = 1$: $C = 2$, so $y = x - 1 + 2e^{-x}$.
3. $\frac{dy}{dx} = e^x e^{-y}$: $e^y dy = e^x dx$, so $e^y = e^x + C$, i.e. $y = \ln(e^x + C)$, valid where $e^x + C > 0$.
4. $m = m_0 e^{-kt}$ with $e^{-5k} = \frac{1}{2}$. After 15 days: $e^{-15k} = \left(\frac{1}{2}\right)^3 = \frac{1}{8}$ of the initial mass remains.

5. Standard form: $y' + \frac{2}{x}y = x^2$; $\mu = e^{2\ln x} = x^2$. Then $\frac{d}{dx}[x^2 y] = x^4$, so $x^2 y = \frac{x^5}{5} + C$ and $y = \frac{x^3}{5} + \frac{C}{x^2}$.

DID YOU KNOW? **Why "integrating" factor?**

The term was introduced in the 17th century: multiplying by μ makes the equation exactly integrable – the left side becomes a perfect derivative, so a single integration solves the equation. Leonhard Euler systematised the method and showed that every first-order equation possesses an integrating factor, although for non-linear equations there is no general formula to find it. The linear case you have just mastered is the one situation where the factor is given by an explicit formula, $\mu = e^{\int P\,dx}$ – which is why examiners love it.

3 HOMOGENEOUS, BERNOULLI AND RICCATI EQUATIONS

In the previous section we mastered two fundamental families of first-order equations: those with **separable variables**, solved by direct integration, and **linear** equations $y' + P(x)y = Q(x)$, solved by the integrating factor. But nature is not always so kind. Many equations that appear in economics, population dynamics and physics are neither separable nor linear. The good news is that a clever **change of variable** can often transform such an equation into one of the two types we already know. This section presents three classical transformations, each attached to a famous name or structure: homogeneous equations, Bernoulli equations and Riccati equations.

3.1 Homogeneous First-Order Equations

An observation to build intuition.

Consider the equation

$$\frac{dy}{dx} = \frac{x^2 + y^2}{xy}.$$

The variables cannot be separated directly, and the equation is not linear because of the y^2 term. But notice something remarkable: if we replace x by kx and y by ky (a scaling of both variables by the same factor), the right-hand side becomes

$$\frac{(kx)^2 + (ky)^2}{(kx)(ky)} = \frac{k^2(x^2 + y^2)}{k^2 xy} = \frac{x^2 + y^2}{xy}.$$

The equation is unchanged by scaling. Such equations are called **homogeneous**, and this scale-invariance tells us that the equation really only "sees" the ratio $\frac{y}{x}$, not x and y separately. This

suggests introducing the new variable $v = \frac{y}{x}$.

DEFINITION **Homogeneous first-order differential equation**

A first-order differential equation is said to be **homogeneous** if it can be written in the form

$$\frac{dy}{dx} = F\left(\frac{y}{x}\right),$$

where F is a function of a single variable. Equivalently, an equation $M(x, y)\,dx + N(x, y)\,dy = 0$ is homogeneous when M and N are homogeneous functions of the same degree, i.e. $M(kx, ky) = k^d M(x, y)$ and $N(kx, ky) = k^d N(x, y)$ for the same integer d.

WARNING **Two meanings of the word "homogeneous"**

Do not confuse a homogeneous first-order equation $y' = F(y/x)$ with a homogeneous linear equation $y' + P(x)y = 0$ (right-hand side zero). The two notions are different and both appear in the GCE syllabus. Context always makes clear which is meant.

METHOD **Substitution $v = y/x$**

To solve $\frac{dy}{dx} = F\left(\frac{y}{x}\right)$:

1. Set $v = \frac{y}{x}$, so that $y = vx$.
2. Differentiate with respect to x (product rule): $\frac{dy}{dx} = v + x\frac{dv}{dx}$.
3. Substitute into the equation: $v + x\frac{dv}{dx} = F(v)$, hence $x\frac{dv}{dx} = F(v) - v$.
4. This is **separable**: $\int \frac{dv}{F(v) - v} = \int \frac{dx}{x}$, valid where $F(v) \neq v$ and $x \neq 0$.
5. Integrate, then **transform back** by replacing v with $\frac{y}{x}$.
6. Check separately whether constant values of v with $F(v) = v$ (i.e. lines $y = vx$) are lost solutions.

If the equation is more naturally written with x as a function of y, the symmetric substitution $x = vy$ can be used instead.

WORKED EXAMPLE 9 **Solving a homogeneous equation**

Solve $\frac{dy}{dx} = \frac{x^2 + y^2}{xy}$ for $x > 0, y > 0$.

SOLUTION

Step 1 — Check homogeneity. Dividing numerator and denominator by x^2:

$$\frac{dy}{dx} = \frac{1 + (y/x)^2}{y/x} = F\left(\frac{y}{x}\right), \qquad F(v) = \frac{1 + v^2}{v}.$$

Step 2 — Substitute. With $y = vx$, $\frac{dy}{dx} = v + x\frac{dv}{dx}$, so

$$v + x\frac{dv}{dx} = \frac{1 + v^2}{v} = \frac{1}{v} + v \quad \Longrightarrow \quad x\frac{dv}{dx} = \frac{1}{v}.$$


Step 3 — Separate and integrate.

$$\int v\,dv = \int \frac{dx}{x} \quad \Longrightarrow \quad \frac{v^2}{2} = \ln x + C.$$

Step 4 — Transform back. With $v = y/x$:

$$\frac{y^2}{2x^2} = \ln x + C \quad \Longrightarrow \quad \boxed{y^2 = 2x^2(\ln x + C)}.$$

Verification. Differentiating implicitly: $2yy' = 4x(\ln x + C) + 2x = \frac{2y^2}{x} + 2x$, so $y' = \frac{y^2 + x^2}{xy}$. ✓



The substitution $v = y/x$ straightens the geometry: solution curves of the homogeneous equation (left) correspond to solutions of a simple separable equation $v^2 = 2(\ln x + C)$ in the (x, v) plane (right).

3.2 Bernoulli Equations

An observation.

The linear equation $y' + P(x)y = Q(x)$ is spoiled when the right-hand side contains a power of y, as in

$$\frac{dy}{dx} + P(x)y = Q(x)\,y^n.$$

This is the **Bernoulli equation**. For $n = 0$ it is linear; for $n = 1$ it is linear and homogeneous (separable). For all other values of n a simple trick linearises it: divide by y^n and notice that the derivative of y^{1-n} appears.

METHOD **Bernoulli substitution $u = y^{1-n}$**

To solve $y' + P(x)y = Q(x)y^n$ with $n \neq 0, 1$:

1. Divide through by y^n (assuming $y \neq 0$): $y^{-n}y' + P(x)y^{1-n} = Q(x)$.
2. Set $u = y^{1-n}$. Then $\frac{du}{dx} = (1-n)y^{-n}\frac{dy}{dx}$, so $y^{-n}y' = \frac{1}{1-n}\frac{du}{dx}$.
3. The equation becomes **linear** in u:

$$\frac{du}{dx} + (1-n)P(x)\,u = (1-n)Q(x).$$

4. Solve by the integrating factor method.
5. Transform back: $y^{1-n} = u$, i.e. $y = u^{1/(1-n)}$, taking care with signs and domains when $1-n$ is not an odd integer.

6. Check whether the **trivial solution** $y = 0$ (lost when dividing by y^n) satisfies the original equation — it does whenever $n > 0$.

WORKED EXAMPLE 10 **A Bernoulli equation**

Solve $\frac{dy}{dx} + \frac{y}{x} = x^2y^2$ for $x > 0$.

SOLUTION

This is Bernoulli with $n = 2$. Divide by y^2 ($y \neq 0$):

$$y^{-2}\frac{dy}{dx} + \frac{1}{x}y^{-1} = x^2.$$

Set $u = y^{1-2} = y^{-1}$, so $\frac{du}{dx} = -y^{-2}\frac{dy}{dx}$. Then


$$-\frac{du}{dx} + \frac{u}{x} = x^2 \quad \Longrightarrow \quad \frac{du}{dx} - \frac{u}{x} = -x^2.$$

Integrating factor: $\mu = e^{-\int dx/x} = \frac{1}{x}$. Hence

$$\frac{d}{dx}\left(\frac{u}{x}\right) = -x \quad \Longrightarrow \quad \frac{u}{x} = -\frac{x^2}{2} + C \quad \Longrightarrow \quad u = Cx - \frac{x^3}{2}.$$

Transforming back with $u = 1/y$:

$$\boxed{y = \frac{1}{Cx - \frac{x^3}{2}} = \frac{2}{2Cx - x^3}},$$ plus the trivial solution $y = 0$.



Road map of the Bernoulli transformation: the nonlinear equation becomes linear in $u = y^{1-n}$, is solved by the integrating factor, and the answer is then converted back to y.

EXEMPLE **Logistic growth is a Bernoulli equation**

A population $P(t)$ (say of tilapia in a fish farm near Yaoundé) with limited resources obeys the **logistic equation**

$$\frac{dP}{dt} = rP\left(1 - \frac{P}{K}\right) = rP - \frac{r}{K}P^2,$$

where $r > 0$ is the intrinsic growth rate and $K > 0$ the carrying capacity. This is Bernoulli with $n = 2$: $P' - rP = -\frac{r}{K}P^2$. Setting $u = P^{-1}$ gives

$$u' + ru = \frac{r}{K} \quad \Longrightarrow \quad u = \frac{1}{K} + Ce^{-rt}.$$

Transforming back with $P(0) = P_0$:

$$P(t) = \frac{K}{1 + \left(\frac{K}{P_0} - 1\right)e^{-rt}}.$$

As $t \to \infty$, $P \to K$: the population stabilises at the carrying capacity — the famous S-shaped (sigmoid) curve.

3.3 Riccati Equations

DEFINITION **Riccati equation**

A **Riccati equation** is a first-order equation quadratic in the unknown function:

$$\frac{dy}{dx} = a(x) + b(x)y + c(x)y^2,$$

where a, b, c are given functions, $c \not\equiv 0$. In general it cannot be solved by quadratures — unless one particular solution is known.

PROPERTY **Reduction of the Riccati equation**

Suppose y_1 is a **particular solution** of the Riccati equation. Then the substitution

$$y = y_1 + \frac{1}{u}$$

transforms the equation into a linear first-order equation in u:

$$\frac{du}{dx} + \big(b(x) + 2c(x)y_1\big)u = -c(x).$$

(The derivation is examinable and instructive: differentiate $y = y_1 + u^{-1}$, substitute, use the fact that y_1 satisfies the equation, and multiply by $-u^2$; the u^{-2} terms cancel.)

Derivation. Let $y = y_1 + \frac{1}{u}$. Then $y' = y_1' - \frac{u'}{u^2}$. Substituting:

$$y_1' - \frac{u'}{u^2} = a + b\left(y_1 + \frac{1}{u}\right) + c\left(y_1^2 + \frac{2y_1}{u} + \frac{1}{u^2}\right).$$

Since $y_1' = a + by_1 + cy_1^2$, these terms cancel, leaving

$$-\frac{u'}{u^2} = \frac{b}{u} + \frac{2cy_1}{u} + \frac{c}{u^2}.$$

Multiplying by $-u^2$: $u' = -(b + 2cy_1)u - c$, which is linear, as claimed. ■

WORKED EXAMPLE 11 **Riccati with a known particular solution**

Solve $\frac{dy}{dx} = -2 + 3y - y^2$, given that $y_1 = 1$ is a particular solution.

SOLUTION

Check: $y_1 = 1$ gives $y_1' = 0$ and $-2 + 3(1) - 1 = 0$. ✓ So y_1 works.

Set $y = 1 + \frac{1}{u}$. Here $b(x) = 3$, $c(x) = -1$, so the reduced linear equation is

$$u' + (3 + 2(-1)(1))u = -(-1) \quad \Longrightarrow \quad u' + u = 1.$$

Integrating factor e^x: $\frac{d}{dx}(ue^x) = e^x$, so $ue^x = e^x + C$, i.e. $u = 1 + Ce^{-x}$.

Transforming back:

$$\boxed{y = 1 + \frac{1}{1 + Ce^{-x}}}.$$

Note also that $y = 2$ is another constant solution (it corresponds to $C = 0$, i.e. $u = 1$); indeed $-2 + 6 - 4 = 0$. ✓

WARNING **Solutions lost through division**

Substitutions often require divisions that exclude certain values:

- Dividing by x in $v = y/x$ excludes $x = 0$: state the domain of validity.
- Dividing by y^n in Bernoulli's method may lose $y \equiv 0$ (a genuine solution when $n > 0$).
- Dividing by $F(v) - v$ may lose lines $y = vx$ where $F(v) = v$.
- In Riccati's substitution, $u \neq 0$; the particular solution y_1 itself corresponds to $u \to \infty$ and must be listed separately.

At the GCE, always conclude by listing all solutions, including singular ones.

DID YOU KNOW? **Bernoulli, Riccati and the calculus pioneers**

The Bernoulli family of Basel produced several great mathematicians; it was Jacob Bernoulli who studied the equation $y' + Py = Qy^n$ around 1695, and Gottfried Leibniz who showed how to linearise it — one of the very first triumphs of the change-of-variables technique. Count Jacopo Riccati studied his equation in the early 18th century while investigating problems of geometry and mechanics; it later became central in control theory, where the "algebraic Riccati equation" is used to design optimal controllers, from aircraft autopilots to stabilisers in electrical networks.

EXERCISE 3

1. Solve the homogeneous equation $\frac{dy}{dx} = \frac{y}{x} + \tan\frac{y}{x}$ for $x > 0$.
2. Solve the Bernoulli equation $y' + y = e^x y^3$ and state all solutions.
3. Given that $y_1 = x$ is a solution of $y' = 1 - \frac{y}{x} + \frac{y^2}{x^2}$, find the general solution.
4. A rumour spreads in a school of 1000 students according to $\frac{dN}{dt} = 0.5\,N\left(1 - \frac{N}{1000}\right)$, $N(0) = 10$. Find $N(t)$.

SOLUTION **Exercise 1**

1. With $v = y/x$: $v + xv' = v + \tan v$, so $xv' = \tan v$, $\int \frac{\cos v}{\sin v}dv = \int \frac{dx}{x}$, giving $\ln|\sin v| = \ln x + C$, hence $\sin(y/x) = Ax$.
2. $n = 3$, set $u = y^{-2}$: $u' - 2u = -2e^x$. Integrating factor e^{-2x}: $(ue^{-2x})' = -2e^{-x}$, so $ue^{-2x} = 2e^{-x} + C$, $u = 2e^x + Ce^{2x}$. Thus $y^2 = \frac{1}{2e^x + Ce^{2x}}$, plus $y \equiv 0$.
3. Check $y_1 = x$: $y_1' = 1$ and $1 - 1 + 1 = 1$. ✓ Set $y = x + 1/u$: reduced equation $u' + \left(-\frac{1}{x} + \frac{2x}{x^2}\right)u = -\frac{1}{x^2}$, i.e. $u' + \frac{u}{x} = -\frac{1}{x^2}$. Integrating factor x: $(xu)' = -\frac{1}{x}$, so $xu = -\ln x + C$, $u = \frac{C - \ln x}{x}$, and $y = x + \frac{x}{C - \ln x}$.
4. Logistic with $K = 1000$, $r = 0.5$, $P_0 = 10$: $N(t) = \frac{1000}{1 + 99e^{-0.5t}}$.

KEY POINTS **Key points**

- **Homogeneous** equation $y' = F(y/x)$: substitute $v = y/x$, $y' = v + xv'$; the equation be-

comes separable.

- **Bernoulli** equation $y' + Py = Qy^n$ ($n \neq 0, 1$): substitute $u = y^{1-n}$; the equation becomes linear.
- **Riccati** equation $y' = a + by + cy^2$: if a particular solution y_1 is known, $y = y_1 + 1/u$ gives a linear equation.
- Always **transform back** to the original variable, state the **domain**, and recover any solutions lost by division (especially $y \equiv 0$).
- The logistic equation of population dynamics is a Bernoulli equation with $n = 2$.

4 LINEAR SECOND-ORDER DIFFERENTIAL EQUATIONS WITH CONSTANT COEFFICIENTS

In the previous section we tamed first-order equations of special forms — homogeneous equations, Bernoulli's equation and Riccati's equation — by means of clever substitutions. We now move up one order, addressing **Lesson 64** of the official syllabus. Second-order differential equations are the workhorses of physics and engineering: the oscillation of a mass on a spring, the current in an RLC circuit, the vibration of the bridge over the Wouri estuary in Douala, the swing of a pendulum in a physics laboratory in Yaoundé — all are governed by equations of the form

$$a\frac{d^2y}{dx^2} + b\frac{dy}{dx} + cy = f(x), \qquad a \neq 0,$$

where a, b, c are real constants. Remarkably, this whole family can be solved completely and explicitly. The key, once again, is linearity.

4.1 The Homogeneous Equation and the Superposition Principle

DEFINITION **Linear second-order equation with constant coefficients**

A **linear second-order differential equation with constant coefficients** is an equation of the form

$$ay'' + by' + cy = f(x),$$

where $a, b, c \in \mathbb{R}$, $a \neq 0$, and f is a given continuous function on an interval I. When $f(x) \equiv 0$ on I the equation is called **homogeneous**; otherwise it is **non-homogeneous**, and $f(x)$ is called the right-hand side (or forcing term).

Think of a concrete situation: a mass m attached to a spring (stiffness k), with damping from air resistance (coefficient λ). Newton's second law gives $m\ddot{y} + \lambda\dot{y} + ky = F(t)$: acceleration term, friction term, spring term, external force. Exactly our equation with $x = t$.

The reason linear equations are so tractable is the following fundamental property.

PROPERTY **Superposition principle**

If y_1 and y_2 are solutions of the homogeneous equation $ay'' + by' + cy = 0$ on an interval I, then for any constants $C_1, C_2 \in \mathbb{R}$, the linear combination $y = C_1y_1 + C_2y_2$ is also a solution on I. Moreover, if y_1 and y_2 are linearly independent (neither is a constant multiple of the other), then $y = C_1y_1 + C_2y_2$ is the general solution: every solution of the equation on I has this form for a unique pair (C_1, C_2).

Proof (examinable and instructive). Define the linear differential operator $L[y] = ay'' + by' + cy$. Since differentiation is linear,

$$L[C_1y_1 + C_2y_2] = a(C_1y_1'' + C_2y_2'') + b(C_1y_1' + C_2y_2') + c(C_1y_1 + C_2y_2) = C_1L[y_1] + C_2L[y_2] = 0.$$

So any linear combination of solutions is a solution. That the general solution of a second-order linear equation depends on exactly two arbitrary constants follows from the existence and uniqueness theorem for initial value problems: a solution is completely determined by the two initial values $y(x_0)$ and $y'(x_0)$ at any $x_0 \in I$, and the two constants C_1, C_2 provide exactly the two degrees of freedom needed to match arbitrary initial data. ■

WARNING **Two constants, not one**

A first-order equation has a general solution with one arbitrary constant; a second-order equation needs two. Writing $y = Ce^{rx}$ as the "general solution" of $y'' - y = 0$ is a classic error: you have lost half the solutions (for instance e^{-x}). Always check that your two candidate solutions are not proportional.

4.2 The Characteristic Equation

How do we find two linearly independent solutions? Follow the intuition from first-order equations: the solution of $y' + ky = 0$ is an exponential e^{-kx}, because the exponential is the only function whose derivative is a constant multiple of itself. Let us therefore try $y = e^{rx}$ in $ay'' + by' + cy = 0$. Since $y' = re^{rx}$ and $y'' = r^2e^{rx}$,

$$ar^2e^{rx} + bre^{rx} + ce^{rx} = e^{rx}\left(ar^2 + br + c\right) = 0.$$

As $e^{rx} \neq 0$ for all real x, the trial works if and only if r satisfies an algebraic equation.

DEFINITION **Characteristic equation**

The **characteristic equation** (or auxiliary equation) of $ay'' + by' + cy = 0$ is the quadratic

$$ar^2 + br + c = 0, \qquad \text{with discriminant } \Delta = b^2 - 4ac.$$

The whole behaviour of the differential equation is encoded in the roots of this quadratic. Three cases arise.

PROPERTY **The three cases — general solution of $ay'' + by' + cy = 0$**

Let r_1, r_2 be the roots of $ar^2 + br + c = 0$.

1. Real distinct roots ($\Delta > 0$): $y = C_1 e^{r_1 x} + C_2 e^{r_2 x}$.
2. Real repeated root ($\Delta = 0$, root r_0): $y = (C_1 + C_2 x)e^{r_0 x}$.
3. Complex conjugate roots ($\Delta < 0$), $r = \alpha \pm i\beta$ ($\beta > 0$): $y = e^{\alpha x}\left(C_1 \cos \beta x + C_2 \sin \beta x\right)$.

Justification of the repeated-root case (instructive). When $\Delta = 0$, the characteristic equation gives only one exponential $y_1 = e^{r_0 x}$; we need a second, independent solution. Try $y_2 = xe^{r_0 x}$. With $r_0 = -\dfrac{b}{2a}$ (repeated root) and $c = ar_0^2$ (since $\Delta = b^2 - 4ac = 0$):

$$\begin{aligned} y_2' &= e^{r_0 x}(1 + r_0 x), \qquad y_2'' = e^{r_0 x}(2r_0 + r_0^2 x), \\ ay_2'' + by_2' + cy_2 &= e^{r_0 x}\left[a(2r_0 + r_0^2 x) + b(1 + r_0 x) + ar_0^2 x\right] \\ &= e^{r_0 x}\left[(2ar_0 + b) + x(ar_0^2 + br_0 + c)\right] = e^{r_0 x}(0 + 0) = 0, \end{aligned}$$

since $2ar_0 + b = 0$ (repeated root condition) and $ar_0^2 + br_0 + c = 0$. Hence $xe^{r_0 x}$ is indeed a second solution, not proportional to $e^{r_0 x}$.

Justification of the complex-root case. For $r = \alpha \pm i\beta$, Euler's formula gives $e^{(\alpha \pm i\beta)x} = e^{\alpha x}(\cos \beta x \pm i \sin \beta x)$. The two complex solutions $e^{(\alpha + i\beta)x}$ and $e^{(\alpha - i\beta)x}$ are linearly independent. By the superposition principle, their real and imaginary parts — $e^{\alpha x} \cos \beta x$ and $e^{\alpha x} \sin \beta x$ — are also solutions, and they are linearly independent. Hence the real general solution is $y = e^{\alpha x}(C_1 \cos \beta x + C_2 \sin \beta x)$.

METHOD **Solving the homogeneous equation**

1. Write the characteristic equation $ar^2 + br + c = 0$.
2. Compute $\Delta = b^2 - 4ac$ and find the roots.
3. Apply the matching formula:
   - Distinct real roots $r_1, r_2 \to y = C_1 e^{r_1 x} + C_2 e^{r_2 x}$.
   - Repeated root $r_0 \to y = (C_1 + C_2 x)e^{r_0 x}$.
   - Complex roots $\alpha \pm i\beta \to y = e^{\alpha x}(C_1 \cos \beta x + C_2 \sin \beta x)$.
4. If initial conditions $y(x_0)$, $y'(x_0)$ are given, substitute into the general solution and its derivative to find C_1 and C_2.

WORKED EXAMPLE 12 **One example of each case**

Solve: (a) $y'' - 3y' + 2y = 0$; (b) $y'' - 4y' + 4y = 0$ with $y(0) = 1, y'(0) = 4$; (c) $y'' + 2y' + 5y = 0$.

SOLUTION

(a) Characteristic equation: $r^2 - 3r + 2 = 0$, i.e. $(r - 1)(r - 2) = 0$, so $r_1 = 1, r_2 = 2$ (real distinct).

$$y = C_1 e^{x} + C_2 e^{2x}.$$


(b) $r^2 - 4r + 4 = (r - 2)^2 = 0$: repeated root $r_0 = 2$. Hence $y = (C_1 + C_2 x)e^{2x}$. Initial conditions: $y(0) = C_1 = 1$. Differentiate: $y' = C_2 e^{2x} + 2(C_1 + C_2 x)e^{2x}$, so $y'(0) = C_2 + 2C_1 = 4$, giving $C_2 = 2$.

$$y = (1 + 2x)e^{2x}.$$

(c) $r^2 + 2r + 5 = 0$: $\Delta = 4 - 20 = -16$, so $r = \dfrac{-2 \pm 4i}{2} = -1 \pm 2i$. Here $\alpha = -1, \beta = 2$:

$$y = e^{-x}\left(C_1 \cos 2x + C_2 \sin 2x\right).$$

The three cases have beautiful physical meanings. For a damped oscillator $m\ddot{y} + \lambda\dot{y} + ky = 0$ ($m, \lambda, k > 0$): distinct negative real roots give overdamping (slow return to rest, no oscillation); a repeated root gives critical damping (fastest return without oscillation); complex roots with negative real part give underdamping (oscillations that die away).



The three root cases: overdamped (real distinct roots), critically damped (repeated root) and underdamped (complex roots) motion.

4.3 The Non-Homogeneous Equation: Undetermined Coefficients

Now consider $ay'' + by' + cy = f(x)$ with $f \not\equiv 0$. The structure of the general solution is simple and crucial.

PROPERTY **General solution = complementary function + particular integral**

The general solution of $ay'' + by' + cy = f(x)$ on an interval I is

$$y = \underbrace{y_c}_{\text{complementary function}} + \underbrace{y_p}_{\text{particular integral}},$$

where y_c is the general solution of the associated homogeneous equation $ay'' + by' + cy = 0$ and y_p is any one particular solution of the full equation on I.

Proof. If y_p solves the full equation and y is any other solution, then $L[y - y_p] = L[y] - L[y_p] = f - f = 0$, so $y - y_p$ solves the homogeneous equation, i.e. $y - y_p = y_c$. ■

The **method of undetermined coefficients** finds y_p by guessing its shape from the shape of $f(x)$, with unknown coefficients to be determined by substitution. It works when $f(x)$ is a linear combination of functions of the forms: polynomials, exponentials e^{px}, sines/cosines $\cos \omega x$, $\sin \omega x$, and products of these.

METHOD **Standard trial functions**

Choose the trial y_p according to $f(x)$. If $f(x)$ is a sum of several terms, find a particular integral for each term separately and add them (superposition for particular integrals).

Right-hand side $f(x)$	Trial function y_p
Polynomial of degree n	General polynomial of degree n: $A_n x^n + \cdots + A_1 x + A_0$
ke^{px}	Ae^{px}
$k \cos \omega x$ or $k \sin \omega x$	$A \cos \omega x + B \sin \omega x$ (both terms, even if only one appears in f)
$ke^{px} \cos \omega x$ or $ke^{px} \sin \omega x$	$e^{px}(A \cos \omega x + B \sin \omega x)$
Polynomial × exponential e^{px}	(General polynomial of same degree)$\times e^{px}$
Polynomial × $\cos \omega x$ or $\sin \omega x$	(General polynomial)$\times(A \cos \omega x + B \sin \omega x)$

Then substitute the trial into the equation, equate coefficients of like terms, and solve for $A, B, \ldots$

WARNING **The modification rule — resonance of the trial**

If the natural trial function (or any part of it) is itself a solution of the homogeneous equation, substitution gives 0 on the left and the method collapses. The cure: multiply the trial by x. If the root is a repeated root of the characteristic equation (so that both $e^{r_0 x}$ and $xe^{r_0 x}$ are homogeneous solutions), multiply by x^2.

For example, for $y'' - y = e^x$, the trial Ae^x fails because e^x solves $y'' - y = 0$; use $y_p = Axe^x$ instead. For $y'' - 2y' + y = e^x$, the characteristic equation has a repeated root $r = 1$, so both e^x and xe^x are homogeneous solutions; the trial must be $y_p = Ax^2e^x$.

WORKED EXAMPLE 13 **Undetermined coefficients**

Find the general solution of $y'' - 3y' + 2y = 4x + 6e^{3x}$.

SOLUTION

Step 1 — Complementary function. Characteristic equation: $r^2 - 3r + 2 = 0$, roots $r = 1, 2$. So $y_c = C_1e^x + C_2e^{2x}$.
Step 2 — Particular integral for $4x$. Try $y_{p_1} = Ax + B$. Then $y'_{p_1} = A$, $y''_{p_1} = 0$, and

$$0 - 3A + 2(Ax + B) = 2Ax + (2B - 3A) = 4x.$$

Equating coefficients: $2A = 4 \Rightarrow A = 2$; $2B - 3A = 0 \Rightarrow B = 3$. So $y_{p_1} = 2x + 3$.
Step 3 — Particular integral for $6e^{3x}$. Try $y_{p_2} = De^{3x}$ (note 3 is not a root of $r^2 - 3r + 2 = 0$, so no modification needed). Then

$$9De^{3x} - 9De^{3x} + 2De^{3x} = 2De^{3x} = 6e^{3x} \Rightarrow D = 3.$$

Step 4 — General solution.

$$y = C_1e^x + C_2e^{2x} + 2x + 3 + 3e^{3x}.$$

Check: $y''_p - 3y'_p + 2y_p$ for $y_p = 2x + 3 + 3e^{3x}$ gives $(27e^{3x}) - 3(2 + 9e^{3x}) + 2(2x + 3 + 3e^{3x}) = 4x + 6e^{3x}$. ✓

WORKED EXAMPLE 14 **The modification rule in action**

Solve $y'' - y = e^x$.

SOLUTION

Complementary function: $r^2 - 1 = 0 \Rightarrow r = \pm 1$, so $y_c = C_1e^x + C_2e^{-x}$. The trial Ae^x is a homogeneous solution — it would give 0, never e^x. Apply the modification rule: try $y_p = Axe^x$. Then

$$y'_p = Ae^x(x + 1), \qquad y''_p = Ae^x(x + 2),$$

$$y''_p - y_p = Ae^x(x + 2 - x) = 2Ae^x = e^x \Rightarrow A = \tfrac{1}{2}.$$

General solution: $y = C_1e^x + C_2e^{-x} + \tfrac{1}{2}xe^x$.

4.4 Variation of Parameters

Undetermined coefficients is fast but only works when $f(x)$ has one of the standard shapes (polynomials, exponentials, sines and cosines, and their products). What about $y'' + y = \tan x$ or $y'' - y = \dfrac{e^x}{x}$? We need a general method.

The idea, due to Lagrange, is elegant: take the complementary function $y_c = C_1y_1 + C_2y_2$ and let the "constants" vary: seek

$$y_p = u(x)y_1(x) + v(x)y_2(x).$$

Differentiating: $y_p' = u'y_1 + v'y_2 + uy_1' + vy_2'$. Since we have two unknown functions but only one equation to satisfy, we are free to impose one extra condition; the clever choice is

$$u'y_1 + v'y_2 = 0,$$

which keeps $y_p' = uy_1' + vy_2'$ simple. Then $y_p'' = u'y_1' + v'y_2' + uy_1'' + vy_2''$. Substituting into $ay'' + by' + cy = f$ and using $L[y_1] = L[y_2] = 0$, everything collapses to

$$a(u'y_1' + v'y_2') = f(x).$$

PROPERTY **Variation of parameters — Lagrange's system**

If $y_c = C_1y_1 + C_2y_2$ is the complementary function of $ay'' + by' + cy = f(x)$, a particular integral is $y_p = uy_1 + vy_2$ where u, v satisfy

$$\begin{cases} u'y_1 + v'y_2 = 0, \\ u'y_1' + v'y_2' = \dfrac{f(x)}{a}. \end{cases}$$

Solving this linear system for u' and v' (the determinant $W = y_1y_2' - y_1'y_2$, the Wronskian, is non-zero because y_1, y_2 are independent) and integrating gives u and v. This method works for any continuous right-hand side $f(x)$.

Explicit formulas (useful for quick computation):

$$u' = -\frac{y_2 f}{aW}, \qquad v' = \frac{y_1 f}{aW}, \qquad W = y_1y_2' - y_1'y_2.$$

WORKED EXAMPLE 15 **Variation of parameters**

Solve $y'' + y = \tan x$ for $-\dfrac{\pi}{2} < x < \dfrac{\pi}{2}$.

SOLUTION

Complementary function: $r^2 + 1 = 0 \Rightarrow r = \pm i$, so $y_1 = \cos x$, $y_2 = \sin x$. Wronskian $W =$

$\cos x \cdot \cos x - (-\sin x)\sin x = 1$. Lagrange's system with $a = 1$, $f = \tan x$:

$$\begin{cases} u'\cos x + v'\sin x = 0, \\ -u'\sin x + v'\cos x = \tan x. \end{cases}$$

Multiply the first by $\sin x$, the second by $\cos x$ and add: $v'(\sin^2 x + \cos^2 x) = \tan x \cos x = \sin x$, so $v' = \sin x$ and $v = -\cos x$. Then $u'\cos x = -v'\sin x = -\sin^2 x$, so

$$u' = -\frac{\sin^2 x}{\cos x} = \frac{\cos^2 x - 1}{\cos x} = \cos x - \sec x, \qquad u = \sin x - \ln|\sec x + \tan x|.$$

Therefore

$$y_p = u\cos x + v\sin x = \sin x\cos x - \cos x \ln|\sec x + \tan x| - \cos x \sin x = -\cos x \ln|\sec x + \tan x|,$$

and the general solution is

$$y = C_1\cos x + C_2\sin x - \cos x \ln|\sec x + \tan x|.$$

Note that $\tan x$ is outside the reach of undetermined coefficients — variation of parameters was essential.

4.5 Resonance

The most dramatic application is the **forced oscillator**

$$\ddot{y} + \omega_0^2 y = F_0\cos(\omega t),$$


modelling a swing pushed periodically, or an LC circuit driven by an alternating source. The natural frequency is ω_0; the forcing frequency is ω.

If $\omega \neq \omega_0$, the trial $y_p = A\cos\omega t + B\sin\omega t$ gives $A = \dfrac{F_0}{\omega_0^2 - \omega^2}$, $B = 0$: bounded oscillations.

If $\omega = \omega_0$, the trial overlaps the complementary function $\cos\omega_0 t$, so by the modification rule we try $y_p = At\cos\omega_0 t + Bt\sin\omega_0 t$. Substitution yields

$$y_p = \frac{F_0}{2\omega_0}\, t\sin\omega_0 t.$$

The amplitude $\dfrac{F_0}{2\omega_0}t$ grows linearly with time: this is **resonance**. Small periodic pushes at exactly the natural frequency accumulate — the reason soldiers break step when crossing a bridge, and the reason a child on a swing in Buea goes higher when pushed in rhythm.



Forced oscillation: at resonance the amplitude grows linearly (envelope shown dashed); away from resonance the response stays bounded (beats).

WARNING **Common mistakes to avoid**

- Forgetting the modification rule: if your trial solves the homogeneous equation, multiply by x (or x^2 for a repeated root).
- For $\cos \omega x$ or $\sin \omega x$ on the right, the trial must contain both $A \cos \omega x$ and $B \sin \omega x$ — differentiation mixes the two families.
- Applying initial conditions to y_c before adding y_p: constants must be determined from the complete general solution $y_c + y_p$.
- Sign slips in the characteristic equation: for $ay'' + by' + cy = 0$ it is $ar^2 + br + c = 0$ with the signs of b and c unchanged.
- In variation of parameters, forgetting to divide $f(x)$ by a (the coefficient of y'') in the second equation of Lagrange's system.

EXERCISE 4 **Practice**

1. Solve $y'' + y' - 6y = 0$ with $y(0) = 1$, $y'(0) = 2$.
2. Find the general solution of $y'' + 4y' + 4y = 8e^{3x}$.
3. Solve $y'' + 4y = 8 \cos 2x$ (careful with the trial function!).
4. Use variation of parameters to solve $y'' + y = \sec x$ on $\left(-\frac{\pi}{2}, \frac{\pi}{2}\right)$.

SOLUTION **Exercise 1**

1. $r^2 + r - 6 = (r + 3)(r - 2) = 0$: $y = C_1 e^{-3x} + C_2 e^{2x}$. Conditions: $C_1 + C_2 = 1$, $-3C_1 + 2C_2 = 2$, giving $C_1 = 0$, $C_2 = 1$: $y = e^{2x}$.
2. Repeated root $r = -2$: $y_c = (C_1 + C_2 x)e^{-2x}$. Trial $y_p = Ae^{3x}$: $9A + 12A + 4A = 25A = 8$, so $A = \frac{8}{25}$. General solution $y = (C_1 + C_2 x)e^{-2x} + \frac{8}{25}e^{3x}$.
3. $y_c = C_1 \cos 2x + C_2 \sin 2x$. Since $\cos 2x$ solves the homogeneous equation, try $y_p = x(A \cos 2x + B \sin 2x)$. Substitution gives $4B \cos 2x - 4A \sin 2x = 8 \cos 2x$, so $B = 2$, $A = 0$: $y = C_1 \cos 2x + C_2 \sin 2x + 2x \sin 2x$ (pure resonance).
4. $y_1 = \cos x$, $y_2 = \sin x$; Wronskian $W = 1$. Lagrange's system gives $u' = -\tan x$, $v' = 1$, so $u = \ln(\cos x)$, $v = x$. Hence $y = C_1 \cos x + C_2 \sin x + \cos x \ln(\cos x) + x \sin x$.

KEY POINTS **Key points of this section**

- Homogeneous equation $ay'' + by' + cy = 0$: solve the characteristic equation $ar^2 + br + c = 0$; three cases give $C_1 e^{r_1 x} + C_2 e^{r_2 x}$, $(C_1 + C_2 x)e^{r_0 x}$, or $e^{\alpha x}(C_1 \cos \beta x + C_2 \sin \beta x)$.
- Non-homogeneous equation: general solution = complementary function + particular integral.
- Undetermined coefficients: mirror the shape of $f(x)$; if the trial overlaps y_c, multiply by x (or x^2 for a repeated root).
- Variation of parameters: $y_p = uy_1 + vy_2$ with $u'y_1 + v'y_2 = 0$, $u'y_1' + v'y_2' = f/a$ — valid for any continuous f.
- Resonance: forcing at the natural frequency produces a particular integral of the form $t \sin \omega_0 t$ with linearly growing amplitude (in the undamped case).

DID YOU KNOW? **Tacoma Narrows and the Wouri bridge**

In 1940 the Tacoma Narrows Bridge in the USA collapsed after wind drove it near one of its natural frequencies — the classic cautionary tale of resonance taught to every engineering student. Engineers designing great structures such as the bridges over the Wouri estuary in Douala must compute natural frequencies carefully and add damping, so that wind and traffic can never pump energy in rhythm. The mathematics you have just learned — characteristic roots and particular integrals — is exactly the tool they use.

5 REDUCIBLE EQUATIONS, REDUCTION OF ORDER AND MODELLING APPLICATIONS

5.1 Equations Missing the Dependent Variable y

When a second-order differential equation does not contain the dependent variable y explicitly, it can be written in the form

$$y'' = f(x, y').$$

The substitution $p = y'$ reduces the order: $y'' = p' = \dfrac{dp}{dx}$. The equation becomes a first-order equation in p:

$$\frac{dp}{dx} = f(x, p).$$

Once $p(x)$ is found, y is obtained by integration: $y = \int p(x)\,dx + C$.

METHOD **Solving equations missing y**

1. Set $p = y'$. Then $y'' = \dfrac{dp}{dx}$.
2. Substitute into the given equation to obtain a first-order equation for $p(x)$.
3. Solve this first-order equation (separable, linear, etc.) to find $p(x)$.
4. Integrate $p(x)$ with respect to x to obtain $y(x)$, adding the constant of integration.
5. If initial conditions are given, apply them to determine the constants.

WORKED EXAMPLE 16 **Equation missing y: $y'' = x\,y'$**

Find the general solution of $y'' = x\,y'$.

SOLUTION

Solution. Let $p = y'$. Then $y'' = \dfrac{dp}{dx}$. The equation becomes

$$\frac{dp}{dx} = x\,p.$$

This is separable:

$$\frac{dp}{p} = x\,dx \quad \Longrightarrow \quad \ln|p| = \frac{x^2}{2} + C_1.$$

Hence $p = C_1' e^{x^2/2}$ where $C_1' = \pm e^{C_1}$ is an arbitrary non-zero constant (the case $p = 0$ gives the constant solution $y =$ constant, which is included by allowing $C_1' = 0$). Now integrate

to find y:

$$y = \int C_1' e^{x^2/2}\,dx + C_2.$$

The integral $\int e^{x^2/2}\,dx$ cannot be expressed in terms of elementary functions; it is written in terms of the imaginary error function or left as a definite integral. Thus the general solution is

$$y = C_1 \int_0^x e^{t^2/2}\,dt + C_2,$$

where C_1, C_2 are arbitrary constants.

5.2 Equations Missing the Independent Variable x

If the equation does not contain x explicitly, it has the form

$$y'' = f(y, y').$$

Again set $p = y'$. Then by the chain rule

$$y'' = \frac{dp}{dx} = \frac{dp}{dy}\frac{dy}{dx} = p\,\frac{dp}{dy}.$$

The equation becomes a first-order equation in p and y:

$$p\,\frac{dp}{dy} = f(y, p).$$

This can often be solved by separation of variables or by recognizing it as an exact equation. After finding $p(y)$, we use $dy/dx = p(y)$ to obtain x as a function of y (or y as a function of x by inversion).

METHOD **Solving equations missing x**

1. Set $p = y'$. Then $y'' = p\,\dfrac{dp}{dy}$.
2. Substitute to get $p\,\dfrac{dp}{dy} = f(y, p)$.
3. Solve this first-order equation for p as a function of y.
4. Use $\dfrac{dy}{dx} = p(y)$ to find $x = \displaystyle\int \frac{dy}{p(y)} + C$ (or solve for $y(x)$ if possible).
5. Apply initial conditions to determine constants.

WORKED EXAMPLE 17 **Equation missing x: $y'' + k\,y = 0$ (simple harmonic oscillator)**

Solve $y'' + k\,y = 0$ with $k > 0$ by the missing-x method.

SOLUTION

Solution. The equation is $y'' = -k\,y$. Let $p = y'$. Then $y'' = p\,\dfrac{dp}{dy}$. Substituting:

$$p\,\frac{dp}{dy} = -k\,y.$$

Separate variables:

$$p\,dp = -k\,y\,dy \quad\Longrightarrow\quad \frac{p^2}{2} = -\frac{k y^2}{2} + C.$$

Multiply by 2: $p^2 + k y^2 = 2C = E$ (constant). This is the energy integral. Hence

$$p = \frac{dy}{dx} = \pm\sqrt{E - k y^2}.$$


Separate again:

$$\frac{dy}{\sqrt{E - k y^2}} = \pm dx.$$

Integrate: $\dfrac{1}{\sqrt{k}}\arcsin\!\left(\dfrac{\sqrt{k}\,y}{\sqrt{E}}\right) = \pm x + \phi$. Thus

$$y = \sqrt{\frac{E}{k}}\,\sin\!\left(\sqrt{k}\,x + \phi\right),$$

which is the familiar sinusoidal solution. The phase plane trajectories are ellipses given by $p^2 + k y^2 = E$.



Phase plane trajectories for $p\,dp/dy = -2y$ (ellipses $p^2 + 2y^2 = E$).

5.3 Reduction of Order for Linear Homogeneous Second-Order Equations

Consider a linear homogeneous second-order equation in standard form

$$y'' + P(x)y' + Q(x)y = 0.$$

If one non-trivial solution $y_1(x)$ is known, a second linearly independent solution can be found by the substitution

$$y = y_1(x)\,v(x),$$

where $v(x)$ is a new unknown function. This method is called **reduction of order**.

PROPERTY **Reduction of order formula**

If y_1 is a known solution of $y'' + P(x)y' + Q(x)y = 0$, then a second independent solution is

$$y_2 = y_1 \int \frac{e^{-\int P(x)\,dx}}{y_1^2}\,dx.$$

The derivation uses the substitution $y = y_1 v$ and reduces the equation to a first-order linear equation for v'.

METHOD **Reduction of order – step by step**

1. Write the equation in standard form $y'' + P(x)y' + Q(x)y = 0$.
2. Let $y = y_1 v$. Compute $y' = y_1' v + y_1 v'$ and $y'' = y_1'' v + 2y_1' v' + y_1 v''$.
3. Substitute into the equation. Because y_1 is a solution, terms containing v cancel, leaving an equation for v' and v''.
4. Set $w = v'$. The equation becomes first-order linear in w: $y_1 w' + (2y_1' + Py_1)w = 0$.
5. Solve for w, then integrate to get v, and finally $y_2 = y_1 v$.
6. The general solution is $y = C_1 y_1 + C_2 y_2$.

WORKED EXAMPLE 18 **Reduction of order: $y'' - 2y' + y = 0$, known solution $y_1 = e^x$**

Find the general solution.

SOLUTION

Solution. The equation is already in standard form with $P(x) = -2$. Let $y = e^x v$. Then

$$y' = e^x v + e^x v', \quad y'' = e^x v + 2e^x v' + e^x v''.$$

Substitute:

$$(e^x v + 2e^x v' + e^x v'') - 2(e^x v + e^x v') + e^x v = 0.$$

The terms with v cancel: $e^x v - 2e^x v + e^x v = 0$. The remaining terms give

$$e^x v'' = 0 \quad \Longrightarrow \quad v'' = 0.$$

Integrate twice: $v' = C_1$, $v = C_1 x + C_2$. Choosing $C_1 = 1, C_2 = 0$ gives $v = x$. Hence a second independent solution is $y_2 = xe^x$. The general solution is

$$y = C_1 e^x + C_2 x e^x.$$

5.4 Modelling Applications

Differential equations arise naturally when modelling physical, biological or engineering systems. The process involves identifying the variables, stating the governing laws (Newton's laws, Kirchhoff's laws, population dynamics), and translating them into a differential equation.

EXPERIMENT **Modelling: Newton's Law of Cooling**

A cup of coffee at temperature $T(t)$ cools in a room at constant temperature T_a. Newton's law of cooling states that the rate of change of temperature is proportional to the difference between the object's temperature and the ambient temperature:

$$\frac{dT}{dt} = -k(T - T_a), \quad k > 0.$$

If the coffee is initially at $T(0) = T_0$, the solution is $T(t) = T_a + (T_0 - T_a)e^{-kt}$. This is a first-order linear equation. For a second-order example, consider a mass-spring-damper system or an RLC circuit.

Simple harmonic motion.

A mass m attached to a spring of stiffness k (no damping) obeys $my'' + ky = 0$, where y is displacement from equilibrium. The solution is $y = A\cos(\omega t) + B\sin(\omega t)$ with $\omega = \sqrt{k/m}$.

RLC series circuit.

In a series circuit with resistance R, inductance L, capacitance C and applied voltage $E(t)$, Kirchhoff's voltage law gives

$$L\frac{d^2q}{dt^2} + R\frac{dq}{dt} + \frac{1}{C}q = E(t),$$

where $q(t)$ is the charge on the capacitor. The voltage across the capacitor is $V_C = q/C$. For a constant voltage E_0 switched on at $t = 0$ with zero initial conditions, the equation becomes

$$LV_C'' + RV_C' + \frac{1}{C}V_C = \frac{E_0}{C}.$$

The homogeneous part is a damped harmonic oscillator. The nature of the response depends on the discriminant $\Delta = R^2 - 4L/C$:

- Overdamped ($\Delta > 0$): two distinct real exponentials.
- Critically damped ($\Delta = 0$): a double real root, response $(A + Bt)e^{-\alpha t}$.
- Underdamped ($\Delta < 0$): complex conjugate roots, damped oscillations.

WORKED EXAMPLE 19 **RLC series circuit – underdamped response**

A series RLC circuit has $L = 1\,\text{H}$, $R = 2\,\Omega$, $C = 0.25\,\text{F}$, and a constant voltage $E_0 = 10\,\text{V}$ applied at $t = 0$. Initial conditions: $q(0) = 0$, $i(0) = q'(0) = 0$. Find the voltage across the capacitor $V_C(t)$.

SOLUTION

Solution. The equation for q is

$$q'' + 2q' + 4q = 10.$$

The homogeneous equation: $r^2 + 2r + 4 = 0$ gives $r = -1 \pm i\sqrt{3}$. So the complementary

solution is

$$q_c = e^{-t}\left(A\cos(\sqrt{3}t) + B\sin(\sqrt{3}t)\right).$$

A particular solution is constant: $q_p = 10/4 = 2.5$. Thus

$$q(t) = 2.5 + e^{-t}\left(A\cos(\sqrt{3}t) + B\sin(\sqrt{3}t)\right).$$


Initial conditions: $q(0) = 0 \Rightarrow 2.5 + A = 0 \Rightarrow A = -2.5$. $q'(t) = e^{-t}\left((-A + \sqrt{3}B)\cos(\sqrt{3}t) + (-B - \sqrt{3}A)\sin(\sqrt{3}t)\right) - e^{-t}\left(A\cos(\sqrt{3}t) + B\sin(\sqrt{3}t)\right)$. At $t = 0$: $q'(0) = -A + \sqrt{3}B - A = -2A + \sqrt{3}B = 0$. With $A = -2.5$, we get $5 + \sqrt{3}B = 0 \Rightarrow B = -5/\sqrt{3}$. Hence

$$q(t) = 2.5 - e^{-t}\left(2.5\cos(\sqrt{3}t) + \frac{5}{\sqrt{3}}\sin(\sqrt{3}t)\right).$$

The capacitor voltage is $V_C = q/C = 4q$:

$$V_C(t) = 10 - 4e^{-t}\left(2.5\cos(\sqrt{3}t) + \frac{5}{\sqrt{3}}\sin(\sqrt{3}t)\right).$$

This is an underdamped oscillation decaying to the steady state 10 V.



Underdamped voltage across the capacitor in a series RLC circuit.

Population with harvesting.

A population $P(t)$ growing logistically with constant harvesting rate h is modelled by

$$\frac{dP}{dt} = rP\left(1 - \frac{P}{K}\right) - h,$$

where r is the intrinsic growth rate and K the carrying capacity. This is a first-order separable equation. The equilibrium points are found by setting the right-hand side to zero; their stability determines whether the population survives or goes extinct.

5.5 Checking Solutions and Interpreting Parameters

After obtaining a solution, it is essential to verify that it satisfies the original differential equation and any initial or boundary conditions. A common mistake is to forget the constant of integration when integrating p to get y, or to misapply the chain rule when reducing the order.

WARNING **Common pitfalls in reducible equations**

- Forgetting to include the constant of integration after the first integration (when solving for p) and after the second integration (when finding y).
- In the missing-x method, incorrectly writing $y'' = dp/dx$ instead of $p\,dp/dy$.
- When using reduction of order, neglecting to check that the obtained y_2 is indeed linearly independent of y_1 (Wronskian non-zero).
- In modelling, misidentifying the sign of the damping or restoring force, leading to an equation that predicts growth instead of decay.
- Always substitute the final solution back into the original equation to catch algebraic errors.

EXEMPLE **Verification example**

For the RLC circuit solution above, check that $V_C(0) = 0$ and $V_C'(0) = 0$. $V_C(0) = 10 - 4(2.5) = 0$. $V_C'(t) = -4e^{-t}[(-2.5 - \frac{5}{\sqrt{3}}\sqrt{3})\cos(\sqrt{3}t) + \dots]$. At $t = 0$, the derivative simplifies to 0. The initial conditions are satisfied.

KEY POINTS **Key points of Section 5**

- Equations missing y: set $p = y'$, solve $p' = f(x, p)$, then integrate.
- Equations missing x: set $p = y'$, use $y'' = p\,dp/dy$, solve for $p(y)$, then integrate $dy/dx = p(y)$.
- Reduction of order: if y_1 is a solution of $y'' + P(x)y' + Q(x)y = 0$, a second solution is $y_2 = y_1 \int \frac{e^{-\int P\,dx}}{y_1^2}\,dx$.
- Modelling: translate physical laws (Newton, Kirchhoff, population dynamics) into differential equations; interpret parameters (damping, frequency, carrying capacity) in the real-world context.
- Always verify solutions by substitution and check initial/boundary conditions.

6 INTEGRATION ACTIVITY

6.1 Aims of the activity

This integration activity closes the chapter on differential equations by placing you in the role of a process engineer. By the end of the activity you should be able to:

- translate a real physical situation (cooling of cocoa beans) into a **first-order differential equation** with a time-dependent forcing term;
- solve a **linear first-order non-homogeneous equation** using an integrating factor, and a **separable** equation as a special case;
- handle a **piecewise constant coefficient** by solving the equation interval by interval, matching the solution at the junctions;
- set up and analyse a **linear second-order equation with constant coefficients** modelling the dynamics of a ventilation fan (damping ratio, natural frequency, settling time);
- interpret solutions graphically, check them against physical constraints, and communicate recommendations in a short technical report.

KEY POINTS **Skills mobilised**

Newton's law of cooling $\frac{dT}{dt} = -k\big(T - T_a(t)\big)$; integrating factor $e^{\int k\,dt}$; continuity of the solution at switching times; auxiliary equation $am^2 + bm + c = 0$; underdamped response and settling time.

6.2 Situation

A cocoa cooperative in **Penja** (Littoral Region) dries fermented beans on raised trays inside a ventilated shed. After the morning heating phase, the beans enter the shed at time $t = 0$ (noon) at a temperature of $T(0) = 55\,^{\circ}\text{C}$. For safe bagging, the beans must be brought down to the target band $30\,^{\circ}\text{C} \le T \le 35\,^{\circ}\text{C}$ and must stay inside this band until bagging at $t = 6$ hours. Beans cooled too slowly risk mould; beans cooled below $30\,^{\circ}\text{C}$ re-absorb moisture from the humid evening air.

The shed's ambient temperature on a typical day is modelled (with t in hours) by

$$T_a(t) = 24 + 6\sin\!\left(\frac{\pi}{12}\,t\right) \quad (^{\circ}\text{C}).$$

With the shutters fixed in a half-open position, the heat transfer coefficient is $k_1 = 0.8\,\text{h}^{-1}$. Opening the shutters fully and switching on the extractor fan raises the coefficient to $k_2 = 1.6\,\text{h}^{-1}$.

The fan itself does not reach its full speed instantly. When a step voltage is applied, its angular velocity $\omega(t)$ (in rad/s) satisfies

$$0.02\,\ddot{\omega} + 0.14\,\dot{\omega} + 2\,\omega = 2\,\Omega, \qquad \omega(0) = 0,\ \dot{\omega}(0) = 0,$$

where $\Omega = 150$ rad/s is the commanded speed.

The cooperative hires you to design the cooling schedule: when should the fan be switched on, and will the fan's own inertia disturb the plan?

6.3 Tasks

Part A — Formulation and analytic solution.

1. State Newton's law of cooling and justify briefly why it leads to the equation $\dot{T} = -k\big(T - T_a(t)\big)$. What are the units of k?

2. With the shutters half-open ($k = k_1 = 0.8$) and a constant ambient temperature $\bar{T}_a = 27\,^{\circ}\text{C}$ (the mean value of T_a), solve the resulting separable equation with $T(0) = 55$. How long does the bean temperature take to reach $35\,^{\circ}\text{C}$? Is the target band ever entered and left again under this strategy?

3. Now use the true sinusoidal ambient temperature with $k = 0.8$. Write the equation in the standard linear form $\dot{T} + 0.8\,T = 0.8\,T_a(t)$, determine an integrating factor, and show that

$$T(t) = 24 + \frac{0.8 \cdot 6}{0.64 + a^2}\Big(0.8\sin(at) - a\cos(at)\Big) + Ce^{-0.8t}, \quad a = \frac{\pi}{12},$$

then determine C using $T(0) = 55$. (You may seek a particular solution of the form $\alpha\sin(at) + \beta\cos(at)$.)

Part B — Designing the ventilation control.

4. Using the simplified constant-ambient model of question 2, show that with $k = 0.8$ alone the beans would fall below $30\,^{\circ}\text{C}$ before $t = 6$ h. Compute the time at which this happens.

5. The engineer proposes a **piecewise constant control**: run at $k_1 = 0.8$ until the beans reach $T = 33\,^{\circ}\text{C}$, then switch to a reduced coefficient k_3 (shutters almost closed) so that the temperature stays constant at $33\,^{\circ}\text{C}$. Assuming $T_a \approx 27\,^{\circ}\text{C}$, find the value of k_3 that makes $T = 33$ an equilibrium, and write the full piecewise solution $T(t)$ for $0 \le t \le 6$.

6. Sketch the graph of your controlled solution and of the uncontrolled solution (question 2) on the same axes, marking the target band.

Part C — Fan dynamics (second-order model).

7. Write the auxiliary equation of the fan model and show that the homogeneous response is underdamped. Compute the natural frequency ω_0 and the damping ratio ζ.

8. Find the steady-state speed ω_p and hence the form of $\omega(t)$. Estimate the settling time $t_s \approx \dfrac{4}{\zeta\omega_0}$ and comment: is the fan fast enough compared with the cooling timescale $1/k_1$?

9. Conclude in 8–10 lines: state your recommended schedule (switching time, shutter positions), one limitation of the model, and one practical recommendation for the cooperative.

6.4 Model answer

Part A.

1. Newton's law of cooling states that the rate of heat loss of a body is proportional to the difference between its temperature and that of the surroundings: $\dot{T} = -k(T - T_a)$, $k > 0$. Since $\dot{T}$ is in $^\circ\text{C h}^{-1}$ and $T - T_a$ in $^\circ$C, k is in h^{-1}.

2. With $T_a = 27$ constant: $\dfrac{dT}{T-27} = -0.8\,dt$, hence $\ln|T-27| = -0.8t + C_0$ and

$$T(t) = 27 + 28e^{-0.8t} \qquad (T(0) = 55).$$

$35 = 27 + 28e^{-0.8t} \Rightarrow e^{-0.8t} = \frac{2}{7} \Rightarrow t = \frac{\ln(7/2)}{0.8} \approx 1.57$ h. But $T \to 27 < 30$ as t grows: the band is entered at $t \approx 1.57$ h and left again — the strategy fails for bagging at $t = 6$ h.

3. The equation is $\dot{T} + 0.8T = 0.8\big(24 + 6\sin(at)\big)$, $a = \pi/12$. Integrating factor: $\mu = e^{0.8t}$, giving $\big(e^{0.8t}T\big)' = e^{0.8t}\,0.8\,T_a(t)$. Seek a particular solution $T_p = 24 + \alpha\sin(at) + \beta\cos(at)$. Substituting and matching coefficients of $\sin(at)$, $\cos(at)$:

$$0.8\alpha - a\beta = 4.8, \qquad a\alpha + 0.8\beta = 0,$$

so $\alpha = \dfrac{0.8 \times 4.8}{0.64 + a^2}$, $\beta = \dfrac{-4.8a}{0.64 + a^2}$, which is the announced form. Then

$$T(t) = 24 + \frac{4.8}{0.64 + a^2}\big(0.8\sin(at) - a\cos(at)\big) + Ce^{-0.8t}.$$

With $a = \pi/12 \approx 0.2618$: $0.64 + a^2 \approx 0.7085$, so $\alpha \approx 5.42$, $\beta \approx -1.77$. The condition $T(0) = 55$ gives $55 = 24 + \beta + C$, hence $C = 55 - 24 + 1.77 = 32.77$:

$$T(t) \approx 24 + 5.42\sin(0.2618\,t) - 1.77\cos(0.2618\,t) + 32.77\,e^{-0.8t}.$$

Check: $T(6) \approx 24 + 5.42 - 1.77(0) + 32.77e^{-4.8} \approx 29.7\,^\circ$C — again slightly below the band: control is needed.

Part B.

4. $30 = 27 + 28e^{-0.8t} \Rightarrow e^{-0.8t} = \frac{3}{28} \Rightarrow t = \dfrac{\ln(28/3)}{0.8} \approx 2.79\,\text{h} < 6\,\text{h}$. The beans leave the band far too early.

5. Phase 1 ($k_1 = 0.8$): $T = 27 + 28e^{-0.8t}$ reaches 33 when $e^{-0.8t_1} = \frac{6}{28} = \frac{3}{14}$, i.e.


$$t_1 = \frac{\ln(14/3)}{0.8} \approx 1.93\,\text{h} \ (\approx 13\text{h}56).$$

Phase 2: for $T \equiv 33$ to be a solution of $\dot{T} = -k_3(33 - 27)$ we need $\dot{T} = 0$, hence $k_3(33 - 27) = 0$: strictly, $k_3 = 0$ (perfect insulation) keeps $T = 33$ exactly; in practice the shutters are closed and the residual leakage $k_3 \approx 0.05\ \text{h}^{-1}$ gives $\dot{T} = -0.3\,^\circ\text{C h}^{-1}$, i.e. a drop of only 1.2 $^\circ$C over 4 h, ending at $\approx 31.8\,^\circ$C — still inside the band. The piecewise solution (ideal case $k_3 = 0$):

$$T(t) = \begin{cases} 27 + 28e^{-0.8t}, & 0 \le t \le t_1, \\ 33, & t_1 \le t \le 6. \end{cases}$$

The solution is continuous at t_1 (both pieces equal 33), as physics requires.

6. Sketch: an exponential decay from 55 to 33 (reached at $t_1 \approx 1.93$ h), then a horizontal segment at 33 until $t = 6$; the uncontrolled curve continues decaying towards 27, crossing 30 at $t \approx 2.79$ h. Shade the band $[30, 35]$.



Controlled vs uncontrolled cooling; dashed green lines delimit the target band.

Part C.

7. Auxiliary equation: $0.02m^2+0.14m+2=0$, i.e. $m^2+7m+100=0$. Discriminant: $49-400=-351<0$ — underdamped. Roots: $m=-3.5\pm i\sqrt{87.75}\approx -3.5\pm 9.37i$. Natural frequency $\omega_0=\sqrt{100}=10$ rad/s; damping ratio $\zeta=\dfrac{7}{2\omega_0}=0.35$.

8. Steady state: $\ddot{\omega}=\dot{\omega}=0\Rightarrow 2\omega_p=2\Omega$, so $\omega_p=\Omega=150$ rad/s. Hence

$$\omega(t)=150+e^{-3.5t}\big(A\cos 9.37t+B\sin 9.37t\big),$$

with $\omega(0)=0\Rightarrow A=-150$ and $\dot{\omega}(0)=0\Rightarrow B=-150\times 3.5/9.37\approx -56.0$. Settling time: $t_s\approx\dfrac{4}{\zeta\omega_0}=\dfrac{4}{3.5}\approx 1.14$ s. The fan reaches its regime in about one second, while the cooling timescale is $1/k_1=1.25$ hours: the fan's inertia is completely negligible, and the schedule of Part B need not be corrected.

9. Conclusion (model report). Recommendation: keep the shutters half-open from noon; at $t\approx 1.9$ h (about 13h55), when the beans reach 33 °C, close the shutters and stop the fan; the beans then remain within $[30,35]$ °C until bagging at 18h00. Limitation: the ambient temperature was treated as constant in the control design; the sinusoidal model of question 3 shows fluctuations of order ±2 °C, so the bean temperature should be re-checked around 16h00. Practical advice: fit the shed with a cheap thermostat set at 33 °C to automate the switching, and record temperatures daily to refine the coefficient k for the local shed.

WARNING **Common errors to avoid**

- Forgetting that after a change of coefficient the solution must be continuous: use the value at the switching time as the new initial condition.
- Mixing units: k in h^{-1} requires t in hours throughout.
- In the second-order model, concluding "underdamped" without checking the sign of the discriminant, or confusing ω_0 with the damped frequency $\omega_0\sqrt{1-\zeta^2}$.

7 METHODS AND WORKED EXAMPLES

8 FIRST-ORDER DIFFERENTIAL EQUATIONS – FOUNDATIONS AND GEOMETRY

DEFINITION **Differential Equation**

A **differential equation** is an equation involving an unknown function and its derivatives. The **order** is the highest derivative present; the **degree** is the power of the highest derivative after the equation has been made rational and polynomial in derivatives.

DEFINITION **General and Particular Solutions**

The **general solution** of an n-th order differential equation contains n arbitrary independent constants. A **particular solution** is obtained by assigning specific values to these constants, usually through **initial conditions** or **boundary conditions**.

KEY POINTS **Formation of a Differential Equation**

Given a family of curves $f(x, y, c_1, c_2, \dots, c_n) = 0$ with n essential parameters, differentiating n times and eliminating the parameters yields an n-th order differential equation satisfied by the family.

WORKED EXAMPLE 20 **Forming a differential equation**

Find the differential equation of the family of curves $y = Ae^{2x} + Be^{-3x}$.

SOLUTION

Differentiate twice:

$$y = Ae^{2x} + Be^{-3x}$$
$$\dot{y} = 2Ae^{2x} - 3Be^{-3x}$$
$$\ddot{y} = 4Ae^{2x} + 9Be^{-3x}$$

Eliminate A and B. From the first two: $Ae^{2x} = \frac{3y+\dot{y}}{5}$, $Be^{-3x} = \frac{2y-\dot{y}}{5}$. Substitute into $\ddot{y}$: $\ddot{y} = 4\left(\frac{3y+\dot{y}}{5}\right)+$

$9\left(\frac{2y-\dot{y}}{5}\right) = \frac{12y+4\dot{y}+18y-9\dot{y}}{5} = \frac{30y-5\dot{y}}{5} = 6y - \dot{y}$. Hence the differential equation is $\boxed{\ddot{y} + \dot{y} - 6y = 0}$.

8.1 Geometric Interpretation – Direction Fields and Integral Curves

DEFINITION **Direction Field**

For a first-order equation $\frac{dy}{dx} = f(x, y)$, at each point (x, y) the slope of the solution curve is $f(x, y)$. A **direction field** (or **slope field**) is a plot of short line segments with these slopes at a grid of points.

DEFINITION **Isoclines**

An **isocline** for slope m is the curve $f(x, y) = m$ along which all solution curves have the same gradient m. Isoclines help sketch direction fields by hand.


PROPERTY **Existence and Uniqueness (Picard–Lindelöf)**

If $f(x, y)$ and $\frac{\partial f}{\partial y}$ are continuous in a rectangle containing (x_0, y_0), then the initial value problem $\frac{dy}{dx} = f(x, y)$, $y(x_0) = y_0$ has a unique solution in some interval around x_0.

EXPERIMENT **Sketching a direction field using isoclines**

Consider $\frac{dy}{dx} = x - y$.

1. Isoclines: $x - y = m \Rightarrow y = x - m$ (parallel lines of slope 1).
2. For $m = 0$: isocline $y = x$ (horizontal segments).
3. For $m = 1$: isocline $y = x - 1$ (segments of slope 1).
4. For $m = -1$: isocline $y = x + 1$ (segments of slope −1).
5. Draw short segments on each isocline with the corresponding slope.
6. The integral curves follow the direction field. The general solution is $y = x - 1 + Ce^{-x}$; all curves approach the line $y = x - 1$ as $x \to \infty$.



Direction field and integral curves for $\frac{dy}{dx} = x - y$.

9 SEPARABLE VARIABLES AND LINEAR FIRST-ORDER NON-HOMOGENEOUS EQUATIONS

METHOD **Separation of Variables**

To solve an equation of the form $\frac{dy}{dx} = f(x)\,g(y)$:

1. Factorise the right-hand side into a product of a function of x alone and a function of y alone.
2. Separate: write $\frac{dy}{g(y)} = f(x)\,dx$, gathering all y's with dy and all x's with dx.
3. Integrate both sides: $\int \frac{dy}{g(y)} = \int f(x)\,dx$. Add one constant of integration only.
4. Make y the subject if possible; otherwise leave the solution implicit.
5. If an initial condition is given, substitute it to find the constant, then state the **particular solution**.

Reflexes: check for **singular solutions** lost when dividing by $g(y)$ (e.g. $y = 0$); remember $\int \frac{dy}{y} = \ln|y| + c$ and the trick $\ln|y| = f(x) + c \Rightarrow y = Ae^{f(x)}$ with $A = \pm e^{c}$.

WORKED EXAMPLE 21 **GCE-style: a separable equation with initial condition**

Find the particular solution of the differential equation

$$\frac{dy}{dx} = \frac{x(y^2+1)}{y}, \qquad y(0) = 2.$$

SOLUTION

Step 1 – Separate the variables. The right-hand side is a product of a function of x and a function of y:

$$\frac{y}{y^2+1}\,dy = x\,dx.$$

Step 2 – Integrate both sides.

$$\int \frac{y}{y^2+1}\,dy = \int x\,dx.$$

For the left integral, note that the numerator is (up to a factor 2) the derivative of the denominator, so

$$\frac{1}{2}\ln(y^2+1) = \frac{x^2}{2} + c.$$

(No modulus needed since $y^2+1 > 0$.) Multiplying by 2:

$$\ln(y^2+1) = x^2 + C, \qquad C = 2c.$$

Step 3 – Apply the initial condition $x = 0$, $y = 2$:

$$\ln(4+1) = 0 + C \;\Rightarrow\; C = \ln 5.$$

Step 4 – Make y the subject.

$$y^2 + 1 = e^{x^2+\ln 5} = 5e^{x^2} \;\Rightarrow\; y^2 = 5e^{x^2} - 1.$$

Since $y(0) = 2 > 0$, we take the positive root:

$$\boxed{y = \sqrt{5e^{x^2} - 1}}.$$

Check: at $x = 0$, $y = \sqrt{5-1} = 2$. ✓

WORKED EXAMPLE 22 **Separable equation with singular solution**

Solve $\frac{dy}{dx} = y^2 \sin x$.

SOLUTION

Separate: $\frac{dy}{y^2} = \sin x\,dx$. Integrate: $\int y^{-2}\,dy = \int \sin x\,dx \Rightarrow -\frac{1}{y} = -\cos x + C$. Hence $\frac{1}{y} = \cos x - C$, so $y = \frac{1}{\cos x + A}$ where $A = -C$. Singular solution: dividing by y^2 assumed $y \neq 0$. $y = 0$ satisfies the original equation and is not included in the general formula for any finite A. It is a **singular solution**.

9.1 Linear First-Order Equations – Integrating Factor

DEFINITION **Linear First-Order Equation**

A **linear first-order differential equation** has the form

$$\frac{dy}{dx} + P(x)y = Q(x)$$

where $P(x)$ and $Q(x)$ are continuous functions of x only. If $Q(x) \equiv 0$, the equation is **homogeneous**; otherwise it is **non-homogeneous**.

METHOD **Integrating Factor for $y' + P(x)y = Q(x)$**

1. Write the equation in standard form $\frac{dy}{dx} + P(x)y = Q(x)$ (coefficient of y' must be 1).
2. Compute the **integrating factor** $\mu(x) = e^{\int P(x)\,dx}$ (no constant needed here).
3. Multiply through by $\mu(x)$. The left-hand side collapses to $\frac{d}{dx}\left[\mu(x)\,y\right]$.
4. Integrate: $\mu(x)\,y = \int \mu(x)Q(x)\,dx + C$.
5. Divide by $\mu(x)$ to obtain the general solution; apply any initial condition.

Reflexes: always check the collapse $\frac{d}{dx}[\mu y] = \mu y' + \mu' y$ with $\mu' = P\mu$; the solution has the structure $y = y_{CF} + y_{PI}$ (complementary function plus particular integral).

WORKED EXAMPLE 23 **GCE-style: integrating factor**

(a) Find the general solution of

$$x\frac{dy}{dx} + 2y = x^3, \qquad x > 0.$$

(b) Hence find the solution for which $y = 1$ when $x = 1$.

SOLUTION

Step 1 – Standard form. Divide by x:

$$\frac{dy}{dx} + \frac{2}{x}y = x^2.$$

Here $P(x) = \dfrac{2}{x}$ and $Q(x) = x^2$.
Step 2 – Integrating factor.

$$\mu(x) = e^{\int \frac{2}{x}dx} = e^{2\ln x} = x^2.$$

Step 3 – Multiply through by x^2:

$$x^2\frac{dy}{dx} + 2xy = x^4 \implies \frac{d}{dx}(x^2y) = x^4.$$

Step 4 – Integrate:

$$x^2y = \frac{x^5}{5} + C.$$

Step 5 – General solution:

$$\boxed{y = \frac{x^3}{5} + \frac{C}{x^2}}.$$

(b) Substituting $x = 1$, $y = 1$: $1 = \dfrac{1}{5} + C \Rightarrow C = \dfrac{4}{5}$. Hence

$$y = \frac{x^3}{5} + \frac{4}{5x^2}.$$

Check: $y' = \frac{3x^2}{5} - \frac{8}{5x^3}$; then $xy' + 2y = \frac{3x^3}{5} - \frac{8}{5x^2} + \frac{2x^3}{5} + \frac{8}{5x^2} = x^3$. ✓

WORKED EXAMPLE 24 **Linear equation with non-constant integrating factor**

Solve $\frac{dy}{dx} + y\tan x = \sec x$, $-\frac{\pi}{2} < x < \frac{\pi}{2}$.

SOLUTION

$P(x) = \tan x$, $\mu = e^{\int \tan x\,dx} = e^{-\ln|\cos x|} = \dfrac{1}{\cos x} = \sec x$ (since $\cos x > 0$ on the interval). Multiply: $\sec x\frac{dy}{dx} + y\sec x\tan x = \sec^2 x$. LHS $= \frac{d}{dx}(y\sec x)$. Integrate: $y\sec x = \int \sec^2 x\,dx = \tan x + C$. General solution: $\boxed{y = \sin x + C\cos x}$.

10 HOMOGENEOUS, BERNOULLI AND RICCATI EQUATIONS

10.1 Homogeneous Equations – the Substitution $y = vx$

DEFINITION **Homogeneous Function and Equation**

A function $F(x, y)$ is **homogeneous of degree** n if $F(tx, ty) = t^n F(x, y)$ for all $t > 0$. A first-order equation $\frac{dy}{dx} = F(x, y)$ is **homogeneous** if F is homogeneous of degree 0, i.e. $F(tx, ty) = F(x, y)$. Equivalently, the right-hand side can be written as a function of $\frac{y}{x}$ alone.

METHOD **Solving $\frac{dy}{dx} = F\left(\frac{y}{x}\right)$**

1. Confirm homogeneity: check that $F(tx, ty) = F(x, y)$, or rewrite the right-hand side in terms of y/x.
2. Substitute $y = vx$, so that $\frac{dy}{dx} = v + x\frac{dv}{dx}$.
3. The equation becomes separable in v and x: $x\frac{dv}{dx} = F(v) - v$.
4. Separate and integrate: $\int \frac{dv}{F(v) - v} = \int \frac{dx}{x} = \ln|x| + c$.
5. Back-substitute $v = \frac{y}{x}$ and simplify; apply initial conditions if given.

Reflex: after substitution, the v terms must cancel on the right – if they do not, the equation was not homogeneous.

WORKED EXAMPLE 25 **GCE-style: homogeneous equation**

Show that the substitution $y = vx$ reduces the equation

$$\frac{dy}{dx} = \frac{x^2 + y^2}{2xy}, \qquad x > 0,\ y > 0,$$

to a separable equation. Hence find the general solution, and the particular solution with $y(1) = 2$.

SOLUTION

Step 1 – Homogeneity. Replacing (x, y) by (tx, ty):

$$\frac{(tx)^2 + (ty)^2}{2(tx)(ty)} = \frac{t^2(x^2 + y^2)}{2t^2xy} = \frac{x^2 + y^2}{2xy},$$

so the equation is homogeneous.
Step 2 – Substitute $y = vx$, $\frac{dy}{dx} = v + x\frac{dv}{dx}$:

$$v + x\frac{dv}{dx} = \frac{x^2 + v^2x^2}{2x \cdot vx} = \frac{1 + v^2}{2v}.$$

Step 3 – Separate:

$$x\frac{dv}{dx} = \frac{1 + v^2}{2v} - v = \frac{1 + v^2 - 2v^2}{2v} = \frac{1 - v^2}{2v}.$$

$$\frac{2v}{1 - v^2}\,dv = \frac{dx}{x}.$$

Step 4 – Integrate:

$$-\ln|1 - v^2| = \ln x + c \implies \ln\left(x(1 - v^2)\right) = -c \implies x(1 - v^2) = A,$$

where $A = e^{-c}$ (we drop the modulus since $x > 0$ and the sign is absorbed into A).
Step 5 – Back-substitute $v = y/x$:

$$x\left(1 - \frac{y^2}{x^2}\right) = A \implies \boxed{x^2 - y^2 = Ax}.$$

Particular solution: $x = 1$, $y = 2$ gives $1 - 4 = A$, so $A = -3$:

$$x^2 - y^2 = -3x \implies y = \sqrt{x^2 + 3x} \quad \text{(positive root since } y > 0\text{)}.$$

Check: at $x = 1$, $y = \sqrt{4} = 2$. ✓

10.2 Bernoulli's Equation

DEFINITION **Bernoulli Equation**

A **Bernoulli equation** has the form

$$\frac{dy}{dx} + P(x)y = Q(x)y^n, \qquad n \in \mathbb{R},\ n \neq 0, 1.$$

For $n = 0$ or $n = 1$ the equation is already linear.

METHOD **Bernoulli:** $y' + P(x)y = Q(x)y^n$

1. Identify the Bernoulli form with $n \neq 0, 1$.
2. Divide through by y^n: $y^{-n}y' + P(x)y^{1-n} = Q(x)$.
3. Substitute $z = y^{1-n}$, so $\dfrac{dz}{dx} = (1-n)y^{-n}\dfrac{dy}{dx}$.
4. The equation becomes linear in z: $\dfrac{dz}{dx} + (1-n)P(x)z = (1-n)Q(x)$.
5. Solve by the integrating factor method, then back-substitute $z = y^{1-n}$.

Reflex: the exponent of the new variable is always $1-n$; do not forget the factor $(1-n)$ on the right-hand side.

WORKED EXAMPLE 26 **GCE-style: Bernoulli equation**

Find the general solution of

$$\frac{dy}{dx} + \frac{y}{x} = x^2y^2, \qquad x > 0.$$

SOLUTION

Step 1. This is Bernoulli with $n = 2$.
Step 2 – Divide by y^2:

$$y^{-2}\frac{dy}{dx} + \frac{1}{x}y^{-1} = x^2.$$

Step 3 – Substitute $z = y^{-1}$, so $\dfrac{dz}{dx} = -y^{-2}\dfrac{dy}{dx}$:

$$-\frac{dz}{dx} + \frac{z}{x} = x^2 \implies \frac{dz}{dx} - \frac{z}{x} = -x^2.$$

Step 4 – Linear in z. Integrating factor: $\mu = e^{-\int \frac{dx}{x}} = e^{-\ln x} = \dfrac{1}{x}$. Multiplying:

$$\frac{d}{dx}\left(\frac{z}{x}\right) = -x.$$

Integrating:

$$\frac{z}{x} = -\frac{x^2}{2} + C \implies z = Cx - \frac{x^3}{2}.$$

Step 5 – Back-substitute $z = 1/y$:

$$\boxed{\frac{1}{y} = Cx - \frac{x^3}{2}} \qquad \text{i.e.} \qquad y = \frac{2}{2Cx - x^3}.$$

Check (sample $C = 0$): $y = -2x^{-3}$, $y' = 6x^{-4}$; then $y' + \frac{y}{x} = 6x^{-4} - 2x^{-4} = 4x^{-4}$ and $x^2y^2 = x^2 \cdot 4x^{-6} = 4x^{-4}$. ✓

10.3 Riccati's Equation

DEFINITION **Riccati Equation**

A **Riccati equation** has the form

$$\frac{dy}{dx} = P(x) + Q(x)y + R(x)y^2.$$

If one particular solution $y_1(x)$ is known, the substitution $y = y_1 + \frac{1}{z}$ reduces it to a linear equation in z.

METHOD **Solving Riccati when a particular solution is known**

Given $\frac{dy}{dx} = P + Qy + Ry^2$ and a known solution y_1:

1. Substitute $y = y_1 + \frac{1}{z}$.
2. Compute $\frac{dy}{dx} = \frac{dy_1}{dx} - \frac{1}{z^2}\frac{dz}{dx}$.
3. Substitute into the equation and use the fact that y_1 satisfies it.
4. The result is a linear first-order equation in z: $\frac{dz}{dx} + (Q + 2Ry_1)z = -R$.
5. Solve for z, then back-substitute $y = y_1 + 1/z$.

WORKED EXAMPLE 27 **Riccati equation**

Solve $\frac{dy}{dx} = 1 + 2xy + x^2y^2$, given that $y_1 = -x$ is a solution.

SOLUTION

Here $P = 1$, $Q = 2x$, $R = x^2$. Substitute $y = -x + \frac{1}{z}$. Then $\frac{dy}{dx} = -1 - \frac{1}{z^2}\frac{dz}{dx}$. Substitute into the equation:

$$-1 - \frac{1}{z^2}\frac{dz}{dx} = 1 + 2x\left(-x + \frac{1}{z}\right) + x^2\left(-x + \frac{1}{z}\right)^2.$$

Expand RHS: $1 - 2x^2 + \frac{2x}{z} + x^2(x^2 - \frac{2x}{z} + \frac{1}{z^2}) = 1 - 2x^2 + \frac{2x}{z} + x^4 - \frac{2x^3}{z} + \frac{x^2}{z^2}$. Since $y_1 = -x$ is a solution, it satisfies $0 = 1 + 2x(-x) + x^2(-x)^2 = 1 - 2x^2 + x^4$. Subtract this identity from the RHS: RHS $= (1 - 2x^2 + x^4) + \frac{2x - 2x^3}{z} + \frac{x^2}{z^2} = 0 + \frac{2x(1-x^2)}{z} + \frac{x^2}{z^2}$. Equate with LHS:

$$-1 - \frac{1}{z^2}\frac{dz}{dx} = \frac{2x(1 - x^2)}{z} + \frac{x^2}{z^2}.$$

Multiply by $-z^2$:

$$z^2 + \frac{dz}{dx} = -2x(1-x^2)z - x^2.$$

But wait – we should use the standard linear form directly: $\frac{dz}{dx} + (Q + 2Ry_1)z = -R$. $Q + 2Ry_1 = 2x + 2x^2(-x) = 2x - 2x^3$. So $\frac{dz}{dx} + (2x - 2x^3)z = -x^2$. Integrating factor: $\mu = e^{\int (2x-2x^3)dx} = e^{x^2 - \frac{1}{2}x^4}$. $\frac{d}{dx}(z\mu) = -x^2\mu$. $ze^{x^2-x^4/2} = -\int x^2 e^{x^2-x^4/2}dx + C$. This integral is non-elementary. However, notice the original equation is $(\frac{dy}{dx} - 1) = (xy+1)^2 - 1$? Let's re-check. Actually, $1 + 2xy + x^2y^2 = (1+xy)^2$. So $\frac{dy}{dx} = (1+xy)^2$. Let $u = 1+xy$, then $\frac{du}{dx} = y + x\frac{dy}{dx} = y + xu^2$. Not simpler. The given $y_1 = -x$ works: $1+2x(-x)+x^2(-x)^2 = 1-2x^2+x^4 = (1-x^2)^2$, and $\frac{d}{dx}(-x) = -1$. So $-1 = (1-x^2)^2$ is false! $y_1 = -x$ is NOT a solution. Let's find a correct example. Equation: $\frac{dy}{dx} = -y^2 + 2xy - x^2 + 1 = 1 - (y-x)^2$. Try $y_1 = x + 1$: $\frac{dy_1}{dx} = 1$. RHS $= 1 - (1)^2 = 0$. No. Try $y_1 = x$: $\frac{dy_1}{dx} = 1$. RHS $= 1 - 0 = 1$. Yes! $y_1 = x$ is a solution. Now solve $\frac{dy}{dx} = 1+2xy-x^2-y^2$? No, standard form. Let's use a standard textbook example: $\frac{dy}{dx} = y^2 - 2xy + x^2 - 1 = (y-x)^2 - 1$. $y_1 = x + 1$: $\frac{dy_1}{dx} = 1$. RHS $= 1^2 - 1 = 0$. No. $y_1 = x - 1$: $\frac{dy_1}{dx} = 1$. RHS $= (-1)^2 - 1 = 0$. No. $y_1 = x$: $\frac{dy_1}{dx} = 1$. RHS $= 0 - 1 = -1$. No. Equation: $\frac{dy}{dx} = 1 - 2xy + y^2$. $y_1 = x$: $1 - 2x^2 + x^2 = 1 - x^2 \neq 1$. Let's use: $\frac{dy}{dx} = x^2 + y^2$. No elementary particular solution. Better example: $\frac{dy}{dx} = 1 + \frac{y}{x} - \frac{y^2}{x^2}$. $y_1 = x$: $1 + 1 - 1 = 1$, $\frac{dy_1}{dx} = 1$. Works! Let's use this one.

WORKED EXAMPLE 28 **Riccati equation – corrected example**

Solve $\frac{dy}{dx} = 1 + \frac{y}{x} - \frac{y^2}{x^2}$, given that $y_1 = x$ is a solution.

SOLUTION

Here $P = 1$, $Q = \frac{1}{x}$, $R = -\frac{1}{x^2}$. Known solution $y_1 = x$. Substitute $y = x + \frac{1}{z}$. Then $\frac{dy}{dx} = 1 - \frac{1}{z^2}\frac{dz}{dx}$. The equation becomes:

$$1 - \frac{1}{z^2}\frac{dz}{dx} = 1 + \frac{1}{x}\left(x + \frac{1}{z}\right) - \frac{1}{x^2}\left(x + \frac{1}{z}\right)^2.$$

Simplify RHS: $1 + 1 + \frac{1}{xz} - \frac{1}{x^2}(x^2 + \frac{2x}{z} + \frac{1}{z^2}) = 2 + \frac{1}{xz} - 1 - \frac{2}{xz} - \frac{1}{x^2z^2} = 1 - \frac{1}{xz} - \frac{1}{x^2z^2}$. Equate with LHS:

$$1 - \frac{1}{z^2}\frac{dz}{dx} = 1 - \frac{1}{xz} - \frac{1}{x^2z^2}.$$

Cancel 1, multiply by $-z^2$:

$$\frac{dz}{dx} = \frac{z}{x} + \frac{1}{x^2}.$$

Linear in z: $\frac{dz}{dx} - \frac{1}{x}z = \frac{1}{x^2}$. Integrating factor: $\mu = e^{-\int \frac{dx}{x}} = \frac{1}{x}$. $\frac{d}{dx}\left(\frac{z}{x}\right) = \frac{1}{x^3}$. $\frac{z}{x} = -\frac{1}{2x^2} + C \Rightarrow z = -\frac{1}{2x} + Cx$. Back-substitute: $y = x + \frac{1}{z} = x + \frac{1}{Cx - \frac{1}{2x}} = x + \frac{2x}{2Cx^2 - 1}$. General solution: $\boxed{y = x + \frac{2x}{Ax^2 - 1}}$ where $A = 2C$.

11 LINEAR SECOND-ORDER DIFFERENTIAL EQUATIONS WITH CONSTANT COEFFICIENTS

11.1 Homogeneous Equations – Complementary Function

METHOD **Solving $a\ddot{y} + b\dot{y} + cy = 0$**

1. Write the **auxiliary (characteristic) equation** $am^2 + bm + c = 0$.
2. Solve for m and read off the **complementary function**:
   - Distinct real roots $m_1 \neq m_2$: $y = Ae^{m_1 x} + Be^{m_2 x}$.
   - Repeated root m: $y = (A + Bx)e^{mx}$.
   - Complex roots $m = \alpha \pm i\beta$: $y = e^{\alpha x}(A\cos\beta x + B\sin\beta x)$.
3. If two boundary/initial conditions are given, determine A and B.

Reflexes: for complex roots, α is the real part and β the imaginary part without the i; a repeated root forces the extra factor x in the second solution.

WORKED EXAMPLE 29 **GCE-style: three cases of the auxiliary equation**

Find the general solution of each equation:

(i) $\ddot{y} - 5\dot{y} + 6y = 0$; (ii) $\ddot{y} + 4\dot{y} + 4y = 0$; (iii) $\ddot{y} - 2\dot{y} + 5y = 0$.

For (iii), find also the solution with $y(0) = 1$, $\dot{y}(0) = 3$.

SOLUTION

(i) Auxiliary equation: $m^2 - 5m + 6 = 0 \Rightarrow (m - 2)(m - 3) = 0$, so $m = 2$ or $m = 3$ (distinct real roots).

$$\boxed{y = Ae^{2x} + Be^{3x}}.$$

(ii) Auxiliary equation: $m^2 + 4m + 4 = 0 \Rightarrow (m + 2)^2 = 0$, so $m = -2$ (repeated root).

$$\boxed{y = (A + Bx)e^{-2x}}.$$

(iii) Auxiliary equation: $m^2 - 2m + 5 = 0$. Using the quadratic formula:

$$m = \frac{2 \pm \sqrt{4 - 20}}{2} = \frac{2 \pm 4i}{2} = 1 \pm 2i.$$

Complex roots with $\alpha = 1, \beta = 2$:

$$\boxed{y = e^{x}(A\cos 2x + B\sin 2x)}.$$

Applying the conditions. $y(0) = 1$: $e^{0}(A\cos 0 + B\sin 0) = A = 1$.
Differentiate using the product rule:

$$\dot{y} = e^{x}(A\cos 2x + B\sin 2x) + e^{x}(-2A\sin 2x + 2B\cos 2x).$$

At $x = 0$: $\dot{y}(0) = A + 2B = 3$. With $A = 1$: $2B = 2 \Rightarrow B = 1$. Hence

$$y = e^{x}(\cos 2x + \sin 2x).$$

Check: $\dot{y}(0) = e^{0}(\cos 0 + \sin 0) + e^{0}(-2\sin 0 + 2\cos 0) = 1 + 2 = 3$. ✓

11.2 Non-Homogeneous Equations – Particular Integral

METHOD **Solving $a\ddot{y} + b\dot{y} + cy = f(x)$**

1. Solve the homogeneous equation to get the complementary function y_{CF}.
2. Choose a trial particular integral according to $f(x)$:
   - $f(x) = k$ (constant): try $y_{PI} = \lambda$;
   - $f(x)$ polynomial of degree n: try a general polynomial of degree n;
   - $f(x) = ke^{px}$: try $y_{PI} = \lambda e^{px}$;
   - $f(x) = k\cos\omega x$ or $k\sin\omega x$: try $y_{PI} = \lambda\cos\omega x + \mu\sin\omega x$;
   - $f(x) = e^{px}(k\cos\omega x + l\sin\omega x)$: try $y_{PI} = e^{px}(\lambda\cos\omega x + \mu\sin\omega x)$.
3. Modification rule: if the trial solution is contained in y_{CF}, multiply by x (and by x again if necessary).
4. Substitute the trial into the full equation and equate coefficients to find the unknown constants.
5. The general solution is $y = y_{CF} + y_{PI}$; only then apply initial conditions.

WARNING **The most common GCE error**

Applying initial conditions to y_{CF} alone, or forgetting the modification rule when $f(x) = ke^{px}$ with p a root of the auxiliary equation. Both cost several marks.

WORKED EXAMPLE 30 **GCE-style: particular integral with the modification rule**

(a) Find the general solution of

$$\ddot{y} - \dot{y} - 2y = 6e^{2x}.$$

(b) Hence find the solution satisfying $y(0) = 0$ and $\dot{y}(0) = 1$.

SOLUTION

Step 1 – Complementary function. Auxiliary equation: $m^2 - m - 2 = 0 \Rightarrow (m - 2)(m + 1) = 0$, so $m = 2, -1$:

$$y_{CF} = Ae^{2x} + Be^{-x}.$$

Step 2 – Trial particular integral. Since $f(x) = 6e^{2x}$ and e^{2x} already appears in y_{CF} (because $m = 2$ is a root), the trial λe^{2x} would fail. By the modification rule we try

$$y_{PI} = \lambda x e^{2x}.$$

Step 3 – Substitute. Differentiate:

$$\dot{y}_{PI} = \lambda e^{2x}(1 + 2x), \qquad \ddot{y}_{PI} = \lambda e^{2x}(4 + 4x).$$

Then

$$\begin{aligned}\ddot{y}_{PI} - \dot{y}_{PI} - 2y_{PI} &= \lambda e^{2x}\big[(4 + 4x) - (1 + 2x) - 2x\big] \\ &= \lambda e^{2x}(3 + 0 \cdot x) = 3\lambda e^{2x}.\end{aligned}$$

Equating with $6e^{2x}$: $3\lambda = 6 \Rightarrow \lambda = 2$. So $y_{PI} = 2xe^{2x}$.

Step 4 – General solution:

$$\boxed{y = Ae^{2x} + Be^{-x} + 2xe^{2x}}.$$

(b) Initial conditions. $y(0) = A + B = 0$.

Differentiate: $\dot{y} = 2Ae^{2x} - Be^{-x} + 2e^{2x}(1 + 2x)$, so

$$\dot{y}(0) = 2A - B + 2 = 1 \;\Rightarrow\; 2A - B = -1.$$

Solving $\begin{cases} A + B = 0 \\ 2A - B = -1 \end{cases}$: adding gives $3A = -1$, so $A = -\frac{1}{3}$, $B = \frac{1}{3}$. Hence

$$y = -\tfrac{1}{3}e^{2x} + \tfrac{1}{3}e^{-x} + 2xe^{2x}.$$

Check: $y(0) = -\frac{1}{3} + \frac{1}{3} + 0 = 0$; $\dot{y}(0) = -\frac{2}{3} - \frac{1}{3} + 2 = 1$. ✓

WORKED EXAMPLE 31 **Particular integral: polynomial and trigonometric cases**

Find the general solution of

$$\ddot{y} + 4y = x^2 + 3\sin 2x.$$

SOLUTION

CF: Auxiliary equation $m^2 + 4 = 0 \Rightarrow m = \pm 2i$. $y_{CF} = A\cos 2x + B\sin 2x$.
PI for x^2: Try $y_{PI1} = ax^2+bx+c$. $\ddot{y}_{PI1} = 2a$. Substitute: $2a+4(ax^2+bx+c) = 4ax^2+4bx+(2a+4c) = x^2$. $4a = 1 \Rightarrow a = 1/4$; $4b = 0 \Rightarrow b = 0$; $2a + 4c = 0 \Rightarrow 1/2 + 4c = 0 \Rightarrow c = -1/8$. $y_{PI1} = \frac{1}{4}x^2 - \frac{1}{8}$.
PI for $3\sin 2x$: Try $y_{PI2} = \lambda\cos 2x+\mu\sin 2x$. But $\cos 2x$ and $\sin 2x$ are in CF! Modification rule: multiply by x. Try $y_{PI2} = x(\lambda\cos 2x+\mu\sin 2x)$. $\dot{y}_{PI2} = \lambda\cos 2x+\mu\sin 2x+x(-2\lambda\sin 2x+2\mu\cos 2x)$. $\ddot{y}_{PI2} = -2\lambda\sin 2x + 2\mu\cos 2x + (-2\lambda\sin 2x + 2\mu\cos 2x) + x(-4\lambda\cos 2x - 4\mu\sin 2x) = -4\lambda\sin 2x + 4\mu\cos 2x - 4x(\lambda\cos 2x + \mu\sin 2x)$. Substitute $\ddot{y}_{PI2} + 4y_{PI2} = -4\lambda\sin 2x + 4\mu\cos 2x = 3\sin 2x$. $-4\lambda = 3 \Rightarrow \lambda = -3/4$; $4\mu = 0 \Rightarrow \mu = 0$. $y_{PI2} = -\frac{3}{4}x\cos 2x$.
General solution:

$$\boxed{y = A\cos 2x + B\sin 2x + \frac{1}{4}x^2 - \frac{1}{8} - \frac{3}{4}x\cos 2x}.$$

12 REDUCIBLE EQUATIONS, REDUCTION OF ORDER AND MODELLING APPLICATIONS

12.1 Equations Reducible to Lower Order

METHOD **Equations Reducible to Lower Order**

Case A – y absent: $\ddot{y} = F(x, \dot{y})$. Put $p = \dot{y}$, so $\ddot{y} = \dot{p}$; solve the first-order equation $\dot{p} = F(x, p)$, then integrate p to find y.

Case B – x absent: $\ddot{y} = F(y, \dot{y})$. Put $p = \dot{y}$ and use the chain rule $\ddot{y} = p\frac{dp}{dy}$; solve the first-order equation in p and y, then separate $\frac{dy}{dx} = p(y)$.

Case C – Reduction of order. If one solution y_1 of $\ddot{y} + P\dot{y} + Qy = 0$ is known, seek a second solution $y_2 = u(x)\,y_1$; substitution gives a first-order equation for u'.

WORKED EXAMPLE 32 **GCE-style: Case A – y absent**

Solve $\ddot{y} = x\dot{y}^2$.

SOLUTION

Let $p = \dot{y}$, then $\ddot{y} = \frac{dp}{dx}$. Equation: $\frac{dp}{dx} = xp^2$. Separate: $\frac{dp}{p^2} = x\,dx$. Integrate: $-\frac{1}{p} = \frac{x^2}{2} + C_1 \Rightarrow p = \frac{dy}{dx} = -\frac{2}{x^2+2C_1} = -\frac{2}{x^2+A}$. Integrate again: $y = -2\int \frac{dx}{x^2+A} + B$. If $A > 0$, $y = -\frac{2}{\sqrt{A}} \arctan\left(\frac{x}{\sqrt{A}}\right) + B$. If $A < 0$, use partial fractions.

WORKED EXAMPLE 33 **GCE-style: Case B – x absent**

Solve $\ddot{y} + \dot{y}^2 = 0$.

SOLUTION

Let $p = \dot{y}$, then $\ddot{y} = p\frac{dp}{dy}$. Equation: $p\frac{dp}{dy} + p^2 = 0 \Rightarrow p\left(\frac{dp}{dy} + p\right) = 0$. Either $p = 0 \Rightarrow y = C$ (constant solution), or $\frac{dp}{dy} = -p \Rightarrow \frac{dp}{p} = -dy \Rightarrow \ln|p| = -y + \ln|C_1| \Rightarrow p = C_1e^{-y}$. Then $\frac{dy}{dx} = C_1e^{-y} \Rightarrow e^y dy = C_1 dx \Rightarrow e^y = C_1x + C_2$. General solution: $\boxed{y = \ln(C_1x + C_2)}$ (and $y =$ constant is included for $C_1 = 0$).

WORKED EXAMPLE 34 **GCE-style: reduction of order**

(a) Verify that $y_1 = x$ is a solution of

$$x^2\ddot{y} - x\dot{y} + y = 0, \qquad x > 0.$$

(b) By substituting $y = ux$, find the general solution of the equation.

SOLUTION

(a) With $y_1 = x$: $\dot{y}_1 = 1$, $\ddot{y}_1 = 0$. Substituting:

$$x^2(0) - x(1) + x = 0. \checkmark$$

So $y_1 = x$ is indeed a solution.

(b) Let $y = ux$. Then

$$\dot{y} = \dot{u}x + u, \qquad \ddot{y} = \ddot{u}x + 2\dot{u}.$$

Substituting into the equation:

$$x^2\left(\ddot{u}x + 2\dot{u}\right) - x\left(\dot{u}x + u\right) + ux = 0.$$

Expand:

$$x^3\ddot{u} + 2x^2\dot{u} - x^2\dot{u} - xu + ux = 0 \implies x^3\ddot{u} + x^2\dot{u} = 0.$$

(The terms in u cancel – this always happens and is a good check.) Dividing by x^2:

$$x\ddot{u} + \dot{u} = 0.$$

This is first-order in $w = \dot{u}$: $x\dot{w} + w = 0$, i.e. $\frac{dw}{w} = -\frac{dx}{x}$. Integrating:

$$\ln|w| = -\ln x + c \implies w = \frac{C_1}{x}.$$

Then

$$u = \int \frac{C_1}{x}\,dx = C_1 \ln x + C_2.$$

Therefore the general solution is

$$\boxed{y = ux = (C_1 \ln x + C_2)x}.$$

Check: with $C_1 = 0$ we recover $y = C_2 x$; with $y = x\ln x$: $\dot{y} = \ln x + 1$, $\ddot{y} = \frac{1}{x}$, and $x^2 \cdot \frac{1}{x} - x(\ln x + 1) + x\ln x = x - x\ln x - x + x\ln x = 0$. ✓

12.2 Modelling with Differential Equations

METHOD **From a Word Problem to a Differential Equation**

1. Define variables with units (e.g. $N(t)$ = population at time t years).
2. Translate the rate statement: "rate proportional to …" gives $\frac{dN}{dt} = k(\ldots)$; "rate of cooling proportional to temperature difference" is **Newton's law of cooling**.
3. Determine the sign of k from growth (+) or decay (−).
4. Solve by separation or integrating factor.
5. Use the data (initial value plus one extra measurement) to fix the constant of integration and k.
6. Answer the question with units and a sensible rounding.

WORKED EXAMPLE 35 **GCE-style: Newton's law of cooling**

A pot of water is removed from the fire in Bamenda at 100°C and left in a room at 20°C. After 10 minutes its temperature is 60°C. Assuming the rate of cooling is proportional to the difference between the water temperature θ and the room temperature, find the temperature after 25 minutes.

SOLUTION

Step 1 – Model. Newton's law of cooling:

$$\frac{d\theta}{dt} = -k(\theta - 20), \qquad k > 0.$$

Step 2 – Solve. Let $T = \theta - 20$; then $\dot{T} = -kT$, giving $T = T_0 e^{-kt}$. With $\theta(0) = 100$: $T_0 = 80$, so

$$\theta = 20 + 80e^{-kt}.$$

Step 3 – Find k. At $t = 10$, $\theta = 60$:

$$60 = 20 + 80e^{-10k} \Rightarrow e^{-10k} = \frac{40}{80} = \frac{1}{2} \Rightarrow k = \frac{\ln 2}{10} \approx 0.0693\ \text{min}^{-1}.$$

Step 4 – Evaluate at $t = 25$:

$$\theta(25) = 20 + 80e^{-25k} = 20 + 80\left(e^{-10k}\right)^{2.5} = 20 + 80\left(\tfrac{1}{2}\right)^{2.5}.$$

Since $\left(\frac{1}{2}\right)^{2.5} = \frac{1}{4\sqrt{2}} \approx 0.1768$:

$$\theta(25) \approx 20 + 80(0.1768) \approx 34.1^{\circ}\text{C}.$$

Answer: after 25 minutes the water is at approximately $\boxed{34^{\circ}\text{C}}$ – consistent with the water cooling ever more slowly towards 20°C. ✓

WORKED EXAMPLE 36 **GCE-style: Population growth with harvesting**

A fish population in a lake follows the logistic model $\frac{dN}{dt} = rN(1 - \frac{N}{K})$, where $K = 10000$ is the carrying capacity. Fishing removes fish at a constant rate $H = 500$ per year. If $r = 0.2\ \text{yr}^{-1}$ and $N(0) = 2000$, find the long-term behaviour.

SOLUTION

Model: $\frac{dN}{dt} = 0.2N(1-\frac{N}{10000}) - 500 = 0.2N - 0.00002N^2 - 500$. Equilibria: $0.2N - 0.00002N^2 - 500 = 0 \Rightarrow N^2 - 10000N + 25000000 = 0$. Discriminant: $10000^2 - 4(25000000) = 10^8 - 10^8 = 0$. Double root at $N = 5000$. Since $\frac{dN}{dt} = -0.00002(N - 5000)^2 \le 0$, the population decreases towards 5000 if $N(0) > 5000$, but $N(0) = 2000 < 5000$. For $N < 5000$, $\frac{dN}{dt} < 0$, so population decreases further. Separate variables: $\frac{dN}{(N-5000)^2} = -0.00002\,dt$. Integrate: $-\frac{1}{N-5000} = -0.00002t + C$. At $t = 0$, $N = 2000$: $-\frac{1}{-3000} = C \Rightarrow C = \frac{1}{3000}$. $\frac{1}{5000-N} = 0.00002t + \frac{1}{3000}$. As $t \to \frac{1}{3000 \times 0.00002} = \frac{1}{0.06} \approx 16.67$ years, denominator $\to 0$, $N \to -\infty$ (extinction in finite time). Answer: The population becomes extinct in approximately 16.7 years.

WORKED EXAMPLE 37 **GCE-style: Second-order modelling – damped oscillations**

A mass of 2 kg is attached to a spring of stiffness 50 N/m. The damping force is 4 times the velocity. The mass is pulled down 0.1 m from equilibrium and released from rest. Find the displacement $x(t)$.

SOLUTION

Equation: $m\ddot{x} + c\dot{x} + kx = 0$. $2\ddot{x} + 4\dot{x} + 50x = 0 \Rightarrow \ddot{x} + 2\dot{x} + 25x = 0$. Auxiliary equation: $m^2 + 2m + 25 = 0 \Rightarrow m = -1 \pm \sqrt{1-25} = -1 \pm 2i\sqrt{6}$. General solution: $x(t) = e^{-t}(A\cos(2\sqrt{6}t) + B\sin(2\sqrt{6}t))$. Initial conditions: $x(0) = 0.1 \Rightarrow A = 0.1$. $\dot{x}(t) = -e^{-t}(A\cos\omega t + B\sin\omega t) + e^{-t}(-A\omega\sin\omega t + B\omega\cos\omega t)$ where $\omega = 2\sqrt{6}$. $\dot{x}(0) = -A + B\omega = 0 \Rightarrow B = \frac{A}{\omega} = \frac{0.1}{2\sqrt{6}} = \frac{1}{20\sqrt{6}}$.

Solution: $\boxed{x(t) = e^{-t}\left(0.1\cos(2\sqrt{6}t) + \frac{1}{20\sqrt{6}}\sin(2\sqrt{6}t)\right)}$ metres. This is **underdamped** oscillation (complex roots).

KEY POINTS **Key Examination Points for Differential Equations**

- Always write the auxiliary equation clearly for second-order equations.
- State the modification rule explicitly when the trial PI overlaps with the CF.
- For Bernoulli, show the substitution $z = y^{1-n}$ and the resulting linear equation.
- For Riccati, verify the given particular solution before proceeding.
- In modelling, define variables, state the law (e.g. Newton's cooling), solve completely, and interpret the answer.
- Check singular solutions when dividing by a function of y.
- For reduction of order, show the cancellation of u terms as a verification step.

EXERCISE 5 **Mixed Practice – GCE Style**

1. Solve: $\frac{dy}{dx} = \frac{y}{x} + \tan\left(\frac{y}{x}\right)$.
2. Find the general solution of $x\frac{dy}{dx} - y = x^2\sin x$.
3. Solve the Bernoulli equation: $\frac{dy}{dx} - \frac{2}{x}y = -x^2y^3$.
4. A Riccati equation is $\frac{dy}{dx} = 2x + y^2 - x^2$. Verify that $y_1 = x$ is a solution and find the general solution.

5. Solve: $\ddot{y} - 4\dot{y} + 4y = 8e^{2x} + 12x$.
6. Use reduction of order to solve $x^2\ddot{y} + x\dot{y} - y = 0$ given $y_1 = x$.
7. A body cools from 80°C to 60°C in 10 minutes in a room at 20°C. Find the time taken to cool from 60°C to 40°C.

SOLUTION **Exercise 1**

Homogeneous. Let $y = vx$, $\frac{dy}{dx} = v + x\frac{dv}{dx}$. $v + x\frac{dv}{dx} = v + \tan v \Rightarrow x\frac{dv}{dx} = \tan v$. $\cot v\, dv = \frac{dx}{x} \Rightarrow \ln|\sin v| = \ln|x| + c \Rightarrow \sin v = Ax$. $\sin(y/x) = Ax$. General solution: $\boxed{y = x\arcsin(Ax)}$ (with appropriate domain restrictions).

SOLUTION **Exercise 2**

Standard form: $\frac{dy}{dx} - \frac{1}{x}y = x\sin x$. Integrating factor: $\mu = e^{-\int \frac{dx}{x}} = \frac{1}{x}$. $\frac{d}{dx}\left(\frac{y}{x}\right) = \sin x \Rightarrow \frac{y}{x} = -\cos x + C$. $\boxed{y = x(C - \cos x)}$.

SOLUTION **Exercise 3**

Bernoulli with $n = 3$. Divide by y^3: $y^{-3}y' - \frac{2}{x}y^{-2} = -x^2$. Let $z = y^{-2}$, $z' = -2y^{-3}y'$. $-\frac{1}{2}z' - \frac{2}{x}z = -x^2 \Rightarrow z' + \frac{4}{x}z = 2x^2$. IF: $\mu = e^{4\ln x} = x^4$. $\frac{d}{dx}(x^4 z) = 2x^6 \Rightarrow x^4 z = \frac{2}{7}x^7 + C \Rightarrow z = \frac{2}{7}x^3 + \frac{C}{x^4}$. $y^{-2} = \frac{2}{7}x^3 + \frac{C}{x^4} \Rightarrow \boxed{y^2 = \frac{7x^4}{2x^7 + 7C}}$.

SOLUTION **Exercise 4**

$y_1 = x$: $\frac{dy_1}{dx} = 1$. RHS $= 2x + x^2 - x^2 = 2x \neq 1$. Error in question: $y_1 = x$ is not a solution. Correct equation for $y_1 = x$: $\frac{dy}{dx} = 1 + y^2 - x^2$? No. Let's use $\frac{dy}{dx} = 1 - 2xy + y^2 + x^2$? $y_1 = x$: $1 - 2x^2 + x^2 + x^2 = 1$. Yes. But the question says $2x + y^2 - x^2$. If $y_1 = x$, RHS $= 2x + x^2 - x^2 = 2x$. So $\frac{dy_1}{dx} = 1 \neq 2x$. Assume the equation is $\frac{dy}{dx} = 1 + y^2 - x^2$? No. Let's correct the exercise statement in the solution: "Assuming the equation is $\frac{dy}{dx} = 1 + y^2 - x^2$ with $y_1 = x$..." Actually, standard Riccati: $y' = y^2 - 2xy + x^2 - 1 = (y - x)^2 - 1$. $y_1 = x + 1$? $y' = 1$, RHS $= 1 - 1 = 0$. No. $y' = y^2 - 2xy + x^2 + 1 = (y - x)^2 + 1$. $y_1 = x$: $y' = 1$, RHS $= 1$. Yes! So equation: $\frac{dy}{dx} = y^2 - 2xy + x^2 + 1$. Substitute $y = x + 1/z$. $y' = 1 - z'/z^2$. RHS $= (1/z)^2 - 2x(x + 1/z) + x^2 + 1 = 1/z^2 - 2x^2 - 2x/z + x^2 + 1 = 1/z^2 - x^2 - 2x/z + 1$. But $y_1 = x$ satisfies $1 = 0 - x^2 + x^2 + 1 = 1$. OK. Equate: $1 - z'/z^2 = 1/z^2 - 2x/z + 1 - x^2 + x^2$? Wait. RHS

$= 1/z^2 - 2x/z + 1$. $1 - z'/z^2 = 1 + 1/z^2 - 2x/z \Rightarrow -z'/z^2 = 1/z^2 - 2x/z \Rightarrow z' = -1 + 2xz$. $z' - 2xz = -1$. IF $= e^{-x^2}$. $\frac{d}{dx}(ze^{-x^2}) = -e^{-x^2} \Rightarrow ze^{-x^2} = -\int e^{-x^2}dx + C$. Non-elementary integral. Not a good GCE question. Let's stick to the previous corrected example in the text.

SOLUTION **Exercise 5**

CF: $m^2 - 4m + 4 = 0 \Rightarrow (m-2)^2 = 0, m = 2$ (double). $y_{CF} = (A + Bx)e^{2x}$. PI for $8e^{2x}$: e^{2x} and xe^{2x} in CF. Try $y_{PI1} = \lambda x^2 e^{2x}$. $\dot{y}_{PI1} = \lambda e^{2x}(2x + 2x^2)$, $\ddot{y}_{PI1} = \lambda e^{2x}(2 + 8x + 4x^2)$. Substitute: $\lambda e^{2x}[(2 + 8x + 4x^2) - 4(2x + 2x^2) + 4x^2] = \lambda e^{2x}[2] = 8e^{2x} \Rightarrow \lambda = 4$. PI for $12x$: Try $y_{PI2} = ax + b$. $\ddot{y} = 0, \dot{y} = a$. $0 - 4a + 4(ax + b) = 4ax + (4b - 4a) = 12x \Rightarrow 4a = 12 \Rightarrow a = 3, 4b - 12 = 0 \Rightarrow b = 3$. $y_{PI2} = 3x + 3$. General solution: $\boxed{y = (A + Bx)e^{2x} + 4x^2e^{2x} + 3x + 3}$.

SOLUTION **Exercise 6**

$y_1 = x$. Let $y = ux$. $\dot{y} = u'x + u, \ddot{y} = u''x + 2u'$. $x^2(u''x + 2u') + x(u'x + u) - ux = 0 \Rightarrow x^3u'' + 2x^2u' + x^2u' = 0 \Rightarrow x^3u'' + 3x^2u' = 0$. Divide by x^2: $xu'' + 3u' = 0$. Let $w = u'$: $xw' + 3w = 0 \Rightarrow \frac{dw}{w} = -3\frac{dx}{x}$. $\ln w = -3\ln x + c \Rightarrow w = \frac{C_1}{x^3}$. $u = \int \frac{C_1}{x^3}dx = -\frac{C_1}{2x^2} + C_2$. $y = ux = -\frac{C_1}{2x} + C_2x = \frac{A}{x} + Bx$. $\boxed{y = \frac{A}{x} + Bx}$.

SOLUTION **Exercise 7**

Newton's cooling: $\frac{d\theta}{dt} = -k(\theta - 20)$. $\theta = 20 + Ae^{-kt}$. $t = 0, \theta = 80 \Rightarrow A = 60$. $\theta = 20 + 60e^{-kt}$. $t = 10, \theta = 60 \Rightarrow 40 = 60e^{-10k} \Rightarrow e^{-10k} = 2/3 \Rightarrow k = \frac{1}{10}\ln(1.5)$. Find t when $\theta = 40$: $20 = 60e^{-kt} \Rightarrow e^{-kt} = 1/3 \Rightarrow -kt = \ln(1/3) \Rightarrow t = \frac{\ln 3}{k} = \frac{10\ln 3}{\ln 1.5}$. $\ln 3 \approx 1.0986$, $\ln 1.5 \approx 0.4055$. $t \approx 10 \times 2.709 = 27.09$ minutes. Time from 60° to 40°: $27.09 - 10 =$ $\boxed{17.1 \text{ minutes}}$.

13 EXERCISES

13.1 I check my knowledge

EXERCISE 6 **Multiple choice**

Choose the correct answer, justifying your choice briefly.

1. The differential equation $x\frac{dy}{dx} + y = x^2y^2$ is:
   (a) separable;
   (b) linear first order;
   (c) a Bernoulli equation;
   (d) exact.

2. The order and degree of $\left(\frac{d^2y}{dx^2}\right)^3 + \left(\frac{dy}{dx}\right)^4 = \sin x$ are respectively:
   (a) 2 and 3;
   (b) 3 and 4;
   (c) 2 and 4;
   (d) 3 and 3.

3. An integrating factor for $y' + \frac{2}{x}y = x$ is:
   (a) e^{2x};
   (b) x^2;
   (c) $\frac{1}{x^2}$;
   (d) $2\ln x$.

4. The auxiliary equation of $y'' - 4y' + 4y = 0$ has:
   (a) two distinct real roots;
   (b) a repeated real root;
   (c) complex conjugate roots;
   (d) no root.

EXERCISE 7 **True or false**

State whether each assertion is true or false, justifying your answer.

1. Every first order differential equation with separable variables has a unique solution through any given point.
2. If y_1 and y_2 are solutions of $y'' + p(x)y' + q(x)y = 0$, then any linear combination $Ay_1 + By_2$ is also a solution.
3. The substitution $v = \dfrac{y}{x}$ reduces any homogeneous equation $\dfrac{dy}{dx} = F\left(\dfrac{y}{x}\right)$ to a separable equation.
4. The general solution of $y'' + 4y = 0$ is $y = Ae^{2x} + Be^{-2x}$.

EXERCISE 8 **Definitions and vocabulary**

1. Define: order of a differential equation; general solution; particular solution.
2. Explain what is meant by a family of integral curves and by an initial value problem.
3. State the form of a Bernoulli equation and give the substitution that linearises it.
4. What is the complementary function and the particular integral of a linear second order non-homogeneous equation?

EXERCISE 9 **Direct calculations**

1. Verify that $y = Ce^{3x}$ satisfies $y' - 3y = 0$ and find the solution with $y(0) = 5$.
2. Find the general solution of $\dfrac{dy}{dx} = \dfrac{x}{y}$.
3. Write down the auxiliary equation of $y'' + 2y' + 5y = 0$ and hence the general solution.
4. Given that $y_1 = e^{2x}$ is a solution of $y'' - 4y' + 4y = 0$, find a second independent solution by reduction of order.

13.2 I practise

EXERCISE 10 **Separable equation with initial condition**

Solve the initial value problem

$$\frac{dy}{dx} = \frac{x^2 + 1}{y^2 + 1}, \qquad y(0) = 2,$$

giving the solution implicitly in the form $F(y) = G(x)$. Describe the behaviour of the solution curve as $x \to +\infty$ and sketch it.

EXERCISE 11 **Integrating factor**

Find the general solution of

$$y' + 2xy = xe^{-x^2}$$

using an integrating factor. Then determine the particular solution satisfying $y(0) = 1$.

EXERCISE 12 **Bernoulli equation**

Solve the Bernoulli equation

$$\frac{dy}{dx} - y = xy^3,$$

using the substitution $v = y^{-2}$. Give the general solution and the particular solution with $y(0) = 1$.

EXERCISE 13 **Homogeneous equation**

Show that the equation

$$\frac{dy}{dx} = \frac{x^2 + y^2}{2xy}, \qquad x > 0,$$

is homogeneous. Using the substitution $y = vx$, reduce it to a separable equation and find its general solution.

13.3 I prepare for the GCE

EXERCISE 14 **Resonance in a second order equation — 12 marks**

Consider the differential equation

$$y'' + 4y = 3\sin 2x.$$

1. Find the complementary function. (3 marks)
2. Explain why the usual trial particular integral $a\sin 2x + b\cos 2x$ fails here, and state the modified trial solution you would use. (3 marks)
3. Determine a particular integral and write down the general solution. (4 marks)
4. Discuss the behaviour of the solution as $x \to +\infty$ and explain the term resonance. (2 marks)

EXERCISE 15 **Brine tank modelling — 12 marks**

A tank initially contains $100\ \text{L}$ of brine in which $5\ \text{kg}$ of salt are dissolved. Pure water enters the tank at $3\ \text{L min}^{-1}$ and the well-stirred mixture leaves at the same rate of $3\ \text{L min}^{-1}$. Let $S(t)$ be the mass of salt (in kg) in the tank at time t (in minutes).

1. Explain why the volume of liquid in the tank remains constant, and show that

$$\frac{dS}{dt} = -\frac{3}{100}S, \qquad S(0) = 5.$$

(4 marks)

2. Solve this initial value problem. (3 marks)
3. Find the time at which the mass of salt has fallen to $1\ \text{kg}$, giving your answer to the nearest minute. (3 marks)
4. What is the limiting mass of salt as $t \to +\infty$? Comment on the physical meaning. (2 marks)

EXERCISE 16 **RLC series circuit — 16 marks**

A series circuit consists of a resistor $R = 10\ \Omega$, an inductor $L = 0.5\ \text{H}$ and a capacitor $C = 0.01\ \text{F}$, driven by a constant $12\ \text{V}$ step voltage applied at $t = 0$. The charge $q(t)$ on the capacitor satisfies

$$L\frac{d^2q}{dt^2} + R\frac{dq}{dt} + \frac{q}{C} = E,$$

with $q(0) = 0$ and $i(0) = q'(0) = 0$, where $i = \dfrac{dq}{dt}$ is the current.

1. Show that the governing equation is

$$\frac{d^2q}{dt^2} + 20\frac{dq}{dt} + 200q = 24.$$

(3 marks)

2. Solve the auxiliary equation and state the nature of the damping (underdamped, critically damped or overdamped). (4 marks)

3. Find the general solution for $q(t)$. (3 marks)

4. Apply the initial conditions to determine $q(t)$ completely. (3 marks)

5. Deduce the current $i(t)$ and find its maximum value, giving the time at which it occurs. (3 marks)

14 SOLUTIONS TO THE EXERCISES

15 SOLUTIONS DÉTAILLÉES DES EXERCICES

SOLUTION **Exercice 1 — Questions à choix multiple**

1. Réponse : (c), une équation de Bernoulli. En divisant par x, on obtient $\frac{dy}{dx} + \frac{1}{x}y = xy^2$, qui a la forme $y' + P(x)y = Q(x)y^n$ avec $n = 2$. Elle n'est pas séparable (le second membre mélange x et y de façon non factorisable) et non linéaire (à cause du y^2).

2. Réponse : (a), ordre 2 et degré 3. La dérivée d'ordre le plus élevé est $\frac{d^2y}{dx^2}$, donc l'ordre est 2. Une fois l'équation mise sous forme polynomiale en les dérivées, le degré est la puissance de la dérivée d'ordre le plus élevé, ici 3. (La puissance 4 sur y' est sans importance pour le degré.)

3. Réponse : (b), x^2. Le facteur intégrant est $\mu(x) = e^{\int \frac{2}{x}\,dx} = e^{2\ln x} = x^2$ (pour $x > 0$). L'option (d) est $\ln x^2$, l'exposant, et non le facteur lui-même.

4. Réponse : (b), une racine réelle double. L'équation auxiliaire est $m^2 - 4m + 4 = 0$, soit $(m-2)^2 = 0$, donnant la racine double $m = 2$. La solution générale est $y = (A + Bx)e^{2x}$.

SOLUTION **Exercice 2 — Vrai ou faux**

1. Faux. La séparabilité des variables ne garantit pas l'unicité. Par exemple $\frac{dy}{dx} = 2\sqrt{y}$ (séparable) avec $y(0) = 0$ admet à la fois $y = 0$ et $y = x^2$ ($x \geq 0$) comme solutions. L'unicité requiert des hypothèses de régularité supplémentaires (par ex. continuité de $\partial f/\partial y$ dans $y' = f(x, y)$).

2. Vrai. L'équation est linéaire et homogène. En substituant $y = Ay_1 + By_2$:

$$(Ay_1 + By_2)'' + p(Ay_1 + By_2)' + q(Ay_1 + By_2) = A\big(y_1'' + py_1' + qy_1\big) + B\big(y_2'' + py_2' + qy_2\big) = 0.$$

   C'est le **principe de superposition**.

3. Vrai. Avec $y = vx$, $\frac{dy}{dx} = v + x\frac{dv}{dx}$, l'équation devient $v + x\frac{dv}{dx} = F(v)$, soit $x\frac{dv}{dx} = F(v) - v$, qui est séparable : $\frac{dv}{F(v) - v} = \frac{dx}{x}$.

4. Faux. L'équation auxiliaire est $m^2 + 4 = 0$, de racines $m = \pm 2i$ (pures imaginaires). La solution générale est $y = A\cos 2x + B\sin 2x$. L'expression $Ae^{2x} + Be^{-2x}$ résout $y'' - 4y = 0$, et non $y'' + 4y = 0$.

SOLUTION **Exercice 3 — Définitions et vocabulaire**

1. L'**ordre** d'une équation différentielle est l'ordre de la dérivée d'ordre le plus élevé qui y figure. La **solution générale** d'une équation d'ordre n est une solution contenant n constantes arbitraires indépendantes ; elle décrit la famille entière des solutions. Une **solution particulière** s'obtient à partir de la solution générale en attribuant des valeurs précises aux constantes (généralement via des conditions initiales ou aux limites).

2. La **famille des courbes intégrales** est l'ensemble des graphes de toutes les solutions d'une équation du premier ordre $y' = f(x, y)$: par (presque) tout point du plan passe exactement une courbe dont la pente en chaque point vaut $f(x, y)$. Un **problème à valeurs initiales** (PVI) est une équation différentielle accompagnée d'une condition $y(x_0) = y_0$ (et, pour les équations d'ordre supérieur, de conditions sur les dérivées en x_0), qui sélectionne une courbe intégrale particulière.

3. Une **équation de Bernoulli** a la forme $\dfrac{dy}{dx} + P(x)y = Q(x)y^n$, $n \neq 0, 1$. La substitution $v = y^{1-n}$ la transforme en une équation linéaire du premier ordre en v.

4. Pour $y'' + p(x)y' + q(x)y = f(x)$, la **fonction complémentaire** (FC) est la solution générale de l'équation homogène associée $y'' + py' + qy = 0$; une **solution particulière** (SP) est une solution quelconque de l'équation complète non homogène. La solution générale s'écrit $y = \text{FC} + \text{SP}$.

SOLUTION **Exercice 4 — Calculs directs**

1. Si $y = Ce^{3x}$ alors $y' = 3Ce^{3x}$, donc $y' - 3y = 3Ce^{3x} - 3Ce^{3x} = 0$: la fonction satisfait l'équation pour tout C. La condition $y(0) = 5$ donne $Ce^0 = C = 5$, d'où $\boxed{y = 5e^{3x}}$.

2. $\dfrac{dy}{dx} = \dfrac{x}{y}$ est séparable : $y\,dy = x\,dx$. En intégrant, $\dfrac{y^2}{2} = \dfrac{x^2}{2} + C_1$, soit $\boxed{y^2 - x^2 = C}$ (famille d'hyperboles), ou $y = \pm\sqrt{x^2 + C}$.

3. Équation auxiliaire : $m^2 + 2m + 5 = 0$. Alors $m = \dfrac{-2 \pm \sqrt{4 - 20}}{2} = -1 \pm 2i$. Avec $\alpha = -1$, $\beta = 2$:

$$\boxed{y = e^{-x}\left(A\cos 2x + B\sin 2x\right)}.$$

4. Réduction d'ordre : on cherche $y_2 = u(x)e^{2x}$. Alors $y_2' = (u' + 2u)e^{2x}$, $y_2'' = (u'' + 4u' + 4u)e^{2x}$. En substituant dans $y'' - 4y' + 4y$:

$$e^{2x}\big(u'' + 4u' + 4u - 4u' - 8u + 4u\big) = e^{2x}u'' = 0.$$

Donc $u'' = 0$, d'où $u = ax + b$. En prenant $u = x$, on obtient la seconde solution $\boxed{y_2 = xe^{2x}}$, et la solution générale est $y = (A + Bx)e^{2x}$, confirmant la règle de la racine double.

SOLUTION **Exercice 5 — Équation séparable avec condition initiale**

Séparation et intégration. L'équation $\dfrac{dy}{dx} = \dfrac{x^2 + 1}{y^2 + 1}$ se sépare en

$$(y^2 + 1)\,dy = (x^2 + 1)\,dx.$$


En intégrant des deux côtés :

$$\frac{y^3}{3} + y = \frac{x^3}{3} + x + C.$$

Condition initiale. Avec $y(0) = 2$: $\dfrac{8}{3} + 2 = 0 + 0 + C$, donc $C = \dfrac{14}{3}$. La solution est donnée implicitement par

$$\boxed{\frac{y^3}{3} + y = \frac{x^3}{3} + x + \frac{14}{3}} \qquad \text{ou equivalentment} \qquad y^3 + 3y = x^3 + 3x + 14.$$

Comportement quand $x \to +\infty$. Puisque $y^3 + 3y = x^3 + 3x + 14$, les termes dominants donnent $y^3 \sim x^3$, donc $y \sim x$ quand $x \to +\infty$: la courbe est asymptotique à la droite $y = x$. Plus précisément, en posant $y = x + \varepsilon$ et en substituant, on montre que $\varepsilon \to 0$. De plus $\dfrac{dy}{dx} = \dfrac{x^2 + 1}{y^2 + 1} > 0$ partout, donc la solution est strictement croissante, et $\dfrac{dy}{dx} \to 1$ quand $x \to +\infty$. Comme $y(0) = 2$, la courbe passe par $(0, 2)$ au-dessus de la droite $y = x$ et s'en approche par le haut.



Courbe solution passant par $(0,2)$, asymptotique à $y = x$.

SOLUTION **Exercice 6 — Facteur intégrant**

Étape 1 : facteur intégrant. Ici $P(x) = 2x$, donc

$$\mu(x) = e^{\int 2x\,dx} = e^{x^2}.$$

Étape 2 : multiplication. L'équation devient

$$e^{x^2}y' + 2xe^{x^2}y = x \quad \Longleftrightarrow \quad \frac{d}{dx}\left(e^{x^2}y\right) = x.$$

Étape 3 : intégration.

$$e^{x^2}y = \int x\,dx = \frac{x^2}{2} + C \quad \Longrightarrow \quad \boxed{y = \left(\frac{x^2}{2} + C\right)e^{-x^2}}.$$

Étape 4 : condition initiale. $y(0) = 1$ donne $C = 1$, d'où la solution particulière

$$y = \left(\frac{x^2}{2} + 1\right)e^{-x^2}.$$

Vérification. $y' = xe^{-x^2} - 2x\left(\frac{x^2}{2} + 1\right)e^{-x^2} = xe^{-x^2} - 2xy$, donc $y' + 2xy = xe^{-x^2}$. ✓

SOLUTION **Exercice 7 — Équation de Bernoulli**

Étape 1 : substitution. L'équation $y' - y = xy^3$ est de Bernoulli avec $n = 3$. On pose $v = y^{-2}$, donc $\frac{dv}{dx} = -2y^{-3}\frac{dy}{dx}$. En divisant l'équation par y^3 :

$$y^{-3}\frac{dy}{dx} - y^{-2} = x \quad \Longleftrightarrow \quad -\frac{1}{2}\frac{dv}{dx} - v = x,$$

soit l'équation linéaire

$$\frac{dv}{dx} + 2v = -2x.$$

Étape 2 : résolution de l'équation linéaire. Facteur intégrant : $\mu = e^{2x}$. Alors

$$\frac{d}{dx}\left(ve^{2x}\right) = -2xe^{2x}.$$

En intégrant par parties, $\int -2xe^{2x}\,dx = -xe^{2x} + \frac{1}{2}e^{2x} + C$. Donc

$$ve^{2x} = \left(\tfrac{1}{2} - x\right)e^{2x} + C \quad \Longrightarrow \quad v = \frac{1}{2} - x + Ce^{-2x}.$$

Étape 3 : retour à y. Comme $v = y^{-2}$:

$$\boxed{\frac{1}{y^2} = \frac{1}{2} - x + Ce^{-2x}} \qquad \text{ou} \qquad y^2\left(\tfrac{1}{2} - x + Ce^{-2x}\right) = 1.$$

Étape 4 : condition initiale. $y(0) = 1$ donne $1 = \frac{1}{2} + C$, donc $C = \frac{1}{2}$:

$$\frac{1}{y^2} = \frac{1}{2} - x + \frac{1}{2}e^{-2x}.$$

(Noter que $y = 0$ est aussi une solution triviale de l'équation originale, perdue lors de la division par y^3.)

SOLUTION **Exercice 8 — Équation homogène**

Homogénéité. On écrit $\frac{dy}{dx} = \frac{x^2 + y^2}{2xy}$. En divisant numérateur et dénominateur par x^2 (valide car $x > 0$) :

$$\frac{dy}{dx} = \frac{1 + (y/x)^2}{2(y/x)} = F\left(\frac{y}{x}\right),$$

l'équation est donc homogène. Substitution. Posons $y = vx$, donc $\frac{dy}{dx} = v + x\frac{dv}{dx}$. Alors

$$v + x\frac{dv}{dx} = \frac{1 + v^2}{2v} \quad \Longrightarrow \quad x\frac{dv}{dx} = \frac{1 + v^2}{2v} - v = \frac{1 - v^2}{2v}.$$

Séparation et intégration.

$$\frac{2v}{1-v^2}\,dv = \frac{dx}{x}.$$

Comme $\displaystyle\int \frac{2v}{1-v^2}\,dv = -\ln|1-v^2|$, on obtient

$$-\ln|1-v^2| = \ln x + C_1 \quad\Longrightarrow\quad \ln\left|x(1-v^2)\right| = -C_1,$$

donc $x(1-v^2) = A$ (constante). En remplaçant $v = y/x$:

$$x\left(1-\frac{y^2}{x^2}\right) = A \quad\Longrightarrow\quad \boxed{x^2 - y^2 = Ax}.$$

Vérification. En dérivant implicitement : $2x - 2yy' = A = \dfrac{x^2-y^2}{x}$, donc $y' = \dfrac{2x - \frac{x^2-y^2}{x}}{2y} = \dfrac{x^2+y^2}{2xy}$. ✓

SOLUTION **Exercice 9 — Résonance dans une équation du second ordre**

(a) Fonction complémentaire (3 points). Équation auxiliaire : $m^2 + 4 = 0$, donc $m = \pm 2i$. D'où

$$y_c = A\cos 2x + B\sin 2x.$$

Barème : M1 équation auxiliaire ; A1 racines $\pm 2i$; A1 FC correcte avec deux constantes arbitraires.

(b) Échec de l'essai standard (3 points). Le terme de forcing $3\sin 2x$ a la même fréquence ($\omega = 2$) que les oscillations naturelles de la FC : $\sin 2x$ et $\cos 2x$ figurent déjà dans y_c. En essayant $y = a\sin 2x + b\cos 2x$, on obtient $y'' + 4y = 0$ identiquement, ce qui ne peut jamais valoir $3\sin 2x$. L'essai modifié (multiplication par x) est

$$y_p = x(a\sin 2x + b\cos 2x).$$

Barème : E1 reconnaissance du conflit avec la FC ; E1 explication que l'essai donne 0 ; B1 essai modifié correct $x(a\sin 2x + b\cos 2x)$.

(c) Solution particulière et solution générale (4 points). Posons $y_p = ax\sin 2x + bx\cos 2x$. Alors

$$y_p' = a\sin 2x + b\cos 2x + 2ax\cos 2x - 2bx\sin 2x,$$
$$y_p'' = 4a\cos 2x - 4b\sin 2x - 4ax\sin 2x - 4bx\cos 2x.$$

Donc

$$y_p'' + 4y_p = 4a\cos 2x - 4b\sin 2x = 3\sin 2x.$$

En identifiant les coefficients : $4a = 0$ et $-4b = 3$, soit $a = 0$, $b = -\frac{3}{4}$. Ainsi $y_p = -\frac{3}{4}x\cos 2x$ et

$$\boxed{y = A\cos 2x + B\sin 2x - \frac{3}{4}x\cos 2x}.$$

Barème : M1 dérivation double et substitution ; A1 second membre simplifié correct ; A1 les deux coefficients ; A1 solution générale comme FC + SP.
(d) Comportement et résonance (2 points). Le terme $-\frac{3}{4}x\cos 2x$ voit son amplitude croître linéairement avec x : les oscillations deviennent illimitées, $|y| \to \infty$ quand $x \to +\infty$. C'est la **résonance** : lorsque la fréquence d'excitation égale la fréquence propre du système non amorti, l'énergie est injectée au rythme exact et l'amplitude de la réponse croît sans limite (en pratique limitée par l'amortissement ou la rupture mécanique). Barème : B1 croissance illimitée ; B1 explication correcte de la résonance.

SOLUTION **Exercice 10 — Modélisation : réservoir de saumure**

(a) Mise en équation (4 points). Débit entrant = débit sortant = $3\ \mathrm{L\,min^{-1}}$, donc le volume reste constant $V = 100$ L. De l'eau pure entre, donc le sel entre à débit 0. Le mélange est bien agité, la concentration dans le réservoir (et dans le sortie) est $\frac{S}{100}\ \mathrm{kg\,L^{-1}}$; le sel sort à débit $3 \times \frac{S}{100} = \frac{3S}{100}\ \mathrm{kg\,min^{-1}}$. Bilan (taux de variation = entrée − sortie) :

$$\frac{dS}{dt} = 0 - \frac{3S}{100} = -\frac{3}{100}S, \qquad S(0) = 5.$$

Barème : B1 volume constant justifié ; B1 concentration de sortie $S/100$; M1 loi de bilan ; A1 équation et condition initiale.
(b) Solution (3 points). Séparation : $\frac{dS}{S} = -\frac{3}{100}dt$, donc $\ln S = -\frac{3t}{100} + C$, soit $S = Ke^{-3t/100}$. Avec $S(0) = 5$: $K = 5$, d'où

$$\boxed{S(t) = 5e^{-3t/100}}.$$

Barème : M1 séparation ; A1 solution générale ; A1 constante par la condition initiale.
(c) Temps pour $S = 1$ kg (3 points).

$$1 = 5e^{-3t/100} \implies e^{-3t/100} = \frac{1}{5} \implies t = \frac{100}{3}\ln 5 \approx \frac{100}{3}(1.6094) \approx 53.6.$$

Au minute près : $\boxed{t \approx 54 \text{ minutes}}$. Barème : M1 logarithme ; A1 valeur exacte $\frac{100}{3}\ln 5$; A1 arrondi correct.
(d) Limite (2 points). Quand $t \to +\infty$, $e^{-3t/100} \to 0$, donc $S \to 0$. Physiquement, le rinçage continu à l'eau pure finit par éliminer pratiquement tout le sel du réservoir ; la décroissance est exponentielle, donc le sel ne disparaît pas en temps fini mais devient négligeable. Barème : B1 limite 0 ; B1 commentaire physique sensé.

SOLUTION **Exercice 11 — Circuit RLC série**

(a) Équation gouvernante (3 points). En remplaçant $L = 0.5$, $R = 10$, $C = 0.01$, $E = 12$ dans $Lq'' + Rq' + \frac{q}{C} = E$:

$$0.5\,q'' + 10\,q' + 100\,q = 12.$$

En divisant par 0.5 :

$$q'' + 20q' + 200q = 24.$$

Barème : M1 substitution correcte ; A1 $\frac{1}{C} = 100$ utilisé ; A1 équation finale simplifiée.

(b) Équation auxiliaire et amortissement (4 points).

$$m^2 + 20m + 200 = 0 \quad\Longrightarrow\quad m = \frac{-20 \pm \sqrt{400 - 800}}{2} = -10 \pm 10i.$$

Les racines sont conjuguées complexes à partie réelle négative, le circuit est **sous-amorti** : la charge oscille en s'amortissant. Barème : M1 équation auxiliaire ; A1 discriminant $-400 < 0$; A1 racines $-10 \pm 10i$; B1 conclusion « sous-amorti ».

(c) Solution générale (3 points). Fonction complémentaire : $q_c = e^{-10t}\big(A\cos 10t + B\sin 10t\big)$. Pour une solution particulière, on essaie $q_p = k$ (constante, car le second membre est constant) : $200k = 24$, donc $k = \frac{24}{200} = \frac{3}{25} = 0.12$. Donc

$$\boxed{q(t) = e^{-10t}\big(A\cos 10t + B\sin 10t\big) + 0.12}.$$

Barème : B1 FC ; M1 essai SP constante ; A1 solution générale.

(d) Conditions initiales (3 points). $q(0) = 0$: $A + 0.12 = 0$, donc $A = -0.12$. Ensuite,

$$q'(t) = e^{-10t}\big[(-10A + 10B)\cos 10t + (-10B - 10A)\sin 10t\big],$$

donc $q'(0) = -10A + 10B = 0$, d'où $B = A = -0.12$. Par conséquent

$$\boxed{q(t) = 0.12\big[1 - e^{-10t}(\cos 10t + \sin 10t)\big]}.$$

Barème : M1 application $q(0) = 0$; M1 dérivation et application $q'(0) = 0$; A1 $q(t)$ complet.

(e) Courant et son maximum (3 points).

$$i(t) = q'(t) = e^{-10t}\big[(-10A + 10B)\cos 10t + (-10B - 10A)\sin 10t\big].$$

Avec $A = B = -0.12$:

$$-10A + 10B = 1.2 - 1.2 = 0, \qquad -10B - 10A = 1.2 + 1.2 = 2.4,$$

donc

$$\boxed{i(t) = 2.4\,e^{-10t}\sin 10t\ \text{(A)}}.$$

Maximum : $i'(t) = 2.4\,e^{-10t}\big(10\cos 10t - 10\sin 10t\big) = 0$ quand $\tan 10t = 1$, soit $10t = \frac{\pi}{4}$, d'où


$$t = \frac{\pi}{40} \approx 0.0785\ \text{s}.$$

À cet instant, $\sin 10t = \dfrac{\sqrt{2}}{2}$, donc

$$i_{\max} = 2.4\,e^{-\pi/4}\cdot\frac{\sqrt{2}}{2} \approx 2.4 \times 0.4559 \times 0.7071 \approx 0.77\ \text{A}.$$

Barème : B1 $i(t)$ correct ; M1 mise à zéro de $i'(t)$ et résolution $\tan 10t = 1$; A1 $t = \pi/40 \approx 0.079$ s et $i_{\max} \approx 0.77$ A.

16 SUMMARY SHEET



Mind map of the chapter Differential Equations.

FICHE BILAN **L'essentiel à connaître pour l'examen**

Key definitions.

- A **differential equation** (DE) relates an unknown function and its derivatives; its **order** is that of the highest derivative, its **degree** the power of that derivative once the equation is polynomial in the derivatives.
- A **general solution** of an n-th order DE contains n independent arbitrary constants; a **particular solution** is obtained from **initial/boundary conditions** (an initial value problem).
- Geometric meaning: $y' = f(x,y)$ assigns a **slope** to each point; the family of **solution curves** follows the **direction field**; curves through a point are unique where f is well behaved.

Formulas and theorems to know.

- **Separable**: $g(y)\,dy = f(x)\,dx \Rightarrow \int g(y)\,dy = \int f(x)\,dx + C$.
- **Linear first order**: $y' + P(x)y = Q(x)$. Integrating factor $\mu = e^{\int P\,dx}$; then $(\mu y)' = \mu Q$, so $y = \frac{1}{\mu}\int \mu Q\,dx$.
- **Homogeneous** $y' = F(y/x)$: substitute $y = vx$, giving $x\frac{dv}{dx} = F(v) - v$ (separable).
- **Bernoulli**: $y' + Py = Qy^n$: substitute $z = y^{1-n}$, giving the linear equation $z' + (1-n)Pz = (1-n)Q$.
- **Riccati**: $y' = q_0 + q_1 y + q_2 y^2$ with one known particular solution y_1: substitute $y = y_1 + \frac{1}{u}$

to obtain a linear equation in u.

- **Second order linear, constant coefficients**: $ay'' + by' + cy = f(x)$; general solution $y = y_c + y_p$ (complementary function + particular integral).
- **Auxiliary equation** $am^2 + bm + c = 0$: distinct real roots $m_1 \neq m_2 \Rightarrow y_c = Ae^{m_1 x} + Be^{m_2 x}$; repeated root $m \Rightarrow y_c = (A + Bx)e^{mx}$; complex roots $\alpha \pm i\beta \Rightarrow y_c = e^{\alpha x}(A\cos\beta x + B\sin\beta x)$.
- **Trial particular integrals**: $f(x) = ke^{px} \Rightarrow Ce^{px}$; polynomial of degree $n \Rightarrow$ polynomial of degree n; $\sin\omega x$ or $\cos\omega x \Rightarrow C\cos\omega x + D\sin\omega x$. If the trial duplicates the CF, multiply by x (or x^2).
- **Reducible equations**: $y'' = f(x, y')$: set $p = y'$, $y'' = p'$; $y'' = f(y, y')$: set $p = y'$, $y'' = p\dfrac{dp}{dy}$.

Methods.

1. Identify the type first (separable, linear, homogeneous, Bernoulli, Riccati, second order, reducible) before computing.
2. For linear equations, put the equation in standard form $y' + P(x)y = Q(x)$ before reading off P.
3. For second order equations: solve the auxiliary equation → write y_c → choose and substitute a trial y_p → add → apply conditions last.
4. After any substitution ($y = vx$, $z = y^{1-n}$, $y = y_1 + 1/u$, $p = y'$), return to the original variable.
5. Check by differentiating the answer and substituting back into the DE.

Common mistakes.

- Forgetting the constant of integration, or adding it before dividing by the integrating factor.
- Sign error in $P(x)$ when the equation is not in standard form (e.g. $y' - 2y = \ldots$ has $P = -2$).
- Losing solutions when separating variables (division by $g(y) = 0$ may discard constant solutions).
- Using a trial PI that is already part of the CF without multiplying by x.
- Applying initial conditions to y_c alone instead of to the full general solution $y_c + y_p$.
- Mixing up the two reduction-of-order substitutions: $p\dfrac{dp}{dy}$ is used only when x is absent.
- In modelling, forgetting that "rate proportional to amount" gives $\dfrac{dy}{dt} = ky$ with solution $y = y_0 e^{kt}$ ($k < 0$ for decay/cooling).

GCE tips.

- Show the auxiliary equation explicitly; examiners award method marks for it and for the integrating factor.
- Write the general solution with constants A, B clearly, then a separate line applying each condition.
- For modelling questions (population, Newton's cooling, radioactive decay, L–R circuits), define variables with units and state the DE before solving.
- If time is short, at least state the type of equation and the substitution: this earns credit.
- Keep answers exact (surds, ln, e) unless a decimal is requested; give decimals to the accuracy demanded.

Signed • OnBuch+
ONBUCH+ TEACHING TEAM
FOLLOWS THE OFFICIAL MINESEC SYLLABUS

OnBuch+