

FURTHER MATHEMATICS • UPPER SIXTH

UPPER SIXTH — FURTHER MATHEMATICS

CHAPTER 8

MODELLING WITH DIFFERENTIAL EQUATIONS

SUGGESTED TIME: 3 PERIODS

IN THIS CHAPTER

This chapter shows how physical laws — cooling, motion under resistance, growth and decay — are translated into differential equations, solved using the techniques of earlier chapters, and interpreted in context. It is the chapter where Further Mathematics meets the real world, and a guaranteed source of GCE Paper 2 modelling questions.

- By the end of this chapter I can translate a worded physical situation into a differential equation with its initial conditions.
- By the end of this chapter I can form a differential equation from a given family of curves by eliminating arbitrary constants.
- By the end of this chapter I can state Newton's law of cooling and set up the equation $dQ/dt = k(Q - Q_0)$.
- By the end of this chapter I can solve cooling problems by separating variables and determine the constants from given data.
- By the end of this chapter I can interpret the sign of k and the long-term behaviour of solutions in a cooling model.
- By the end of this chapter I can apply Newton's second law to a particle moving in a straight line with resistance depending on speed.



DOWNLOAD ON- BUCH

Free • Google Play
AI tutor, past papers,
results



GO ONBUCH+

All signed courses, unlimited AI
tutor, PDF sheets — OnBuch+
tab in the app

THIS SIGNED COURSE CONTAINS

COURSE

complete, illustrated,
step by step

METHODS

and worked examples

EXERCISES

exam style + solutions

SUMMARY SHEET

the essentials to
remember



Signed • OnBuch+

ONBUCH+ TEACHING TEAM
FOLLOWS THE OFFICIAL MINESEC SYLLABUS

OnBuch+

CONTENTS

- | | |
|---|---|
| 1. Section 1: Forming Differential Equations from Situations and Families of Curves | ity as a Function of Displacement and Mixed Exam Problems |
| 2. Section 2: Newton's Law of Cooling — Setting Up and Solving | 5. Integration activity |
| 3. Section 3: Resisted Motion I — Velocity as a Function of Time | 6. Methods and worked examples |
| 4. Section 4: Resisted Motion II — Veloc- | 7. Exercises |
| | 8. Solutions to the exercises |
| | 9. Summary sheet |

CHAPTER OBJECTIVES

- By the end of this chapter I can translate a worded physical situation into a differential equation with its initial conditions.
- By the end of this chapter I can form a differential equation from a given family of curves by eliminating arbitrary constants.
- By the end of this chapter I can state Newton's law of cooling and set up the equation $dQ/dt = k(Q - Q_0)$.
- By the end of this chapter I can solve cooling problems by separating variables and determine the constants from given data.
- By the end of this chapter I can interpret the sign of k and the long-term behaviour of solutions in a cooling model.
- By the end of this chapter I can apply Newton's second law to a particle moving in a straight line with resistance depending on speed.
- By the end of this chapter I can use dv/dt or $v dv/dx$ appropriately to obtain velocity-time or velocity-displacement relations.
- By the end of this chapter I can find terminal (limiting) velocity and interpret it physically.
- By the end of this chapter I can criticise a model, state its assumptions, and extract exam-ready conclusions from a solution.

PREREQUISITES

- Solving first-order differential equations by separation of variables (Lower Sixth / FMA earlier chapter).
- Solving linear first-order equations with an integrating factor.
- Exponential and logarithm laws, especially $\ln$ and e in solving equations.
- Kinematics: acceleration as dv/dt and as $v dv/dx$; Newton's second law $F = ma$ (Mechanics, Lower Sixth).
- Sketching and interpreting exponential growth and decay curves.

1 SECTION 1: FORMING DIFFERENTIAL EQUATIONS FROM SITUATIONS AND FAMILIES OF CURVES

In Douala, a pot of ndolé taken off the fire at 95 °C is left in a kitchen at 30 °C: after 10 minutes it is at 60 °C — can we predict when it will be safe to serve at 40 °C? Meanwhile, a benskin rider in Bamenda who cuts his engine feels the bike slow down faster when it is fast than when it is slow, because air resistance grows with speed. Both situations share a common mathematical engine: a quantity whose **rate of change** depends on the quantity itself. In this chapter we learn to translate such real situations into differential equations, solve them, and use them to make predictions — exactly the skill the GCE Advanced Level examiner rewards.

The central problem of this section is therefore: **given a worded law or a family of curves, how do we write down the differential equation that governs it?** Once the equation is written, the techniques of previous chapters (separation of variables, integrating factor) take over.

1.1 What is a Differential Equation? Quick Recap

DEFINITION Differential equation, order and degree

A **differential equation** (DE) is an equation involving an unknown function and one or more of its derivatives. If the unknown function depends on a single variable, it is an ordinary differential equation.

The **order** of a DE is the order of the highest derivative present. The **degree** is the power to which that highest derivative is raised, after the equation has been freed of fractions and radicals in the derivatives.

EXAMPLE Identifying order and degree

- $\frac{dy}{dx} = 2y$: order 1, degree 1.
- $\frac{d^2y}{dx^2} + y = 0$: order 2, degree 1.
- $\left(\frac{d^2y}{dx^2}\right)^3 + \frac{dy}{dx} = x$: order 2, degree 3.
- $y = x \frac{dy}{dx} + \left(\frac{dy}{dx}\right)^2$: order 1, degree 2 (the highest derivative is $\frac{dy}{dx}$, raised to the power 2).

A **general solution** of a DE of order n contains n independent arbitrary constants; a **particular solution** is obtained by giving those constants definite values, usually fixed by **initial conditions** (values of y and its derivatives at one point) or **boundary conditions** (values at two different points).

1.2 Modelling Vocabulary: From Words to Symbols

Most GCE modelling questions begin with an English sentence. The translation rules are:

English phrase	Mathematical translation
rate of change of y (with respect to time)	$\frac{dy}{dt}$
y is proportional to x	$y = kx$ for some constant k
y is inversely proportional to x	$y = \frac{k}{x}$
rate of change of P is proportional to P	$\frac{dP}{dt} = kP$
Q decreases at a rate proportional to Q	$\frac{dQ}{dt} = -kQ$, with $k > 0$
rate of change of y is proportional to $(a - y)$	$\frac{dy}{dt} = k(a - y)$

METHOD Translating “rate of change of P is proportional to P ”

1. Name the variables: P the quantity, t the time; state their units.
2. Write “rate of change” as $\frac{dP}{dt}$ and “proportional to P ” as kP .
3. Decide the sign: if P is growing, $\frac{dP}{dt} = kP$ with $k > 0$; if P is decaying, write $\frac{dP}{dt} = -kP$ with $k > 0$ so the negative sign is visible.
4. State what k represents and its units (here k is a rate constant, in time^{-1}).

WARNING The sign trap

“ Q is decreasing at a rate proportional to Q ” does not give $\frac{dQ}{dt} = kQ$. Since $Q > 0$ and Q decreases, $\frac{dQ}{dt}$ must be negative: the correct equation is $\frac{dQ}{dt} = -kQ$ with $k > 0$. Writing the wrong sign makes your model predict explosive growth instead of decay — an error examiners penalise heavily. A useful reflex: after writing your equation, ask yourself “does my equation make the quantity behave the way the problem describes?”

1.3 Forming a DE from a Family of Curves

A formula like $y = Ae^{2x}$ describes not one curve but a whole **family of curves**, one for each value of the arbitrary constant A . All these curves share a common geometric property, which can be expressed without mentioning A : this property is a differential equation. The principle is simple:

METHOD Eliminating n arbitrary constants

1. Count the number n of independent arbitrary constants.
2. Differentiate n times, obtaining $n + 1$ equations (the original plus n derived ones).
3. Eliminate the constants between these equations (by substitution, subtraction, or division).
4. The result is a DE of order n , free of arbitrary constants, whose general solution is the original family.

WORKED EXAMPLE 1 Family $y = Ae^{2x}$

Form the differential equation satisfied by every curve of the family $y = Ae^{2x}$, where A is an arbitrary constant.

SOLUTION


There is one constant, so we differentiate once:

$$\frac{dy}{dx} = 2Ae^{2x}.$$

But $Ae^{2x} = y$, so substituting back:

$$\boxed{\frac{dy}{dx} = 2y}.$$

Every member of the family satisfies this first-order DE, and conversely its general solution is $y = Ae^{2x}$.



Curves of the family $y = Ae^{2x}$ for several values of A . At every point, the gradient equals twice the ordinate: all these curves satisfy the same equation $\frac{dy}{dx} = 2y$.

WORKED EXAMPLE 2 Family $y = A \sin x + B \cos x$

Form the differential equation of the family $y = A \sin x + B \cos x$, where A and B are arbitrary constants.

SOLUTION

There are two constants, so differentiate twice:

$$\begin{aligned} y &= A \sin x + B \cos x, \\ \frac{dy}{dx} &= A \cos x - B \sin x, \\ \frac{d^2y}{dx^2} &= -A \sin x - B \cos x = -(A \sin x + B \cos x) = -y. \end{aligned}$$

Hence the required equation is

$$\frac{d^2y}{dx^2} + y = 0,$$

a second-order DE — as expected, since two constants were eliminated.

WORKED EXAMPLE 3 Family $y = Ae^x + Be^{2x}$

Form the differential equation of the family $y = Ae^x + Be^{2x}$, where A and B are arbitrary constants.

SOLUTION

Two constants, so differentiate twice:

$$\begin{aligned}y &= Ae^x + Be^{2x}, \\ \frac{dy}{dx} &= Ae^x + 2Be^{2x}, \\ \frac{d^2y}{dx^2} &= Ae^x + 4Be^{2x}.\end{aligned}$$

Neither A nor B disappears by simple substitution this time, so we eliminate them systematically. Subtracting the first equation from the second:

$$\frac{dy}{dx} - y = Be^{2x}.$$

Subtracting the second equation from the third:

$$\frac{d^2y}{dx^2} - \frac{dy}{dx} = 2Be^{2x}.$$

Comparing these two results, $\frac{d^2y}{dx^2} - \frac{dy}{dx} = 2\left(\frac{dy}{dx} - y\right)$, which tidies to

$$\frac{d^2y}{dx^2} - 3\frac{dy}{dx} + 2y = 0.$$

Check: the general solution of this equation is precisely $y = Ae^x + Be^{2x}$, since 1 and 2 are the roots of the auxiliary equation $m^2 - 3m + 2 = 0$.

WORKED EXAMPLE 4 Family $y = Cx + C^2$

Form the differential equation of the family of straight lines $y = Cx + C^2$.

SOLUTION

One constant, so differentiate once:

$$\frac{dy}{dx} = C.$$

Substitute $C = \frac{dy}{dx}$ into the original relation:

$$y = x\frac{dy}{dx} + \left(\frac{dy}{dx}\right)^2.$$

This is a first-order DE of degree 2: the order counts the highest derivative, the degree its power. Note that the general solution of this equation is indeed the family of lines we started from.

WARNING Differentiate exactly n times

A very common mistake is to differentiate fewer times than there are constants, leaving a constant in the final answer, or to differentiate too many times, producing an equation of unnecessarily high order whose general solution contains more constants than the original family. The rule is rigid: n constants $\Rightarrow n$ differentiations $\Rightarrow$ DE of order n . Always finish by checking that no arbitrary constant survives in your final equation.

1.4 Forming DEs from Stated Physical Laws

The same translation skill applies to laws of nature stated in words.

Population growth. “A bacterial population grows at a rate proportional to its size.” With $P(t)$ the population at time t :

$$\frac{dP}{dt} = kP \quad (k > 0), \quad \text{giving } P = P_0 e^{kt},$$

where P_0 is the population at time $t = 0$.

Radioactive decay. “A radioactive substance decays at a rate proportional to the mass present.” With $m(t)$ the mass at time t :


$$\frac{dm}{dt} = -k m \quad (k > 0), \quad \text{giving } m = m_0 e^{-kt},$$

where m_0 is the initial mass.

Mixture problems (brief). A tank contains V litres of brine; a solution of concentration c_{in} flows in at rate r and the well-stirred mixture flows out at the same rate. If $Q(t)$ is the mass of salt in the tank, then

$$\frac{dQ}{dt} = \underbrace{r c_{\text{in}}}_{\text{salt in}} - \underbrace{\frac{rQ}{V}}_{\text{salt out}},$$

a first-order linear equation. The key idea is always: rate of change = rate in – rate out.



The modelling pipeline: from a worded law to a differential equation, then to the general solution, and finally to a particular solution using an initial condition.

1.5 Initial and Boundary Conditions: Pinning Down the Answer

The general solution $P = P_0 e^{kt}$ describes every exponentially growing population. To answer a concrete question — this pot of ndolé, this sample of radioactive material — we must fix the constants. That is the role of initial conditions.

EXAMPLE Why one condition per constant

The equation $\frac{dP}{dt} = kP$ has general solution $P = Ae^{kt}$, with two unknowns: the integration constant A and the rate constant k . We therefore need two pieces of data, e.g. $P(0) = 500$ and $P(2) = 800$. Then $A = 500$ and $e^{2k} = \frac{8}{5}$, so $k = \frac{1}{2} \ln \frac{8}{5}$, and the model is fully determined.

This is exactly the structure of the ndolé problem in the introduction: the kitchen temperature (30°C), the initial temperature (95°C) and the reading after 10 minutes (60°C) are the data that will fix all the constants of Newton's law of cooling in Section 2 — and then predict the serving time.

1.6 Exam Technique

KEY POINTS What the examiner expects

1. Write the DE first, in symbols, before any solving; define every variable (t in minutes, Q in $^\circ\text{C}$, ...).
2. State the meaning and units of each constant: k is a proportionality (rate) constant, in min^{-1} ; Q_0 is the ambient temperature, in $^\circ\text{C}$.
3. Get the sign right: growth $\Rightarrow +k$; decay or decrease $\Rightarrow -k$ with $k > 0$.
4. When forming a DE from a family of curves, count the constants and differentiate exactly that many times; check that no constant survives in your final equation.
5. Use initial conditions to find the constants, and conclude with a sentence in the language of the problem ("the pot will reach 40°C after ...minutes").

DID YOU KNOW? Why this skill matters beyond the exam

Differential equations are the native language of science and engineering: epidemiologists model the spread of diseases, engineers design cooling systems and predict the motion of vehicles on steep roads such as the Bamenda escarpment, and economists model growth — all with equations of the form "rate of change = function of the quantity". Mastering the formation of the equation is the first and most creative step; the solving is then routine.

EXERCISE 1 Forming differential equations

- Form the differential equation of each family of curves:
 - $y = Ae^{-3x}$;
 - $y = Ax^2 + B$;
 - $y = A \cos 2x + B \sin 2x$.
- A sum of money in a savings account grows at a rate proportional to the amount present. Write down the differential equation, stating the meaning and units of each symbol.
- The mass m grams of a drug in a patient's bloodstream decreases at a rate proportional to the mass present. Initially $m = 12$ and after 4 hours $m = 6$. Write the DE, solve it, and find the mass remaining after 12 hours.

SOLUTION Exercise 1

1(a) Differentiate once: $\frac{dy}{dx} = -3Ae^{-3x} = -3y$, so $\frac{dy}{dx} + 3y = 0$.

1(b) Two constants, differentiate twice: $\frac{dy}{dx} = 2Ax$, $\frac{d^2y}{dx^2} = 2A$. From the first, $A = \frac{1}{2x} \frac{dy}{dx}$; substituting into the second: $\frac{d^2y}{dx^2} = \frac{1}{x} \frac{dy}{dx}$, i.e. $x \frac{d^2y}{dx^2} - \frac{dy}{dx} = 0$.

1(c) Differentiate twice: $\frac{d^2y}{dx^2} = -4A \cos 2x - 4B \sin 2x = -4y$, so $\frac{d^2y}{dx^2} + 4y = 0$.

2 Let M (FCFA) be the amount at time t (years). $\frac{dM}{dt} = kM$, where $k > 0$ is the growth rate constant, in year⁻¹.

3 $\frac{dm}{dt} = -km$ ($k > 0$, in h⁻¹), giving $m = Ae^{-kt}$. From $m(0) = 12$: $A = 12$. From $m(4) = 6$: $e^{-4k} = \frac{1}{2}$, so $k = \frac{1}{4} \ln 2$. Then $m(12) = 12e^{-12k} = 12\left(\frac{1}{2}\right)^3 = 1.5$ grams.

2 SECTION 2: NEWTON'S LAW OF COOLING — SETTING UP AND SOLVING

In Section 1 we learned how to translate a verbal description or a geometric property into a differential equation. We now apply that skill to one of the most famous and useful models in physics: **Newton's law of cooling**. This law describes how the temperature of a body changes when it is placed in an environment at a different temperature. It appears frequently in GCE Advanced Level papers, often in the context of a cooling cup of tea, a forensic estimation of time of death, or a metal bar heating in a furnace. The mathematics is exactly the separable first-order equation we have already mastered; the challenge lies in setting up the correct sign convention and interpreting the constants in a physical context.

2.1 The Physical Law and Its Mathematical Formulation

EXPERIMENT Observing a Cooling Body

Imagine you have just prepared a pot of hot soup at 95°C in a kitchen where the air temperature is a steady 28°C . You notice that the soup cools very quickly at first, but as its temperature approaches that of the kitchen, the cooling slows down dramatically. If you measured the temperature every minute and plotted the graph, you would see a curve that starts steep and gradually flattens out, approaching the room temperature asymptotically.

This observation is the heart of Newton's law: the rate of heat loss is proportional to the excess temperature over the surroundings.

DEFINITION Newton's Law of Cooling

Let $Q(t)$ (or $\theta(t)$) be the temperature of a body at time t , and let Q_0 (or θ_0) be the constant temperature of the surrounding medium. Newton's law of cooling states that

$$\frac{dQ}{dt} = k(Q - Q_0),$$

where k is a negative constant ($k < 0$) that depends on the nature of the body, its surface area, and the heat transfer mechanism (conduction, convection, radiation).

WARNING Sign Convention — The Number One Trap

Many candidates write $\frac{dQ}{dt} = k(Q - Q_0)$ and then treat k as a positive number. This is wrong for cooling. Since $Q > Q_0$ during cooling, the excess temperature $(Q - Q_0)$ is positive. The temperature Q is decreasing, so $\frac{dQ}{dt}$ is negative. Therefore k must be negative.

An equivalent formulation that avoids this sign confusion is

$$\frac{dQ}{dt} = -k(Q - Q_0) \quad (k > 0).$$

Both forms are acceptable provided you state the sign of your constant clearly. In this course we will use the first form ($k < 0$) because it follows directly from the proportionality statement, but we will always write $k = -\alpha$ with $\alpha > 0$ when solving.

KEY POINTS Meaning of the Symbols

- $Q(t)$ or $\theta(t)$: temperature of the body at time t (variable).

- Q_0 or θ_0 : ambient (surrounding) temperature (constant).
- t : time (usually in minutes or seconds).
- k : constant of proportionality; $k < 0$ for cooling.
- $Q - Q_0$: excess temperature (temperature difference driving the heat flow).

2.2 Solving the Differential Equation

The equation $\frac{dQ}{dt} = k(Q - Q_0)$ is separable. We solve it in three systematic steps.

METHOD Three Steps to the Solution of Newton's Law

Step 1 — Separate the variables.

$$\frac{dQ}{Q - Q_0} = k dt$$

Step 2 — Integrate both sides.

$$\int \frac{dQ}{Q - Q_0} = \int k dt \implies \ln |Q - Q_0| = kt + C$$

Step 3 — Exponentiate and simplify.

$$|Q - Q_0| = e^{kt+C} = e^C e^{kt}$$

Since $Q - Q_0$ keeps a constant sign (positive for cooling, negative for heating), we can drop the absolute value and write

$$Q - Q_0 = Ae^{kt},$$

where $A = \pm e^C$ is a non-zero constant determined by the initial condition. If the body starts at temperature Q_1 at $t = 0$, then $A = Q_1 - Q_0$.

PROPERTY General Solution of Newton's Law of Cooling

$$Q(t) = Q_0 + (Q_1 - Q_0)e^{kt} \quad (k < 0)$$

where $Q_1 = Q(0)$ is the initial temperature of the body.

EXAMPLE Finding the Constants A and k

A metal sphere is heated to 200°C and placed in a room at 25°C . After 10 minutes its temperature has fallen to 120°C . Find the temperature after 20 minutes.

Solution. Here $Q_0 = 25$, $Q_1 = 200$. The model is $Q = 25 + 175e^{kt}$. Use the second data point: $Q(10) = 120$.

$$120 = 25 + 175e^{10k} \Rightarrow 95 = 175e^{10k} \Rightarrow e^{10k} = \frac{95}{175} = \frac{19}{35}.$$

Take natural logarithms (remember $k < 0$):


$$10k = \ln\left(\frac{19}{35}\right) \Rightarrow k = \frac{1}{10} \ln\left(\frac{19}{35}\right) \approx -0.0611 \text{ min}^{-1}.$$

Now find $Q(20)$:


$$Q(20) = 25 + 175e^{20k} = 25 + 175(e^{10k})^2 = 25 + 175\left(\frac{19}{35}\right)^2 = 25 + 175 \times \frac{361}{1225} = 25 + \frac{361}{7} \approx 76.6^{\circ}\text{C}.$$

2.3 Interpreting the Solution — The Cooling Curve

The solution $Q(t) = Q_0 + (Q_1 - Q_0)e^{kt}$ (with $k < 0$) is an exponential decay of the excess temperature $Q - Q_0$ towards zero. The graph has a horizontal asymptote $Q = Q_0$.



Cooling curve $Q(t) = Q_0 + (Q_1 - Q_0)e^{kt}$ with asymptote $Q = Q_0$ and initial tangent. The tangent at $t = 0$ would reach Q_0 at $t = -1/k$ (the time constant).



Newton's law: heat flows from the hotter body to the cooler surroundings at a rate proportional to the temperature difference $Q - Q_0$.

PROPERTY Long-Term Behaviour and Time Constant

- As $t \rightarrow \infty$, $e^{kt} \rightarrow 0$ (since $k < 0$), so $Q(t) \rightarrow Q_0$. The body eventually reaches the ambient temperature.
- The time constant $\tau = -1/k$ is the time it would take for the excess temperature to fall to $1/e \approx 36.8\%$ of its initial value if the initial rate of cooling were maintained. It is the t -intercept of the tangent at $t = 0$.
- The half-life of the excess temperature is $t_{1/2} = \frac{\ln 2}{-k} = \tau \ln 2$.

2.4 Worked Example: A Cameroonian Context — Cooling of a Pot of Eru Soup

WORKED EXAMPLE 5 Cooling of a Pot of Eru Soup

A pot of eru soup is removed from the fire at 98°C in a kitchen where the air temperature is a constant 28°C . After 5 minutes the soup has cooled to 70°C .

- Write down the differential equation satisfied by the temperature $Q(t)$ of the soup, defining all symbols.
- Solve the differential equation to show that $Q = 28 + 70e^{kt}$.
- Find the value of k correct to three significant figures.
- How long, to the nearest minute, will it take for the soup to cool to 40°C ?
- Sketch the graph of Q against t , indicating the asymptote and the initial temperature.

SOLUTION

Detailed Solution.

(i) Let $Q(t)$ be the temperature of the soup ($^{\circ}\text{C}$) at time t minutes. The ambient temperature is $Q_0 = 28^{\circ}\text{C}$. By Newton's law of cooling, the rate of change of temperature is proportional to the excess temperature:

$$\frac{dQ}{dt} = k(Q - 28), \quad k < 0.$$

(ii) Separate variables:

$$\int \frac{dQ}{Q - 28} = \int k dt \implies \ln |Q - 28| = kt + C.$$

Exponentiate: $|Q - 28| = e^C e^{kt}$. Since $Q > 28$ during cooling, $Q - 28 = Ae^{kt}$ with $A > 0$. At $t = 0$, $Q = 98$, so $A = 98 - 28 = 70$. Hence

$$Q = 28 + 70e^{kt}.$$

(iii) Use $Q(5) = 70$:

$$70 = 28 + 70e^{5k} \implies 42 = 70e^{5k} \implies e^{5k} = \frac{42}{70} = 0.6.$$

$$5k = \ln 0.6 \implies k = \frac{\ln 0.6}{5} \approx -0.102165 \approx -0.102 \text{ min}^{-1} \text{ (3 s.f.)}.$$

(iv) Find t when $Q = 40$:

$$40 = 28 + 70e^{kt} \implies 12 = 70e^{kt} \implies e^{kt} = \frac{12}{70} = \frac{6}{35}.$$

$$kt = \ln\left(\frac{6}{35}\right) \implies t = \frac{\ln(6/35)}{k} = \frac{\ln(6/35)}{\ln(0.6)/5} = 5 \frac{\ln(35/6)}{\ln(1/0.6)}.$$

Using $k \approx -0.102165$:

$$t \approx \frac{\ln(6/35)}{-0.102165} \approx \frac{-1.763}{-0.102165} \approx 17.26 \text{ minutes.}$$

To the nearest minute: 17 minutes.

(v) Sketch:

- Axes: $t \geq 0$, $Q \geq 28$.
- Horizontal asymptote $Q = 28$ (dashed line).
- Point $(0, 98)$ marked.
- Curve decreasing, concave up, approaching $Q = 28$.
- Tangent at $t = 0$ with slope $k(98 - 28) = -0.102 \times 70 \approx -7.14$, crossing $Q = 28$ at $t \approx 9.8$ min (the time constant $\tau = -1/k \approx 9.8$ min).

2.5 Heating Problems: The Same Law

Newton's law applies equally when a cold object is placed in a warmer environment (e.g., a bottle of Malta taken out of a fridge into a hot Douala afternoon). The differential equation is identical:

$$\frac{dQ}{dt} = k(Q - Q_0), \quad k < 0.$$

Now $Q_1 < Q_0$, so $Q - Q_0$ is negative. Since k is also negative, the product $k(Q - Q_0)$ is positive, meaning $\frac{dQ}{dt} > 0$: the object warms up. The solution $Q = Q_0 + (Q_1 - Q_0)e^{kt}$ still holds; the excess temperature $Q - Q_0$ is negative and its magnitude decays exponentially to zero.

KEY POINTS Heating and Cooling Unified

The single formula

$$Q(t) = Q_0 + (Q_1 - Q_0)e^{kt} \quad (k < 0)$$

covers both cooling ($Q_1 > Q_0$) and heating ($Q_1 < Q_0$). The excess temperature $Q - Q_0$ always decays exponentially towards zero.

EXAMPLE Warming a Cold Drink

A can of Top drink at 4°C is placed in a room at 30°C . After 3 minutes the drink reaches 10°C . Find its temperature after 10 minutes.

Solution. $Q_0 = 30$, $Q_1 = 4$. Model: $Q = 30 + (4 - 30)e^{kt} = 30 - 26e^{kt}$. At $t = 3$, $Q = 10$:

$$10 = 30 - 26e^{3k} \implies -20 = -26e^{3k} \implies e^{3k} = \frac{10}{13}.$$

$$3k = \ln(10/13) \implies k = \frac{1}{3} \ln(10/13) \approx -0.0870.$$

At $t = 10$:

$$Q(10) = 30 - 26e^{10k} = 30 - 26(e^{3k})^{10/3} = 30 - 26\left(\frac{10}{13}\right)^{10/3} \approx 30 - 26 \times 0.438 \approx 18.6^\circ\text{C}.$$

2.6 Examination Technique and Common Pitfalls

WARNING Common Mistakes in Newton's Law Questions

1. Sign of k : Writing $k > 0$ in $\frac{dQ}{dt} = k(Q - Q_0)$ for cooling. Always state " $k < 0$ " or use $\frac{dQ}{dt} = -k(Q - Q_0)$ with $k > 0$.
2. Confusing Q and Q_0 : Q_0 is the constant surrounding temperature; Q is the variable body temperature. Never solve for Q_0 as if it were unknown unless the problem ex-

plicitly says the ambient temperature is unknown (rare).

3. Logarithm errors: From $e^{kt} = c$, writing $kt = \ln c$ is correct only if $c > 0$. Since $e^{kt} > 0$ always, the ratio $\frac{Q-Q_0}{Q_1-Q_0}$ must be positive — which it is, because numerator and denominator have the same sign.
4. Units: Time t must be consistent (minutes or seconds). If k is found in min^{-1} , do not plug in t in seconds.
5. Rounding too early: Keep k in exact form ($\frac{1}{t} \ln(\dots)$) until the final calculation to avoid rounding errors.
6. Interpretation: Always add a concluding sentence: “The soup takes approximately 17 minutes to cool to 40°C .”

KEY POINTS Exam Checklist for Newton's Law Questions

- ☐ State the law: $\frac{dQ}{dt} = k(Q - Q_0)$, define Q , Q_0 , t , and state $k < 0$.
- ☐ Separate variables and integrate correctly.
- ☐ Use $Q(0) = Q_1$ to find the constant $A = Q_1 - Q_0$.
- ☐ Use the second data point to find k (exact form preferred).
- ☐ Answer the specific question (time to reach a temperature, or temperature at a given time).
- ☐ Give final answer to required accuracy (usually 3 s.f. or nearest minute/degree).
- ☐ Interpret the result in the context of the problem.

2.7 Practice Exercise

EXERCISE 2 Cooling of a Metal Bar

A metal bar is heated to 350°C and then placed in a large tank of oil maintained at a constant temperature of 50°C . The temperature of the bar falls to 200°C in 2 minutes.

1. Write down the differential equation for the temperature $\theta(t)$ of the bar.
2. Show that $\theta = 50 + 300e^{kt}$.
3. Find the exact value of k in the form $\frac{1}{a} \ln b$.
4. Calculate the time taken for the bar to cool to 100°C , giving your answer in minutes and

seconds.

5. Sketch the graph of θ against t , showing the asymptote and the initial temperature.

SOLUTION Exercise 1

(i) $\frac{d\theta}{dt} = k(\theta - 50)$, $k < 0$. θ is bar temperature ($^{\circ}\text{C}$), t in minutes, 50°C is oil temperature.

(ii) Separate: $\int \frac{d\theta}{\theta - 50} = \int k dt \Rightarrow \ln(\theta - 50) = kt + C$. $\theta - 50 = Ae^{kt}$. At $t = 0$, $\theta = 350 \Rightarrow A = 300$. Hence $\theta = 50 + 300e^{kt}$.

(iii) $\theta(2) = 200$: $200 = 50 + 300e^{2k} \Rightarrow 150 = 300e^{2k} \Rightarrow e^{2k} = \frac{1}{2}$. $2k = \ln(1/2) = -\ln 2 \Rightarrow k = -\frac{1}{2} \ln 2$.

(iv) Find t when $\theta = 100$: $100 = 50 + 300e^{kt} \Rightarrow 50 = 300e^{kt} \Rightarrow e^{kt} = \frac{1}{6}$. $kt = \ln(1/6) = -\ln 6$. $t = \frac{-\ln 6}{-\frac{1}{2} \ln 2} = \frac{2 \ln 6}{\ln 2} = 2 \log_2 6 \approx 2 \times 2.585 = 5.17$ minutes. $0.17 \times 60 \approx 10$ seconds. Answer: 5 minutes 10 seconds.

(v) Graph: axes $t \geq 0$, $\theta \geq 50$. Asymptote $\theta = 50$. Point $(0, 350)$. Curve decreasing, concave up. Tangent at $t = 0$ has slope $k(300) = -150 \ln 2 \approx -104$, crossing $\theta = 50$ at $t = -1/k = 2/\ln 2 \approx 2.89$ min.

DID YOU KNOW? Forensic Application — Time of Death

Newton's law of cooling is the basis of the algor mortis method used by forensic pathologists to estimate the time of death. A corpse cools approximately according to Newton's law (with modifications for clothing, body mass, air movement). By measuring the rectal temperature at two known times and knowing the ambient temperature, the pathologist can solve for k and then extrapolate back to the normal body temperature (37°C) to estimate the time of death. This is a classic GCE Further Mathematics problem — often disguised as “a body is discovered at 6 am...”.

3 SECTION 3: RESISTED MOTION I — VELOCITY AS A FUNCTION OF TIME

In Section 2 we modelled the cooling of a cup of ndolé left on the table: the temperature difference obeys a first-order differential equation, and the solution approaches the ambient temperature exponentially. Exactly the same mathematical structure appears when a benskinner cuts the engine and coasts along the road from Buea to Mutengene, or when a parachutist jumps from an aircraft: a driving force pushes the body forward, air resistance pushes back, and the velocity tends exponentially towards a limiting value. In this section we build and solve the equation of motion when we want the **velocity as a function of time**.

3.1 Setting Up: Newton's Second Law with Resistance

Consider a particle of mass m moving in a straight line. Suppose a constant driving force F acts in the direction of motion (engine thrust, or the weight for a falling body), while a resistance $R(v)$, which depends on the speed v , acts opposite to the motion.

PROPERTY Newton's Second Law with Resistance

For a particle of constant mass m moving in a straight line with velocity v , subject to a driving force F in the direction of motion and a resistance $R(v)$ opposing the motion, the equation of motion is

$$m \frac{dv}{dt} = F - R(v).$$

The resultant force equals mass times acceleration, and the resistance always enters with a negative sign because it opposes the velocity. This is a direct application of Newton's second law, $\sum \vec{F} = m\vec{a}$, projected on the axis of motion; no separate proof is required in the examination, but the equation must be derived from a force diagram each time.

WARNING The resistance opposes the motion

The resistance force always acts against the velocity. If the particle moves in the positive direction, $R(v)$ points in the negative direction; if the particle reverses, so does the resistance. When you change the positive direction of your axis, or when the body moves upward instead of downward, the sign of the resistance term must change accordingly. Never write R with a fixed sign "because it was negative in the previous question".

3.2 The Two Common Resistance Models

Two models dominate the GCE Advanced Level examinations:

- **Linear resistance:** $R = kv$, where $k > 0$ is a constant. Appropriate for slow motion through a fluid (viscous drag), small particles, or as a first approximation.
- **Quadratic resistance:** $R = kv^2$. Appropriate for fast-moving objects through air (a car, a parachutist), where drag grows rapidly with speed.

The examination question will always state the model, for example: "the resistance to motion is proportional to the speed" ($R = kv$) or "proportional to the square of the speed" ($R = kv^2$).

METHOD Exam tip: state the model first

Before writing any equation of motion, write one sentence stating the modelling assumption, e.g. "Assume the resistance is $R = kv$ N, where v is the speed in m s^{-1} ." Then draw a small force diagram and apply Newton's second law. Examiners award a mark for a clearly

stated model and a correctly signed equation.

3.3 Choosing the Form of the Acceleration

Acceleration can be written in two useful ways:

$$a = \frac{dv}{dt} \quad \text{or} \quad a = v \frac{dv}{dx}.$$

The second form comes from the chain rule: $a = \frac{dv}{dt} = \frac{dv}{dx} \cdot \frac{dx}{dt} = v \frac{dv}{dx}$.

METHOD Choosing between dv/dt and $v dv/dx$

1. If the question asks for velocity at a given time, time to reach a given speed, or gives information about time, use $a = \frac{dv}{dt}$: the equation separates in v and t .
2. If the question asks for velocity after travelling a given distance, or distance covered, use $a = v \frac{dv}{dx}$: the equation separates in v and x .

In this section we use only $\frac{dv}{dt}$; the displacement form is treated in Section 4.

3.4 Solving $m \frac{dv}{dt} = F - kv$

This is the linear-resistance equation with constant driving force. We solve it by **separation of variables**:

$$m \frac{dv}{dt} = F - kv \implies \frac{dv}{F - kv} = \frac{dt}{m}.$$

Integrating both sides:

$$-\frac{1}{k} \ln |F - kv| = \frac{t}{m} + C.$$

Suppose the particle starts with speed u at $t = 0$, so $v(0) = u$. Then $C = -\frac{1}{k} \ln |F - ku|$, and substituting back:

$$\ln \left| \frac{F - kv}{F - ku} \right| = -\frac{kt}{m}.$$

Exponentiating gives $F - kv = (F - ku)e^{-kt/m}$, and solving for v :

PROPERTY Velocity under constant force and linear resistance

The solution of $m \frac{dv}{dt} = F - kv$ with $v(0) = u$ is

$$v = \frac{F}{k} + \left(u - \frac{F}{k}\right) e^{-kt/m}.$$

The derivation above (separation, integration, initial condition) is examinable and you must be able to reproduce it in full.

The same result can be obtained with the integrating factor method, since the equation is linear: $\frac{dv}{dt} + \frac{k}{m}v = \frac{F}{m}$, with integrating factor $e^{kt/m}$.

3.5 Terminal (Limiting) Velocity

DEFINITION Terminal velocity

The **terminal velocity** (or limiting velocity) v_T is the speed at which the driving force exactly balances the resistance, so the acceleration is zero:

$$\frac{dv}{dt} = 0 \implies F - kv_T = 0 \implies v_T = \frac{F}{k}.$$


Look at the solution again: as $t \rightarrow \infty$, the exponential $e^{-kt/m} \rightarrow 0$, so

$$v \longrightarrow \frac{F}{k} = v_T,$$


whatever the initial speed u . If $u < v_T$ the particle accelerates towards v_T ; if $u > v_T$ it decelerates towards v_T ; if $u = v_T$ it moves uniformly. The line $v = v_T$ is a horizontal asymptote of every solution curve.

WARNING Terminal velocity is approached, not reached

In this model the particle never attains v_T in finite time: $v = v_T$ would require $e^{-kt/m} = 0$, which is impossible for finite t . Examination questions exploit this by asking for the time to reach, say, 90% or 99% of the terminal velocity, or the speed after a given time. Never answer “the particle reaches v_T after a long time” as if it were an exact event.



Velocity curves for $m \frac{dv}{dt} = F - kv$: every solution tends to the terminal velocity $v_T = F/k$, from below if $u < v_T$ and from above if $u > v_T$.



Force diagram for a particle falling vertically: weight mg acts downward, air resistance kv acts upward, opposite to the velocity v .

3.6 Worked Examples with Linear Resistance

WORKED EXAMPLE 6 The parachutist

A parachutist of mass 80 kg jumps from rest from a helicopter and falls vertically. The air resistance is $R = 20v$ N, where v is her speed in m s^{-1} . Take $g = 10 \text{ m s}^{-2}$.

1. Show that $4 \frac{dv}{dt} = 40 - v$.
2. Find the terminal velocity.
3. Find v in terms of t , and her speed after 8 s.
4. Find the time at which her speed is 30 m s^{-1} .

SOLUTION

Solution.

1. Taking the downward direction as positive, the forces are the weight $mg = 800$ N downward and the resistance $20v$ upward. Newton's second law gives

$$80 \frac{dv}{dt} = 800 - 20v \implies 4 \frac{dv}{dt} = 40 - v \quad (\text{dividing by } 20).$$

2. Terminal velocity: set $\frac{dv}{dt} = 0$, so $40 - v_T = 0$, giving $v_T = 40 \text{ m s}^{-1}$.
3. Separate variables:

$$\frac{dv}{40 - v} = \frac{dt}{4} \implies -\ln |40 - v| = \frac{t}{4} + C.$$

At $t = 0, v = 0$: $C = -\ln 40$. Hence

$$\ln \frac{40}{40 - v} = \frac{t}{4} \implies 40 - v = 40e^{-t/4} \implies v = 40(1 - e^{-t/4}).$$

At $t = 8$: $v = 40(1 - e^{-2}) \approx 40(1 - 0.1353) \approx 34.6 \text{ m s}^{-1}$.

4. Set $v = 30$: $30 = 40(1 - e^{-t/4})$, so $e^{-t/4} = \frac{1}{4}$, giving $t = 4 \ln 4 \approx 5.55$ s.

WORKED EXAMPLE 7 The benskin rider coasting

A motorcyclist and machine have total mass 200 kg. Travelling at 20 m s^{-1} on a horizontal road, the rider cuts the engine. The resistance is $R = 10v$ N.

- Write the equation of motion after the engine is cut.
- Find the speed after 10 s.

SOLUTION

Solution.

1. With the engine cut there is no driving force ($F = 0$); only resistance acts. Newton's second law:

$$200 \frac{dv}{dt} = -10v \implies \frac{dv}{dt} = -\frac{v}{20}.$$

2. Separating: $\frac{dv}{v} = -\frac{dt}{20}$, so $\ln v = -\frac{t}{20} + C$. With $v(0) = 20$: $C = \ln 20$, hence

$$v = 20e^{-t/20}.$$

At $t = 10$: $v = 20e^{-0.5} \approx 20 \times 0.6065 \approx 12.1 \text{ m s}^{-1}$.

Note that here the “terminal velocity” is 0: with no driving force, the rider slows down towards rest (in this idealised model, never quite stopping).

3.7 A Quadratic Resistance Example

When the resistance is kv^2 , separation of variables still works, but the integral involves $\frac{dv}{a^2 - v^2}$, which is handled by partial fractions (or a logarithmic standard form). The terminal velocity is now $v_T = \sqrt{F/k}$.

WORKED EXAMPLE 8 Falling with quadratic resistance

A body of mass 2 kg falls from rest. The air resistance is $\frac{v^2}{50}$ N. Take $g = 10 \text{ m s}^{-2}$.

1. Show that $\frac{dv}{dt} = \frac{1000 - v^2}{100}$.
2. Find the terminal velocity.

SOLUTION

Solution.

1. Downward positive. Newton's second law:

$$2 \frac{dv}{dt} = 20 - \frac{v^2}{50} = \frac{1000 - v^2}{50} \implies \frac{dv}{dt} = \frac{1000 - v^2}{100}.$$

2. Setting $\frac{dv}{dt} = 0$: $v_T^2 = 1000$, so $v_T = \sqrt{1000} = 10\sqrt{10} \approx 31.6 \text{ m s}^{-1}$.

(Solving for $v(t)$ requires $\int \frac{dv}{1000 - v^2}$, treated via partial fractions; the displacement form of this problem appears in Section 4.)

3.8 Vertical Motion: Sign Care with Weight

For vertical motion the weight plays the role of the driving force when the body moves downward, but it acts against the motion when the body moves upward. The resistance always opposes the velocity. Take care:

- **Falling body** (downward positive): $m \frac{dv}{dt} = mg - kv$. Terminal velocity $v_T = \frac{mg}{k}$.
- **Body projected upward** (upward positive): both weight and resistance act downward, so $m \frac{dv}{dt} = -mg - kv$. There is no terminal velocity on the way up; the body simply decelerates until $v = 0$.

WARNING Mixing units

Speeds are often given in km h^{-1} while the formula needs m s^{-1} . Convert before substituting:

$$v \text{ m s}^{-1} = \frac{v \text{ km h}^{-1}}{3.6}.$$

For example $72 \text{ km h}^{-1} = 20 \text{ m s}^{-1}$. Mixing the two is one of the most common causes of lost marks.

DID YOU KNOW? Why parachutes work

A skydiver in free fall with a closed parachute reaches a terminal velocity of about 50 m s^{-1} — fatal on landing. Opening the parachute multiplies the drag coefficient enormously (a much larger k), so the new terminal velocity $v_T = \sqrt{mg/k}$ drops to about 5 m s^{-1} , comparable to jumping off a low wall. The mathematics of this section is literally a matter of life and death.

EXERCISE 3

A stone of mass 0.5 kg is dropped from rest from the top of a building. The air resistance is $0.1v \text{ N}$. Take $g = 10 \text{ m s}^{-2}$.

1. Form the differential equation of motion.
2. Find the terminal velocity and v in terms of t .
3. Find the time at which the stone reaches 80% of its terminal velocity.

SOLUTION Exercise 1

1. Downward positive: $0.5 \frac{dv}{dt} = 5 - 0.1v$, i.e. $5 \frac{dv}{dt} = 50 - v$.
2. Setting $\frac{dv}{dt} = 0$: $v_T = 50 \text{ m s}^{-1}$. Separating with $v(0) = 0$ gives $v = 50(1 - e^{-t/5})$.
3. $0.8 \times 50 = 40$: $40 = 50(1 - e^{-t/5})$, so $e^{-t/5} = 0.2$, hence $t = 5 \ln 5 \approx 8.05 \text{ s}$.

EXERCISE 4

A car of mass 1000 kg has an engine producing a constant tractive force of 3000 N . The

resistance to motion is $60v$ N, where v is the speed in m s^{-1} . The car starts from rest.

1. Show that $50 \frac{dv}{dt} = 150 - 3v$.
2. Find the terminal velocity of the car.
3. Find v in terms of t and the time taken to reach 40 m s^{-1} .

SOLUTION Exercise 2

1. Newton's second law: $1000 \frac{dv}{dt} = 3000 - 60v$; dividing by 20: $50 \frac{dv}{dt} = 150 - 3v$.
2. Setting $\frac{dv}{dt} = 0$: $v_T = \frac{150}{3} = 50 \text{ m s}^{-1}$.
3. Separating: $\frac{dv}{150 - 3v} = \frac{dt}{50}$, so $-\frac{1}{3} \ln |150 - 3v| = \frac{t}{50} + C$. With $v(0) = 0$: $150 - 3v = 150e^{-3t/50}$, hence

$$v = 50(1 - e^{-3t/50}).$$

Setting $v = 40$: $e^{-3t/50} = 0.2$, so $t = \frac{50}{3} \ln 5 \approx 26.8 \text{ s}$.

KEY POINTS Key points of Section 3

- Newton's second law with resistance: $m \frac{dv}{dt} = F - R(v)$; resistance opposes motion.
- Linear model $R = kv$; quadratic model $R = kv^2$ — the question states which to use.
- Use $\frac{dv}{dt}$ when time is involved; $v \frac{dv}{dx}$ when displacement is involved (Section 4).
- Solution of $m\dot{v} = F - kv$: $v = \frac{F}{k} + \left(u - \frac{F}{k}\right)e^{-kt/m}$.
- Terminal velocity: $v_T = \frac{F}{k}$ (linear model) or $v_T = \sqrt{F/k}$ (quadratic model), found by setting $\frac{dv}{dt} = 0$; every solution tends to it but never reaches it in finite time.
- Convert km h^{-1} to m s^{-1} (divide by 3.6) before substituting.

4 SECTION 4: RESISTED MOTION II — VELOCITY AS A FUNCTION OF DISPLACEMENT AND MIXED EXAM PROBLEMS

In Section 3 we mastered the time-domain approach: we wrote Newton's second law as $m \frac{dv}{dt} = F - R(v)$, separated variables, and obtained $v(t)$. Integrating once more gave $x(t)$. That route is perfect when the question asks "How long does it take to reach..." or "Find the velocity after 5 seconds." But many GCE questions ask instead: "Find the distance travelled before the particle reaches speed V " or "Show that the particle comes to rest after travelling X metres." For those, the distance-domain approach using $a = v \frac{dv}{dx}$ is dramatically faster and avoids a double integration. This section builds that tool, shows when to use it, and finishes with a full exam-style synthesis.

4.1 From Time to Distance: The Chain Rule Trick

The key is a simple identity that gives acceleration three equivalent faces.

DEFINITION The Three Faces of Acceleration

For a particle moving in a straight line with displacement x , velocity v and time t ,

$$a = \frac{dv}{dt} = v \frac{dv}{dx} = \frac{d^2x}{dt^2}.$$

The middle form follows from the chain rule:

$$\frac{dv}{dt} = \frac{dv}{dx} \cdot \frac{dx}{dt} = v \frac{dv}{dx}.$$

KEY POINTS Why $v \frac{dv}{dx}$ is a Superpower

When the net force $F - R(v)$ depends only on velocity (not explicitly on t or x), writing Newton's law as

$$m v \frac{dv}{dx} = F - R(v)$$

allows immediate separation of variables:

$$\frac{m v}{F - R(v)} dv = dx.$$

Integrating once gives x as a function of v directly — no need to find $v(t)$ first.

4.2 Solving for $x(v)$: Separation and Integration

METHOD Distance–Domain Solution for Linear Resistance $R = kv$

Step 1. Write the equation of motion using $a = v \frac{dv}{dx}$:

$$mv \frac{dv}{dx} = F - kv.$$

Step 2. Separate variables:

$$\frac{mv}{F - kv} dv = dx.$$

Step 3. Integrate. The left-hand side requires a simple algebraic rewrite (see Warning below). Step 4. Apply limits carefully: when $x = 0$, $v = u$ (initial speed); when $x = x$, $v = v$. Step 5. Solve for x in terms of v or v in terms of x as required.

WARNING The Classic Algebraic Slip: Integrating $\frac{v}{a-bv}$

Never integrate $\int \frac{v}{a-bv} dv$ by guessing. Rewrite the integrand first using polynomial long division:

$$\frac{v}{a-bv} = -\frac{1}{b} + \frac{a/b}{a-bv}.$$

Proof: $-\frac{1}{b} + \frac{a/b}{a-bv} = \frac{-(a-bv)+a}{b(a-bv)} = \frac{bv}{b(a-bv)} = \frac{v}{a-bv}$. Then

$$\int \frac{v}{a-bv} dv = -\frac{v}{b} - \frac{a}{b^2} \ln |a-bv| + C.$$

Forgetting the linear term $-\frac{v}{b}$ is the #1 source of lost marks in this topic.

EXAMPLE Worked Example: Particle Projected Upwards with Resistance

A particle of mass m is projected vertically upwards with speed u in a medium where the resistance is kv ($k > 0$). Gravity acts downwards. Find the maximum height H reached.

Solution. Take upward as positive. Forces: weight $-mg$, resistance $-kv$ (always opposes motion).

$$mv \frac{dv}{dx} = -mg - kv = -(mg + kv).$$

Separate:

$$\frac{mv}{mg + kv} dv = -dx.$$

Rewrite the integrand (with $a = mg$, $b = k$):

$$\frac{v}{mg + kv} = \frac{1}{k} - \frac{mg/k}{mg + kv}.$$


Integrate from $x = 0, v = u$ to $x = H, v = 0$:

$$m \int_u^0 \left(\frac{1}{k} - \frac{mg/k}{mg + kv} \right) dv = - \int_0^H dx.$$

$$m \left[\frac{v}{k} - \frac{mg}{k^2} \ln(mg + kv) \right]_u^0 = -H.$$

$$m \left(0 - \frac{mg}{k^2} \ln(mg) - \frac{u}{k} + \frac{mg}{k^2} \ln(mg + ku) \right) = -H.$$

$$H = \frac{mu}{k} - \frac{m^2g}{k^2} \ln \left(1 + \frac{ku}{mg} \right).$$



Velocity against displacement for a particle falling from rest with linear resistance. The curve approaches terminal velocity $v_T = mg/k$ asymptotically.

4.3 Applications: Inclined Planes and Powered Vehicles

The same technique handles any situation where the net force is a function of v only.

PROPERTY Inclined Plane with Resistance

A particle of mass m slides down a plane inclined at α to the horizontal. Resistance $R = kv$. The component of weight down the plane is $mg \sin \alpha$. Equation of motion:

$$mv \frac{dv}{dx} = mg \sin \alpha - kv.$$

Terminal velocity down the plane: $v_T = \frac{mg \sin \alpha}{k}$. Distance to reach speed v from rest ($v < v_T$):

$$x = \frac{m}{k} \left[v_T \ln \left(\frac{v_T}{v_T - v} \right) - v \right].$$

PROPERTY Powered Vehicle with Constant Driving Force

A vehicle of mass m experiences a constant driving force F and resistance kv . Equation:

$$mv \frac{dv}{dx} = F - kv.$$

Terminal velocity: $v_T = F/k$. Distance to accelerate from u to v (with $u, v < v_T$):

$$x = \frac{m}{k} \left[(u - v) + v_T \ln \left(\frac{v_T - u}{v_T - v} \right) \right].$$

Exam flag: This model assumes the engine can deliver constant force at all speeds — unrealistic at high speed where power $P = Fv$ would become infinite. GCE questions sometimes ask you to criticise this assumption.

WORKED EXAMPLE 9 Inclined Plane with Resistance

A block of mass 2 kg slides down a rough plane inclined at 30° . The resistance to motion is $0.5v$ newtons where v is the speed in m s^{-1} . The block starts from rest. Find the distance travelled when the speed reaches 3 m s^{-1} . Take $g = 9.8 \text{ m s}^{-2}$.

SOLUTION

Setup. Down the plane positive. Weight component: $mg \sin 30^\circ = 2 \times 9.8 \times 0.5 = 9.8 \text{ N}$. Resistance: $0.5v$. Equation: $2v \frac{dv}{dx} = 9.8 - 0.5v$. Terminal velocity: $v_T = 9.8/0.5 = 19.6 \text{ m s}^{-1}$. Separate: $\frac{2v}{9.8 - 0.5v} dv = dx$. Rewrite: $\frac{v}{9.8 - 0.5v} = -2 + \frac{19.6}{9.8 - 0.5v}$. Integrate from $v = 0$ to $v = 3$:

$$\int_0^3 2 \left(-2 + \frac{19.6}{9.8 - 0.5v} \right) dv = \int_0^x dx.$$


$$2 [-2v - 39.2 \ln(9.8 - 0.5v)]_0^3 = x.$$

$$2 (-6 - 39.2 \ln(8.3) + 39.2 \ln(9.8)) = x.$$

$$x = -12 + 78.4 \ln \left(\frac{9.8}{8.3} \right) \approx -12 + 78.4 \times 0.166 \approx 1.0 \text{ m}.$$

Answer: Approximately 1.0 m.

4.4 Choosing the Right Approach: $v(t)$ vs $v(x)$



KEY POINTS Efficiency Comparison

- Question asks for time or $v(t)$: Use $\frac{dv}{dt}$. You must integrate once for $v(t)$, and if x is also needed, integrate $v(t)$ again.
- Question asks for distance or $v(x)$: Use $v \frac{dv}{dx}$. One integration gives $x(v)$ directly. Invert if $v(x)$ is required.
- Question asks for both: Either route works. $v(t) \rightarrow x(t)$ is often algebraically simpler if the integrals are standard; $v(x) \rightarrow t(x)$ via $dt = dx/v$ can involve nastier integrals. Choose the path with cleaner algebra.

4.5 Modelling Assumptions: A Critical Eye

GCE modelling questions almost always reserve the final 1–2 marks for “State one modelling assumption you have made” or “Criticise the model”. Be ready.

DEFINITION Standard Modelling Assumptions for Resisted Motion

1. The particle is a point mass (no rotation, no size).
2. The mass m is constant (no fuel loss, no accretion).
3. The resistance force depends only on speed v , usually linearly $R = kv$ or quadratically $R = kv^2$, and acts exactly opposite to velocity.
4. The medium is uniform and at rest (no wind, no density variation with height).
5. The gravitational field is uniform (g constant).
6. For powered vehicles: the driving force is constant (or constant power $P = Fv$).

WARNING Common Critique Points — Memorise These

- “The resistance law $R = kv$ is only valid for low speeds (laminar flow); at high speeds $R \propto v^2$ (turbulent flow).”
- “Constant driving force implies infinite power as $v \rightarrow \infty$; a constant power model $P = Fv$ is more realistic.”
- “Air density decreases with height, so k is not truly constant for large vertical displacements.”
- “The particle is modelled as a point mass, ignoring rotational effects and buoyancy.”
- “No wind or gusts are assumed; in reality the relative velocity determines resistance.”

Always phrase critiques in context: “The model assumes the resistance is proportional to velocity, but for a car at motorway speeds the quadratic law $R = kv^2$ would be more accurate.”

4.6 Synthesis: A Complete GCE–Style Problem**WORKED EXAMPLE 10** Full Exam Question — Resisted Motion on an Incline

A particle P of mass 0.5 kg is projected up a line of greatest slope of a rough plane inclined at α to the horizontal, where $\sin \alpha = 0.6$. The initial speed of P is 10 m s^{-1} . The coefficient of friction between P and the plane is 0.25 . Air resistance acts on P and has magnitude $0.1v$ newtons where v is the speed in m s^{-1} . The particle comes to instantaneous rest after travelling a distance x metres up the plane. Take $g = 10 \text{ m s}^{-2}$.

(a) Show that, while P is moving up the plane, the equation of motion can be written as

$$v \frac{dv}{dx} = -8 - 0.2v.$$

(b) Find the distance x travelled before P comes to rest.

(c) State one modelling assumption you have made about the air resistance.

SOLUTION

Solution.

(a) Forces acting up the plane (positive direction):

- Component of weight down the plane: $-mg \sin \alpha = -0.5 \times 10 \times 0.6 = -3 \text{ N}$.
- Friction (opposes motion, so down the plane): $-\mu R = -\mu mg \cos \alpha$. $\cos \alpha = \sqrt{1 - 0.6^2} = 0.8$. Friction $= -0.25 \times 0.5 \times 10 \times 0.8 = -1.0 \text{ N}$.
- Air resistance (opposes motion): $-0.1v$.

Total force: $F = -3 - 1.0 - 0.1v = -4 - 0.1v$. Newton's second law using $a = v \frac{dv}{dx}$:

$$0.5v \frac{dv}{dx} = -4 - 0.1v.$$

Divide by 0.5:

$$v \frac{dv}{dx} = -8 - 0.2v.$$

(Shown)

(b) Using the equation from (a):

$$v \frac{dv}{dx} = -8 - 0.2v = -0.2(40 + v).$$

Separate variables:

$$\frac{v}{40 + v} dv = -0.2 dx.$$

Rewrite integrand:

$$\frac{v}{40 + v} = 1 - \frac{40}{40 + v}.$$

Integrate from $x = 0, v = 10$ to $x = x, v = 0$:

$$\int_{10}^0 \left(1 - \frac{40}{40 + v}\right) dv = -0.2 \int_0^x dx.$$

$$\left[v - 40 \ln(40 + v)\right]_{10}^0 = -0.2x.$$

$$(0 - 40 \ln 40) - (10 - 40 \ln 50) = -0.2x.$$

$$-40 \ln 40 - 10 + 40 \ln 50 = -0.2x.$$

$$40 \ln\left(\frac{50}{40}\right) - 10 = -0.2x.$$

$$40 \ln(1.25) - 10 = -0.2x.$$

$$x = \frac{10 - 40 \ln(1.25)}{0.2} = 50 - 200 \ln(1.25).$$

Using $\ln(1.25) \approx 0.22314$:

$$x \approx 50 - 200 \times 0.22314 = 50 - 44.628 = 5.37 \text{ m}.$$

(c) Modelling assumption about air resistance: The air resistance is proportional to the speed v (linear law) and acts in the opposite direction to the velocity. The constant of proportionality 0.1 remains constant throughout the motion (no change in air density or particle orientation).

4.7 Revision Grid: Decision Table for Exam Questions

Question asks for...	Start with...	Key integration	Watch out for...
Time t to reach speed v	$m \frac{dv}{dt} = F - kv$	$\int \frac{dv}{F - kv}$	Signs when $F < kv$ (deceleration)
Speed v after time t	$m \frac{dv}{dt} = F - kv$	Same, then invert	Terminal velocity $v_T = F/k$ as limit
Distance x to reach speed v	$mv \frac{dv}{dx} = F - kv$	$\int \frac{v dv}{F - kv}$	Rewrite $\frac{v}{F - kv} = -\frac{1}{k} + \frac{F/k}{F - kv}$
Speed v after distance x	$mv \frac{dv}{dx} = F - kv$	Same, then invert	Logarithm argument must be positive
Maximum height (upward projection)	$mv \frac{dv}{dx} = -mg - kv$	$\int \frac{v dv}{mg + kv}$	$v = 0$ at top; limits $u \rightarrow 0$
Distance to stop (horizontal with resistance)	$mv \frac{dv}{dx} = -kv$	$\int \frac{v dv}{-kv} = -\frac{1}{k} \int v dv$	Simple: $x = \frac{mu^2}{2k}$ (work-energy)
Powered vehicle: distance to accelerate $u \rightarrow v$	$mv \frac{dv}{dx} = F - kv$	$\int \frac{v dv}{F - kv}$	Constant force $\neq$ constant power
Inclined plane (up or down)	$mv \frac{dv}{dx} = \pm mg \sin \alpha - kv$ $\mp \mu mg \cos \alpha$	$\int \frac{v dv}{a \pm bv}$	Signs of each component; friction always opposes motion

DID YOU KNOW? The Work–Energy Connection

For a particle on a horizontal line with resistance $R = kv$, the distance to stop from speed u can be analysed via work–energy: Work done by resistance = Loss of kinetic energy.

$$\int_0^x kv \, dx = \frac{1}{2} mu^2.$$

But v varies with x , so you still need $v(x)$ to evaluate the integral... unless you use the $v \frac{dv}{dx}$ equation multiplied by dx : $mv \, dv = -kv \, dx \Rightarrow m \int_u^0 v \, dv = -k \int_0^x v \, dx$. This just gives $\frac{1}{2} mu^2 = k \int_0^x v \, dx$, which is the work–energy equation. The work–energy theorem is a check, not a shortcut to x when resistance depends on v . However, for constant resistance $R = F$, it gives $x = \frac{mu^2}{2F}$ instantly.

EXERCISE 5 Consolidation Exercises

1. A particle of mass m falls from rest in a medium with resistance kv . Use $v \frac{dv}{dx}$ to find the distance fallen when the speed reaches $\frac{1}{2}v_T$, where $v_T = mg/k$ is the terminal velocity.
2. A car of mass 1200 kg has a constant driving force of 4000 N and experiences resistance $20v$ newtons. Starting from rest, find the distance required to reach 20 m s^{-1} .
3. A particle is projected up a smooth plane inclined at 30° with speed 15 m s^{-1} . Air resistance is $0.05v \text{ N}$. Mass = 0.2 kg . Find the maximum height reached (vertical height, not distance along plane). $g = 9.8 \text{ m s}^{-2}$.
4. Critique: In the car problem above, the model assumes constant driving force. Explain why a constant power model might be more realistic, and write the differential equation for $v(x)$ if the engine delivers constant power P .

SOLUTION Exercise 1

$v_T = mg/k$. Equation: $mv \frac{dv}{dx} = mg - kv = k(v_T - v)$. $\frac{mv}{k(v_T - v)} dv = dx$. Rewrite $\frac{v}{v_T - v} = -1 + \frac{v_T}{v_T - v}$.
 Integrate $v : 0 \rightarrow v_T/2, x : 0 \rightarrow x$: $\frac{m}{k} \int_0^{v_T/2} (-1 + \frac{v_T}{v_T - v}) dv = x$. $\frac{m}{k} [-v - v_T \ln(v_T - v)]_0^{v_T/2} = x$.
 $\frac{m}{k} (-\frac{v_T}{2} - v_T \ln(v_T/2) + v_T \ln v_T) = x$. $x = \frac{mv_T}{k} (\ln 2 - \frac{1}{2}) = \frac{mg}{k^2} (\ln 2 - \frac{1}{2})$.

SOLUTION Exercise 2

$m = 1200, F = 4000, k = 20$. $v_T = 200 \text{ m s}^{-1}$. $1200v \frac{dv}{dx} = 4000 - 20v = 20(200 - v)$.
 $60 \frac{v}{200 - v} dv = dx$. $\frac{v}{200 - v} = -1 + \frac{200}{200 - v}$. $\int_0^{20} 60(-1 + \frac{200}{200 - v}) dv = \int_0^x dx$. $60[-v - 200 \ln(200 - v)]_0^{20} = x$.
 $60(-20 - 200 \ln 180 + 200 \ln 200) = x$. $x = 60(-20 + 200 \ln \frac{200}{180}) = 60(-20 + 200 \ln \frac{10}{9})$.
 $x \approx 60(-20 + 200 \times 0.10536) = 60(1.072) \approx 64.3 \text{ m}$.

SOLUTION Exercise 3

Up plane positive. $mg \sin 30^\circ = 0.2 \times 9.8 \times 0.5 = 0.98 \text{ N}$ down. Resistance $0.05v$ down.
 $0.2v \frac{dv}{dx} = -0.98 - 0.05v$. $v \frac{dv}{dx} = -4.9 - 0.25v$. Separate: $\frac{v}{4.9 + 0.25v} dv = -dx$. $\frac{v}{4.9 + 0.25v} = 4 - \frac{19.6}{4.9 + 0.25v}$.
 Integrate $v : 15 \rightarrow 0, x : 0 \rightarrow s$ (distance along plane). $\int_{15}^0 (4 - \frac{19.6}{4.9 + 0.25v}) dv = -s$.
 $[4v - 78.4 \ln(4.9 + 0.25v)]_{15}^0 = -s$. $(0 - 78.4 \ln 4.9) - (60 - 78.4 \ln 8.65) = -s$. $s = 60 + 78.4 \ln(4.9/8.65) = 60 - 78.4 \ln(1.765) \approx 60 - 78.4 \times 0.568 \approx 15.5 \text{ m}$ along plane. Vertical height $h = s \sin 30^\circ = 7.75 \text{ m}$.

SOLUTION Exercise 4

Constant force F means power $P = Fv$ increases with v ; real engines have maximum power.

Constant power P : driving force $F = P/v$. Equation: $mv \frac{dv}{dx} = \frac{P}{v} - kv = \frac{P - kv^2}{v}$. Separate: $\frac{mv^2}{P - kv^2} dv = dx$. This integrates to an inverse hyperbolic tangent or logarithmic form.

5 INTEGRATION ACTIVITY

5.1 Aims of the activity

This integration activity closes the chapter Modelling with Differential Equations by asking you to use, in one single session, all three lessons studied: the **formation** of a differential equation from a physical situation, **Newton's law of cooling**, and the **resisted motion** of a particle in a straight line.

By the end of the activity you should be able to:

- translate a concrete, real-life situation into a differential equation, stating clearly the variables, the parameters and the modelling assumptions;
- solve a first-order separable differential equation of the type $\frac{dQ}{dt} = k(Q - Q_0)$ or $m\frac{dv}{dt} = -kv$ and determine the unknown constants from experimental data;
- use both forms of the acceleration, $\frac{dv}{dt}$ and $v\frac{dv}{dx}$, choosing the appropriate one according to the question asked;
- interpret a solution physically: limiting behaviour, time to reach a threshold, distance travelled before slowing down;
- criticise a model: identify which assumptions are questionable and explain how the model could be refined.

Work in groups of three or four. Each group produces one poster containing: the differential equation, its solution, the numerical answers, and **one criticism** of the modelling assumptions.

5.2 Situation

Part A — The cooling achu pot.

Mama Ngum runs a small chop house in Bamenda. At 12:00 she serves a pot of achu (yellow soup) at a temperature of 90°C in a dining room whose temperature is a constant 25°C . She notices that after 8 minutes the soup has cooled to 55°C . Experience tells her that customers complain when the soup is below 35°C , so she wants to know at what time the soup will reach 35°C .

Let $Q(t)$ be the temperature of the soup, in $^\circ\text{C}$, t minutes after serving. It is assumed that the rate of cooling is proportional to the difference between the temperature of the soup and the temperature of the room (**Newton's law of cooling**):

$$\frac{dQ}{dt} = k(Q - Q_0),$$

where $Q_0 = 25$ is the room temperature and k is a constant.

Part B — The coasting benskin rider.

The same afternoon, a benskin (commercial motorcycle) rider and his machine, of total mass $m = 150\text{ kg}$, are travelling on a level tarred road on the outskirts of Bamenda at 20 m s^{-1} when the rider switches off the engine and lets the bike coast. The motion is opposed by a resistance (air

drag and rolling friction) modelled as a force of magnitude $6v$ newtons, where v is the speed in m s^{-1} . The road is horizontal, so the weight is balanced by the normal reaction of the road.

The rider wants to know: how does his speed decay with time, and how far does he travel before his speed drops to 5 m s^{-1} ?

5.3 Tasks

Part A — The cooling pot.

1. Explain, in one or two sentences, why the constant k in $\frac{dQ}{dt} = k(Q - Q_0)$ must be negative. What does the sign of $\frac{dQ}{dt}$ tell you?
2. Show, by separating the variables, that the general solution of the differential equation is

$$Q(t) = Q_0 + Ae^{kt},$$
 where A is an arbitrary constant.
3. Use the initial condition $Q(0) = 90$ to find A , and write down $Q(t)$ in terms of k .
4. Use the observation $Q(8) = 55$ to show that $k = \frac{1}{8} \ln\left(\frac{6}{13}\right)$, and give the value of k correct to 4 significant figures.
5. Hence find, to the nearest minute, the time at which the soup reaches 35°C . Advise Mama Ngum.
6. Sketch the graph of $Q(t)$ for $0 \leq t \leq 30$. What is the limiting value of Q as $t \rightarrow \infty$? Is this physically sensible?
7. **Criticism.** Suppose the pot is now covered with a lid. Does Newton's law of cooling still apply with the same value of k ? Discuss briefly, and state one other assumption of the model that could be questioned.

Part B — The coasting rider.

1. Draw a force diagram for the rider and bike while coasting, and use Newton's second law to show that

$$150 \frac{dv}{dt} = -6v, \quad \text{i.e.} \quad \frac{dv}{dt} = -\frac{v}{25}.$$
2. Solve this equation with $v(0) = 20$ to obtain $v(t) = 20e^{-t/25}$.
3. Find the time at which the speed has fallen to 5 m s^{-1} , giving your answer to 1 decimal place.
4. Using the alternative form of the acceleration $a = v \frac{dv}{dx}$, show that v and the displacement x satisfy

$$\frac{dv}{dx} = -\frac{1}{25},$$

and hence find v as a function of x .

5. Calculate the distance travelled from the moment the engine is switched off until the speed drops to 5 m s^{-1} .
6. What is the limiting speed as $t \rightarrow \infty$? Using your answer to question 4, show that the total distance the bike would travel before stopping (in this model) is finite, and find it.
7. **Criticism.** The resistance was modelled as $6v$. In reality, air resistance is often modelled as proportional to v^2 . Write down the differential equation you would obtain with a resistance kv^2 , and state (without solving) whether you expect the total stopping distance to be finite or infinite in that model.

5.4 Model answer

Part A — The cooling pot.

1. Since the soup is hotter than the room, $Q - Q_0 > 0$, and the soup is cooling, so $\frac{dQ}{dt} < 0$. Therefore k must be negative. The negative sign of $\frac{dQ}{dt}$ expresses the fact that the temperature decreases with time.

2. The equation $\frac{dQ}{dt} = k(Q - Q_0)$ is separable. Since $Q > Q_0$ throughout the cooling, $|Q - Q_0| = Q - Q_0$, and

$$\frac{dQ}{Q - Q_0} = k dt \implies \ln(Q - Q_0) = kt + C \implies Q - Q_0 = e^C e^{kt},$$

so $Q(t) = Q_0 + Ae^{kt}$, where $A = e^C$ is an arbitrary (positive) constant.

3. With $Q_0 = 25$ and $Q(0) = 90$: $90 = 25 + A$, so $A = 65$ and

$$Q(t) = 25 + 65e^{kt}.$$

4. Using $Q(8) = 55$:


$$55 = 25 + 65e^{8k} \implies e^{8k} = \frac{30}{65} = \frac{6}{13} \implies k = \frac{1}{8} \ln\left(\frac{6}{13}\right) \approx -0.09665 \text{ min}^{-1}.$$

5. Set $Q(t) = 35$:

$$35 = 25 + 65e^{kt} \implies e^{kt} = \frac{10}{65} = \frac{2}{13} \implies t = \frac{1}{k} \ln\left(\frac{2}{13}\right) = \frac{8 \ln(2/13)}{\ln(6/13)} \approx 19.4 \text{ min}.$$

The soup reaches 35°C after about 19 minutes. Mama Ngum should serve the soup within roughly 19 minutes of dishing it out.

6. As $t \rightarrow \infty$, $e^{kt} \rightarrow 0$ (since $k < 0$), so $Q \rightarrow 25^\circ\text{C}$: the soup tends to room temperature, which is physically sensible. The graph is a decreasing exponential curve starting at $(0, 90)$, passing through $(8, 55)$ and $(19.4, 35)$, with horizontal asymptote $Q = 25$.




Cooling curve of the achu soup: $Q(t) = 25 + 65e^{kt}$, with $k \approx -0.09665 \text{ min}^{-1}$.

7. With a lid, heat escapes more slowly, so Newton's law may still describe the form of the cooling, but the constant k changes (it becomes smaller in magnitude). The value of k found experimentally applies only to the uncovered pot. Other questionable assumptions: the room temperature may not be exactly constant; the soup may not be at a uniform temperature (stirring matters); evaporation at the surface contributes to cooling and is not proportional to $Q - Q_0$.

Part B — The coasting rider.

1. The forces acting on the rider and bike are shown below: the weight mg and the normal reaction R balance vertically, while horizontally the only force is the resistance $6v$ opposing the motion.



Force diagram for the coasting bike: R and mg cancel; only the resistance $6v$ acts horizontally.

Taking the direction of motion as positive, Newton's second law gives

$$150 \frac{dv}{dt} = -6v \implies \frac{dv}{dt} = -\frac{6}{150}v = -\frac{v}{25}.$$

2. Separating variables (with $v > 0$):

$$\frac{dv}{v} = -\frac{dt}{25} \implies \ln v = -\frac{t}{25} + C \implies v = Ae^{-t/25}.$$

With $v(0) = 20$, $A = 20$, so $v(t) = 20e^{-t/25}$.

3. Set $v = 5$:

$$5 = 20e^{-t/25} \implies e^{-t/25} = \frac{1}{4} \implies t = 25 \ln 4 \approx 34.7 \text{ s.}$$

4. With $a = v \frac{dv}{dx}$, the equation of motion becomes

$$150 v \frac{dv}{dx} = -6v \implies \frac{dv}{dx} = -\frac{6}{150} = -\frac{1}{25} \quad (v \neq 0).$$

Integrating with respect to x : $v = -\frac{x}{25} + C'$, and $v = 20$ when $x = 0$ gives $C' = 20$, so

$$v(x) = 20 - \frac{x}{25}.$$

5. When $v = 5$:

$$5 = 20 - \frac{x}{25} \implies x = 25(20 - 5) = 375 \text{ m.}$$

The bike travels 375 m while slowing from 20 to 5 m s⁻¹.

6. As $t \rightarrow \infty$, $v = 20e^{-t/25} \rightarrow 0$: the bike approaches rest but (in this model) never quite reaches it in finite time. However, from question 4, $v = 0$ when $x = 25 \times 20 = 500$ m: the total distance travelled before stopping is finite, namely 500 m. This is a remarkable feature of linear resistance: infinite stopping time, finite stopping distance.

7. With resistance kv^2 , the equation of motion is $m \frac{dv}{dt} = -kv^2$. Using $v \frac{dv}{dx} = -\frac{k}{m}v^2$ gives $\frac{dv}{dx} = -\frac{k}{m}v$, whose solution is $v = 20e^{-kx/m}$: this is positive for all finite x , so the model predicts an infinite stopping distance (the speed decays exponentially with distance and never reaches exactly zero). This contrasts with the linear model and shows how the choice of resistance law affects the predictions.

WARNING Frequently observed errors

- Forgetting that $k < 0$ in Newton's law of cooling, or writing $Q = Ae^{kt}$ without the constant term Q_0 : the temperature tends to Q_0 , not to 0.
- Rounding k too early: keep $k = \frac{1}{8} \ln\left(\frac{6}{13}\right)$ in exact form and only round at the final step (the correct 4 s.f. value is $-0.09665 \text{ min}^{-1}$).
- In question 4 of Part B, dividing by v without noting $v \neq 0$; the relation $\frac{dv}{dx} = -\frac{1}{25}$ holds only while the bike is moving.
- Confusing the two forms of acceleration: use $\frac{dv}{dt}$ when time is involved, $v \frac{dv}{dx}$ when displacement is involved.
- Concluding "the bike never stops, so it travels infinitely far": for linear resistance the stopping time is infinite but the stopping distance is finite.

DID YOU KNOW? Why two case studies?

Newton's law of cooling and linear resisted motion lead to the same mathematical object: the exponential function as the solution of $\frac{dy}{dt} = k(y - y_0)$. Recognising that two apparently unrelated situations — a pot of soup in Bamenda and a coasting benskin — share one mathematical model is precisely the skill of **mathematical modelling** that the GCE Advanced Level examination rewards.

6 METHODS AND WORKED EXAMPLES

6.1 Skill 1: Forming a Differential Equation from a Family of Curves

METHOD Eliminating arbitrary constants

To find the differential equation of a family of curves containing n arbitrary constants:

1. Count the number n of **arbitrary constants** in the equation of the family. The differential equation will be of **order** n .
2. Differentiate the equation n times with respect to x , treating each constant as fixed. Remember the chain rule: if y depends on x , then $\frac{d}{dx}(y^2) = 2y \frac{dy}{dx}$.
3. You now have $n + 1$ equations (the original plus n derivatives). Use them to **eliminate** the n constants, usually by substitution or by subtracting pairs of equations.
4. The result is a relation between $x, y, y', \dots, y^{(n)}$ containing no arbitrary constant: this is the required differential equation.

Reflexes: isolate the constant before differentiating when it appears as a factor (e.g. write $\frac{y}{x} = A$); differentiate $\ln y, e^{ky}, y^2$ with care; always check your final equation contains no constant.

WORKED EXAMPLE 11 Family of parabolas

Find the differential equation of the family of parabolas $y = Ax^2$, where A is an arbitrary constant. Hence state the order of the equation obtained.

SOLUTION

Solution.

Step 1. The family has one arbitrary constant A , so we expect a first order differential equation.

Step 2. Differentiate once with respect to x :

$$\frac{dy}{dx} = 2Ax.$$

Step 3. We eliminate A between the two equations

$$y = Ax^2 \quad \text{and} \quad \frac{dy}{dx} = 2Ax.$$

From the first equation, $A = \frac{y}{x^2}$ (for $x \neq 0$). Substituting into the second:

$$\frac{dy}{dx} = 2\left(\frac{y}{x^2}\right)x = \frac{2y}{x}.$$

Step 4. The differential equation of the family is

$$x \frac{dy}{dx} = 2y \quad (\text{order 1}).$$

Check. If $y = Ax^2$, then $x \frac{dy}{dx} = x(2Ax) = 2Ax^2 = 2y$. ✓

WORKED EXAMPLE 12 Family with two constants

Find the differential equation of the family of curves $y = Ae^{2x} + Be^{-x}$, where A and B are arbitrary constants.

SOLUTION

Solution.

Step 1. Two arbitrary constants $\Rightarrow$ a second order differential equation.

Step 2. Differentiate twice:

$$\begin{aligned} y &= Ae^{2x} + Be^{-x}, \\ y' &= 2Ae^{2x} - Be^{-x}, \\ y'' &= 4Ae^{2x} + Be^{-x}. \end{aligned}$$

Step 3. Eliminate A and B . Adding the first two equations eliminates B :

$$y + y' = 3Ae^{2x} \quad \Rightarrow \quad Ae^{2x} = \frac{y + y'}{3}.$$

Subtracting the first from the third:

$$y'' - y = 3Ae^{2x} \quad \Rightarrow \quad Ae^{2x} = \frac{y'' - y}{3}.$$

Equating the two expressions for Ae^{2x} :

$$\frac{y + y'}{3} = \frac{y'' - y}{3} \quad \Rightarrow \quad y + y' = y'' - y.$$

Step 4. Hence

$$\frac{d^2y}{dx^2} - \frac{dy}{dx} - 2y = 0.$$

Check. With $y = Ae^{2x} + Be^{-x}$: $y'' - y' - 2y = (4 - 2 - 2)Ae^{2x} + (1 + 1 - 2)Be^{-x} = 0$. ✓

WARNING Constants hidden inside functions

A constant may be disguised: in $y = A \sin x$, the constant A is a factor, but in $y = \sin(x + c)$ the constant c is inside the sine and cannot be isolated by division. Differentiate first, then eliminate. Also, never leave a constant in your final answer: an equation like $y' = 2Ax$ is not a differential equation of the family until A has been removed.

6.2 Skill 2: Forming a Differential Equation from a Practical Situation**METHOD** Translating a statement into a differential equation

1. **Define variables:** choose a letter for the quantity that varies (population P , temperature θ , volume V ...) and identify the independent variable (usually time t). State the units.
2. Identify the **rate of change** mentioned in the statement: “rate of increase”, “decays”, “cools” $\rightarrow \frac{dP}{dt}, \frac{d\theta}{dt}, \dots$
3. Translate the **proportionality**: “proportional to X ” gives kX ; “inversely proportional to X ” gives $\frac{k}{X}$; “proportional to the square of X ” gives kX^2 .
4. Fix the **sign**: positive constant $k > 0$ with a minus sign if the quantity decreases ($\frac{dV}{dt} = -kV$), plus sign if it increases.
5. Add any **initial condition** given (value at $t = 0$): this will later fix the constant of integration.

Reflex: if a quantity decreases towards a fixed value Q_0 , the driving term is the difference $(Q - Q_0)$, not Q itself.

WORKED EXAMPLE 13 Modelling a water tank and a population

- (a) A water tank in Buea leaks so that the volume V litres of water decreases at a rate proportional to the volume present. Initially the tank contains 5000 litres. Form a differential equation with its initial condition.
- (b) A bacterial culture grows so that its population P increases at a rate proportional to P , and a harvest removes bacteria at the constant rate of h bacteria per hour. Form a differential equation for P .

SOLUTION

Solution.

(a) Variables: V = volume of water (litres), t = time.

Rate of change: the volume decreases, so $\frac{dV}{dt} < 0$.

Proportionality: rate proportional to the volume present $\Rightarrow$ magnitude kV with $k > 0$.

Sign: decreasing $\Rightarrow$ minus sign. Hence

$$\frac{dV}{dt} = -kV, \quad V(0) = 5000.$$

(b) Two contributions act on $\frac{dP}{dt}$:

- natural growth: $+kP$ (proportional to P , increasing);
- harvesting: $-h$ (constant removal).

Combining:

$$\frac{dP}{dt} = kP - h.$$

Note the model is only meaningful while $P > \frac{h}{k}$; if $P = \frac{h}{k}$ then $\frac{dP}{dt} = 0$ and the population is in equilibrium.

6.3 Skill 3: Newton's Law of Cooling

DEFINITION Newton's law of cooling

The rate at which a body loses heat to its surroundings is proportional to the **excess temperature**, the difference between the temperature θ of the body and the constant ambient temperature θ_0 of the surroundings:

$$\frac{d\theta}{dt} = -k(\theta - \theta_0), \quad k > 0.$$

The minus sign expresses that a body hotter than its surroundings cools down ($\theta > \theta_0 \Rightarrow \frac{d\theta}{dt} < 0$).

METHOD Solving $\frac{d\theta}{dt} = -k(\theta - \theta_0)$

1. Identify the **ambient temperature** θ_0 (constant temperature of the surroundings) and write the law

$$\frac{d\theta}{dt} = -k(\theta - \theta_0), \quad k > 0,$$

where θ is the temperature of the body at time t .

2. **Separate variables** using the difference $\theta - \theta_0$:

$$\int \frac{d\theta}{\theta - \theta_0} = \int -k dt \implies \ln |\theta - \theta_0| = -kt + C.$$


3. Exponentiate: $\theta - \theta_0 = Ae^{-kt}$ where $A = \pm e^C$.

4. Use the **initial temperature** $\theta(0) = \theta_i$ to get $A = \theta_i - \theta_0$, hence

$$\theta = \theta_0 + (\theta_i - \theta_0)e^{-kt}.$$

5. Use a second measured temperature to find k (take logarithms: $kt = \ln \frac{\theta_i - \theta_0}{\theta - \theta_0}$), then answer the question asked.

Reflex: the body never quite reaches θ_0 in finite time; $\theta \rightarrow \theta_0$ as $t \rightarrow \infty$.



Newton's law of cooling: the excess temperature $\theta - \theta_0$ decays exponentially towards zero.

WORKED EXAMPLE 14 Cooling of a pot of water

A pot of water is removed from the fire in a kitchen in Bamenda at a temperature of 100°C and placed in a room kept at 20°C . After 10 minutes the water is at 60°C . Assuming Newton's law of cooling, find:

- the temperature of the water after a further 10 minutes;
- the time at which the temperature reaches 30°C , giving your answer to the nearest minute.

SOLUTION

Solution.

Setting up. Ambient temperature $\theta_0 = 20$. Newton's law:

$$\frac{d\theta}{dt} = -k(\theta - 20).$$

Separating variables and integrating:

$$\ln(\theta - 20) = -kt + C \implies \theta = 20 + Ae^{-kt}.$$

Initial condition $\theta(0) = 100$: $A = 100 - 20 = 80$. Hence

$$\theta = 20 + 80e^{-kt}.$$

Finding k . At $t = 10$, $\theta = 60$:

$$60 = 20 + 80e^{-10k} \implies e^{-10k} = \frac{40}{80} = \frac{1}{2}.$$

Taking logarithms: $-10k = \ln \frac{1}{2} = -\ln 2$, so

$$k = \frac{\ln 2}{10} \approx 0.0693 \text{ min}^{-1}.$$

Part 1. "A further 10 minutes" means $t = 20$:

$$\theta(20) = 20 + 80e^{-20k} = 20 + 80(e^{-10k})^2 = 20 + 80\left(\frac{1}{2}\right)^2 = 20 + 20 = \boxed{40^\circ\text{C}}.$$

(Elegant shortcut: the excess temperature $80 \rightarrow 40 \rightarrow 20$ is halved every 10 minutes.)

Part 2. Solve $\theta = 30$:

$$30 = 20 + 80e^{-kt} \implies e^{-kt} = \frac{10}{80} = \frac{1}{8}.$$

$$kt = \ln 8 = 3 \ln 2 \implies t = \frac{3 \ln 2}{\ln 2/10} = 30 \text{ minutes}.$$

The water reaches 30°C after exactly $\boxed{30}$ minutes (three half-lives of the excess temperature).

WARNING**Working with the excess temperature**

All the exponential behaviour concerns the difference $\theta - \theta_0$, never θ alone. A frequent error is to write $\theta = 100e^{-kt}$, which wrongly sends the temperature to 0°C instead of the room temperature. Always subtract the ambient temperature first.

6.4 Skill 4: Resisted Motion — Velocity as a Function of Time

METHOD Solving $m \frac{dv}{dt} = F - kv$ or $F - kv^2$

1. Draw a **force diagram**: driving force F (weight mg , engine force...) in the direction of motion, resistance $R(v)$ opposing motion.
2. Apply **Newton's second law**: $m \frac{dv}{dt} = F - R(v)$.
3. **Separate variables**:
 - Linear resistance $R = kv$: $t = \int \frac{m dv}{F - kv} = -\frac{m}{k} \ln |F - kv| + C$.
 - Quadratic resistance $R = kv^2$: use partial fractions on $\frac{1}{F - kv^2}$, giving a logarithm of the form $\ln \left| \frac{V + v}{V - v} \right|$.
4. Use the initial velocity to find C , then make v the **subject**.
5. Read off the **terminal velocity**: either set $\frac{dv}{dt} = 0$ in the equation of motion ($F = R(v_T)$), or let $t \rightarrow \infty$ in $v(t)$.

WORKED EXAMPLE 15 Vehicle with linear resistance

A car of mass 1000 kg moves along a straight horizontal road. Its engine exerts a constant tractive force of 3000 N and the resistance to motion is $50v$ N, where $v \text{ m s}^{-1}$ is the speed. The car starts from rest.

1. Show that $20 \frac{dv}{dt} = 60 - v$.
2. Find v in terms of t and state the terminal velocity.
3. Find the time taken to reach 90% of the terminal velocity, to 3 significant figures.

SOLUTION

Solution.

Part 1. Newton's second law along the road:

$$m \frac{dv}{dt} = F - R \implies 1000 \frac{dv}{dt} = 3000 - 50v.$$

Dividing by 50:

$$20 \frac{dv}{dt} = 60 - v.$$

Part 2. Separate variables:

$$\int \frac{20 dv}{60 - v} = \int dt \implies -20 \ln |60 - v| = t + C.$$

Initial condition $v = 0$ at $t = 0$: $C = -20 \ln 60$. Hence

$$-20 \ln \frac{60 - v}{60} = t \implies \frac{60 - v}{60} = e^{-t/20}.$$

Making v the subject:


$$v = 60(1 - e^{-t/20}).$$

As $t \rightarrow \infty$, $e^{-t/20} \rightarrow 0$, so the **terminal velocity** is $v_T = 60 \text{ m s}^{-1}$.

Check via equilibrium: $dv/dt = 0 \implies 60 - v = 0 \implies v_T = 60$. ✓

Part 3. 90% of 60 is 54 m s^{-1} :

$$54 = 60(1 - e^{-t/20}) \implies e^{-t/20} = 0.1 \implies t = 20 \ln 10 \approx 46.1 \text{ s}.$$



Speed approaching the terminal velocity asymptotically under linear resistance.

6.5 Skill 5: Resisted Motion — Velocity as a Function of Displacement

METHOD Using $a = v \frac{dv}{dx}$

When the question asks for velocity in terms of displacement (or distance travelled to reach a given speed), time is not wanted, so:

1. Replace the acceleration by the **chain rule form**

$$a = \frac{dv}{dt} = \frac{dv}{dx} \cdot \frac{dx}{dt} = v \frac{dv}{dx}.$$

2. Write Newton's second law: $m v \frac{dv}{dx} = F - R(v)$.
 3. **Separate** v and x : put all v 's with dv and integrate with respect to x .
 4. Apply the initial condition ($v = v_0$ when $x = 0$) to fix the constant.
 5. For a stopping distance, set $v = 0$ in the integrated relation (or take the limit as $v \rightarrow 0$).
- Reflex: choose $\frac{dv}{dt}$ when time is involved, $v \frac{dv}{dx}$ when displacement is involved. This choice is the single most important decision in resisted-motion questions.

WORKED EXAMPLE 16 Stopping distance of a boat

A boat of mass 500 kg is moving in a straight line at 8 m s^{-1} when its engine is switched off. The water resistance is $100v \text{ N}$, where $v \text{ m s}^{-1}$ is the speed.

1. Show that $v \frac{dv}{dx} = -\frac{v}{5}$, where x is the distance travelled after the engine stops.
2. Find the distance the boat travels before coming to rest.

SOLUTION

Solution.

Part 1. After the engine stops, the only horizontal force is the resistance $100v$ opposing motion. Newton's second law with $a = v \frac{dv}{dx}$:

$$500 v \frac{dv}{dx} = -100v \implies \boxed{v \frac{dv}{dx} = -\frac{v}{5}}$$

Part 2. For $v \neq 0$ divide by v :

$$\frac{dv}{dx} = -\frac{1}{5} \implies v = -\frac{x}{5} + C.$$

Initial condition: $v = 8$ when $x = 0$, so $C = 8$ and

$$v = 8 - \frac{x}{5}.$$

The boat stops when $v = 0$:

$$0 = 8 - \frac{x}{5} \implies \boxed{x = 40 \text{ m.}}$$

The boat travels exactly 40 m before stopping.

Remark. Here the resistance is proportional to v , so v decreases linearly with distance and the stopping distance is finite. (With time as variable, $v = 8e^{-t/5}$ only tends to 0: the boat "never stops" in finite time, yet covers a finite distance $\int_0^\infty 8e^{-t/5} dt = 40 \text{ m}$ — a reassuring consistency check!)

6.6 Skill 6: Mixed Examination Problems

METHOD Strategy for full GCE-style questions

1. **Read the whole question first:** part (a) usually asks you to form the equation, part (b) to solve it, part (c) to interpret (terminal velocity, limiting temperature, time or distance for a given value).
2. Show the forming step clearly: state Newton's second law or the given proportionality in symbols before substituting numbers — method marks are awarded here.
3. Keep the constant of integration symbolic until the initial condition is applied; apply it immediately after integrating.
4. When asked to “show that” a given solution holds, you may verify by substitution into the differential equation instead of solving — often much faster.
5. Finish with the **interpretation** in context, with units: “the limiting speed is 12 m s^{-1} ”.

WORKED EXAMPLE 17 Parachutist with quadratic resistance

A parachutist of mass 80 kg falls vertically from rest. The air resistance has magnitude $2v^2 \text{ N}$, where $v \text{ m s}^{-1}$ is her speed. Take $g = 10 \text{ m s}^{-2}$.

1. Show that $\frac{dv}{dt} = \frac{400 - v^2}{40}$.
2. Hence show that $t = 40 \int_0^v \frac{du}{400 - u^2}$, and by using partial fractions show that

$$t = \ln\left(\frac{20 + v}{20 - v}\right).$$
3. Deduce v as a function of t and state the terminal velocity.
4. Find the distance fallen while her speed increases from 0 to 10 m s^{-1} , giving your answer to 3 significant figures.

SOLUTION

Solution.

Part 1. Forces: weight $mg = 800 \text{ N}$ downwards, resistance $2v^2 \text{ N}$ upwards. Newton's second law (downwards positive):

$$80 \frac{dv}{dt} = 800 - 2v^2 \quad \Rightarrow \quad \frac{dv}{dt} = \frac{800 - 2v^2}{80} = \frac{400 - v^2}{40}.$$

Part 2. Separating variables and integrating from rest ($v = 0$ at $t = 0$):

$$dt = \frac{40 dv}{400 - v^2} \implies t = 40 \int_0^v \frac{du}{400 - u^2}.$$

Partial fractions: $\frac{1}{400 - u^2} = \frac{1}{(20 - u)(20 + u)} = \frac{1}{40} \left(\frac{1}{20 + u} + \frac{1}{20 - u} \right)$, since $\frac{1}{40}[(20 - u) + (20 + u)] = 1$. Therefore

$$\begin{aligned} t &= 40 \cdot \frac{1}{40} \int_0^v \left(\frac{1}{20 + u} + \frac{1}{20 - u} \right) du \\ &= \left[\ln(20 + u) - \ln(20 - u) \right]_0^v = \ln \frac{20 + v}{20 - v} - \ln 1 = \boxed{\ln \left(\frac{20 + v}{20 - v} \right)}. \end{aligned}$$

Part 3. Exponentiate: $\frac{20 + v}{20 - v} = e^t$. Solving for v :

$$20 + v = e^t(20 - v) \implies v(e^t + 1) = 20(e^t - 1),$$

$$\boxed{v = 20 \frac{e^t - 1}{e^t + 1} = 20 \frac{1 - e^{-t}}{1 + e^{-t}}}.$$

(Dividing numerator and denominator by $e^{t/2}$ gives the equivalent compact form $v = 20 \tanh \frac{t}{2}$.) As $t \rightarrow \infty$, $e^{-t} \rightarrow 0$, so the terminal velocity is $\boxed{v_T = 20 \text{ m s}^{-1}}$.

Check: equilibrium: $2v^2 = 800 \Rightarrow v = 20$. ✓

Part 4. Displacement is involved, so use $a = v \frac{dv}{dx}$:

$$80 v \frac{dv}{dx} = 800 - 2v^2 \implies dx = \frac{80 v dv}{800 - 2v^2} = \frac{40 v dv}{400 - v^2}.$$

Integrating from $v = 0$ to $v = 10$:

$$x = 40 \int_0^{10} \frac{v dv}{400 - v^2} = 40 \left[-\frac{1}{2} \ln(400 - v^2) \right]_0^{10} = -20 \ln \frac{300}{400} = 20 \ln \frac{4}{3}.$$

Numerically, $x = 20 \ln(1.3333) \approx \boxed{5.75 \text{ m}}$ (3 s.f.). The parachutist falls about 5.75 m while accelerating from rest to 10 m s^{-1} .

WORKED EXAMPLE 18 Cooling with a “show that” verification

The temperature $\theta^\circ\text{C}$ of a corpse discovered in a mortuary satisfies Newton’s law of cooling with ambient temperature 4°C , so that $\frac{d\theta}{dt} = -k(\theta - 4)$. At time $t = 0$ the temperature is 15°C .

1. Verify that $\theta = 4 + 11e^{-kt}$ satisfies both the differential equation and the initial condition.

2. Given that after 2 hours the temperature is 10°C , find k to 3 significant figures, and the time at which the temperature will be 6°C .

SOLUTION

Solution.

Part 1. Differentiate the proposed solution:

$$\frac{d\theta}{dt} = -11ke^{-kt}.$$

Now compute the right-hand side of the differential equation:

$$-k(\theta - 4) = -k(4 + 11e^{-kt} - 4) = -11ke^{-kt}.$$

Both sides agree, so $\theta = 4 + 11e^{-kt}$ satisfies the equation. Also $\theta(0) = 4 + 11e^0 = 15$, so the initial condition holds. ✓

Part 2. At $t = 2$, $\theta = 10$:

$$10 = 4 + 11e^{-2k} \implies e^{-2k} = \frac{6}{11} \implies k = \frac{1}{2} \ln \frac{11}{6} \approx \boxed{0.303 \text{ h}^{-1}}.$$

For $\theta = 6$:

$$6 = 4 + 11e^{-kt} \implies e^{-kt} = \frac{2}{11} \implies t = \frac{\ln(11/2)}{k} = \frac{2 \ln(11/2)}{\ln(11/6)}.$$

Numerically $t \approx \frac{2 \times 1.7047}{0.6061} \approx \boxed{5.63 \text{ hours}}$ (3 s.f.).

KEY POINTS Chapter essentials

- A family with n arbitrary constants satisfies a differential equation of **order** n : differentiate n times, then eliminate the constants.
- Modelling: rate of change = (rate in) – (rate out); a quantity tending to a limit Q_0 is driven by the **difference** $Q - Q_0$.
- Newton's law of cooling: $\frac{d\theta}{dt} = -k(\theta - \theta_0)$, with solution $\theta = \theta_0 + (\theta_i - \theta_0)e^{-kt}$.
- Resisted motion: $m\frac{dv}{dt} = F - R(v)$ for time questions; $mv\frac{dv}{dx} = F - R(v)$ for displacement questions.
- **Terminal velocity**: set the acceleration to zero, i.e. solve $F = R(v_T)$.

EXERCISE 6 Practice

1. Find the differential equation of the family of curves $y = \frac{A}{x} + B$, where A and B are arbitrary constants.
2. A radioactive substance decays so that the mass m grams decreases at a rate proportional to the mass present. Initially there are 200 g and after 5 days 150 g remain. Form the differential equation, solve it, and find the mass remaining after 12 days (3 s.f.).
3. A body falls from rest under gravity against a resistance of $\frac{mv}{10}$ N per unit mass, i.e. $\frac{dv}{dt} = 10 - \frac{v}{10}$. Find v in terms of t , the terminal velocity, and the time to reach half the terminal velocity.
4. A particle of mass 2 kg moving at 6 m s^{-1} is slowed by a resistance $4v$ N. Using $a = v \frac{dv}{dx}$, find the distance travelled before the speed falls to 2 m s^{-1} .

SOLUTION Exercise 1

1. $y = \frac{A}{x} + B \Rightarrow y' = -\frac{A}{x^2}$, so $A = -x^2 y'$. Then $y'' = \frac{2A}{x^3} = \frac{2(-x^2 y')}{x^3} = -\frac{2y'}{x}$, giving $xy'' + 2y' = 0$.
2. $\frac{dm}{dt} = -km$, $m(0) = 200$, so $m = 200e^{-kt}$. From $150 = 200e^{-5k}$: $k = \frac{1}{5} \ln \frac{4}{3} \approx 0.0575 \text{ day}^{-1}$.
Then $m(12) = 200e^{-12k} = 200 \left(\frac{3}{4}\right)^{12/5} \approx 100 \text{ g}$ (3 s.f.: 100 g, more precisely 100.2 g).
3. Separating: $-10 \ln |100 - v| \cdot \frac{1}{10} \dots$ directly: $\int \frac{10 dv}{100 - v} = \int dt$ gives $v = 100(1 - e^{-t/10})$.
Terminal velocity $v_T = 100 \text{ m s}^{-1}$. Half of it: $e^{-t/10} = \frac{1}{2} \Rightarrow t = 10 \ln 2 \approx 6.93 \text{ s}$.
4. $2v \frac{dv}{dx} = -4v \Rightarrow \frac{dv}{dx} = -2 \Rightarrow v = 6 - 2x$. Setting $v = 2$: $x = 2 \text{ m}$.

7 EXERCISES

7.1 I check my knowledge

EXERCISE 7 Multiple choice question

A family of curves is given by $y = Ae^{2x}$, where A is an arbitrary constant. Which of the following differential equations is satisfied by every member of the family?

1. $\frac{dy}{dx} = 2x$
2. $\frac{dy}{dx} = 2y$
3. $\frac{dy}{dx} = e^{2x}$
4. $\frac{dy}{dx} = \frac{y}{2}$

EXERCISE 8 True or false, with justification

Answer true or false to each statement, justifying your answer in one or two sentences.

1. The equation $\frac{d\theta}{dt} = -k(\theta - \theta_0)$ with $k > 0$ models the temperature θ of a body cooling in surroundings at temperature θ_0 .
2. In Newton's law of cooling, the constant k depends on the initial temperature of the body.
3. For a particle moving with resistance proportional to its velocity, the terminal velocity is the velocity at which the acceleration is zero.
4. To obtain velocity as a function of displacement, one replaces $\frac{dv}{dt}$ by $v \frac{dv}{dx}$.

EXERCISE 9 Definitions and key results

1. State Newton's law of cooling as a differential equation, defining every symbol used.
2. Explain what is meant by the **terminal velocity** of a particle falling through a resisting medium.

3. Write down the two forms of acceleration used in resisted motion, and state when each is appropriate.

EXERCISE 10 Direct calculations

1. Form the differential equation of the family of curves $y = Ax^2$ by eliminating the constant A .
2. A body cools according to $\frac{d\theta}{dt} = -0.1(\theta - 20)$. Find the rate of cooling at the instant when $\theta = 60^\circ\text{C}$.
3. A particle of mass 4 kg moves under a resistance of $8v$ N and no other horizontal force. Write down the equation of motion in the form $m\frac{dv}{dt} = \dots$

7.2 I practise**EXERCISE 11** Forming a differential equation from a family of curves

A family of curves is given by $y = Ax^2 + Bx$, where A and B are arbitrary constants.

1. Write down $\frac{dy}{dx}$ and $\frac{d^2y}{dx^2}$.
2. Hence form the differential equation satisfied by all members of the family by eliminating A and B . Give your answer in the form $x^2y'' - 2xy' + 2y = 0$ or show that it reduces to it.

EXERCISE 12 Population growth

The population P of a town grows at a rate proportional to its size. The population doubles in 20 years.

1. Form the differential equation satisfied by $P(t)$ and solve it, expressing the constant of proportionality in terms of $\ln 2$.
2. Find the time taken for the population to triple, giving your answer to the nearest year.

EXERCISE 13 Newton's law of cooling

A body cools from 80°C to 60°C in 10 minutes in a room kept at 20°C . The temperature θ of the body satisfies $\frac{d\theta}{dt} = -k(\theta - 20)$.

1. Solve the differential equation and show that $\theta = 20 + 60e^{-kt}$.
2. Use the given data to find the exact value of k .
3. Find the temperature of the body after a further 10 minutes.

EXERCISE 14 Resisted motion with driving force

A particle of mass 2 kg moves in a straight line under a constant driving force of 20 N and a resistance of $4v$ N, where v is its speed in m s^{-1} . The particle starts from rest.

1. Show that $\frac{dv}{dt} = 10 - 2v$.
2. Find v in terms of t .
3. State the terminal velocity and find the time taken to reach half of it.

7.3 I prepare for the GCE**EXERCISE 15** Cooling and sketch of the solution — 12 marks

A body warms from 5°C to 15°C in 5 minutes in a room maintained at 30°C . The temperature θ of the body at time t minutes satisfies Newton's law of cooling.

1. Write down the differential equation modelling this situation, explaining the sign of the constant. (2 marks)
2. Solve the equation and use the data to determine the value of the constant, giving your answer in terms of a logarithm. (5 marks)
3. Find the time at which the body reaches 25°C , giving your answer to one decimal place. (3 marks)
4. Sketch the graph of θ against t for $t \geq 0$, indicating the asymptote and the initial value. (2 marks)

EXERCISE 16 Vertical projection with resistance — structured proof, 14 marks

A ball of mass m is projected vertically upwards with speed u in a medium whose resistance has magnitude mkv per unit mass, where v is the speed and k is a positive constant. Take the upward direction as positive.

1. Explain why, while the ball is rising, the equation of motion is $\frac{dv}{dt} = -(g + kv)$. (3 marks)
2. Solve this equation with the initial condition $v(0) = u$ to obtain $v = \left(u + \frac{g}{k}\right)e^{-kt} - \frac{g}{k}$. (5 marks)
3. Hence show that the time taken to reach the greatest height is $T = \frac{1}{k} \ln\left(1 + \frac{ku}{g}\right)$. (3 marks)
4. Using $v \frac{dv}{dx} = -(g + kv)$, or otherwise, find the greatest height reached. (3 marks)

EXERCISE 17 Cyclist freewheeling downhill — synthesis, 16 marks

A cyclist of total mass m kg freewheels down a straight slope inclined at an angle α to the horizontal. The resistance to motion has magnitude kv^2 N, where v is the speed in m s^{-1} and k is a positive constant. The cyclist starts from rest.

1. Draw a diagram showing the forces acting on the cyclist and write down the equation of motion. (3 marks)
2. Show that the terminal speed is $v_T = \sqrt{\frac{mg \sin \alpha}{k}}$. (3 marks)
3. Using $v \frac{dv}{dx} = g \sin \alpha - \frac{k}{m}v^2$, show that $v^2 = v_T^2 (1 - e^{-2kx/m})$, where x is the distance travelled from rest. (6 marks)
4. Deduce the distance travelled before the cyclist reaches half the terminal speed, expressing your answer in terms of m , k and a logarithm. (3 marks)
5. State one assumption of the model and comment on its realism. (1 mark)

8 SOLUTIONS TO THE EXERCISES

SOLUTION Exercise 1 — Multiple choice question

Answer: (b) $\frac{dy}{dx} = 2y$.

Justification. Given $y = Ae^{2x}$, differentiate with respect to x :

$$\frac{dy}{dx} = 2Ae^{2x}.$$

But $Ae^{2x} = y$, so substituting eliminates the arbitrary constant A :

$$\frac{dy}{dx} = 2y.$$

Every member of the family, whatever the value of A , satisfies this equation.

Why the other options fail.

- (a) $\frac{dy}{dx} = 2x$ would give $y = x^2 + C$, an entirely different family.
- (c) $\frac{dy}{dx} = e^{2x}$ still contains x explicitly on the right and is not satisfied: $2Ae^{2x} \neq e^{2x}$ in general.
- (d) $\frac{dy}{dx} = \frac{y}{2}$ would give $y = Ce^{x/2}$, not Ae^{2x} .

SOLUTION Exercise 2 — True or false, with justification

1. True. The rate of change of temperature is proportional to the excess $\theta - \theta_0$ of the body's temperature over the surroundings; the negative sign ensures θ decreases when $\theta > \theta_0$ (cooling). This is exactly **Newton's law of cooling**.
2. False. The constant k depends on the physical properties of the body and its environment (surface area, nature of the surface, air circulation), not on the initial temperature. The initial temperature only fixes the constant of integration when solving.
3. True. **Terminal velocity** v_T is the limiting velocity reached asymptotically; at $v = v_T$ the driving force exactly balances the resistance, so the resultant force — and hence the acceleration $\frac{dv}{dt}$ — is zero.
4. True. By the chain rule, $\frac{dv}{dt} = \frac{dv}{dx} \cdot \frac{dx}{dt} = v \frac{dv}{dx}$. This substitution removes t and produces a differential equation relating v and x .

SOLUTION Exercise 3 — Definitions and key results

1. **Newton's law of cooling.** If θ is the temperature of a body at time t and θ_0 is the (constant) temperature of the surrounding medium, then

$$\frac{d\theta}{dt} = -k(\theta - \theta_0),$$

where $\frac{d\theta}{dt}$ is the rate of change of the body's temperature and $k > 0$ is a constant depending on the body and its environment. The negative sign expresses that the temperature difference decreases with time.

2. **Terminal velocity.** The terminal velocity v_T of a particle falling through a resisting medium is the limiting velocity which the speed approaches as $t \rightarrow \infty$. It is the velocity at which the resistance exactly balances the driving force (e.g. weight), so that the acceleration is zero: $\frac{dv}{dt} = 0$ when $v = v_T$.
3. Two forms of acceleration.
- $a = \frac{dv}{dt}$: used when we want v as a function of time t .
 - $a = v \frac{dv}{dx}$: used when we want v as a function of displacement x (the time variable is eliminated via the chain rule).

SOLUTION Exercise 4 — Direct calculations

1. Given $y = Ax^2$, differentiate: $\frac{dy}{dx} = 2Ax$. From the original equation, $A = \frac{y}{x^2}$. Substituting:

$$\frac{dy}{dx} = 2 \cdot \frac{y}{x^2} \cdot x = \frac{2y}{x}, \quad \text{i.e.} \quad x \frac{dy}{dx} = 2y.$$

2. The rate of cooling is $\frac{d\theta}{dt} = -0.1(\theta - 20)$. At $\theta = 60$:

$$\frac{d\theta}{dt} = -0.1(60 - 20) = -0.1 \times 40 = -4^\circ\text{C min}^{-1}.$$

The body is cooling at 4°C per minute at that instant (the negative sign indicates decreasing temperature).

3. The only horizontal forces are the resistance $8v$ opposing the motion. Newton's second law gives

$$m \frac{dv}{dt} = -8v, \quad \text{i.e.} \quad 4 \frac{dv}{dt} = -8v \iff \frac{dv}{dt} = -2v.$$

SOLUTION Exercise 5 — Forming a differential equation from a family of curves

1. Given
- $y = Ax^2 + Bx$
- :

$$\frac{dy}{dx} = 2Ax + B, \quad \frac{d^2y}{dx^2} = 2A.$$

2. From the second derivative,
- $A = \frac{y''}{2}$
- . Substitute into the first derivative:

$$B = y' - 2Ax = y' - xy''.$$

Now substitute A and B into the original equation:

$$y = \frac{y''}{2}x^2 + (y' - xy'')x = \frac{x^2y''}{2} + xy' - x^2y''.$$

Hence

$$y = xy' - \frac{x^2y''}{2}.$$

Multiplying through by 2 and rearranging:

$$2y = 2xy' - x^2y'' \iff x^2y'' - 2xy' + 2y = 0.$$

This second-order differential equation, free of arbitrary constants, is satisfied by every member of the two-parameter family.

SOLUTION Exercise 6 — Population growth

1. “Rate proportional to size” gives

$$\frac{dP}{dt} = kP.$$

Separating variables: $\int \frac{dP}{P} = \int k dt$, so $\ln P = kt + c$, i.e.

$$P = P_0 e^{kt}, \quad \text{where } P_0 = P(0).$$

Doubling in 20 years: $2P_0 = P_0 e^{20k}$, so $e^{20k} = 2$ and

$$k = \frac{\ln 2}{20}. \quad \text{Hence } P = P_0 e^{(\ln 2)t/20} = P_0 \cdot 2^{t/20}.$$

2. Tripling:
- $3P_0 = P_0 e^{kt}$
- , so
- $e^{kt} = 3$
- and

$$t = \frac{\ln 3}{k} = \frac{20 \ln 3}{\ln 2} \approx \frac{20 \times 1.0986}{0.6931} \approx 31.7.$$

The population triples after approximately 32 years (to the nearest year).

SOLUTION Exercise 7 — Newton's law of cooling

1. The equation is $\frac{d\theta}{dt} = -k(\theta - 20)$. Separating variables:

$$\int \frac{d\theta}{\theta - 20} = \int -k dt \implies \ln |\theta - 20| = -kt + c.$$

Hence $\theta - 20 = Ce^{-kt}$. At $t = 0$, $\theta = 80$, so $C = 80 - 20 = 60$. Therefore

$$\theta = 20 + 60e^{-kt}.$$

2. At $t = 10$, $\theta = 60$:

$$60 = 20 + 60e^{-10k} \implies e^{-10k} = \frac{40}{60} = \frac{2}{3}.$$

Taking logarithms: $-10k = \ln \frac{2}{3} = -\ln \frac{3}{2}$, so

$$k = \frac{1}{10} \ln \frac{3}{2}.$$

3. After a further 10 minutes means $t = 20$:

$$\theta = 20 + 60e^{-20k} = 20 + 60(e^{-10k})^2 = 20 + 60\left(\frac{2}{3}\right)^2 = 20 + 60 \cdot \frac{4}{9} = 20 + \frac{80}{3}.$$

$$\theta = \frac{140}{3} \approx 46.7^\circ\text{C}.$$

SOLUTION Exercise 8 — Resisted motion with driving force

1. Newton's second law along the line of motion (driving force positive, resistance opposing):

$$m \frac{dv}{dt} = 20 - 4v.$$

With $m = 2$: $2 \frac{dv}{dt} = 20 - 4v$, i.e.

$$\frac{dv}{dt} = 10 - 2v.$$

2. Separating variables:

$$\int \frac{dv}{10 - 2v} = \int dt \implies -\frac{1}{2} \ln |10 - 2v| = t + c.$$

So $10 - 2v = Ae^{-2t}$. Initial condition $v(0) = 0$: $A = 10$. Hence

$$10 - 2v = 10e^{-2t} \implies v = 5(1 - e^{-2t}).$$

3. As $t \rightarrow \infty$, $e^{-2t} \rightarrow 0$, so the terminal velocity is $v_T = 5 \text{ m s}^{-1}$ (equivalently, set $\frac{dv}{dt} = 0$: $10 - 2v = 0$).

Half the terminal velocity: $v = 2.5$:

$$2.5 = 5(1 - e^{-2t}) \implies e^{-2t} = \frac{1}{2} \implies t = \frac{\ln 2}{2} \approx 0.35 \text{ s.}$$

SOLUTION Exercise 9 — Cooling and sketch of the solution (12 marks)

1. Since the body (5°C initially) is warming towards the room temperature 30°C , $\theta < 30$ and θ increases. Newton's law of cooling applies with the temperature difference $\theta - 30$:

$$\frac{d\theta}{dt} = -k(\theta - 30), \quad k > 0.$$

The constant is taken positive with a negative sign: since $\theta - 30 < 0$, the right-hand side is positive, correctly giving an increasing temperature. [M1 A1]

2. Separating variables:

$$\int \frac{d\theta}{\theta - 30} = \int -k dt \implies \ln |\theta - 30| = -kt + c,$$

$$\text{so } \theta - 30 = Ce^{-kt}.$$

[M1]

At $t = 0$, $\theta = 5$: $C = 5 - 30 = -25$, hence

$$\theta = 30 - 25e^{-kt}. \quad [\text{A1}]$$

At $t = 5$, $\theta = 15$:

$$15 = 30 - 25e^{-5k} \implies e^{-5k} = \frac{15}{25} = \frac{3}{5}. \quad [\text{M1}]$$

Therefore

$$-5k = \ln \frac{3}{5} \implies k = \frac{1}{5} \ln \frac{5}{3}. \quad [\text{A1}]$$

(With $k = \frac{1}{5} \ln \frac{5}{3} \approx 0.102$.)

3. Setting $\theta = 25$:


$$25 = 30 - 25e^{-kt} \implies e^{-kt} = \frac{5}{25} = \frac{1}{5}. \quad [\text{M1}]$$

Hence

$$t = \frac{\ln 5}{k} = \frac{5 \ln 5}{\ln(5/3)} \approx \frac{5 \times 1.6094}{0.5108} \approx 15.8. \quad [\text{A1}]$$

The body reaches 25°C after approximately 15.8 minutes. [B1]

4. The graph starts at $\theta = 5$ when $t = 0$, is increasing and concave down, and approaches the horizontal asymptote $\theta = 30$ as $t \rightarrow \infty$.



Warming curve $\theta = 30 - 25e^{-kt}$ with asymptote $\theta = 30$.

[B1 shape through (0, 5), B1 asymptote $\theta = 30$ labelled]

Examiner's expectations: correct sign discussion in (a); clean separation of variables and use of both data points in (b); exact logarithmic forms accepted throughout; the sketch must show monotonic increase, correct curvature and the asymptote.

SOLUTION Exercise 10 — Vertical projection with resistance (14 marks)

1. While the ball rises, the velocity v is positive (upwards). Two forces act on the ball:

- its weight mg , acting downwards;
- the resistance mkv , opposing the motion, hence also acting downwards while the ball rises. [B1]

Both forces are therefore negative relative to the upward positive direction. Newton's second law gives

$$m \frac{dv}{dt} = -mg - mkv, \quad [\text{M1}]$$

and dividing by m :

$$\frac{dv}{dt} = -(g + kv). \quad [\text{A1}]$$

2. Separating variables:

$$\int \frac{dv}{g + kv} = - \int dt \implies \frac{1}{k} \ln |g + kv| = -t + c. \quad [\text{M1}]$$

Hence $g + kv = Ae^{-kt}$. [A1] At $t = 0$, $v = u$: $A = g + ku$. [M1] Therefore

$$kv = (g + ku)e^{-kt} - g,$$

and dividing by k :

$$v = \left(u + \frac{g}{k}\right)e^{-kt} - \frac{g}{k}. \quad [\text{A1}]$$

(One mark for correct separation, one for integration, one for applying the initial condition, one for the manipulation to the required form.)

3. At the greatest height, $v = 0$:

$$\left(u + \frac{g}{k}\right)e^{-kT} = \frac{g}{k} \implies e^{-kT} = \frac{g/k}{u + g/k} = \frac{g}{g + ku}. \quad [\text{M1}]$$

Taking reciprocals: $e^{kT} = \frac{g + ku}{g} = 1 + \frac{ku}{g}$. [M1] Taking logarithms:

$$T = \frac{1}{k} \ln\left(1 + \frac{ku}{g}\right). \quad [\text{A1}]$$

4. Using $v \frac{dv}{dx} = -(g + kv)$ with x measured upwards from the point of projection:

$$\int \frac{v dv}{g + kv} = - \int dx. \quad [\text{M1}]$$

Write $\frac{v}{g + kv} = \frac{1}{k} \cdot \frac{kv}{g + kv} = \frac{1}{k} \left(1 - \frac{g}{g + kv}\right)$. Then

$$\int \frac{v dv}{g + kv} = \frac{1}{k} \int \left(1 - \frac{g}{g + kv}\right) dv = \frac{v}{k} - \frac{g}{k^2} \ln |g + kv| + C.$$

Applying the limits: $v = u$ at $x = 0$, and $v = 0$ at $x = H$:

$$H = \int_0^u \frac{v dv}{g + kv} = \left[\frac{v}{k} - \frac{g}{k^2} \ln(g + kv) \right]_0^u = \frac{u}{k} - \frac{g}{k^2} \ln\left(\frac{g + ku}{g}\right). \quad [\text{M1}]$$


Hence the greatest height is

$$H = \frac{u}{k} - \frac{g}{k^2} \ln\left(1 + \frac{ku}{g}\right). \quad [\text{A1}]$$

Examiner's expectations: in (a) the direction of both forces must be justified; in (d) the division $\frac{v}{g + kv} = \frac{1}{k} \left(1 - \frac{g}{g + kv}\right)$ is the key step; answers must be given exactly in the required form.

SOLUTION Exercise 11 — Cyclist freewheeling downhill (16 marks)

1. The forces on the cyclist are: the weight mg vertically downwards, the normal reaction R perpendicular to the slope, and the resistance kv^2 acting up the slope (opposing the motion).



Forces on the cyclist; the component $mg \sin \alpha$ acts down the slope.

[B1 diagram with three forces, B1 resistance up the slope]

Resolving along the slope (down the slope positive), Newton's second law gives

$$m \frac{dv}{dt} = mg \sin \alpha - kv^2. \quad [\text{B1}]$$

2. At terminal speed the acceleration is zero: $\frac{dv}{dt} = 0$. [M1] Hence

$$mg \sin \alpha - kv_T^2 = 0 \quad \Rightarrow \quad kv_T^2 = mg \sin \alpha, \quad [\text{M1}]$$

so

$$v_T = \sqrt{\frac{mg \sin \alpha}{k}}. \quad [\text{A1}]$$

3. With $a = v \frac{dv}{dx}$, the equation of motion becomes

$$v \frac{dv}{dx} = g \sin \alpha - \frac{k}{m} v^2. \quad [\text{B1}]$$

Note that $g \sin \alpha = \frac{k}{m} v_T^2$ from part (b), so

$$v \frac{dv}{dx} = \frac{k}{m} (v_T^2 - v^2). \quad [\text{M1}]$$

Separating variables:

$$\int \frac{v dv}{v_T^2 - v^2} = \frac{k}{m} \int dx \quad \Rightarrow \quad -\frac{1}{2} \ln |v_T^2 - v^2| = \frac{k}{m} x + c. \quad [\text{M1 A1}]$$

Initial condition: $v = 0$ when $x = 0$, so $c = -\frac{1}{2} \ln v_T^2$. [M1] Therefore

$$\ln \left(\frac{v_T^2 - v^2}{v_T^2} \right) = -\frac{2kx}{m} \implies 1 - \frac{v^2}{v_T^2} = e^{-2kx/m},$$

i.e.

$$v^2 = v_T^2 (1 - e^{-2kx/m}). \quad [\text{A1}]$$

4. Half the terminal speed: $v = \frac{v_T}{2}$, so $v^2 = \frac{v_T^2}{4}$:

$$\frac{1}{4} = 1 - e^{-2kx/m} \implies e^{-2kx/m} = \frac{3}{4}. \quad [\text{M1}]$$

Taking logarithms: $-\frac{2kx}{m} = \ln \frac{3}{4} = -\ln \frac{4}{3}$, hence

$$x = \frac{m}{2k} \ln \frac{4}{3}. \quad [\text{M1 A1}]$$


5. Possible assumptions (any one): [B1]

- the resistance is taken as exactly kv^2 — in reality air resistance is only approximately quadratic and also depends on wind and the rider's posture;
- the slope angle α is constant — real roads vary in gradient;
- no friction in the bearings and no pedalling — a real freewheeling cyclist still experiences rolling resistance.

The model is a reasonable first approximation but ignores these effects.

Examiner's expectations: a clear force diagram with the resistance directed up the slope; correct use of $g \sin \alpha = \frac{k}{m} v_T^2$ to simplify before separating; careful handling of the constant of integration using $v(0) = 0$; exact logarithmic answers. A common error is to write the resistance as $+kv^2$ or to forget that $v < v_T$ throughout, so $v_T^2 - v^2 > 0$ and the logarithm is well defined.

9 SUMMARY SHEET



Mind map of Chapter FMA08: Modelling With Differential Equations.

FICHE BILAN L'essentiel à connaître pour l'examen

Key definitions and ideas

- A **differential equation** (DE) is an equation linking a quantity and its rate(s) of change, e.g. $\frac{dy}{dx} = ky$.
- **Modelling**: translate a real situation (cooling coffee in Bamenda, a taxi braking in Douala) into a DE, solve it, then interpret the answer in context.
- To **form a DE from a family of curves** $y = f(x, c_1, \dots, c_n)$: differentiate n times and eliminate the n arbitrary constants.
- **Newton's law of cooling**: the rate of change of temperature Q of a body is proportional to the difference between Q and the ambient temperature Q_0 :

$$\frac{dQ}{dt} = k(Q - Q_0), \quad k < 0 \text{ for cooling.}$$

- **Resisted motion**: a particle of mass m moving in a straight line against a resistance $R(v)$ (often $R = mkv$ or $R = mkv^2$) obeys Newton's second law $m \frac{dv}{dt} = F - R(v)$.

- **Terminal velocity** v_T : the limiting speed when acceleration vanishes, i.e. when driving force = resistance.

Laws and formulas to know

- Newton's cooling solution: with $\theta = Q - Q_0$, $\frac{d\theta}{dt} = k\theta$ gives

$$Q - Q_0 = Ae^{kt}, \quad A = Q(0) - Q_0.$$

- Linear resistance, velocity vs time ($R = mkv$, constant driving force F):

$$\frac{dv}{dt} = \frac{F}{m} - kv \implies v = \frac{F}{mk} + \left(v_0 - \frac{F}{mk}\right)e^{-kt}, \quad v_T = \frac{F}{mk}.$$

- Velocity vs displacement: use the chain rule

$$\frac{dv}{dt} = v \frac{dv}{dx} \implies mv \frac{dv}{dx} = F - mkv,$$

then separate: $\int \frac{v}{F - mkv} dv = \int \frac{dx}{m}.$

- Standard integrals used constantly: $\int \frac{du}{u} = \ln |u| + c$ and $\int \frac{du}{a + bu} = \frac{1}{b} \ln |a + bu| + c.$

Methods (step by step)

1. Set up: define the variable (with units), write the physical law in symbols, fix the sign of each term (resistance opposes motion).
2. Separate: put all v (or Q) terms on one side, all t (or x) terms on the other.
3. Integrate: usually a logarithm appears; do not forget the constant.
4. Apply conditions: use $v(0) = v_0$ or $Q(0) = Q_1$ to find the constant, then a second measurement to find k if needed.
5. Interpret: state the limit as $t \rightarrow \infty$ (temperature tends to Q_0 ; velocity tends to v_T) and answer the question asked, with units.

Common mistakes to avoid

- Wrong sign in Newton's law: for cooling write $k < 0$ (or write $\frac{dQ}{dt} = -k(Q - Q_0)$ with $k > 0$). A positive k makes the temperature explode.
- Forgetting that resistance always opposes motion: when the particle moves downwards under gravity, resistance acts upwards.
- Mixing the two forms of acceleration: use $\frac{dv}{dt}$ when time is involved, $v \frac{dv}{dx}$ when displacement is involved.
- Dropping the modulus in $\ln |Q - Q_0|$ or forgetting the constant of integration before applying initial conditions.

- Solving for v but never answering the actual question (time? distance? temperature at a given instant?).
- Eliminating constants incorrectly when forming a DE: with two constants you must differentiate twice.

GCE tips

- The GCE often gives a cooling problem in two stages: first find the constant A , then use a second reading to find k ; keep k in exact logarithmic form as long as possible.
- In resisted motion, marks are awarded for a correct force diagram and a correct sign convention before any integration.
- When asked to “show that” a DE holds, start from Newton’s second law and make every step explicit.
- Always end with a sentence of interpretation: examiners reward physical meaning (e.g. “the body approaches room temperature”).
- Check dimensions: k in $\frac{dQ}{dt} = k(Q - Q_0)$ has unit s^{-1} (or min^{-1}); a quick unit check catches many errors.



Signed • OnBuch+

ONBUCH+ TEACHING TEAM
FOLLOWS THE OFFICIAL MINESEC SYLLABUS

OnBuch+