

BIRZEIT UNIVERSITY

Department of Electrical & Computer Engineering
ENCS4110 – Computer Design Laboratory

Experiment 07

Character LCD Display Interface

Date: July 2026

7 Character LCD Display Interface

Learning Objectives

After completing this experiment, you will be able to:

- Understand the architecture and operation of the HD44780-based 16x2 LCD module.
- Differentiate between command and data registers and their respective control signals.
- Configure the LCD in 4-bit mode to minimize GPIO pin usage.
- Implement the initialization sequence for 4-bit LCD operation.
- Send commands and data to the LCD using proper timing and enable pulse sequences.
- Display text strings at specific cursor positions on the LCD.
- Implement scrolling and dynamic display effects using LCD commands.
- Integrate LCD interfacing with GPIO and interrupt-driven input from push buttons.

Experiment Overview

This experiment introduces LCD interfacing using the HD44780-based 16x2 character display module. You will learn the controller's architecture, implement 4-bit communication mode to minimize GPIO usage, and create a reusable LCD driver library with functions for initialization, command transmission, and data display. By the end of this lab, you will be able to interface an LCD with the TM4C123 microcontroller and create interactive display applications combining LCD output with GPIO input and interrupts.

7.1 Theoretical Background

7.1.1 HD44780 LCD Controller Architecture

The HD44780 is an LCD controller/driver developed by Hitachi and widely adopted as an industry standard for character-based LCD modules. It provides a simple microprocessor interface for controlling alphanumeric displays with minimal external components.

7.1.1.1 LCD Module Overview

The 16x2 LCD module consists of:

- **HD44780 Controller**: Manages display operations, character generation, and timing
- **LCD Panel**: 2 rows x 16 columns of character positions
- **Character Generator ROM (CGROM)**: Contains 208 predefined character patterns (alphanumeric, symbols, Japanese kana)
- **Character Generator RAM (CGRAM)**: 64 bytes for up to 8 user-defined custom characters (5x8 pixels each)
- **Display Data RAM (DDRAM)**: 80 bytes storing characters currently displayed (40 bytes per line)
- **Backlight**: Optional LED backlight for improved visibility

The controller handles all low-level display refresh, character rendering, and cursor management automatically. The microcontroller simply writes characters to DDRAM and issues commands for cursor positioning, display control, and special effects.

7.1.1.2 LCD Registers

The HD44780 has two main registers accessible by the microcontroller:

Instruction Register (IR) The Instruction Register receives commands that control display operations:

- Clear display and return cursor to home
- Set cursor position in DDRAM
- Control display on/off, cursor visibility, and blinking
- Set entry mode (cursor direction, display shift)
- Shift cursor or entire display left/right
- Configure interface width (4-bit or 8-bit), number of lines, and font size

Data Register (DR) The Data Register receives character codes (ASCII) to be displayed:

- Writing to DR displays a character at the current cursor position
- The cursor automatically advances after each write (direction set by entry mode)
- Reading from DR retrieves the character at the current cursor position (rarely used)

7.1.2 LCD Pin Configuration

The HD44780 interface consists of 16 pins (some modules have 18 pins with additional backlight control):

Pin	Name	Description
1	VSS	Ground (0V)
2	VDD	Power supply (+5V or +3.3V)
3	V0	Contrast adjustment (connect to potentiometer)
4	RS	Register Select: 0 = Instruction (command), 1 = Data (character)
5	RW	Read/Write: 0 = Write to LCD, 1 = Read from LCD (usually grounded for write-only)
6	E	Enable: Falling edge latches data/command into LCD
714	D0-D7	8-bit data bus (D0-D3 unused in 4-bit mode)
15	A	Backlight anode (+5V, typically with series resistor)
16	K	Backlight cathode (Ground)

Table 7.1: HD44780 LCD Pin Definitions

7.1.3 4-Bit vs. 8-Bit Communication Mode

The HD44780 supports two communication modes:

7.1.3.1 8-Bit Mode

- Uses all 8 data pins (D0-D7)
- Each command or character requires one write cycle
- Faster communication (single byte transfer)
- Requires 11 GPIO pins total (3 control + 8 data)

7.1.3.2 4-Bit Mode

- Uses only upper 4 data pins (D4-D7), D0-D3 are left unconnected
- Each command or character requires two write cycles (upper nibble, then lower nibble)
- Slightly slower due to two transfers per byte
- Requires only 7 GPIO pins total (3 control + 4 data)
- **Preferred mode** for GPIO-constrained systems

4-Bit Communication Protocol:

1. Set RS and RW to appropriate values
2. Place upper 4 bits (bits 7-4) on D7-D4
3. Generate enable pulse: E high → delay → E low
4. Place lower 4 bits (bits 3-0) on D7-D4
5. Generate another enable pulse: E high → delay → E low

In this experiment, we use 4-bit mode with the following connections:

- **PB0** → RS (Register Select)
- **PB2** → E (Enable)
- **PB4-PB7** → D4-D7 (Data pins)
- **RW** → Ground (write-only operation)

7.1.4 LCD Initialization Sequence

Proper initialization is critical for reliable LCD operation. The HD44780 requires a specific sequence of commands with precise timing delays, especially during the transition to 4-bit mode.

7.1.4.1 Initialization Steps (4-Bit Mode)

The initialization sequence must account for the fact that the LCD powers up in 8-bit mode and must be switched to 4-bit mode:

1. **Wait for power-on stabilization**: Delay at least 40 ms after VDD rises to 4.5V
2. **Initial function set (8-bit interface)**: Send `0x30` (upper nibble only) three times:
   - First time: Wait $>$ 4.1 ms
   - Second time: Wait $>$ 100 μs
   - Third time: Wait $>$ 100 μs
3. **Switch to 4-bit mode**: Send `0x20` (upper nibble only), wait $>$ 100 μs
4. **Configure display parameters**: Now send full 8-bit commands in two nibbles:
   - `0x28`: Function set — 4-bit mode, 2 lines, 5x8 font
   - `0x0C`: Display control — Display ON, cursor OFF, blink OFF
   - `0x06`: Entry mode set — Increment cursor, no display shift
   - `0x01`: Clear display
   - `0x02`: Return home

Critical Note: Steps 2-3 send only the *upper nibble* because the LCD is still in 8-bit mode. After step 3 completes, the LCD switches to 4-bit mode, and all subsequent commands must be sent as two nibbles (upper first, then lower).

7.1.5 LCD Command Set

The HD44780 supports a comprehensive set of commands for display control, cursor manipulation, and special effects.

Command	Hex Code	Description
Clear Display	`0x01`	Clears entire display, sets DDRAM address 0, cursor to home
Return Home	`0x02`	Sets DDRAM address 0, cursor to home (display content unchanged)
Entry Mode Set	`0x04-0x07`	Controls cursor direction and display shift
	`0x04`	Cursor moves left, no shift
	`0x06`	Cursor moves right, no shift (default)
	`0x05`	Cursor moves left, display shifts right
	`0x07`	Cursor moves right, display shifts left
Display Control	`0x08-0x0F`	Controls display, cursor, and blink on/off
	`0x08`	Display OFF
	`0x0C`	Display ON, cursor OFF, blink OFF
	`0x0E`	Display ON, cursor ON, blink OFF
	`0x0F`	Display ON, cursor ON, blink ON
Cursor/Display Shift	`0x10-0x1F`	Shifts cursor or display left/right
	`0x10`	Shift cursor left
	`0x14`	Shift cursor right
	`0x18`	Shift display left
	`0x1C`	Shift display right
Function Set	`0x20-0x3F`	Sets interface length, line number, font
	`0x28`	4-bit mode, 2 lines, 5x8 font
	`0x38`	8-bit mode, 2 lines, 5x8 font
Set DDRAM Address	`0x80 + addr`	Positions cursor at DDRAM address (see §7.1.6 for the full address layout)

Table 7.2: Common HD44780 LCD Commands

7.1.6 DDRAM Address Mapping

The Display Data RAM (DDRAM) is 80 bytes, but only 32 bytes (16 per line) are visible at any time. Understanding the address mapping is essential for cursor positioning:

Display Position	DDRAM Address	Command
Line 1, Column 0	`0x00`	`0x80`
Line 1, Column 1	`0x01`	`0x81`
Line 1, Column 15	`0x0F`	`0x8F`
Line 2, Column 0	`0x40`	`0xC0`
Line 2, Column 1	`0x41`	`0xC1`
Line 2, Column 15	`0x4F`	`0xCF`

Table 7.3: DDRAM Address Mapping for 16x2 LCD

Formula for cursor positioning:

$$\text{Command} = \begin{cases} 0x80 + \text{column} & \text{for line 1 (row 0)} \\ 0xC0 + \text{column} & \text{for line 2 (row 1)} \end{cases}$$

7.1.7 Timing Requirements

The HD44780 datasheet specifies minimum pulse widths and setup/hold times (e.g., enable pulse width ≥450 ns, enable cycle ≥1 μs, RS/data setup and hold times of tens of nanoseconds) that are far shorter than anything achievable with a simple software delay loop — in practice, the driver below uses generously-rounded, safe delays instead of hitting those minimums precisely:

- **Around each enable pulse** (`LCD_EnablePulse()`): a ∼1 μs `delay_us()` before and after toggling E, comfortably covering the enable pulse width/cycle and RS/data setup-hold requirements together.
- **After most commands**: ∼1-2 ms (datasheet minimum is ∼40 μs).
- **After `Clear Display (0x01)` or `Return Home (0x02)`**: ∼2 ms (datasheet minimum is ∼1.6 ms), since these two commands take noticeably longer than other commands.

We implement these delays using the SysTick timer (at 50 MHz, 1 μs = 50 clock cycles) for precise, non-blocking-free timing.

7.1.8 LCD Driver Implementation Strategy

A well-structured LCD driver separates concerns into distinct layers:

Low-Level Functions

- `LCD_EnablePulse()`: Generates enable pulse (E high → delay → E low)
- `LCD_SendNibble()`: Sends 4 bits on D7-D4 with enable pulse
- `delay_us()`, `delay_ms()`: Precise timing using SysTick

Mid-Level Functions

- `LCD_Command()`: Sends 8-bit command (RS=0) as two nibbles
- `LCD_Data()`: Sends 8-bit character (RS=1) as two nibbles

High-Level API

- `LCD_Init()`: Complete initialization sequence
- `LCD_Clear()`: Clears display
- `LCD_SetCursor(row, col)`: Positions cursor
- `LCD_Print(string)`: Displays string at current cursor position

7.2 Procedure

7.2.1 Example: Basic LCD Driver Implementation




Figure 7.1: LCD Connection Schematic - TM4C123 to 16×2 HD44780 LCD Module[1]

This figure shows the complete wiring diagram for connecting the 16x2 LCD module to the TM4C123 microcontroller using 4-bit mode. The connections are:

- **Power**: VDD to VBus, VSS to Ground, V0 to contrast potentiometer
- **Control**: RS to PB0, E to PB2, RW to Ground (write-only)
- **Data**: D4-D7 to PB4-PB7 respectively
- **Backlight**: A to VBus, K to Ground

The contrast potentiometer (typically 10kΩ) allows adjustment of the display visibility - rotating it changes the voltage on V0 pin between 0V and VDD. The following code demonstrates a complete LCD driver in 4-bit mode with initialization, command/data transmission, and text display functions.

[1]Source: https://microcontrollerslab.com/16x2-lcd-interfacing-with-tm4c123-tiva-launchpad-keil-uvision/

7.2.1.1 LCD Header File

```c
#ifndef LCD_H
#define LCD_H

#include "TM4C123.h"

// LCD pin definitions (connected to PORTB)
#define RS         (1 << 0)  // PB0
#define RW         (1 << 1)  // PB1
#define EN         (1 << 2)  // PB2
#define DATA_MASK  0xF0      // PB4-PB7

// Function prototypes
void LCD_Init(void);
void LCD_Command(unsigned char cmd);
void LCD_Data(unsigned char data);
void LCD_Clear(void);
void LCD_SetCursor(unsigned char row, unsigned char col);
void LCD_Print(char *str);
void delay_us(int us);
void delay_ms(int ms);

#endif
```

Listing 7.1: LCD driver header file (`lcd.h`)

7.2.1.2 LCD Implementation File

```c
#include "lcd.h"

#define CYCLES_PER_US   (SystemCoreClock / 1000000u)



//====================[ SysTick Delay Functions ]====================
void SysTick_Init(void)
{
    SysTick->CTRL = 0;
    SysTick->LOAD = CYCLES_PER_US - 1;  // 1us delay at 50MHz
    SysTick->VAL = 0;
    SysTick->CTRL = 0x5;     // Enable with system clock
}

void delay_us(int us)
{
    SysTick->LOAD = (CYCLES_PER_US * us) - 1;
    SysTick->VAL = 0;
    SysTick->CTRL = 0x5; // Enable with system clock
    while ((SysTick->CTRL & 0x10000) == 0);
    SysTick->CTRL = 0;
}

void delay_ms(int ms)
{
```

```
    while (ms--)
        delay_us(1000);
}

//====================[ LCD Helper Functions ]====================
void LCD_EnablePulse(void)
{
    delay_us(1);
    GPIOB->DATA |= EN;
    delay_us(1);
    GPIOB->DATA &= ~EN;
    delay_us(1);
}

void LCD_SendNibble(unsigned char nibble)
{
    // Send nibble to PB4-PB7
    GPIOB->DATA = (GPIOB->DATA & ~DATA_MASK) | ((nibble << 4) & DATA_MASK);
    LCD_EnablePulse();
}

//====================[ LCD Initialization ]====================
void LCD_Init(void)
{
    // Enable clock to PORTB
    SYSCTL->RCGCGPIO |= (1 << 1);
    while ((SYSCTL->PRGPIO & (1 << 1)) == 0)
        ;

    // Configure PB0 (RS), PB1 (RW), PB2 (EN), PB4-PB7 (data) as output
    GPIOB->DIR |= RS | RW | EN | DATA_MASK;
    GPIOB->DEN |= RS | RW | EN | DATA_MASK;
    GPIOB->DATA &= ~(RS | RW | EN | DATA_MASK);  // Clear all

    SysTick_Init();

    delay_ms(50);  // Wait for LCD to power up

    // Initialization sequence (8-bit interface mode to start)
    LCD_SendNibble(0x03);
    delay_ms(5);

    LCD_SendNibble(0x03);
    delay_us(150);

    LCD_SendNibble(0x03);
    delay_us(150);

    LCD_SendNibble(0x02);  // Set 4-bit mode
    delay_us(150);

    // Now in 4-bit mode: use full commands
    LCD_Command(0x28); // Function set: 4-bit, 2 lines, 5x8 dots
    LCD_Command(0x0C); // Display ON, Cursor OFF
    LCD_Command(0x06); // Entry mode: increment cursor
    LCD_Command(0x01); // Clear display
```

```
    delay_ms(2);
}

//====================[ LCD Command/Data API ]====================
void LCD_Command(unsigned char command)
{
    GPIOB->DATA &= ~RS; // RS = 0 for command
    delay_us(1);
    LCD_SendNibble(command >> 4);      // Upper nibble
    LCD_SendNibble(command & 0x0F);    // Lower nibble
    delay_ms(2);
}

void LCD_Data(unsigned char data)
{
    GPIOB->DATA |= RS; // RS = 1 for data
    delay_us(1);
    LCD_SendNibble(data >> 4);
    LCD_SendNibble(data & 0x0F);
    delay_ms(1);
}

void LCD_Clear(void)
{
    LCD_Command(0x01);
    delay_ms(2);
}

void LCD_SetCursor(unsigned char row, unsigned char col)
{
    unsigned char address = (row == 0) ? 0x80 + col : 0xC0 + col;
    LCD_Command(address);
    delay_ms(1);
}

void LCD_Print(char *str)
{
    while (*str)
    {
        LCD_Data(*str++);
    }
}
```

Listing 7.2: LCD driver implementation (`lcd.c`)

7.2.1.3 Main Application

```
#include "TM4C123.h"
#include "lcd.h"



int main(void)
```

```
{

    LCD_Init();
    LCD_Clear();        // Ensure display is clear
    LCD_SetCursor(0,0); // Set cursor to beginning
    LCD_Print("ENCS4110 Lab");

    while(1)
    {
    }
}
```

Listing 7.3: Main application using LCD driver (`main.c`)

7.2.2 Code Explanation

Initialization Sequence The `LCD_Init()` function implements the complete 4-bit initialization:

1. Enables the PORTB clock, then **polls `SYSCTL->PRGPIO` bit 1** until it reads back as ready before touching `GPIOB` — this is the peripheral-ready-register alternative to the fixed-`NOP`-count delay described in Experiment 4, and configures pins as outputs. The driver also configures PB1 (`RW`) as an output and drives it low in software; this is the code-level equivalent of the hardware section's "RW to Ground" wiring, so no physical wire from PB1 to the LCD's RW pin is required.
2. Waits 50 ms for LCD power-on stabilization
3. Sends `0x03` (upper nibble) three times with delays (8-bit mode reset)
4. Sends `0x02` (upper nibble) to switch to 4-bit mode
5. Sends configuration commands: `0x28` (4-bit, 2 lines), `0x0C` (display on), `0x06` (entry mode), `0x01` (clear)

Nibble Transmission The `LCD_SendNibble()` function:

- Masks out current data bits (PB4-PB7)
- Places the 4-bit nibble on PB4-PB7 (shifted left by 4)
- Generates enable pulse: delay → E high → delay → E low → delay

Command vs. Data

- `LCD_Command()`: Sets RS=0, sends upper nibble, sends lower nibble
- `LCD_Data()`: Sets RS=1, sends upper nibble, sends lower nibble

Cursor Positioning The `LCD_SetCursor(row, col)` function calculates the DDRAM address:

```
address = (row == 0) ? 0x80 + col : 0xC0 + col;
```

Then sends the address as a command.

String Printing The `LCD_Print(str)` function iterates through the string and sends each character using `LCD_Data()`.

7.2.3 Tasks

7.2.3.1 Task 1: Display Your Name and ID

Update the main program to display your name on the first line and your student ID on the second line of the LCD.

Requirements:

- Clear the display
- Set cursor to line 1, column 0
- Print your name (up to 16 characters)
- Set cursor to line 2, column 0
- Print your student ID

Hint:

```
LCD_Clear();
LCD_SetCursor(0, 0);  // Line 1
LCD_Print("Your Name");
LCD_SetCursor(1, 0);  // Line 2
LCD_Print("ID: 1234567");
```

7.2.3.2 Task 2: Button-Controlled Name Scrolling

Write a program that displays your name on the LCD and allows the user to scroll the text left or right using the two on-board push buttons (SW1 and SW2).

Requirements:

- Display your name on line 1
- Configure SW1 (PF4) and SW2 (PF0) with GPIO interrupts (falling edge, internal pull-up)
- When SW1 is pressed: Shift display left (command `0x18`)
- When SW2 is pressed: Shift display right (command `0x1C`)
- The display should not scroll automatically; only respond to button presses

7.2.3.3 Task 3: Bidirectional Continuous Scrolling

Write a program that displays your name on line 1 and your student ID on line 2, with continuous scrolling in opposite directions after a button press.

Requirements:

- Display your name on line 1 and ID on line 2
- Initially, the display is static (no scrolling)
- When SW1 is pressed, start continuous scrolling:
  - Line 1 scrolls right
  - Line 2 scrolls left
- Pressing SW1 again stops the scrolling
- Use a timer interrupt to handle the scrolling at a fixed interval (e.g., every 500 ms)