

```
EXP-14.C
1  #include <reg51.h>
2  #include <stdio.h>
3
4  void main(void)
5  {
6      SCON = 0x50;      // UART mode 1, 8-bit UART, enable receiver
7      TMOD = 0x20;      // Timer1, Mode2 (8-bit auto reload)
8      TH1 = 0xFD;       // 9600 baud rate (11.0592 MHz crystal)
9      TR1 = 1;          // Start Timer1
10     TI = 1;           // Set TI to send the first character
11
12     while(1)
13     {
14         printf("Hello World!\n");
15     }
16 }
```

