OOMWOO Hall sensor board (rev 1, 2026-10-28). One design, fitted twice: dust bin present (magnet in the bin) and the LiDAR tower bumper (magnet in the tower cover). Omnipolar: either magnet pole works. OUT goes low with the magnet near; the main board pulls OUT up (47k), so open-drain and push-pull outputs both work. It samples at ~20-45 Hz.
Refs 87xx: unique on the OOMWOO panel.



J8701 to the main board HALL-BIN1 or HALL-TOWER1, pin 1 to pin 1:
1 3.3 V, 2 OUT, 3 GND



Mounting: 1x M2 (pad to GND)

OOMWOO Hall sensor		
Sheet: /		
File: Hall Sensor.kicad_sch		
Title: Hall sensor board (fit 2x)		
Size: USLetter	Date: 2026-10-28	**Rev: 1**
KiCad E.D.A. 10.0.4		Id: 1/1