

ON CHARACTERISTICS ⁽⁵⁾					
h_{FE}	DC Current Gain		$I_C = 0.1 \text{ mA}, V_{CE} = 1.0 \text{ V}$	40	
			$I_C = 1.0 \text{ mA}, V_{CE} = 1.0 \text{ V}$	70	
			$I_C = 10 \text{ mA}, V_{CE} = 1.0 \text{ V}$	100	300
			$I_C = 50 \text{ mA}, V_{CE} = 1.0 \text{ V}$	60	
			$I_C = 100 \text{ mA}, V_{CE} = 1.0 \text{ V}$	30	