

BCD

segment

	w	x	y	z		A	B	C	D	E	F	G
0	0	0	0	0		1	1	1	1	1	1	0
1	0	0	0	1		0	1	1	0	0	0	0
2	0	0	1	0		1	1	0	1	1	0	1
3	0	0	1	1		1	1	1	1	0	0	1
4	0	1	0	0		0	1	1	0	0	1	1
5	0	1	0	1		1	0	1	1	0	1	1
6	0	1	1	0		1	0	1	1	1	1	1
7	0	1	1	1		1	1	1	0	0	0	0
8	1	0	0	0		1	1	1	1	1	1	1
9	1	0	0	1		1	1	1	1	0	1	1
A	1	0	1	0		1	1	1	0	1	1	1
b	1	0	1	1		0	0	1	1	1	1	1
C	1	1	0	0		1	0	0	1	1	1	0
d	1	1	0	1		0	1	1	1	1	0	1
E	1	1	1	0		1	0	0	1	1	1	1
F	1	1	1	1		1	0	0	0	1	1	1

A

WX/YZ	00	01	11	10
00	1	0	1	1
01	0	1	1	1
11	1	0	1	1
10	1	1	0	1

Maxterms:

$$W + X + Y + Z'$$

$$W + X' + Y + Z$$

$$W' + X' + Y + Z'$$

$$W' + X + Y' + Z'$$

B

WX/YZ	00	01	11	10
00	1	1	1	1
01	1	0	1	0
11	0	1	0	0
10	1	1	0	1

Maxterms:

$$W + X' + Y + Z'$$

$$W' + X' + Z$$

$$X' + Y' + Z$$

$$W' + Y' + Z'$$

C

WX/YZ	00	01	11	10
00	1	1	1	0
01	1	1	1	1
11	0	1	0	0
10	1	1	1	1

Maxterms:

$$W + X + Y' + Z$$

$$W' + X' + Y'$$

$$W' + X' + Z$$

D

WX/YZ	00	01	11	10
00	1	0	1	1
01	0	1	0	1
11	1	1	0	1
10	1	1	1	0

Maxterms:

$$W + X + Y + Z'$$

$$W + X' + Y + Z$$

$$W' + X + Y' + Z$$

$$X' + Y' + Z'$$

E

WX/YZ	00	01	11	10
00	1	0	0	1
01	0	0	0	1
11	1	1	1	1
10	1	0	1	1

Maxterms:

$$W + X' + Y$$

$$X + Y + Z'$$

$$W + Z'$$

F

WX/YZ	00	01	11	10
00	1	0	0	0
01	1	1	0	1
11	0	1	1	1
10	1	1	1	1

Maxterms:

$$W' + X' + Y + Z'$$

$$W + Y' + Z'$$

$$W + X + Z'$$

$$W + X + Y'$$

G

WX/YZ	00	01	11	10
00	0	0	1	1
01	1	1	0	1
11	0	1	1	1
10	1	1	1	1

Maxterms:

$$W + X' + Y' + Z'$$

$$W' + X' + Y + Z$$

$$W + X + Y$$