

BRAC University
Department of Computer Science and Engineering
CSE420:Compiler Design

Examination: Quiz 2
Time: 25 min

Semester: Fall 25
Marks: 15

Name:		ID:	Section:
-------	--	-----	----------

1. Consider the following SLR grammar:

$S \rightarrow A D$
 $A \rightarrow \text{int} \mid \text{float}$
 $D \rightarrow (B) \mid \epsilon$
 $B \rightarrow \text{id} \mid B$

- (a) Construct the LR(0) automaton for the grammar above. [5]
- (b) Build the SLR(1) parsing table using the automaton. [5]
- (c) Show the parsing simulation using a stack for the input: **float (id)** [5]

[Note: Making the rule $B \rightarrow \text{id} , B \mid \text{id}$ could resolve the conflict]