maths

_travelers guide _for counting to infinity

4 channels	3 bus outs	25 min to 1 khz

[cycle] press · patch › then noon = 12 o'clock cw / ccw = clockwise / counter

an analog computer for music · envelopes, lfos, slew, offsets, logic, mixing

maths 2013 · 20 hp · no menus, no hidden functions

LEDs: green = + · red = –

01 channels 1 + 4

mx_01 · the function generators

[signal in]	slews whatever you patch · lag, portamento, a gate = rise / sustain / fall · ±10 v · also feeds the bus
[trig]	fires a 0 → 10 v rise then fall, no sustain · retriggers only while falling
[cycle]	loops it: an lfo · LED shows on · [cycle in] gate high (2.5 v+) does the same
[rise] [fall]	cw = slower · together they set the period
[vari-response]	log ‹ linear (the tick) › expo › hyper-expo (fig.01)
[unity out]	straight from the core, not on the bus · 0–8 v cycling · LED ● + ● –

02 control inputs

mx_02 · ±8 v

[rise cv] [fall cv]	linear · + = longer, – = shorter, around the knob
[both cv]	exponential, and backwards: + = faster, – = slower, the whole function
need more range?	add an offset from ch 2 or 3 into the cv jack
need attenuation?	run the cv through ch 2 or 3 first

03 pulse outs

mx_03 · 0 or 10 v

[eor] ch 1	goes high at the end of the rise · low at rest · pulse delay, clock division
[eoc] ch 4	goes high at the end of the fall · **high at rest**, LED on when idle
chain them	eor / eoc into the other channel's trig, signal or cycle input (fig.04)


04 channels 2 + 3

mx_04 · scale · invert · offset

[2 in]	nothing patched = a **±10 v** offset from the knob
[3 in]	nothing patched = a **±5 v** offset from the knob
[attenuverter]	noon = zero · cw = more, up to amplifying · ccw = upside down

_fig.01 : vari-response

four curves



log rises fast, then eases in · expo starts slow, then snaps
log = the longest cycles · extreme expo = the fastest


05 the bus

mx_05 · fig.02

[1] [2] [3] [4]	variable outs, after each attenuverter · each feeds sum and or until you patch it
[sum]	adds them, ±10 v · [inv] = the same, upside down
[or]	the highest voltage wins, 0–10 v · ignores negatives, so it rectifies
unused 2 / 3	set to noon or plug a dummy cable, or their offset rides the bus

_fig.02 : the bus


four channels, three answers



patch a var out = it leaves the bus · ch 1 + 4 unity outs never join it

_fig.06 : 281 mode

quadrature lfos



both cycling · eor › ch 4 trig · eoc › ch 1 trig = two lfos a quarter-cycle apart

10 the module

mx_10 · 2013

size	20 hp · 60 mA +12 v · 50 mA –12 v
2013 vs original	unity outs, inv out, bus + eor / eoc LEDs, cycle in, ±10 v offset on ch 2

07 shapes

mx_07 · one channel

triangle lfo
[cycle] on · rise, fall noon · linear · ch 2 into [both] sets the rate
unity or variable out

ramp / saw
same, rise full ccw, fall noon or more

attack / decay
gate or trigger into [trig]
retriggers while falling


attack / sustain / release
gate into [signal in]: rises to the gate level, holds, falls when it ends

clock / pulse
cycle it, take [eor] or [eoc] · [cycle in] = run / stop
ch 1: rise = rate, fall = width · ch 4: the reverse

pulse delay
gate into ch 1 [trig], take [eor]
rise = delay · fall = width

_fig.04 : counting clocks


trig · eor · eoc



one eor pulse per accepted trigger · here every third clock gets in

_fig.05 : an adsr from or

ch 1 + ch 4 › or



ch 4 fall = decay · ch 1 knob = sustain level · ch 1 fall = release · set 2 + 3 to noon

06 time

mx_06 · 25 minutes to 1 khz

slowest	rise and fall full cw, log response, plus cv: "slow-ver-drive"
fastest	extreme expo response, knobs ccw: audio rate
response	moving vari-response changes the times too
one rule	maths can slow a signal down but never speed it up

08 two channels

mx_08 · patches from the manual

adsr
gate › ch 1 [signal in] · ch 1 [eor] › ch 4 [trig] · take [or]
ch 4 fall = decay · ch 1 knob = sustain (below ch 4) · ch 1 fall = release

281 mode
both cycling · [eor] › ch 4 trig · [eoc] › ch 1 trig
two lfos 90° apart · nudge ch 1 cycle if they stall

bouncing ball
ch 1 rise ccw, fall 3:00 · ch 4 rise ccw, fall 11:00, linear · [eor] › ch 4 cycle in · ch 1 var out › ch 4 fall cv
trig ch 1 to drop the ball · ch 4 out › vca or lpg

arcade trill
ch 4 cycling, expo · [eoc] › ch 1 trig and ch 2 in · ch 2 (10:00) › ch 1 both
ch 1 rise noon, fall ccw · tiny ch 1 rise moves = big changes

independent contours
ch 1 var out back into its own [rise cv] or [fall cv] · its knob shapes that slope alone
vari-response at noon · take the unity out

pseudo-vca
audio into ch 1, rise + fall ccw · ch 2 cw (+ ch 3) until silent · envelope on ch 4, knob ccw › [sum]
asymmetrical clipping · try inv

trilling envelope
ch 1 [eor] › ch 4 [cycle in] · ch 4 rise 1:00, fall 11:00, expo · take [or]
trills on the fall · swap channels to trill on the rise

09 utilities

mx_09 · maths as a computer

clock divider
clock into [trig] · longer rise ignores more clocks
fall = width · too wide and it stays high

envelope / peak follower
audio into [signal in] · rise noon (or 3:00 for peaks) · fall sets the response
or out for a positive follower

rectify
half wave: any input › [or] · full wave: same signal into 2 and 3, 2 cw, 3 ccw › [or]

voltage mirror
cv into 2, knob full ccw · 3 empty, knob full cw › [sum]

gate extractor
signal into 2 · 3 negative = threshold · [sum] › ch 1 in, rise + fall 0 › [eor]
rise = how long above threshold · fall = gate length

logic inverter
gate into ch 4 [signal in] › [eoc]

flip-flop
set › ch 1 trig · reset › ch 1 both · rise ccw, fall cw, linear › [eoc]
forgets after about 3 minutes

_fig.03 : front panel

ch 4 mirrors ch 1



[01]	_ch 1 in : slew · ±10 v	[11]	_1–4 : attenuverters
[02]	_trig : fire a function	[12]	_ch 2 in : +10 v if empty
[03]	_cycle : loop · LED	[13]	_ch 3 in : +5 v if empty
[04]	_rise : up time	[14]	_var outs : feed the bus
[05]	_fall : down time	[15]	_or · sum · inv : the bus
[06]	_vari-resp. : log ‹› expo	[16]	_eor : end of rise
[07]	_rise cv : + = longer	[17]	_unity : ch 1 core out
[08]	_both cv : + = faster	[18]	_eoc : end of cycle
[09]	_fall cv : + = longer	[19]	_ch 4 : mirror of ch 1
[10]	_cycle in : gate = loop		

_where things hide

in the normals · mx_11

hidden voltages

- ch 2 empty +10 v offset
- ch 3 empty +5 v offset
- var outs empty all feed sum / or / inv

easy to miss

- eoc high at rest, low while busy
- both cv runs backwards: + = faster
- trig deaf during the rise

LED codes

unity · sum	● positive ● negative brightness = level
cycle	● cycling
eor · eoc	● pulse high