

ELECTRICAL ENGINEERING

Complete Technical Reference & Interview Guide

Concepts · Industrial Examples · Practical Applications · Interview Questions

- 1. Transformers
- 2. Motors
- 3. Protection Systems
- 4. SCADA
- 5. PLC (Programmable Logic Controller)
- 6. Power Systems
- 7. Power Electronics
- 8. Renewable Energy
- 9. Industrial Automation
- 10. Summary Quick-Reference Table

1. Transformers

1.1 Concept & Working Principle

A transformer transfers electrical energy between two or more circuits through electromagnetic induction, without a direct electrical connection, based on Faraday's Law.

$$V_1 / V_2 = N_1 / N_2 = I_2 / I_1$$

Where: V_1, V_2 = Primary/Secondary voltage | N_1, N_2 = Primary/Secondary turns | I_1, I_2 = Primary/Secondary current

Key Components

Component	Function
Core (CRGO steel)	Provides low-reluctance magnetic path
Primary Winding	Receives input energy
Secondary Winding	Delivers output energy
Tap Changer	Adjusts turns ratio for voltage regulation
Bushings	Insulated entry/exit for conductors
Conservator Tank	Handles oil expansion
Breather (Silica gel)	Removes moisture from air entering tank
Buchholz Relay	Detects internal faults (gas accumulation)

Types (by application)

- **Power Transformer** — used at generating stations (step-up), 400kV/220kV, high efficiency at full load
- **Distribution Transformer** — step-down at consumer end (11kV/415V), designed for varying load efficiency
- **Instrument Transformers** — CT (Current) & PT (Potential) for metering/protection
- **Auto Transformer** — single winding, used in motor starting (star-delta alternative)

Cooling Methods

Type	Description	Used In
ONAN	Oil Natural, Air Natural	Small/medium transformers
ONAF	Oil Natural, Air Forced	Fans added for higher rating
OFAF	Oil Forced, Air Forced	Large power transformers
OFWF	Oil Forced, Water Forced	Very high capacity, near water source

🏭 **Industrial Example — Steel Plant:** A 33kV/11kV, 20MVA power transformer steps down grid supply for arc furnace operations. Due to heavy inrush current during furnace startup, the transformer uses OFAF cooling and is protected by a differential + Buchholz relay combination to prevent internal fault damage.

✔ Practical Applications:

- Voltage step-up at generating stations for long-distance transmission (reduces I²R losses)
- Step-down at substations for industrial/residential distribution
- Isolation transformers for sensitive control panels (noise isolation)
- Auto-transformers for motor soft-starting

🎯 Interview Questions:

1. Why is the transformer core laminated? What happens if a solid core is used?
2. Explain the difference between Buchholz relay and differential relay protection.
3. What is the significance of the vector group (e.g., Dyn11) in transformer specification?
4. Why do we use CRGO steel instead of ordinary steel for cores?
5. What causes a transformer to hum, and how is magnetostriction related to this?
6. Explain the difference between copper loss and iron loss. Which one is load-dependent?
7. What is the purpose of an on-load tap changer (OLTC), and how does it differ from off-load tap changing?
8. Why is the star point of a transformer grounded in power systems?
9. What is inrush current in a transformer, and how does it affect protection relay settings?
10. Explain the procedure and purpose of the Sweep Frequency Response Analysis (SFRA) test.

2. Motors

2.1 Concept

Motors convert electrical energy into mechanical energy via electromagnetic force ($F = BIL$).

Type	Working Principle	Starting Method
Induction Motor (IM)	Rotating stator field induces current in rotor (slip-based)	DOL, Star-Delta, Soft Starter, VFD
Synchronous Motor	Rotor locked to stator field speed (needs DC excitation)	Requires auxiliary starting (damper winding/VFD)
DC Motor	Fixed field + commutated armature current	Rheostatic starter
Servo / Stepper Motor	Precise position/speed control	Driver-controlled (used in automation)

$$N_s = 120f / P \quad \text{Slip (\%)} = [(N_s - N_r) / N_s] \times 100$$

 **Industrial Example — Cement Plant:** A 3-phase squirrel cage induction motor (415V, 200HP) drives a raw mill. Due to high starting torque requirement, it uses a soft starter to limit inrush current (6-7× FLC) and reduce mechanical stress on the mill gearbox.

 Practical Applications:

- VFD-driven pumps/fans for energy savings (reduces power ~30% vs throttling)
- Star-Delta starters for medium HP motors (5.5kW-90kW range)
- Servo motors in CNC machines/robotics for precision positioning

 Interview Questions:

- Why does an induction motor never reach synchronous speed?
- Explain the difference between star-delta starting and soft starter in terms of torque profile.
- What causes a single-phasing fault, and what protection is used against it?
- Why is the starting current of an induction motor 6-8 times the full load current?
- Explain the working of a VFD (V/f control) and why it maintains constant torque at low speeds.

3. Protection Systems

3.1 Concept

Protection systems detect abnormal conditions (fault, overload, imbalance) and isolate the faulty section to prevent equipment damage and personnel hazard.

Relay Type	Function
Overcurrent (50/51)	Trips on excess current (instantaneous/time-delayed)
Differential (87)	Compares in/out current; trips on internal fault
Earth Fault (50N/51N)	Detects current leakage to ground
Distance Relay (21)	Used in transmission lines, measures impedance to fault
Buchholz Relay	Transformer gas/oil surge detection
REF (Restricted Earth Fault)	Sensitive internal earth fault protection for transformers

Protection Coordination principle: Downstream relay trips first (faster), upstream acts as backup (Time-Current grading).

🏭 **Industrial Example — Distribution Substation:** An 11kV feeder uses numerical relays (IDMT characteristic) with 50/51 + 50N/51N protection. Relay coordination ensures a fault on a specific feeder trips only that feeder's breaker — not the entire busbar.


- ✔ **Practical Applications:**
- Motor protection relays (thermal overload, phase imbalance, stall protection)
 - Transformer differential protection to isolate internal winding faults
 - Generator protection (loss of excitation, reverse power, over-fluxing)

- 🎯 **Interview Questions:**
1. Explain IDMT (Inverse Definite Minimum Time) relay characteristic and why it's used over fixed time relays.
 2. What is the difference between REF and standard differential protection?
 3. Why is CT saturation a concern in differential protection, and how is it mitigated?
 4. Explain zone of protection and why overlapping zones are necessary.
 5. What is the difference between primary and backup protection?

4. SCADA (Supervisory Control and Data Acquisition)

4.1 Concept

SCADA is a centralized system for monitoring and controlling industrial processes over large geographic areas (substations, pipelines, water treatment).



Component	Role
RTU (Remote Terminal Unit)	Collects field data, sends to master
MTU (Master Terminal Unit)	Central control/monitoring station
HMI	Operator interface (graphics, trends)
Historian	Logs data for trend analysis
Communication Protocol	Modbus, DNP3, IEC 61850 (substation), OPC-UA

 **Industrial Example — 132kV Substation:** SCADA (IEC 61850 protocol) remotely monitors breaker status, transformer temperature, and controls switchgear from a central control room, enabling operators to trip/close breakers without on-site presence.

✔ **Practical Applications:**

- Remote monitoring of unmanned substations
- Real-time alarm management in power plants
- Pipeline pressure/flow monitoring in oil & gas

🔗 **Interview Questions:**

- What is the difference between SCADA and DCS?
- Explain the role of RTU vs PLC in a SCADA system.
- What is IEC 61850, and why is it preferred in modern substations over Modbus?
- How does a SCADA system handle communication failure with an RTU (fail-safe design)?
- What is a Historian, and why is it critical for trend analysis?

5. PLC (Programmable Logic Controller)

5.1 Concept

A PLC is an industrial digital computer that executes control logic (Ladder Logic, FBD, ST) to automate machinery — replacing hardwired relay logic.



Programming Language	Use Case
Ladder Logic (LD)	Most common, resembles relay logic
Function Block Diagram (FBD)	Graphical, good for process control
Structured Text (ST)	Text-based, similar to programming languages
Sequential Function Chart (SFC)	Step-based sequential processes

 **Industrial Example — Bottling Plant Conveyor:** A PLC (Siemens S7-1200) controls motor start/stop sequences using ladder logic with interlocks, ensuring the filling station only activates when a bottle sensor confirms correct positioning, preventing spillage/jams.

-  **Practical Applications:**
- Motor interlocking (prevent simultaneous operation of conflicting equipment)
 - Sequential batch control in chemical processing
 - Safety interlocks (emergency stop, guard door sensing)

-  **Interview Questions:**
1. Explain the PLC scan cycle and why input/output scanning happens before/after logic execution.
 2. What is the difference between a Normally Open (NO) and Normally Closed (NC) contact in ladder logic?
 3. How do you implement motor interlocking logic in a ladder diagram (e.g., prevent two motors running together)?
 4. What is a "latching" circuit in PLC programming, and where is it used?
 5. Explain the difference between PLC and microcontroller-based control.

6. Power Systems

6.1 Concept

Power systems cover generation, transmission, and distribution of electrical energy, focusing on stability, load flow, and fault analysis.

Stage	Voltage Level	Key Concern
Generation	11kV-25kV	Synchronization, frequency control
Transmission	132kV-765kV	Minimizing losses, stability
Distribution	11kV/415V	Voltage regulation, load balancing

Key Concepts

- **Load Flow Analysis** — determines voltage/power at each bus (Newton-Raphson, Gauss-Seidel methods)
- **Fault Analysis** — symmetrical (3-phase) and unsymmetrical (LG, LL, LLG) faults
- **Power Factor** — $\cos(\phi)$ between voltage & current; low PF increases losses
- **Reactive Power Compensation** — capacitor banks to improve PF and voltage stability

🏭 **Industrial Example — Manufacturing Plant:** A plant with large induction motor loads operates at 0.75 PF. By installing a capacitor bank (APFC panel), PF is improved to 0.98, reducing kVA demand charges and I²R losses in cables.

✔ Practical Applications:

- Load flow studies for new substation planning
- Short circuit studies to size circuit breakers correctly
- Power factor correction to avoid utility penalties

🎯 Interview Questions:

1. Why is reactive power compensation important, and how do capacitor banks improve power factor?
2. Explain symmetrical vs unsymmetrical faults with examples.
3. What is the significance of the per-unit (p.u.) system in power system analysis?
4. Explain the difference between active power, reactive power, and apparent power.
5. What is load shedding, and when is it implemented in a power grid?

7. Power Electronics

7.1 Concept

Power electronics deals with conversion and control of electrical power using semiconductor devices (SCR, IGBT, MOSFET, Diode).

Converter Type	Function	Example
Rectifier (AC-DC)	Converts AC to DC	Battery chargers
Inverter (DC-AC)	Converts DC to AC	Solar inverters, UPS
Chopper (DC-DC)	Variable DC voltage control	EV motor control
Cycloconverter (AC-AC)	Frequency conversion	Large ship propulsion

VFD (Variable Frequency Drive) — Most Important Industrial Application

AC Supply --> Rectifier --> DC Bus (Capacitor) --> Inverter (IGBT) --> Variable V/f Output --> Motor

 **Industrial Example — Water Treatment Plant:** VFDs on pump motors match flow demand — instead of running at full speed and throttling with a valve, the VFD reduces motor speed directly, saving up to 40% energy (Affinity Laws: Power ∝ Speed³).

- ✔ **Practical Applications:**
- VFDs for energy-efficient pump/fan control
 - UPS systems for critical load backup (hospitals, data centers)
 - Soft starters for reducing motor starting current

- 🎯 **Interview Questions:**
1. Explain the working principle of an IGBT-based inverter in a VFD.
 2. What is PWM (Pulse Width Modulation), and why is it used in inverters?
 3. Explain the Affinity Laws and their relevance to VFD energy savings in pumps/fans.
 4. What is the difference between a rectifier and an inverter?
 5. Why do VFDs generate harmonics, and how are they mitigated (e.g., using harmonic filters)?

8. Renewable Energy

8.1 Concept

Covers integration of solar, wind, and other renewable sources into the grid, focusing on conversion, synchronization, and storage.

Technology	Key Component	Function
Solar PV	Solar Inverter (String/Central)	DC → AC conversion, MPPT tracking
Wind Energy	DFIG (Doubly Fed Induction Generator)	Variable speed power generation
Battery Storage (BESS)	Bi-directional Inverter	Store excess energy, supply during peak
Grid-Tie Inverter	Synchronization circuit	Matches grid voltage/frequency/phase before connecting

MPPT (Maximum Power Point Tracking): Algorithm that continuously adjusts operating point to extract maximum power from solar panels despite varying irradiance/temperature.

🏭 **Industrial Example — 50MW Solar Power Plant:** String inverters with MPPT maximize energy harvest across varying panel orientations, synchronized to the grid via a grid-tie inverter that monitors voltage/frequency before closing the grid connection (anti-islanding protection).

- ✔ **Practical Applications:**
- Rooftop solar systems with net metering for commercial buildings
 - Hybrid solar-wind-diesel systems for remote/off-grid locations
 - BESS for peak shaving and grid frequency support

- 🎯 **Interview Questions:**
1. Explain MPPT and why it's necessary in solar inverters.
 2. What is anti-islanding protection, and why is it critical for grid-tied solar systems?
 3. Explain the difference between string inverters and central inverters.
 4. How does a DFIG in a wind turbine allow variable-speed operation while maintaining constant grid frequency?
 5. What is the role of battery storage in grid frequency regulation?

9. Industrial Automation

9.1 Concept

Integration of SCADA + PLC + DCS + Sensors/Actuators to achieve automated, coordinated control of industrial processes with minimal human intervention.

System	Best Suited For
PLC	Discrete, fast logic control (machine automation)
DCS (Distributed Control System)	Continuous process control (refineries, power plants)
SCADA	Wide-area monitoring/supervisory control

Typical Automation Hierarchy (ISA-95 Model)

Level 0: Field devices (sensors/actuators)
Level 1: PLC/RTU (control)
Level 2: SCADA/HMI (supervision)
Level 3: MES (Manufacturing Execution System)
Level 4: ERP (Business planning)

 **Industrial Example — Automobile Assembly Plant:** PLCs control individual robotic welding stations, while a SCADA system at the plant level monitors overall line efficiency, and an MES system tracks production data for quality traceability.

- ✔ **Practical Applications:**
- Integration of PLC + SCADA for real-time production monitoring
 - DCS for continuous process plants (oil refineries, power generation)
 - IIoT (Industrial IoT) sensors feeding data to cloud analytics for predictive maintenance

- 🔗 **Interview Questions:**
1. What is the difference between PLC, DCS, and SCADA — when would you choose one over another?
 2. Explain the ISA-95 automation pyramid and the role of each level.
 3. What is predictive maintenance, and how does IIoT enable it?
 4. How does OPC-UA facilitate communication between different automation systems (PLC to SCADA to MES)?
 5. What are the key considerations when integrating a new PLC-based system into an existing SCADA network?

10. Summary — Quick Reference Table

Topic	Core Function	Key Industrial Use
Transformers	Voltage transformation	Grid step-up/down
Motors	Electrical → Mechanical energy	Pumps, conveyors, mills
Protection	Fault detection/isolation	Relay coordination in substations
SCADA	Wide-area monitoring/control	Substation automation
PLC	Discrete logic control	Machine/conveyor automation
Power Systems	Generation-transmission-distribution	Load flow, fault studies
Power Electronics	Power conversion	VFDs, inverters, UPS
Renewable Energy	Clean power generation	Solar/wind grid integration
Industrial Automation	System integration	Plant-wide process control