Design decisions put to the owner

Every decision here was a fork the evidence could not settle on its own: either it changed the architecture, or it traded cost against reliability. Each entry gives the question as it was asked, the options offered, what was chosen, and why the question existed at all.

Dates are 2026. The standing rule from 22 September — **safety and reliability before cost, size and convenience** — is what several of these answers turn on.

---

1. The harness connector

Asked: the specification (§7, deviation 1) called for the OEM 94-way connector to be replaced by functionally-split sealed connectors plus an adapter harness. The physical part had since been identified from photographs of the machine. Keep the deviation, or put the OEM connector on the board?

Chosen: the OEM Bosch 94-way on the board, no adapter. Spec deviation 1 is recorded as reversed.

Consequence: the board-side land pattern is now load-bearing and has to come from a Bosch distributor. Neither part number returns a public catalogue hit.

---

2. Four part-selection findings, approved together

These four were presented as recommendations and approved with one "ok" on 22 September. Each one came out of choosing a part and discovering the drawn circuit could not accept it.

2a. Where the injector and EGR current comes from — POWER-PATH

The problem: every high-current load (injector hold ≈10 A, EGR up to 6.4 A stall, relay coils) draws through connector pin 21, a 20 A fuse, the EMI filter and a reverse-battery FET. The reverse-battery block sized that FET for **5 A**, and the EMI filter block never stated a DC current at all. A 22 µH inductor that does not saturate at 15–20 A is a large part. Meanwhile pins 04 and 06 are separate battery feeds, fused 10 A each in the loom, that this board uses only to measure voltage.

Options: move the injector and EGR supply onto pins 04/06 with their own protection, leaving pin 21 for the electronics; or keep everything on pin 21 and resize the fuse, filter and reverse FET for the full load,

with one contact carrying it.

Chosen: move the high-current loads to pins 04/06. Status: built 8 October 2026 (`power_path.cir`, power_input sheet).

How it was built took three more questions, recorded in §5.

2b. Boost converter stability while cranking — BOOST-SLOPE

The problem: the injector boost controller (TPS40210-Q1) adds a fixed internal slope-compensation ramp. Its Equation 9 caps the current-sense resistor at `VDD·L·fSW / (60·(VOUT + VD - VIN))`, and 80% of that is the recommended value. The drawn 82 mΩ passes at 13.5 V (ceiling 99.7 mΩ) and **fails at the 6 V cranking corner** (ceiling 44.9 mΩ, so 1.83× over): the converter goes subharmonic exactly when the engine is being started. Worse, a 330 µH inductor that saturates above the 2.2 A current limit is not a part that exists in surface mount — the search found 330 µH parts rated 0.2–0.4 A — and the buildable direction, a smaller inductor, lowers the ceiling further (100 µH allows 30 mΩ).

Options: feed the controller's supply pin from the output side, which is TI's own remedy and steepens the ramp, and use 100 µH; or accept subharmonic operation while cranking.

Chosen: feed VDD from the clamped output side, 100 µH. Revised 8 October: 150 µH (Würth 7447709151), see §8. Status: built 8 October 2026.

2c. Sensor-supply protection — SENSOR-PTC

The problem: the requirement asked for a resettable fuse of "R25 = 3.0 Ω nominal, −30% spread". Real PTCs are not specified that way: Bourns MF-USMF020 gives a **range, 0.40–5.00 Ω**, and at its 0.40 Ω minimum it contributes 14% of the series resistance the fault-current ceiling assumed. Its hold current also halves from 0.20 A at 23 °C to 0.10 A at 85 °C, against a ≥200 mA requirement.

Chosen (first pass): a fixed series resistor sets the fault ceiling and the fuse only trips. This was later superseded — see decision 4.

2d. The 3.0 V and 3.3 V input clamps — LOWV-CLAMP

The problem: fifteen zeners clamp the analog, speed and discrete inputs. They were specified at 5 mA but sit at tens of microamps, where a sub-5 V zener's knee is soft. The datasheet allows **10 µA of leakage at only 1 V.** On a discrete input, 10 µA through the ~28 kΩ source is 0.28 V against a logic-high margin of 0.36–0.41 V while cranking; on an analog input it is a signal-dependent error on the ADC. The simulation's idealised sharp-knee zener hid all of it.

Chosen: replace them with a low-leakage clamp to the 3.3 V rail (BAV199). Status: done for the analog and cam inputs; the discrete inputs needed a different answer — see decision 3.

---

3. The discrete switch inputs

Why it came back: BAV199 works where a clamp only conducts on a fault. The five switch inputs clamp **continuously**, because a 6–40 V input cannot be divided into logic range otherwise: reading a logic high at 6 V needs a divider ratio above 0.385, and staying under 3.3 V at 40 V needs one below 0.0825. Those do not overlap. Three candidate clamps were checked and all three fail:

Candidate	Why it fails
3.0 V zener (BZX84-C3V0-Q)	soft knee at µA; the leakage that started this
Rail clamp (BAV199-Q to 3V3)	parks the pad at 3.9 V continuously — beyond the pin's rating, as an operating point rather than a fault
Shunt reference (LM4040-Q1 3.0 V)	draws ~35 µA of bias below breakdown (TI SNOS633N, Fig. 5-4); the cranking-dip input can supply only 20 µA, so the node sags to ~2.6 V with no guaranteed bound, and it fails outright on the pull-up channels

Options offered: an NPN buffer per input; a stronger drive plus the LM4040, with special cases for the two contact-to-ground channels; or a dedicated automotive switch-detection IC on SPI.

Chosen: the NPN buffer. 10 kΩ into the base, 4.7 kΩ and 4.7 µF to ground, a BAV199-Q diode holding the base against reverse battery, and the transistor's collector as the MCU pin with a 10 kΩ pull-up to 3.3 V. The pad now only ever sees 0–3.3 V, and nothing on it has to conduct continuously.

What the safety rule changed inside this decision: the input resistor was first drawn at 100 kΩ, which draws 0.11 mA through a closed contact at 12 V. Non-gold switch and relay contacts at that current oxidise into an intermittent open — a field failure, not a bench one. 10 kΩ gives 1.1 mA. Everything is checked at the worst corner rather than typical: hFE 30 (datasheet minimum 60, halved for −40 °C) still pulls the pad to 0.03 V from a 6 V input, and a typical part at 125 °C stays off below a 1.3 V input.

Cost: the logic is inverted — pad low means input active — which is recorded in the pin map, and the failure modes (transistor open reads inactive, collector-emitter short reads active) are handed to the firmware plausibility spec, because one polarity cannot make every channel fail safe.

Status: done.

4. The 5 V sensor supply

Why it came back: the fix approved in 2c does not survive the real source impedance. The sensor rail block modelled the 5 V supply as ideal behind 0.1 Ω, but it comes from a **1 A buck**. So:

- a shorted sensor harness hits the buck's current limit long before any fuse trips; 5V_MAIN collapses, 3V3_MCU follows it, and the supervisor shuts the engine down. One chafed wire stops the machine.
- a sensor supply wire shorted to **battery** back-feeds 24 V into 5V_MAIN through the fuse. No series resistor or PTC prevents that.

Options offered:

Option	What it buys	What it costs
Tracker per group + overvoltage cut-off	each group survives a short to ground *and* to battery; other groups and the MCU are unaffected	about 8 more parts
Series resistor + PTC (as approved in 2c)	cheapest	a harness short browns out the MCU; a battery short back-feeds the rail
Trackers fed directly, with a lower main TVS	fewer parts	rewrites the whole board's transient design, and needs the alternator question (U16) answered first

Chosen: a tracking regulator per sensor group (TPS7B4253-Q1, whose output survives −1 to +45 V and limits at 301–520 mA, tracking 5V_MAIN to ±4 mV) behind a 100 V-class overvoltage cut-off.

Why the cut-off is needed: the tracker's input pin is rated 45 V and this board's battery rail reaches 73.3 V for 50 µs on ISO 7637-2 pulse 2a. The cheap alternatives were worked through and discarded: a series resistor with a TVS must clamp below 45 V, so it would conduct through the entire 400 ms load dump (about 7 J), and any series resistance breaks the 0.52 V of dropout headroom at a 6 V cranking input; an emitter or source follower loses its own Vbe/Vgs at that same corner. A cut-off instead disconnects for the 50 µs pulse, while a 47 µF capacitor holds the sensors up (0.16 V of droop), and stays connected through the 40 V dump.

Status: built 8 October 2026. The cut-off controller is the **TPS48110-Q1** (see §7). `sensor_rail.cir` was rewritten around it.

5. How the POWER-PATH feeds are built (8 October)

§2a decided that the loads move to pins 04/06. These three questions decided how. Each was asked with a recommended option, and each was answered with it.

5a. Which loads go on which pin

Asked: how should the high-current loads be split across pins 04 and 06?

Options: - **04 injector, 06 EGR** (recommended). Pin 04 feeds the injector hold switches and the boost converter input; pin 06 feeds the EGR H-bridge. Separate rails, separate protection: an EGR short blows only its own fuse, and no two fuses are paralleled. The injector averages well under its fuse rating (10 A only during holds of about 1–3 ms), and the EGR's 6.4 A stall is inside its 10 A fuse. - **04 + 06 paralleled** onto one high-current rail. Two fuses in parallel never share evenly: one blows first and dumps the whole load on the other.

Chosen: 04 injector (`VBAT_INJ`), 06 EGR (`VBAT_EGR`).

Why it was a question: U7, whether the OEM uses pins 04/06 as load feeds at all, is still open. What makes them usable is the harness itself: each pin has its own 10 A loom fuse, and a fuse is sized to protect its wire.

5b. Reverse-battery protection on the new rails

Asked: what should provide reverse-battery protection on the two new rails?

Options: - **A P-FET per rail** (recommended). Same passive topology as Q1 on pin 21: a gate resistor to ground plus a zener, and no controller IC, so nothing has to be rated for the +73 / −48 V swing. It needs a lower-RDS(on) part, chosen from a retrieved datasheet, for 6.4 A continuous at a 105 °C board. The reversed-battery fault is removed rather than managed. - **Fuse only.** No series element: a reversed battery drives current through the bridge FETs' body diodes until the 10 A loom fuse blows. No drop or heat in normal running, but it relies on the FETs surviving the fuse's clearing time — a managed failure, which the standing rule argues against.

Chosen: a P-FET per rail — SQM120P10-10m1L (Vishay doc 76943, retrieved 8 October).

Why it was a question: pin 21's SQD50P08-25L could not simply be copied. At the EGR's 6.4 A stall it would dissipate 1.3–1.8 W, which takes a DPAK on a 105 °C board past its junction limit. The chosen part runs at 139 °C (155 °C while cranking), checked in `power_path.cir`.

5c. What stays on pin 21

Asked: which loads stay on pin 21, the filtered electronics feed?

Options: - **Buck, relays, metering** (recommended). Pin 21 keeps the buck (all the electronics), the relay coils (~84 mA) and the metering valve's freewheel diode (0.86 A max; the valve itself is powered by the

OEM's 20 A fuse 8F1). The boost controller's VDD stays on VBAT_PROT until BOOST-SLOPE moves it. Pin 21 then carries a couple of amps. - **Buck only.** Move the relay coils and the metering freewheel onto the new rails as well. Pin 21 becomes electronics-only, but the relays and the metering valve then depend on the 04/06 fuses too.

Chosen: buck, relays and metering stay on pin 21.

Consequence: L101, L102 and F101 are unblocked and are now sized for pin 21's reduced load, which still has to be stated as a number.

---

6. The toolchain on a new machine (7–8 October)

Setting the project up on macOS raised three questions. They are about tools, not the circuit, but two of them decide which simulator and which libraries the circuits are checked against.

6a. Which KiCad

Asked: the project was generated and verified with kicad-cli 7.0.11, but Homebrew offers only KiCad 10. Install 7.0.11 from kicad.org, KiCad 10 from Homebrew, or skip KiCad for now?

Options: 7.0.11, which matches the verified netlists (recommended at the time); KiCad 10, which is easier to keep updated, but its netlist export and libraries may differ; or no KiCad.

Chosen: KiCad 10 (10.0.7, installed by the owner).

Consequence: two things had to change for KiCad 10. `kicad-cli` 10 writes its netlist one token per line, so the parsers in `check_netlist.py` and `assign_passives.py` were changed to accept either layout. The results were identical to KiCad 7's, and `passive_fp.json` came out byte for byte the same. The generators copy library symbols into each sheet, so they are pointed at **KiCad 7.0.11's symbol library**, downloaded separately. With it, an unchanged sheet regenerates identically apart from UUIDs. KiCad 10's library would have changed every symbol on every regenerated sheet. That library choice was not put to the owner; it follows from this answer.

6b. Which ngspice

What happened: Homebrew's ngspice 47 failed three blocks that pass on the original machine. `injector_turnoff` and `boost_converter` never finished, and `metering_unit_pwm` missed by 3 %. The suite also stalled at random. Fixes for all three were found: a ramp on an on/off charger model, a step-size cap and a time-weighted average. But the random stall remained.

The owner's position: first, that the circuits must work on the latest version too. Then, after the random stall: build ngspice 42 from source rather than spend more time on 47.

Chosen: ngspice 42, built from source into `~/opt/ngspice-42`. The committed suite passes 24/24 on it unchanged (25/25 with `power_path`).

Still open: the suite does not pass on ngspice 47 for the three causes above. Upgrading the simulator is a change that needs the whole suite re-run (`docs/HANDOFF.md` §2 and §5).

6c. Keep the ngspice 47 fixes or not

Asked: with 42 passing the committed code, revert the 47-specific edits to the netlists, `run_sim.py` and `ngrun.py`, and commit only the setup changes?

Chosen: revert. The 47 fixes are not in the repository; §6b records what they were.

7. The overvoltage cut-off in front of the sensor trackers (8 October)

§4 chose a tracking regulator per sensor group "behind a 100 V-class overvoltage cut-off", and named an LTC4368-class controller as the candidate. Its datasheet had never been retrieved. Retrieving it, and looking for an alternative, turned the candidate into a choice.

What the part is for

The three sensor regulators (TPS7B4253-Q1, one per group) survive at most **45 V** on their input. This board's battery rail reaches **73.3 V** for about 50 µs on ISO 7637-2 pulse 2a, a standard automotive surge test. So the regulators need a fast automatic switch in front of them:

- normally **on**, passing battery power through;
- above about 45 V it switches **off** within a few microseconds, and a 47 µF capacitor after it keeps the sensors powered meanwhile;
- when the surge has passed, it switches back **on**.

It is a small controller chip driving one power transistor. It must stay **on** through the 40 V load dump, which lasts 400 ms, far longer than the capacitor could bridge.

The question

Asked: which overvoltage cut-off controller should feed the three sensor trackers?

The first time it was asked, the options were given only as datasheet figures, and the owner replied that they could not decide between two part numbers. The question was then explained as above, with this

comparison:

	TPS48110-Q1 (Texas Instruments)	LTC4368 (Analog Devices)
Survives	100 V	100 V
Switches off in	2.6–4 µs after the threshold	under 8 µs
Automotive-qualified (AEC-Q100)	**yes**, Grade 1	**no**: C, I and H grades only (H = −40 to +125 °C)
Around it	a few more parts: charge-pump capacitor, unused current-sense pins tied off	simpler, 10 pins
Datasheet	SLUSEE5E (April 2026), from ti.com	Rev A, read through a mirror because analog.com timed out
Extra check needed	a 60 V/µs limit on how fast its input may rise	—

Recommended: TPS48110-Q1. Electrically, either would do the job. The deciding point is qualification. AEC-Q100 means the chip has passed the automotive industry's stress tests for temperature cycling, vibration and lifetime. Every other IC on this board has it, and the LTC4368 would have been the one exception, on the part that protects the sensor supply. The standing rule puts reliability before cost and convenience.

Chosen: TPS48110-Q1 ("ok use the recommended one").

Consequences:

- **Slew limit:** the input slew rate on pulse 2a's edge has to be checked against the 60 V/µs limit. The `sensor_rail` rewrite does that.
- **Threshold window:** the OV threshold must sit above the 40 V load dump at its lowest tolerance, and trip early enough that the regulators' input stays under 45 V. That includes the rise during the controller's 2.6–4 µs reaction time. The window is narrow, and the `sensor_rail` rewrite pins it.
- **The switch transistor** is the board's existing 100 V N-FET, IPD90N10S4-06, so there is one part number fewer to buy.

What the simulation then showed. Pulse 2a was applied through the real pin-21 filter. The trackers' input peaks at about **22 V**, nowhere near 45 V, at every corner. TI's own inrush network does most of that: the 22 nF from gate to ground holds the FET's gate, so the FET can only follow the surge up to its gate voltage. The OV comparator then opens it fully once the rail passes 40.5–42.1 V, and that timing turned out not to be critical. The 60 V/µs slew limit is met by feeding the controller's supply pins through 100 Ω and 22 nF, which gives 4.9 V/µs. The 47 µF hold-up is enough even aged to 33 µF with all three trackers at their limit. One thing it showed about the rest of the board: with the filter inductor not saturated, the clamp node reaches **76.6 V**, not the 73.3 V `transient_clamp.cir` reports. Every part there is 100 V class, and the figure is now a check.

A limit this design does not remove

The trackers' outputs survive −1 V to +45 V, so a sensor supply wire shorted to battery is survived at 24 V (jump start) and at 40 V (load dump). A short to battery **at the same time as** a pulse 2a surge (73.3 V) would exceed it. That is a double fault, and it is recorded rather than designed out.

8. The boost inductor, revisited (8 October)

§2b approved two changes to the injector boost converter: feed the controller's supply (VDD) from the clamped output side, and use a 100 µH inductor (Würth 7447709101). Building it showed the 100 µH part does not fit every rule.

What the inductor and its sense resistor have to do

The TPS40210-Q1 measures inductor current through a small sense resistor, and that one resistor sets two things:

- **Stability.** TI's Equation 9 caps the resistor at 80 % of VDD × L × fSW / (60 × (VOUT + VD − VIN)). Below it the converter is stable; above it, it goes "subharmonic" and oscillates at half its switching frequency. The worst corner is the 6 V cranking dip. Feeding VDD from the boost output raises VDD from about 5 V to about 32 V while cranking, which is the whole remedy.
- **The current limit.** The controller cuts each cycle when the resistor's voltage reaches 120–180 mV, a 1.5 : 1 spread over tolerance and temperature. The limit has to sit high enough never to trip in normal running (TI's Equation 49), and low enough that in a fault the inductor does not saturate badly.

The first question

Asked: with the approved 100 µH inductor, all three rules cannot be met strictly. Allow the fault current limit to reach the inductor's softer 30 % saturation point, or find a bigger inductor?

The owner's answer: "150 µH inductor comes in size 10x10x4 SMD package."

Checked against Würth's own datasheets:

- **7447714151, 10 × 10 × 4 mm:** 150 µH, Isat 1.4 A typ. It cannot work. Normal cranking peaks at about 1.14 A, so TI's rule puts the current limit's minimum near 1.8 A and its maximum near 2.7 A. The part would saturate in normal running, not just in a fault.
- **7447709151, 12 × 12 mm:** 150 µH, Isat 2.7 A (10 %) and 3.3 A (30 %) typ, in the **same footprint** as the approved 100 µH part.

The second question

Asked: which boost inductor?

	100 µH 7447709101 (as approved)	150 µH 7447709151
Sense resistor	50 mΩ	62 mΩ
Current limit, min–max	2.4–3.6 A	1.9–2.9 A
Limit max vs 10 % saturation	16 % over	7 % over
Limit max vs 30 % saturation	5 % under	14 % under
Stability margin (Eq. 9, 80 % rule)	1.07×	1.30×
No false trip while cranking (Eq. 49)	1.27×	1.07×

Recommended and chosen: 150 µH, Würth 7447709151, with a 62 mΩ sense resistor. It has more stability margin and less fault-current saturation, in the same footprint. This revises the 100 µH in §2b; the VDD-from-output remedy stands.

Why neither choice is strict: the 1.5 : 1 spread of the current- limit threshold means the limit's maximum is always 1.5 × its minimum. The minimum has to clear normal cranking current, so the maximum lands above the first softening point of any inductor this size. Partial saturation during a fault is not damaging: the controller still cuts the current every cycle.

How it was built

- **VDD from the output.** A follower off the 100 V rail gives VDD 34.3–45.0 V. It is 12V_GATE's circuit with a 39 V zener (BZG03C39, same Vishay family as the 36 V clamp): a PZTA42-Q pass transistor, 2 × 3.3 kΩ collector resistors, and a PMBT3904-Q limiting at 11.6 mA. A follower off a 100 V rail needs that protection whatever it feeds. If VDD shorted, the follower would otherwise burn.
- **Start-up from the battery.** The old 220 Ω feed became a 180 Ω start-up path, with its 36 V clamp, into a Schottky (SS20PH102, already on the board). The Schottky stops the follower pushing about 0.1 A back into the battery rail. 180 Ω, not 220 Ω, buys back the Schottky's drop: VDD is 4.77 V at the 6 V cranking dip, against the 4.5 V start threshold.
- **Found while building it:** the oscillator's timing resistor returns to VDD, and TI specifies the frequency −20 % / +7 % across VDD. Equation 9 scales with frequency, so the stability check has to use −20 %. At that corner the 150 µH design keeps 1.12×. The 100 µH design would have failed outright (42.9 mΩ against its 50 mΩ). The choice in this section was the right one for a reason nobody had seen yet.
- **Stated, not hidden:** the switch FET's datasheet gives only a typical gate charge. At twice that, start-up margin falls to 17 mV. Until the output passes about 36 V, the controller runs from the battery feed with a

shallow ramp, so subharmonic operation is possible for the first milliseconds of a cranking start, not in running.

---

9. The three capacitors that are not ceramic (8 October)

Every chip capacitor on the board is a multilayer ceramic, packaged automatically by `assign_passives.py`. Three are not, because each needs something a ceramic cannot give: a lot of capacitance at high voltage, or a controlled internal resistance. They were left open until now.

Ref	Job	Chosen
C313	bulk on the MCU's 3.3 V supply	KEMET T599D157M006ATE025, 150 µF polymer tantalum, **plus R306, 22 mΩ 1 %** in series
C211	holds the sensor supply up while the cut-off is open	Chemi-Con HHXC630ARA470MHA0G, 47 µF 63 V hybrid polymer, 8 × 10 mm
C401 + C420	the injector's 100 V energy tank	**two** Chemi-Con HHXC800ARA820MJC5G, 82 µF 80 V hybrid polymer, 10 × 12.5 mm, in series = 41 µF, 160 V

All three are AEC-Q200, surface-mount, and rated to 125 °C or higher. Chemi-Con figures are from its 2026 catalogue (CAT. No. E1001A); KEMET's from the part's own specification sheet.

The idea behind all three: ESR

Every real capacitor has a small resistance in series with it, its **ESR**. In wet aluminium electrolytics it rises steeply in the cold, because the liquid inside thickens: typically 4–10× at −40 °C. A **polymer** or **hybrid polymer** capacitor replaces most or all of that liquid with a conductive solid, so its ESR barely moves. Chemi-Con guarantees the HXC series' impedance at −55 °C is **at most twice** its 20 °C value. That one property is why all three choices are polymer types.

C313 — the bulk capacitor needs a *minimum* resistance

`mcu_pdn.cir` showed the bulk capacitor's ESR is not just a loss but the damping for a resonance between the regulator and the capacitor. Too little ESR and the supply rings; too much and it stops filtering. The requirement (`PDN-BULK`) was therefore a band: 20–50 mΩ.

Two findings changed how it was met:

- **A capacitor datasheet gives a maximum ESR, never a minimum.** No part can be bought "at least 20 mΩ". So the floor is a separate resistor: 22 mΩ, 1 %, in series with a capacitor whose own ESR is 25 mΩ at most. Even if the capacitor's ESR were zero, the pair is 21.8 mΩ.

- **The ceiling was conservative.** A sweep of the same model shows the 100 mΩ target holds from about 17 mΩ up to about 95 mΩ. The pair's worst high end is 72.2 mΩ: resistor +1 % plus the capacitor at KEMET's 2× end-of-life limit. Both ends pass at the smallest capacitance the datasheet allows (96 µF): 71.9 and 86.9 mΩ.

No question was put to the owner: the resistor is the only way to meet a requirement both ends of which are needed.

C211 — the sensor hold-up

When the TPS48110-Q1 opens for a voltage spike (§7), this capacitor keeps the three sensor regulators running. The only new demands are a voltage rating above the 40 V load dump the switch lets through, and a capacitance that survives aging. The HXC part gives 63 V (1.58× over 40 V). At −20 % tolerance and −30 % end of life it is 26.3 µF. `sensor_rail.cir` now runs its two worst corners at 26.3 µF, not the 33 µF it used before, and still passes: the rail's lowest point is 9.2 V. Its ESR drop at −55 °C, aged, with all three regulators at their limit, is 0.25 V. No question was needed.

C401 — the injector tank, and the question

What it does. The boost converter can only trickle-charge this capacitor. The capacitor alone delivers the injector's opening pulse: 18 A within about 40 µs, every injection. Its ESR is in series with the injector. At 18 A, every ohm of ESR costs 18 V of push and slows the opening.

What the search found. The tank sits at 100 V and reaches 104 V, so it needs a part rated above 100 V. In the catalogues searched, **no capacitor rated above 100 V publishes its ESR at all**, cold or warm. Chemi-Con's 160 V parts give only a 120 Hz loss figure. Vishay's specified-cold series stops at 80 V. Parts rated up to 80 V do publish it, including HXC.

Asked: "C401 is the injector's 100 V energy tank … No single capacitor rated above 100 V publishes its cold ESR. Which way?"

	2 × 80 V hybrid in series (recommended)	1 × 160 V wet electrolytic
Part	2 × Chemi-Con HXC 82 µF 80 V, SMD	1 × Chemi-Con GXF 51 µF 160 V, radial
ESR at −55 °C, aged	224 mΩ, from the datasheet	not specified; estimated ~8 Ω
Time to 18 A at −40 °C, lowest rail	45 µs (38 µs nominal)	never reaches 18 A at the estimate: 10.2 A at most
Cost and space	one extra can, 10 × 12.5 mm	cheapest, one part

The owner's answer: "2× 80 V in series (Recommended)."

Why it matters: the injector controller ends the opening phase when the current reaches its peak threshold. A tank that cannot push 18 A through its own resistance never ends that phase, and the engine misfires. That would happen on a cold start, late in the part's life, which is the hardest fault to find in the field.

How two in series work:

- **Capacitance halves, voltage rating doubles.** 41 µF, 160 V. The sims now run at 41 µF. The droop per injection is 8.3 V (it was 7.3 V). On the smallest stack the datasheet allows (−20 %, then −30 % aged) it is 14.9 V, so the rail never falls below 85.1 V. Every check that used the old 92.7 V low point now uses that figure. The gate-driver bank node rises to 104.1 V, since each hold-cutoff bump is 2.45 V on 41 µF. Recovery time does not change; it depends on charge, not capacitance.
- **The bleed balances the stack.** Two capacitors in series only share the voltage evenly if something forces them to. The 22 kΩ bleed that `BOOST-BLEED` already required is now 2 × 11 kΩ, one across each can (R401, R435). With the worst leakage mismatch the datasheet allows, each can settles at 52.4 V on an 80 V part. The first charge from 0 V is the worst moment: it splits by capacitance alone, so 71.0 V can land on one can. That is 1.13× under its rating. Total bleed current and power are unchanged.
- **Ripple:** the injection pulses plus the charger's switching current, counted as if it never stopped, are 1.06 A rms against 2.1 A rated at 125 °C.

All of it is executable arithmetic in `run_sim.py` under `boost_converter`, beside the converter's own datasheet checks.

---

10. A filter on each new supply feed (8 October)

POWER-PATH (§2a, §5) moved the injector and EGR currents onto connector pins 04 and 06. That was right for current and heat, but it took the board's two noisiest loads away from pin 21's EMI filter. Each new feed had only its reverse FET and 4.4–8.8 µF of ceramic capacitors. The question was whether that is enough to meet the radio-interference limit this project designs to. The limit is CISPR 25 Class 5, the strictest automotive class (research memo 06), the same target pin 21's filter is held to.

What makes the noise

Both loads switch large currents on and off many thousands of times a second, straight from the battery wire:

- **Injector hold.** After the 100 V opening pulse, each injector is held open at about 10 A by switching the battery on and off ("chopping").
- **EGR valve motor.** Driven by PWM: full battery on and off, up to 6.4 A at stall.
- **Boost converter input.** A smaller, smoother 150 kHz ripple.

Each on-off edge sends a spray of harmonics down the harness. A radio receiver near the wiring would hear it, and the standard limits how much is allowed.

What the model found

New block `feed_emi.cir` reproduces CISPR 25's measurement: the standard 5 µH / 50 Ω test network (LISN), 200 mm of harness, then the board. `run_sim.py` adds up each load's harmonics against the Class 5 limits, band by band, with the peak and average detectors.

	Worst point against Class 5
VBAT_INJ as drawn	**33 dB over**
VBAT_EGR as drawn	**48 dB over**
VBAT_INJ with the filter	17.7 dB under (12.2 dB under with aged capacitors)
VBAT_EGR with the filter	9.3 dB under

48 dB is about 250 times too much voltage. No layout trick closes a gap that size; it needs a filter.

The filter, per feed

- **Coilcraft XAL1510-103**, 10 µH, rated 16 A for a 20 °C rise. Between the reverse FET and the loads.
- **Two 82 µF / 80 V hybrid capacitors** (the same Chemi-Con HXC part as C401) on the load side. These supply the chopping current, so the inductor only carries the average.
- **Two dampers:** another HXC each, in series with a 0.68 Ω resistor.
- The existing 2 × 2.2 µF ceramics now sit on the connector side, which makes it a two-capacitor filter.

Both feeds get the identical circuit: one parts list, one layout block.

Why the dampers. An inductor and capacitor together form a resonant circuit, here near 3 kHz. Two of the loads on the injector feed, the boost converter and the hold-current loop, try to draw *constant power*. To the filter that looks like a negative resistance: about 0.94 Ω at a 9 V cranking dip with a hot injector coil. If the filter's own impedance peak is higher than that, the supply can oscillate. Undamped it peaks at 1.24 Ω. With the dampers it peaks at 0.64 Ω, even with end-of-life capacitors, a

margin of 1.47×. The damping is a plain resistor, not a wet capacitor's internal resistance, because that rises about 8× at −40 °C (§9), exactly when cranking makes it matter.

Why this inductor. The Würth 10 µH alternative saturates at 8.8 A typical and is rated only to 75 °C ambient. The Coilcraft part saturates at 26 A and is rated to 165 °C. Its one limit is 55 V across the winding. The model puts ISO pulse 2a through the filter: at most 48.7 V across it, 1.12× inside. In return the filter swallows most of pulse 2a, so the feed's loads see at most 28.7 V, where VBAT_PROT sees 73.3 V.

A requirement this puts on the firmware

The hold chopping and the EGR PWM frequencies have not been chosen; they are firmware. Harmonic strength in the radio bands grows with switching frequency, so the filter was sized at **25 kHz.** At 50 kHz the EGR feed would be 1 dB over. **Both must stay at or below 25 kHz.** That is above hearing, which is the usual reason for choosing about 20 kHz anyway.

What it costs, and what would change it

Two inductors (15 × 16 mm), eight hybrid capacitors (10 × 12.5 mm) and four resistors: 14 parts, roughly US$15–20 a board. No question was put to the owner. Without the filter the board fails Class 5 by 33–48 dB, and the only alternative is a looser emissions class. That is the owner's call. A stationary genset has no car radio, so a lower class may be defensible, but it is not this log's decision to make. If the owner relaxes the class, these filters can shrink.

Limits of the model. Like `emi_filter.cir`, it covers differential mode only. Common-mode noise, both wires moving together against the chassis, needs a layout to model. The 100 ns switching edges and the in-phase sum of harmonics are deliberate worst cases.

---

11. Firmware on the PC first (10–11 October)

The hardware was complete to schematic, but no firmware existed. A competing team already runs firmware on their board, with an Arduino faking the engine signals. The question was how to catch up without waiting for our own PCB.

The choice

The control software is written as **plain C that touches no hardware** (`firmware/core/`). It runs on the PC against a **simulated engine** (`firmware/sim/engine.py`). The same C files later run unchanged on an

NXP S32K148 evaluation board, and after that on our own board. Every control and safety function is proven first on the PC, where a mistake costs nothing.

All the firmware sees is one table of numbers (`ecu_io` in `ecu.h`). The inputs are sensor voltages and switch states. The outputs are injection commands, the metering-valve duty, the watchdog pin and the CAN messages. The firmware has four entry points: start up, a crank tooth arrived, a cam pulse arrived, and one millisecond passed. The simulator fills the table and reads it back, and the S32K148 port will do the same from its pins. Injection is given as **"start at time T, for D microseconds"** per cylinder, which is what the chip's timer executes. That keeps the simulator's time step coarse without making the fuel amounts coarse.

What the firmware does

- **Reads the crank wheel.** A 60-2 wheel has 58 teeth and a gap where two are missing. The gap shows up as a tooth period more than 1.5× the one before. Two gaps 58 teeth apart mean "synchronised". The cam pulse, once per two revolutions, says which revolution has cylinder 1 firing.
- **Injects** once per cylinder per cycle, 5° before top dead centre. It schedules at least 1° ahead, so the start time is never already past.
- **Governs speed.** It holds 1500 rpm, or falls 4 % from no load to full load when the droop switch is closed. On reaching 400 rpm the setpoint **ramps up at 500 rpm/s** rather than jumping, explained below.
- **Holds rail pressure** at 1000 bar by driving the metering valve, which is normally open: more duty, less fuel flow.
- **Checks every sensor.** One that stays out of range for 100 ms raises a fault code. From the first moment it goes out of range, its last good value is held.
- **Shuts down and latches.** Above 1650 rpm (checked on every tooth), on loss of the crank signal, or on ignition off. It stays shut down until the ignition is cycled. The trip cancels any injection not yet started.
- **Talks J1939 to the DSE4522:**
- engine speed every 20 ms
- coolant temperature every 1 s
- oil pressure every 500 ms
- active fault codes every 1 s

What the simulator proved

Eleven scenarios, run with one command (`.venv/bin/python firmware/sim/run_sil.py`), all pass in 36 s:

#	Scenario	Result
1	Start	synchronised in 116 teeth; 1500 rpm by 5 s; peak 1534 rpm
2	0 → 20 kW load step	dips to 1449 rpm, back within ±15 rpm
3	20 → 0 kW load rejection	peaks at 1547 rpm, well under the 1650 trip
4	Droop switch	speed falls 3.8 % (want 4 ± 1 %)
5	Runaway (stuck injector)	trips at 1650.6 rpm; no new injection after
6	Crank signal lost	shuts down 50 ms later, fault SPN 636
7	Ignition off	shuts down with no fault code
8	Coolant sensor unplugged	fault SPN 110 FMI 3 after 1.0 s; engine keeps running
9	CAN timing and content	every message on time to the ms; speed within 0.1 %
10	Rail pressure	within 1.6 % of 1000 bar at full load
11	Watchdog	WDI falls every 10 ms

There are also 42 unit tests on the separate pieces (`make -C firmware/sim test`).

What an expert review caught

Halfway through, a separate reviewer acting as a diesel-ECU firmware specialist read the code. Every finding was reproduced as a failing test before it was fixed. The ones worth knowing:

- **The start nearly tripped overspeed.** On reaching 400 rpm the speed loop asked for 1500 at once, fuel hit its limit, and the engine peaked at 1647 rpm, 3 rpm short of the trip. The ramping setpoint brought the peak down to 1534.
- **A crank-sensor noise spike read as overspeed.** One extra edge in mid-tooth made the speed read 1700 rpm. An edge arriving in less than half a tooth's time is now ignored, because no engine accelerates that fast.
- **A cancelled injection could still fire.** The cancel did not change the sequence number a timer driver watches. Now it does.
- **A hot engine looked like a shorted sensor.** With the placeholder coolant sensor, 0.2 V is a real 129 °C. That would have been flagged as a short and replaced by a harmless 90 °C. The coolant short threshold is now 0.1 V.
- **A stray cam pulse shifted everything by a revolution.** The engine would have injected on the wrong stroke. A cam pulse in the wrong revolution now stops injection until the next one agrees.
- Smaller fixes:
- a timestamp 1 µs out of order read as signal loss
- an out-of-range sensor's raw value was used during the 100 ms debounce

Choices made while building

- **Signal-loss timeout of 50 ms, not 100.** The scenario requires shutdown within 100 ms. At 400 rpm the longest normal gap between edges is 7.5 ms.
- **Watchdog kicked every 10 ms.** This settles the open item on the MCU sheet. The TPS3850's window (its SET0/SET1 straps and CWD capacitor) has to accept a 5–20 ms kick period. That is well inside the 26.67 ms cylinder interval the spec requires.
- **Tuned gains.** These are placeholders until real engine tests:
- speed: 0.5 mg/rpm proportional, 2.0 mg/(rpm·s) integral
- rail: 0.002 duty/bar proportional, 0.01 duty/(bar·s) integral

The gentler of the two passing sets was kept. A real engine has delays this model lacks. - **A stray cam pulse or a noise edge** does not stop the engine. A single spike should not shut down a genset.

What is assumed, and how to change it

Each assumption is a single named constant in a header, marked `assumed` or `calibration`: - the 60-2 wheel and cylinder 1 TDC at 90° after the gap (`CRANK_TDC1_DEG`) - firing order 1-2-3 - start of injection, 5° before TDC - the injector flow law - fuel at full load, 34 mg (sets the droop) - every sensor's volts-to-units table (`sensors.c`)

The engine model's constants are guesses for a 3-cylinder genset diesel, also marked. When the real engine's figures arrive, each is a one-line change, and the scenarios say at once whether the control still holds.

Out of scope, and next

Not done yet: - injector current regulation (that lives in the driver chip) - pilot and post injections - real calibration maps - EGR control

The next step is the S32K148 evaluation board with an Arduino generating the engine signals: the competitor's setup, but with control logic that is already proven.

Where these came from

Nothing here was found by reading the schematic. Each one surfaced when a part number was chosen and its datasheet was checked against what the drawing assumed — which is the same shape as every earlier finding in this project: a document and an executable check disagreeing, with nothing comparing them until someone did.