12.ATM SIMULATION SYSTEM -DEPOSIT WITHDRAW BALANCE CHECK

```
import java.util.Scanner;

class ATM {
    private double balance = 1000.0;

    public void deposit(double amount) {
        if (amount > 0) {
            balance += amount;
            System.out.println("Amount deposited successfully.");
        } else {
            System.out.println("Invalid amount.");
        }
    }

    public void withdraw(double amount) {
        if (amount > 0 && amount <= balance) {
            balance -= amount;
            System.out.println("Amount withdrawn successfully.");
        } else {
            System.out.println("Insufficient balance or invalid amount.");
        }
    }

    public void checkBalance() {
        System.out.println("Current Balance: Rs." + balance);
    }
}

public class Main {
    public static void main(String[] args) {
        Scanner sc = new Scanner(System.in);
        ATM atm = new ATM();
        int choice;
        double amount;

        do {
            System.out.println("\n--- ATM MENU ---");
            System.out.println("1. Deposit");
            System.out.println("2. Withdraw");
            System.out.println("3. Check Balance");
            System.out.println("4. Exit");
            System.out.print("Enter your choice: ");
            choice = sc.nextInt();
```

```
            switch (choice) {
                case 1:
                    System.out.print("Enter deposit amount: ");
                    amount = sc.nextDouble();
                    atm.deposit(amount);
                    break;

                case 2:
                    System.out.print("Enter withdrawal amount: ");
                    amount = sc.nextDouble();
                    atm.withdraw(amount);
                    break;

                case 3:
                    atm.checkBalance();
                    break;

                case 4:
                    System.out.println("Thank you for using ATM.");
                    break;

                default:
                    System.out.println("Invalid choice.");
            }
        } while (choice != 4);

        sc.close();
    }
}
```

OUTPUT:

```
--- ATM MENU ---
1. Deposit
2. Withdraw
3. Check Balance
4. Exit
Enter your choice: 1
Enter deposit amount: 500
Amount deposited successfully.

--- ATM MENU ---
1. Deposit
2. Withdraw
3. Check Balance
4. Exit
```

Enter your choice: 2
Enter withdrawal amount: 200
Amount withdrawn successfully.

--- ATM MENU ---
1. Deposit
2. Withdraw
3. Check Balance
4. Exit
Enter your choice: 3
Current Balance: Rs.1300.0

--- ATM MENU ---
1. Deposit
2. Withdraw
3. Check Balance
4. Exit
Enter your choice: 4
Thank you for using ATM.