

Exp No: 8 GAS SENSOR MQ-2 IN PROTEUS USING ARDUINO

Program:

```
/*  
MQ-6 Gas Sensor with Arduino UNO  
LED on D13  
MQ-6 OUT -> A0  
Baud Rate : 9600  
*/  
  
#define MQ6 A0  
#define LED 13  
  
int sensorValue = 0;  
int threshold = 600;  
  
void setup()  
{  
  pinMode(LED, OUTPUT);  
  digitalWrite(LED, LOW);  
  Serial.begin(9600);  
  Serial.println("=====");  
  Serial.println(" MQ-6 GAS SENSOR MONITOR");  
  Serial.println("=====");  
}  
  
void loop()  
{  
  // Read analog value from MQ-6  
  sensorValue = analogRead(MQ6);  
  
  // Display sensor value  
  Serial.print("Analogic Value coming from the sensor : ");  
  Serial.println(sensorValue);
```

```

// Gas detection

if (sensorValue >= threshold)
{
    digitalWrite(LED, HIGH);

    Serial.println("Gas Leakage Detected!");
}

else
{
    digitalWrite(LED, LOW);

    Serial.println("Gas Level Normal");
}

delay(500);
}

```

