RAJALAKSHMI ENGINEERING COLLEGE

Monish K V 251801190-2025-AIDS

M2

Started on	Monday, 24 August 2026, 6:49 PM
State	Finished
Completed on	Tuesday, 25 August 2026, 5:23 PM
Time taken	22 hours 33 mins
Marks	1.00/1.00
Grade	**10.00** out of 10.00 (**100**%)

Question 1 | Correct Mark 1.00 out of 1.00

Convert the following algorithm into a program and find its time complexity using the counter method.

```
void func(int n)
{
    if(n==1)
    {
      printf("*");
    }
    else
    {
     for(int i=1; i<=n; i++)
     {
       for(int j=1; j<=n; j++)
       {
          printf("*");
          printf("*");
          break;
       }
     }
   }
 }
```

Note: No need of counter increment for declarations and scanf() and count variable printf() statements.

Input:

A positive Integer n

Output:

Print the value of the counter variable

Answer: (penalty regime: 0 %)

Ace editor not ready. Perhaps reload page?

Falling back to raw text area.

```
#include <stdio.h>

int main()
{
    int n, count = 0;

    scanf("%d", &n);

    if (n == 1)
    {
        count = 1;
    }
    else
    {
        for (int i = 1; i <= n; i++)
        {
            count += 5;
        }
```

	Input	Expected	Got	
✔	2	12	12	✔
✔	1000	5002	5002	✔
✔	143	717	717	✔

Passed all tests! ✔

Correct

Marks for this submission: 1.00/1.00.

Back to Course