Digital Signal Processing Exercise Sheet 0

Getting Started: Wokwi and JSLinux

Script: Preface, Chapter 1.1

Learning goals

- Run, modify and share an Arduino project in the Wokwi simulator.
- *Bonus (optional):* compile and run C programs in JSLinux, plot results in the terminal, and transfer measured data from Wokwi (Serial Monitor) to JSLinux.
- Get to know the course library `code/common/engine_signals.h`, the *virtual engine* used on all following sheets.

The virtual engine

Throughout the exercises we cannot measure on a real engine. Instead, a *virtual engine* generates the sensor signals introduced in Chapter 1 of the script. Exactly the same C model is used in three places:

Where	How
JSLinux	`#include "engine_signals.h"` in your C program
Wokwi (sketch)	add `engine_signals.h` as an extra file to the project
Wokwi (custom chip)	part `chip-engine-sim`: outputs CRANK, CAM, KNOCK, ION, and the ground-truth signals TDC and KNK

The conventions of the model are fixed for all sheets:

- 4-cylinder 4-stroke engine, crank angle $\theta \in [0°, 720°)$, firing order 1–3–4–2, combustion TDC at 120°, 300°, 480°, 660°.
- 60-2 trigger wheel: tooth $k = 0, \ldots, 57$ is HIGH for $\theta \bmod 360° \in [6k°, 6k° + 3°)$; teeth 58 and 59 are missing.
- Camshaft signal HIGH for $0° \le \theta < 180°$.
- Knock: damped oscillation with modes at 6.5 kHz and 10.5 kHz, decay time 0.8 ms, onset 5–25° after TDC.
- Disturbances: broadband noise, valve impacts (8 kHz, 90° after TDC), low-frequency combustion vibration, a 1 % speed ripple at twice crankshaft frequency.

Alternative: Wokwi in VS Code

All Wokwi exercises run in the browser; nothing has to be installed. If you prefer working locally, every Wokwi project of the course is also available as a project for the *Wokwi for VS Code* extension in `code/wokwi_vscode/` (same sketches and circuits). There you build the firmware with PlatformIO and Wokwi simulates it; the custom chips come precompiled. You need VS Code with the extensions *PlatformIO IDE* and *Wokwi Simulator* and a free Wokwi license. Setup and workflow are described step by step in `code/wokwi_vscode/README.md`. In the exercises, "open the project in Wokwi" then means: open the folder of the same name in `code/wokwi_vscode/` and edit `src/sketch.ino`. The logic analyzer recording is written to `wokwi.vcd` in the project folder when you stop the simulation.

Exercise 0.1 First steps in Wokwi

WOKWI

Open `https://wokwi.com`, create a new *Arduino Uno* project and replace `sketch.ino` and `diagram.json` by the files in `code/wokwi/sheet00_hello/`.

a) Start the simulation, turn the potentiometer and watch the Serial Monitor. Which ADC value corresponds to 2.5 V? What is the voltage resolution (1 LSB) of the 10-bit ADC?

b) The sketch toggles pin 13 at every sample. Stop the simulation after about one second, download the logic analyzer recording (`.vcd`) and determine the sampling period. Does it match `TS_US`?

c) Change the sampling rate to 1 kHz. Explain why the printed `t_us` values still show regular increments although the `Serial.print` calls take time.

d) Wokwi runs in *simulated time*. Compare the simulated time in the status bar with the time on your wall clock. Why is this important when we later measure execution times?

Exercise 0.2 The engine simulator chip

WOKWI

Every Wokwi project of the following sheets contains the custom chip `engine-sim`. Add the files `engine-sim.chip.c` and `engine-sim.chip.json` from `code/wokwi/chips/` to the Uno project of Exercise 0.1 and add the part `{ "type": "chip-engine-sim", "id": "eng", "attrs": { "vmax": "5", "of` to `diagram.json`. *VS Code:* work in `code/wokwi_vscode/sheet00_hello/`; instead of copying the chip files, add the precompiled chip to `wokwi.toml` (as in `sheet01_crank/wokwi.toml`):

```
[[chip]]
name = 'engine-sim'
binary = '../chips/engine-sim.chip.wasm'
```

a) Connect `eng:CRANK` to logic analyzer D1, `eng:CAM` to D2 and `eng:TDC` to D3 (and `eng:GND` to ground). Record 100 ms at 3000 rpm and view the `.vcd` file (e.g. in PulseView or GTKWave). Identify the missing-tooth gap and verify the tooth period.

b) How many crank teeth lie between the gap and the first TDC pulse? Compare with the conventions above.

c) Change the engine speed with the slider of the chip and repeat the tooth-period measurement at 6000 rpm.

Deliverables

Screenshot of the Wokwi logic analyzer view (or VCD plot) with the gap marked. Bonus (optional): terminal output of `hello_signals`; the CSV-plot program of 0.B1 d).

Bonus: JSLinux (optional)

The lab exercises above use only Wokwi. Interested students can in addition process the engine signals in plain C on a Linux system that runs in the browser. The JSLinux exercises of the following sheets build on this one.

Exercise 0.B1 First steps in JSLinux

JSLINUX

Open `https://bellard.org/jslinux` and start the *x86 Alpine Linux* (console) virtual machine.

a) Check the toolchain: `gcc -version` (or `tcc -v`). Upload `engine_signals.h`, `asciiplot.h`, `csvio.h` (`code/common/`) and `code/bonus/jslinux/sheet00/hello_signals.c` with the upload button below the terminal.

```
gcc -O2 -o hello_signals hello_signals.c -lm
./hello_signals
```

b) Explain the plot of the knock signal: where does the burst start, how long does it last, and what is visible before the burst?

c) Modify the program such that it plots one full engine cycle (720°) at 3000 rpm with `knock_prob = 0`. How many samples are needed at $f_s = 50\,\text{kHz}$? Identify the valve impacts and the combustion vibration in the plot.

d) Copy 2–3 seconds of the Wokwi Serial Monitor output from Exercise 0.1 into a file `pot.csv` in JSLinux (`cat > pot.csv`, paste, `Ctrl-D`). Write a short program that reads it with `csv_read()` and plots the voltage column.