

Signed flag	SF	PL
Carry flag	CF	CY
Overflow flag	OF	OV
Parity flag	PF	PE
Zero flag	ZF	ZR
Auxiliary flag	AF	AC

Logical operations always clear Carry & overflow flag.

Not operation doesn't do anything

Unsigned			Signed
cmp	CF	ZF	flags
dest < source	1	0	SF $\neq$ OF
dest > source	0	0	SF = OF
dest = source	0	1	ZF = 1

CLC : clear Carry flag

STC : Set Carry flag

Jmps based on flags, equality, signed & unsigned comparisons.

LOOPZ/LOOPE and LOOPNZ/LOOPNE are same as loop except zero flag is checked.

jz is read as "jump if zero flag is set".

SETTING FLAGS ON CMP/SUB

Unsigned Calculation	Signed Calculation
→ Direct binary sub. → Used for above, below jumps → Check for ZF, CF, AF	→ Conversion to 2's complement & add → Used for greater/less jump → Check for SF, OF → XOR method for OF