

Question 1:**(10 marks)**

Perform Signed Multiplication using Booth's algorithm? Where Multiplicand is **059H** and Multiplier is **(-21)₁₀**?

A(Accumulator)	Q (Multiplier)	Q ₋₁	Steps

Name: _____ Roll No: _____ Section: _____

Question 2:**(10 marks)**

Perform Unsigned Multiplication using Booth's algorithm? Where Multiplicand is and **0DAH**
Multiplier is **(113)₁₀**?

C	Accumulator	Q	Steps

Question 3**(5 marks)**

Run following code and update registers accordingly in HEXA?

<pre> clc mov ax,0B5C9H SHL al,2 SAR ax,3 SAL ax,1 SHR al,1 ROL ax,4 RCR al,2 RCL ax,1 ROR ax,8 </pre>	<table> <tr><td>AX</td><td></td></tr> <tr><td>AL</td><td></td></tr> <tr><td>AX</td><td></td></tr> <tr><td>AX</td><td></td></tr> <tr><td>AL</td><td></td></tr> <tr><td>AX</td><td></td></tr> <tr><td>AL</td><td></td></tr> <tr><td>AX</td><td></td></tr> <tr><td>AX</td><td></td></tr> </table>	AX		AL		AX		AX		AL		AX		AL		AX		AX	
AX																			
AL																			
AX																			
AX																			
AL																			
AX																			
AL																			
AX																			
AX																			