

Mid Tearm

Pdf - 01

1. What is Microprocessors?


Ans: Microprocessor is the core of computer systems. A microprocessor is a multipurpose, programmable, clock-driven, register based electronic device that reads binary instructions from a storage device called memory.

2. Why do we need to learn Microprocessors and Microcontrollers?

Today there is no electronic gadget on the earth which is designed without a Microcontroller. Ex: communication devices, digital entertainment, portable devices etc...

- **Personal information products:** Cell phone, pager, watch, pocket recorder, calculator.
- **Laptop components:** mouse, keyboard, modem, fax card, sound card, battery charger
- **Home appliances:** Door lock, alarm clock, air conditioner, Tv remote etc.
- **Industrial equipment:** Temperature/pressure controllers, Counters, timers, RPM Controllers
- **Toys:** video games, cars, dolls, etc.

3. Explain Microprocessor with block diagram.



i. Arithmetic and Logic Unit (ALU) : It is the place where actual computations take place. Consist of circuits which performs arithmetic operations.

ii. Control Unit (CU): The coordination and control of a computer is the sole responsibility of the Control Unit.

iii. Registers: Registers are temporary storage locations inside microprocessor that holds data and address.


iv. Program counter (PC): It is commonly known as IP (Instruction Pointer) in 8086, is a register in microprocessor that contains the address of the next instruction to be executed.

v. Stack Pointer (SP): It is a small register that stores the address of the last program/instruction request in a stack.

Fig. Block diagram of a Microprocessor.

4. Microprocessor:

- CPU for Computers
- No RAM, ROM, I/O on CPU chip itself
- Example: Intel's x86, Motorola's 680x0



5. What is Microcontroller?

Ans: A microcontroller is a highly integrated single chip, which consists of on chip CPU (Central Processing Unit), RAM (Random Access Memory), EPROM/PROM/ROM (Erasable Programmable Read Only Memory), I/O (input/output) – serial and parallel ports, timers, interrupt controller.

For example: Intel 8051 is 8-bit microcontroller and Intel 8096 is 16-bit microcontroller.

6. Block Diagram of Microcontroller:





Fig. Block Diagram of a Microcontroller

7. Applications of Microcontrollers:

Cell phone, Pager, watch, calculator, video games, Alarm clock, air conditioner, Tv remote, Microwave oven, washing machines, robotic system, anti-lock braking system monitor.

8. Microcontroller:

- A smaller computer
- On-chip RAM, ROM, I/O ports...
- Example: Motorola's 6811, Intel's 8051, Zi log's Z8 and PIC



9. What is RISC (Reduced Instruction Set Computer)?

It stands for Reduced Instruction Set Computer. It is a type of microprocessor architecture that uses a small set of instructions of uniform length. These are simple instructions that are generally executed in one clock cycle. RISC chips are relatively simple to design and inexpensive. **Examples: SPARC, POWER PC etc.**

10. What is CISC (Complex Instruction Set Computer)?

It stands for Complex Instruction Set Computer. These processors offer the users, hundreds of instructions of variable sizes. CISC architecture includes a complete set of special-purpose circuits that carry out these instructions at a very high speed. CISC processors reduce the program size and hence lesser number of memory cycles are required to execute the programs. This increases the overall speed of execution.

Examples: Intel architecture, AMD

11. Distinguish with Microprocessor and Microcontroller.

Microprocessor	Microcontroller
CPU is stand-alone, RAM, ROM, I/O, timer is separate	CPU, RAM, ROM, I/O and timer are all on a single chip
General-purpose	Single-purpose (control-oriented)
Designer can decide on the amount of ROM, RAM and I/O ports.	Fixed amount of on-chip ROM, RAM, I/O ports
High processing power	Low processing power
Typically, 16/32/64 – bit	Typically, 8/16 bit
Typically, deep pipeline (5-20 stages)	Typically, single-cycle/two-stage pipeline

12. Distinguish with RISC and CISC.


RISC	CISC
RISC stands for Reduced Instruction Set Computer. It's focus on software.	CISC stands for Complex Instruction Set Computer. It's focus on Hardware.
Uses only Hardwired control unit.	Uses both hardwired and microprogrammed control unit.
Can perform only Register to Register Arithmetic operations	Can perform REG to REG or REG to MEM or MEM to MEM
RISC is Reduced Instruction Cycle.	CISC is Complex Instruction Cycle.
Simple and limited addressing modes.	Complex and more addressing modes.
Code size is large	Code size is small
Here, addressing modes are less.	Here, addressing modes are more.

Pdf – 02

1. Explain the 8086 Microprocessor

- ✓ It is a 16-bit microprocessor
- ✓ It has 16-bit data bus
- ✓ It has 20-bit address bus
- ✓ 8086 CPU is divided into two independent functional parts.
- ✓ Bus interface unit (BIU)
- ✓ Execution unit (EU)

2. Draw the 8086 internal block diagram and explain the Bus Interface Unit(BIU) and Execution Unit(EU)



***Bus Interface Unit:

1. Instruction Queue-

- ❖ 6-byte queue
- ❖ Prefetch instructions (FIFO)


2. Segment Register-

Start address of a data. It has 4 segment registers that holds address of instruction and data in memory.

- Code Segment register
- Data Segment register
- Extra Segment register
- Stack Segment register

3. Instruction Pointer –

It's a 16 bit register that holds offset of the next instructions in the CS.



***Execution Unit in 8086:

This is an execution unit where instruction decoding and execution takes place.

1. General Purpose Register : Four 16 bit register divided into 2 parts low [8bit] and high [8bit] use for data handling.

- i. AX iii. CX
- ii. BX iv. DX

2. Pointers register : contain offset address.


- SP(Stack pointer)- point to stack, top of stack segment.
 $PA = [SS] * 10H + [SP]$
- BP(Base pointer)- use to access random location of stack.
 $PA = [DS] * 10H + [BP]$

3. Index register:


- DI (Destination Index)
- SI (Source Index)

4. Temporary register: Store temporary

5. ALU : Perform arithmetic and logical Operation.



3. Explain Flag registers with diagram/ format



The flag register is a 16-bit register in the Intel 8086 microprocessor that contains information about the state of the processor after executing an instruction. There are two types of flag register:

1) conditional/status and 2) control flag

1. Conditional/ Status flag:

- **Carry flag-** It is set whenever there is a carry or borrow out of the MSB (most significant bit) of a result. D7 bit for an 8-bit operation and D15 bit for a 16-bit operation.
- **Auxiliary carry flag-** this flag is set when ALU perform BCD operation of 8-bit and if result in a carry or borrow.
- **Parity flag-** It is set if the result has even parity. If parity is odd, PF is reset.
- **Zero flag-** This flag is set 1 when the result of ALU operation is zero else it is set to zero.
- **Sign flag-** It is set if the MSB of the result is 1.
- **Overflow flag-** It will be set if the result of a signed operation is too large to fit in the number of bits available to represent it.

2. Control Flag:

- **Trap flag-** It is used to set the trace mode i.e. start single stepping mode.
- **Interrupt flag-** this flag is used to enable or disable interrupt. It is set to 1 for interrupt enabled and set to 0 for interrupt disabled
- **Direction flag-** It is used in string operation.