

Comprehensive Foundation in Quantum Computing

From Probability and Complex Numbers to Qubits, Interference, Entanglement and Multi-Qubit Systems

Dr. Syed Muzamil Basha

Professor, School of Computer Science and Engineering
REVA University

Learning Journey

Mathematical foundation

- Probability and measurement
- Complex numbers and amplitudes
- Vectors, matrices and transformations
- Bra-ket notation for quantum states

Quantum foundation


- Classical bit vs qubit
- Superposition and interference
- Entanglement and correlations
- Multi-qubit state spaces and circuits

Guiding idea

Quantum computing becomes easier when every mathematical object is connected to a physical meaning and a practical operation.

Why Mathematics Matters in Quantum Computing

Math tool	Quantum role
Probability	Predicts measurement outcomes
Complex numbers	Store probability amplitudes and phase
Vectors	Represent quantum states
Matrices	Represent gates and transformations
Tensor products	Build multi-qubit states



Think of the mathematics as the language used to describe, transform and finally measure a quantum system.

Probability Theory: From Chance to Quantum Measurement

Classical probability

For mutually exclusive outcomes 0 and 1,

$$P(0) + P(1) = 1.$$


Example: a fair coin gives $P(H) = P(T) = 0.5$.

Quantum interpretation

A qubit can produce either 0 or 1 when measured, but before measurement its state may contain amplitudes for both outcomes.

$$P(0) = |\alpha|^2, \quad P(1) = |\beta|^2.$$

Real-world link: quantum sensors and communication protocols rely on predicting measurement statistics, not a single deterministic readout.




Complex Numbers: The Hidden Language of Phase

A complex number is written as

$$z = a + ib, \quad i^2 = -1.$$

- a is the real part.
- b is the imaginary part.
- Magnitude: $|z| = \sqrt{a^2 + b^2}$.
- Phase controls how amplitudes combine.



Quantum connection

Quantum amplitudes are generally complex. Measurement probabilities use the squared magnitude $|\alpha|^2$, while the relative phase influences interference.

Real-world link: phase-sensitive measurements appear in quantum communication, sensing and interferometry.

Vectors and Matrices: States and Quantum Gates

State = vector

The computational basis is

$$|0\rangle = \begin{bmatrix} 1 \\ 0 \end{bmatrix}, \quad |1\rangle = \begin{bmatrix} 0 \\ 1 \end{bmatrix}.$$

A general qubit state is

$$|\psi\rangle = \alpha |0\rangle + \beta |1\rangle, \quad |\alpha|^2 + |\beta|^2 = 1.$$

Gate = matrix transformation

A quantum gate is a unitary matrix U :

$$|\psi'\rangle = U |\psi\rangle.$$

For example, the Pauli- X gate is

$$X = \begin{bmatrix} 0 & 1 \\ 1 & 0 \end{bmatrix}$$


and swaps $|0\rangle \leftrightarrow |1\rangle$.

Key intuition

Vectors describe *where the quantum state is*; matrices describe *how we move it*.

Classical System vs Quantum System

	Classical	Quantum
Information unit	Bit: 0 or 1	Qubit: $\alpha 0\rangle + \beta 1\rangle$
State description	Usually one definite value	Probability amplitudes + phase
Operations	Boolean/logical operations	Unitary quantum gates
Observation	Reads stored state	Measurement produces classical outcome
Correlation	Classical correlation	Can include entanglement



Quantum computing does not replace classical computing everywhere; it changes the computational model for selected problems.

Qubits: The Basic Quantum Information Unit

Definition

A qubit is a two-level quantum system with state


$$|\psi\rangle = \alpha |0\rangle + \beta |1\rangle .$$

The normalization condition is

$$|\alpha|^2 + |\beta|^2 = 1.$$

- $|0\rangle$ and $|1\rangle$ are basis states.
- α, β are probability amplitudes.
- **Measurement returns a classical result.**

The Bloch sphere is a visualization for a single qubit; it turns an abstract two-dimensional complex state into a geometric picture.



Superposition: More Than a Classical 0-or-1 Choice

Start with $|0\rangle$ and apply the Hadamard gate:


$$H = \frac{1}{\sqrt{2}} \begin{bmatrix} 1 & 1 \\ 1 & -1 \end{bmatrix}.$$

Then

$$H|0\rangle = \frac{|0\rangle + |1\rangle}{\sqrt{2}}.$$

Therefore,

$$P(0) = P(1) = \frac{1}{2}.$$



Real-world link

Superposition enables quantum algorithms to manipulate amplitudes before measurement. It is the starting point for interference-based speedups.

Interference: Why Amplitudes, Not Just Probabilities, Matter

Core idea

Quantum amplitudes can be positive, negative or complex. When computational paths meet, amplitudes add before probabilities are calculated.

$$P(x) = |A_x|^2.$$


Constructive interference increases $|A_x|$; destructive interference reduces it.

Simple intuition

$$+A + A = 2A \quad \text{constructive}$$

$$+A - A = 0 \quad \text{destructive}$$

Quantum algorithms are designed so desirable outcomes interfere constructively and undesirable outcomes interfere destructively.



Bra-Ket Notation: A Compact Language for Quantum States

Ket: state vector

$$|\psi\rangle$$

reads as “the state ψ ”. For a qubit,

$$|\psi\rangle = \alpha |0\rangle + \beta |1\rangle.$$

Bra: dual vector

$$\langle\psi|$$

is the conjugate transpose of $|\psi\rangle$.

Inner product

$$\langle\psi|\phi\rangle$$

measures overlap between states.

Outer product

$$|\psi\rangle\langle\phi|$$

produces an operator (matrix).

Why use it?


Bra-ket notation keeps equations short while preserving the physical meaning of states, overlaps and operators.

Quantum Gates: Controlled State Transformations

Gate	Interpretation
X	Bit flip: $ 0\rangle \leftrightarrow 1\rangle$
Z	Phase flip: $ 1\rangle \mapsto - 1\rangle$
H	Creates/removes equal superposition
CNOT	Conditional flip; essential for entanglement

Unitary principle

Quantum gates preserve total probability. Mathematically, $U^\dagger U = I$.



Entanglement: Correlation Beyond Independent Qubits


Bell state example

A common two-qubit entangled state is

$$|\Phi^+\rangle = \frac{|00\rangle + |11\rangle}{\sqrt{2}}.$$

The two qubits cannot be described independently by assigning each one a complete pure state.

- Measuring in the computational basis gives 00 or 11.
- Each individual qubit is locally random.
- The joint outcomes are strongly correlated.



Real-world quantum applications

Entanglement is central to quantum communication, distributed quantum protocols, teleportation and many quantum algorithms.

Multi-Qubit Systems: The State Space Grows Exponentially

For n qubits, the computational basis contains

$$2^n$$

basis states.

Qubits	Basis states
1	2
2	4
3	8
4	16
10	1024
20	1,048,576

Tensor product

Two single-qubit states combine as

$$|\psi_1\rangle \otimes |\psi_2\rangle .$$

For example,

$$|0\rangle \otimes |1\rangle = |01\rangle .$$

Why it matters

The exponential state-space size is one reason quantum systems are difficult to simulate classically and potentially useful for certain computational tasks.

Measurement: Turning Quantum Information into Classical Information


Single qubit

For

$$|\psi\rangle = \alpha |0\rangle + \beta |1\rangle,$$

measurement in the computational basis returns

0 with probability $|\alpha|^2$, 1 with probability $|\beta|^2$.



Important distinction

The quantum state contains amplitudes; measurement produces a classical sample. Repeating the experiment lets us estimate probabilities.

From Theory to Practice: A Minimal Quantum Workflow



Prepare

Initialize qubits in $|0\rangle$, $|1\rangle$ or a designed state.

Transform

Use unitary gates such as X , H , Z and controlled gates.

Measure and analyse

Convert quantum information to samples, counts, probabilities or application-specific results.

This workflow underlies practical quantum programs in SDKs such as Qiskit and other quantum software stacks.

Real-World Quantum Applications

Near-term / hybrid applications

- Quantum machine learning experiments
- Variational optimization
- Quantum chemistry and materials simulation
- Quantum-enhanced sensing and metrology

Longer-term directions

- Cryptography and secure communication
- Large-scale simulation of quantum systems
- Fault-tolerant quantum algorithms
- Selected combinatorial and algebraic problems

Use the right question

The key question is not “Is quantum computing faster for everything?” but “Which problem structure can benefit from quantum state preparation, interference, entanglement or a quantum subroutine?”

Foundation Check: Can You Connect the Pieces?

Quick questions

- 1 Why must probabilities add to 1?
- 2 Why do quantum amplitudes use complex numbers?
- 3 What does $|\psi\rangle = \alpha|0\rangle + \beta|1\rangle$ mean?
- 4 What does a unitary matrix do?

Explain in your own words

- 1 Superposition
- 2 Interference
- 3 Entanglement
- 4 Multi-qubit state space

If you can explain these four ideas without equations, the equations become much easier to learn.

Summary: The Quantum Computing Foundation

Mathematical toolkit

- Probability $\rightarrow$ measurement statistics
- Complex numbers $\rightarrow$ amplitudes and phase
- Vectors $\rightarrow$ quantum states
- Matrices $\rightarrow$ quantum operations
- Tensor products $\rightarrow$ multi-qubit systems

Quantum concepts

- Qubit instead of classical bit
- Superposition before measurement
- Interference of probability amplitudes
- Entanglement between quantum systems
- Measurement produces classical information

Foundation: Mathematics $\rightarrow$ Quantum states $\rightarrow$ Gates $\rightarrow$ Measurement $\rightarrow$ Applications