

Comprehensive Foundation in Quantum Computing

From Probability and Complex Numbers to Qubits, Interference, Entanglement and Multi-Qubit Systems

Dr. Syed Muzamil Basha

Professor, School of Computer Science and Engineering
REVA University

Learning Journey

Mathematical foundation

- Probability and measurement
- Complex numbers and amplitudes
- Vectors, matrices and transformations
- Bra-ket notation for quantum states

Quantum foundation

- Classical bit vs qubit
- Superposition and interference
- Entanglement and correlations
- Multi-qubit state spaces and circuits

Guiding idea

Quantum computing becomes easier when every mathematical object is connected to a physical meaning and a practical operation.

Understand: Think of the course as a new language: mathematics is the vocabulary, qubits are the objects, and gates are the actions that change them.


Learn with Fun: Imagine a 4-level game: Math, Qubits, Quantum Effects, Applications. Unlock each level by explaining the previous one in plain words.

Why Mathematics Matters in Quantum Computing

Math tool	Quantum role
Probability	Predicts measurement outcomes
Complex numbers	Store probability amplitudes and phase
Vectors	Represent quantum states
Matrices	Represent gates and transformations
Tensor products	Build multi-qubit states

Understand: Probability predicts outcomes, complex numbers carry phase, vectors describe states, and matrices describe transformations. Each mathematical tool has a specific job.

Learn with Fun: Think of a smartphone: numbers describe its state and commands change it. Quantum computing follows the same idea, but with quantum rules.



Probability Theory: From Chance to Quantum Measurement

Classical probability

For mutually exclusive outcomes 0 and 1,

$$P(0) + P(1) = 1.$$


Example: a fair coin gives $P(H) = P(T) = 0.5$.

Quantum interpretation

A qubit can produce either 0 or 1 when measured, but before measurement its state may contain amplitudes for both outcomes.

$$P(0) = |\alpha|^2, \quad P(1) = |\beta|^2.$$

Understand: A quantum computer usually gives samples rather than one guaranteed answer. Repeated measurements reveal the underlying probabilities.




Learn with Fun: Coin-toss game: predict 0 or 1, repeat 20 times, and draw a histogram. That simple activity is a good model for learning quantum measurement statistics.

Complex Numbers: The Hidden Language of Phase

A complex number is written as

$$z = a + ib, \quad i^2 = -1.$$

- a is the real part.
- b is the imaginary part.
- Magnitude: $|z| = \sqrt{a^2 + b^2}$.
- Phase controls how amplitudes combine.



Quantum connection

Quantum amplitudes are generally complex. Measurement probabilities use the squared magnitude $|\alpha|^2$, while the relative phase influences interference.

Understand: Magnitude tells us how large an amplitude is; phase tells us how it is oriented relative to another amplitude. Relative phase can change the final result.

Learn with Fun: Imagine two people pushing a swing. Push together and the motion grows; push in opposite directions and they can cancel. Phase captures this relative relationship.

Vectors and Matrices: States and Quantum Gates

State = vector

The computational basis is

$$|0\rangle = \begin{bmatrix} 1 \\ 0 \end{bmatrix}, \quad |1\rangle = \begin{bmatrix} 0 \\ 1 \end{bmatrix}.$$

A general qubit state is

$$|\psi\rangle = \alpha |0\rangle + \beta |1\rangle, \quad |\alpha|^2 + |\beta|^2 = 1.$$

Gate = matrix transformation

A quantum gate is a unitary matrix U :

$$|\psi'\rangle = U |\psi\rangle.$$

For example, the Pauli- X gate is

$$X = \begin{bmatrix} 0 & 1 \\ 1 & 0 \end{bmatrix}$$

and swaps $|0\rangle \leftrightarrow |1\rangle$.

Key intuition


Vectors describe *where the quantum state is*; matrices describe *how we move it*.

Understand: A vector describes the current quantum state. A matrix gives the rule for transforming that state. Read $U|\psi\rangle$ as: apply U to the state $|\psi\rangle$.

Learn with Fun: Use a game controller analogy: the character position is the state, while a button press is the operation that changes the state.

Classical System vs Quantum System

	Classical	Quantum
Information unit	Bit: 0 or 1	Qubit: $\alpha 0\rangle + \beta 1\rangle$
State description	Usually one definite value	Probability amplitudes + phase
Operations	Boolean/logical operations	Unitary quantum gates
Observation	Reads stored state	Measurement produces classical outcome
Correlation	Classical correlation	Can include entanglement



Understand: A classical bit is 0 or 1. A qubit uses amplitudes for basis states before measurement. The important difference is how quantum states are transformed, not the ability to read many answers at once.

Learn with Fun: Light-switch scenario: a normal switch is ON or OFF. A qubit is better imagined as a controllable quantum state whose measurement eventually gives 0 or 1.

Qubits: The Basic Quantum Information Unit

Definition

A qubit is a two-level quantum system with state


$$|\psi\rangle = \alpha |0\rangle + \beta |1\rangle .$$

The normalization condition is

$$|\alpha|^2 + |\beta|^2 = 1.$$

- $|0\rangle$ and $|1\rangle$ are basis states.
- α, β are probability amplitudes.
- Measurement returns a classical result

Understand: Alpha and beta are amplitudes, not ordinary probabilities. Their squared magnitudes become probabilities at measurement, and normalization makes the total probability equal to 1.



Learn with Fun: Imagine a quantum dial pointing somewhere on a globe. You do not need the geometry yet; remember that a qubit has many possible internal states but two computational measurement labels.

Superposition: More Than a Classical 0-or-1 Choice

Start with $|0\rangle$ and apply the Hadamard gate:

$$H = \frac{1}{\sqrt{2}} \begin{bmatrix} 1 & 1 \\ 1 & -1 \end{bmatrix}.$$


Then

$$H|0\rangle = \frac{|0\rangle + |1\rangle}{\sqrt{2}}.$$

Therefore,

$$P(0) = P(1) = \frac{1}{2}.$$

Understand: Superposition means the state is a linear combination of basis states. Measurement still returns one classical result, so superposition describes the state before observation.



not a classical mixture
of hidden values

Real-world link

Superposition enables quantum algorithms to manipulate amplitudes before measurement. It is the starting point for interference-based speedups.

Learn with Fun: Spinner scenario: before a spinner stops, several landing directions are possible. The analogy is not exact, but it helps separate the pre-measurement state from the final observed result.


Interference: Why Amplitudes, Not Just Probabilities, Matter

Core idea

Quantum amplitudes can be positive, negative or complex. When computational paths meet, amplitudes add before probabilities are calculated.

$$P(x) = |A_x|^2.$$

Constructive interference increases $|A_x|$; destructive interference reduces it.



Simple intuition

$$+A + A = 2A \quad \text{constructive}$$

$$+A - A = 0 \quad \text{destructive}$$

Understand: Quantum algorithms control amplitudes so useful paths reinforce one another and unwanted paths cancel. This is why interference is more than simply adding probabilities.

Learn with Fun: Wave-on-a-rope game: waves moving together can grow; waves moving in opposite phase can flatten. Quantum amplitudes can combine in the same constructive or destructive way.

Bra-Ket Notation: A Compact Language for Quantum States

Ket: state vector

$$|\psi\rangle$$

reads as “the state ψ ”. For a qubit,

$$|\psi\rangle = \alpha |0\rangle + \beta |1\rangle.$$

Bra: dual vector

$$\langle\psi|$$

is the conjugate transpose of $|\psi\rangle$.

Understand: A ket names a state, a bra is its conjugate-transpose partner, and an inner product measures overlap between states. Outer products can build operators.

Inner product

$$\langle\psi|\phi\rangle$$

measures overlap between states.

Outer product

$$|\psi\rangle\langle\phi|$$

produces an operator (matrix).


Why use it?

Bra-ket notation keeps equations short while preserving the physical meaning of states, overlaps and operators.

Learn with Fun: Think of two contact cards: one is the state being described, the other is the comparison query. The inner product acts like a similarity score.

Quantum Gates: Controlled State Transformations

Gate	Interpretation
X	Bit flip: $ 0\rangle \leftrightarrow 1\rangle$
Z	Phase flip: $ 1\rangle \mapsto - 1\rangle$
H	Creates/removes equal superposition
CNOT	Conditional flip; essential for entanglement



Unitary principle

Quantum gates preserve total probability. Mathematically,
 $U^\dagger U = I$.

Understand: X flips the computational value, Z changes phase, H creates or removes balanced superposition, and CNOT applies a conditional flip. Gates are reversible and preserve total probability.

Learn with Fun: Board-game scenario: each gate is a legal move. You can rearrange the state, but you cannot create or destroy total probability. CNOT means: flip the second player only when the first player is 1.

Entanglement: Correlation Beyond Independent Qubits


Bell state example

A common two-qubit entangled state is

$$|\Phi^+\rangle = \frac{|00\rangle + |11\rangle}{\sqrt{2}}.$$

The two qubits cannot be described independently by assigning each one a complete pure state.

- Measuring in the computational basis gives 00 or 11.
- Each individual qubit is locally random.
- The joint outcomes are strongly correlated.



H + CNOT
generates entanglement

Real-world quantum applications

Entanglement is central to quantum communication, distributed quantum protocols, teleportation and many quantum algorithms.

Understand: Entanglement means the joint quantum state cannot always be reduced to two independent single-qubit states. Measuring one part can strongly constrain correlated outcomes of the other.

Learn with Fun: Paired-glove analogy: finding a left glove tells you the other is right. Quantum entanglement is richer than this classical analogy because the correlations come from one joint quantum state.

Multi-Qubit Systems: The State Space Grows Exponentially

For n qubits, the computational basis contains

$$2^n$$

basis states.

Qubits	Basis states
1	2
2	4
3	8
4	16
10	1024
20	1,048,576

Understand: Every additional qubit doubles the number of computational basis states. The state space grows rapidly, but preparing, controlling and reading that space is challenging.

Tensor product

Two single-qubit states combine as

$$|\psi_1\rangle \otimes |\psi_2\rangle.$$

For example,

$$|0\rangle \otimes |1\rangle = |01\rangle.$$

Why it matters

The exponential state-space size is one reason quantum systems are difficult to simulate classically and potentially useful for certain computational tasks.

Learn with Fun: Library scenario: one yes-or-no choice gives 2 possibilities; two give 4; three give 8. Keep doubling as each new independent binary dimension is added.

Measurement: Turning Quantum Information into Classical Information


Single qubit

For

$$|\psi\rangle = \alpha |0\rangle + \beta |1\rangle,$$

measurement in the computational basis returns

0 with probability $|\alpha|^2$, 1 with probability $|\beta|^2$.



Important distinction

The quantum state contains amplitudes; measurement produces a classical sample. Repeating the experiment lets us estimate probabilities.

Understand: Measurement is the bridge from quantum information to ordinary data. One run produces one outcome; many runs let us estimate the probability distribution.

Learn with Fun: Mystery-box scenario: one opening is only one data point. Open many boxes, count the results, and use the frequencies to understand the hidden distribution.

From Theory to Practice: A Minimal Quantum Workflow



Prepare

Initialize qubits in $|0\rangle$, $|1\rangle$ or a designed state.

Understand: A practical quantum program follows a loop: prepare, transform, measure, then analyse repeated results. Classical computers usually coordinate these steps.

Transform

Use unitary gates such as X , H , Z and controlled gates.

Measure and analyse

Convert quantum information to samples, counts, probabilities or application-specific results.

Learn with Fun: Recipe scenario: gather ingredients, cook, taste one sample, then adjust and repeat. Quantum workflows also combine preparation, operations, measurement and analysis.

Real-World Quantum Applications

Near-term / hybrid applications

- Quantum machine learning experiments
- Variational optimization
- Quantum chemistry and materials simulation
- Quantum-enhanced sensing and metrology

Longer-term directions

- Cryptography and secure communication
- Large-scale simulation of quantum systems
- Fault-tolerant quantum algorithms
- Selected combinatorial and algebraic problems

Use the right question

The key question is not “Is quantum computing faster for everything?” but “Which problem structure can benefit from quantum state preparation, interference, entanglement or a quantum subroutine?”

Understand: Quantum computing is not a replacement for classical computing. Potential benefit depends on the problem structure, the algorithm and the ability to control a useful quantum processor.

Learn with Fun: Choose-the-tool scenario: use a calculator for arithmetic, a database for lookup and a microscope for tiny objects. Quantum hardware is another specialised tool.

Foundation Check: Can You Connect the Pieces?

Quick questions

- 1 Why must probabilities add to 1?
- 2 Why do quantum amplitudes use complex numbers?
- 3 What does $|\psi\rangle = \alpha|0\rangle + \beta|1\rangle$ mean?
- 4 What does a unitary matrix do?

Explain in your own words

- 1 Superposition
- 2 Interference
- 3 Entanglement
- 4 Multi-qubit state space

If you can explain these four ideas without equations, the equations become much easier to learn.

Understand: Explain the ideas without equations first. If you can describe state, operation, interference, correlation and measurement in plain language, the formulas become easier to learn.

Learn with Fun: 30-second challenge: explain superposition using a coin, spinner or music-wave example. Do not use the word amplitude until the final sentence.

Summary: The Quantum Computing Foundation

Mathematical toolkit

- Probability → measurement statistics
- Complex numbers → amplitudes and phase
- Vectors → quantum states
- Matrices → quantum operations
- Tensor products → multi-qubit systems

Quantum concepts

- Qubit instead of classical bit
- Superposition before measurement
- Interference of probability amplitudes
- Entanglement between quantum systems
- Measurement produces classical information

Foundation: Mathematics → Quantum states → Gates → Measurement → Applications

Understand: The complete story is one chain: mathematics describes states, gates transform them, interference reshapes amplitudes, entanglement creates joint correlations, and measurement produces classical data.

Learn with Fun: Imagine a quantum storyboard: build the scene, move the characters, let waves reinforce or cancel, observe the ending, and use the result in an application.