D | Crimping your own cable

R
KMK III

Sie arbeiten als Netzwerk Adminstrator in einem deutschen Unternehmen. Ein Kollege muss ein neues Netzwerkkabel krimpen und hat folgende Anweisung aus dem Internet heruntergeladen. Da er nur wenig Englisch kann, bittet er Sie um Hilfe. Lesen Sie den Text durch und führen Sie folgende Schritte aus:

1. Erstellen Sie eine Liste der Werkzeuge und Materialien, die er brauchen wird. Geben Sie auch die deutschen Bezeichnungen an.
2. Erstellen Sie eine stichwortartige Liste der einzelnen Arbeitsschritte auf Deutsch.

http://ww#.10minutetutorials.net

Tutorial number 3 | **Crimping your own CAT5 ethernet cable**

- Cut off the desired length plus a few extra centimetres from the cable roll.
- Strip the outer insulation of both ends using the insulation stripping pliers.
- Strip away about 20mm of the outer insulation. It will make it easier to work with the inner wires.

  ! Safety notice: Do this with great care so as not to damage the insulation of the inner wires.
- Examine the inner wires. If you have damaged the insulation, you will have to cut away the exposed wire and start again. Damaged insulation and subsequently bridging the wires may cause crosstalk.
- There are 8 wires with different colours. Two of them are twisted together at a time to form four twisted pairs.
- Untwist those pairs. Next align them from left to right as follows:

  white orange | orange | white green | blue | white blue | green | white brown | brown
- Once the wires are correctly arranged, shorten the inner wires by about 12 mm.
- This is done to ensure that the wires will fit neatly into the RJ-45 plug later.
- Recheck the alignment and insert the wires into the plug. Make sure that you push the wires all the way to the front end of the plug.
- Insert the wired plug into the crimping tool and firmly but evenly squeeze the handles. You should hear a ratcheting sound.
- Release the pressure on the handles and let them return to the starting position.
- Better safe than sorry so crimp it once more.
- Repeat the steps for the other end of the wire.
- When you are done, test the new wire with the circuit indicator.

WORD BANK

central node – zentraler Knotenpunkt
data delivery – Datenauslieferung
go down (v) – ausfallen
helpdesk – Hotline
insulation – Isolierung
mesh – Gitter
node – Knotenpunkt
plug in (v) – einstecken

WORD BANK ⊙

engineering department – Konstruktionsabteilung
IP address field – IP-Adressfeld
mail server tab – Mail-Server-Karteireiterkarte
menu bar – Menüleiste
operating system – Betriebssystem
secure connection – sichere Verbindung
VPN client installer – Installationsprogramm für den VPN Client