

- Verify primary/backup path
 - From R1, `traceroute 192.168.4.1`
- 1/3-second timers
 - On R1, R2, R3, R4,

```

conf t

int gi0/0
 ip ospf hello-interval 1
 ip ospf dead-interval 3
 exit

int gi0/1
 ip ospf hello-interval 1
 ip ospf dead-interval 3
 exit

end

```

- Failure + convergence test
 - From R1, shutdown g0/0 link
 -
- ```

Neighbor ID Pri State Dead Time Address
3.3.3.3 1 FULL/DR 00:00:02 10.0.13.2
r1#traceroute 192.168.4.1
Type escape sequence to abort.
Tracing the route to 192.168.4.1

 0 10.0.13.2 0 msec 0 msec 0 msec
 1 10.0.34.2 0 msec 0 msec 0 msec

```
- Now, up the port and notice ospf chooses

lowest cost,

o

```
r1#
r1#traceroute 192.168.4.1
Type escape sequence to abort.
Tracing the route to 192.168.4.1

 1 10.0.12.2 0 msec 0 msec 0 msec
 2 10.0.24.2 0 msec 0 msec 0 msec
r1#
--
```

- `show ip ospf neighbor`
- `show ip ospf interface`
- `show ip ospf`
- `show ip route ospf`
- `show ip protocols`
- `show ip ospf database`
- `show bfd neighbors`