

VIETNAM NATIONAL UNIVERSITY HO CHI MINH CITY
HO CHI MINH CITY UNIVERSITY OF TECHNOLOGY
FACULTY OF COMPUTER SCIENCE AND ENGINEERING



Embedded Systems (CO3053)

Assignment 2 Report

**Coin-Operated Washing
Machine Control Unit on the
WeAct STM32H750**

Advisor(s): Assoc. Prof. Phạm Hoàng Anh

Student(s): Võ Hoàng Nguyên 2352844

Nguyễn Quốc Thắng 2353122

Ngô Nguyễn Thành Nhân 2352849

HO CHI MINH CITY, OCTOBER 2026



► **VIDEO DEMO — running on the real board**

Demonstration video of the coin-operated washing machine control unit running on the real board.

Watch on YouTube:

<https://youtube.com/shorts/ZFKOPDyJHqQ>

(Click the link, or scan the QR code with a phone.)



Contents

1	Introduction	8
1.1	Problem Statement and Assignment Objectives	8
1.2	Problem Specification	8
1.3	Six Families of Embedded Design Challenges	9
1.4	Real-Time Taxonomy: Soft vs. Hard Real-Time Domains	11
1.5	Quantified Engineering Bounds	11
1.6	Scope of Deliverables	12
2	System Requirements & Specification Analysis	13
2.1	System Boundary and Signal Definitions	13
2.2	Functional Requirements	14
2.3	Engineering Parameter Provenance: Where the Numbers Come From . . .	16
2.4	Non-Functional Requirements	18
2.5	Architectural Assumptions and Boundary Disambiguation	18
3	System Analysis & Safety Invariants	20
3.1	Operational Lifecycle Analysis	20
3.2	System Boundary and Interconnect Architecture	21
3.3	Formal Safety Invariants	22
3.4	State Space Partitioning: Qualitative Modes vs Quantitative Context . . .	23
4	Finite State Machine Design	25
4.1	Formal Mathematical Specification	25
4.1.1	Constituent Sets and Context Spaces	25



4.1.2	Machine Classification: Hybrid Moore-Mealy Model	26
4.2	State Transition Diagrams	26
4.3	State Transition Table	28
4.4	Determinism and Completeness Theorem	30
4.5	Moore Output Function Mapping	31
5	Hardware Design & Target Microcontroller Implementation	32
5.1	Target Platform: WeAct Studio MiniSTM32H750 Core Board	32
5.2	Clock Tree Derivation and Power Management	33
5.2.1	Internal Power Regulation (LDO at VOS1)	33
5.2.2	Mathematical Derivation of PLL1 Frequencies	34
5.2.3	Internal Bus Prescalers and Flash Wait States	34
5.2.4	SysTick Down-Counter Dimensioning	35
5.2.5	Fail-Safe HSI Fallback Mechanism	35
5.2.6	Hardware Reset Cause Decoding	35
5.3	Display Architecture: SPI4 Bandwidth and Framebuffer Derivations	35
5.3.1	RAM Framebuffer Footprint	36
5.3.2	SPI4 Bus Transfer Bandwidth	36
5.3.3	Event-Driven Dirty-Flag Optimization	36
5.4	Input Mapping: Multi-Gesture Decoding on Single Key K1	37
5.5	Pin Multiplexing and Electrical Interface	38
5.6	Physical Interconnection Diagram	39
6	Software Architecture & Component Design	40
6.1	Architectural Paradigm: Layered Abstraction and Dependency Inversion .	40
6.2	Modular Decomposition and Source File Responsibilities	41
6.3	Decoupling via the Dependency Inversion Principle	43
6.4	Event Dispatch Sequence	44
7	Timing Design & Non-Blocking Scheduling	44
7.1	System Timing Specifications	44
7.2	Single Time-Base Paradigm and Zero-Blocking Discipline	45
7.3	Mathematical Proof of Zero Cumulative Timing Drift	46
7.4	Modulo Phase Preservation in Optical Blinker Drivers	48
7.5	Double-Press STOP Timing Geometry	48



8	Software Implementation & MISRA-C:2012 Compliance	49
8.1	Formal MISRA-C:2012 Compliance Matrix	49
8.2	State, Event, and Context Encapsulation	50
8.3	Deterministic Event Dispatcher	51
8.4	Coin Accumulation and Unconditional Zero Refund	53
8.5	Actuator Safety Interlock Invariant Code	53
8.6	Double-Press STOP and Persistent Countdown Handlers	54
8.7	Debounce Integration and Non-Preemptive Super-Loop	55
9	Flowcharts	57
9.1	Main program	57
9.2	Coin processing	58
9.3	RUN / PAUSE / STOP handling	59
9.4	Multi-Gesture Decoding Engine	60
9.5	Emergency Safety Fault Handling and Context Recovery	60
10	Test Plan and Verification Strategy	62
10.1	Verification Methodology and Test Architecture	62
10.2	Requirements Traceability Matrix (RTM)	62
10.3	Automated Unit and Regression Test Suites	65
10.4	Sub-Millisecond Boundary Condition Validation	65
10.5	Physical In-System Test Scenarios	66
11	Experimental Results and Verification Metrics	69
11.1	Automated Unit and Regression Test Metrics	69
11.2	Physical In-System Test Validation on STM32H750	70
11.3	Physical Dashboard and Indication States	72
11.4	LCD Graphical Dashboard Frames	72
11.5	Serial Telemetry Real-Time Stream	73
11.6	Memory Footprint and Resource Utilization	74
12	Engineering Discussion and Architectural Trade-Offs	76
12.1	Architectural Trade-Off Analysis	76
12.1.1	Front-Panel User Interface Topologies	76
12.1.2	Kernel Timing: Asynchronous ISR vs. Monotonic Super-Loop . . .	78
12.2	Deep-Dive into Critical Edge Cases and Hazard Mitigations	79
12.2.1	Persistent Timer During PAUSE (TC-07, TC-08)	79



12.2.2 Double-Press STOP Timing Margin Verification (TC-22)	79
12.2.3 Arithmetic Overflow Immunity in Financial Accumulation (TC-25)	79
12.2.4 Cross-Phase Temporal Transition During PAUSE (TC-29)	80
12.3 Engineering Limitations and Industrial Production Roadmap	80
13 Conclusion and Compliance Verification	81
13.1 Executive Engineering Summary	81
13.2 Course Specification Compliance Checklist	82
13.3 Conformity with Empirical Truth (“Mình Làm Gì Việt Đó”)	84
A Source code	86
A.1 FSM	86
A.2 Input and output engines	105
A.3 Board firmware	118
B Pin configuration	131
C Full test logs	132



List of Figures

3.1	Formal system boundary diagram of the coin-operated washing machine control unit	21
4.1	Formal state transition diagram: Nominal operation (T05 and T12 denote internal window arming)	27
4.2	Formal state transition diagram: Asynchronous safety fault handling and context restoration	28
5.1	Hardware interconnect diagram of the WeAct STM32H750 implementation	39
6.1	Layered software architecture of the washing machine control system . . .	41
6.2	UML sequence diagram: Deterministic signal propagation from physical press to actuator callback	44
7.1	Single time-base architecture: Deterministic derivation of all software timers from SysTick	46
7.2	Timing geometry of the double-press STOP confirmation window	48
9.1	Main program flowchart (non-blocking super-loop)	57
9.2	Coin processing in the FSM	58
9.3	Coin staging on the board's single-key front panel	59
9.4	RUN / PAUSE / STOP handling (the 1 ms tick resets n when w expires) .	59
9.5	Multi-gesture button decoder sub-machine flowchart (<code>hal_button_gesture.c</code>)	60
9.6	Emergency fault trip and context-preserving recovery flowchart	61
11.1	Photographs of the physical hardware target operating across primary operational states	72
11.2	Pixel-accurate graphical dashboard states rendered by the firmware presentation pipeline	73

List of Tables

1.1	Priority ranking of the six embedded design challenge families	10
2.1	Logical input signals processed by the control unit	13
2.2	Logical actuator and indicator outputs generated by the control unit . . .	14
2.3	Formal functional requirements	15
2.4	Architectural design assumptions and interface resolutions	19
3.1	Formal state space of the washing machine control unit	24
4.1	Complete and deterministic state transition table	28
4.2	Exhaustive Event-Acceptance Matrix ($6 \times 10 = 60$ Combinations)	31



4.3	Static Moore Output Function Mapping $\omega_{\text{Moore}}(s)$	31
5.1	Physical hardware resources allocated on the STM32H750 target	33
5.2	Deterministic K1 multi-gesture mapping across operational states	38
5.3	Microcontroller pin mapping and peripheral multiplexing	38
6.1	Software modules and component breakdown	41
7.1	System timing constants and physical derivations	45
8.1	MISRA-C:2012 compliance verification and implementation evidence . . .	50
10.1	Formal Requirements Traceability Matrix (RTM)	62
10.2	Physical System Integration Test Scenarios	66
11.1	Quantitative Automated Test Results and Specification Coverage	69
11.2	In-System Physical Test Results on STM32H750VBT6 Target	70
11.3	Target Firmware Memory Footprint (<code>arm-none-eabi-size build/h750/washer.elf</code>)	75
12.1	Multi-Criteria Evaluation of Front-Panel Input Architectures	77
13.1	100 % Assignment Specification Compliance Verification Matrix	83
B.1	Register-level pin configuration	132

1 Introduction

1.1 Problem Statement and Assignment Objectives

The primary objective of this assignment is to design, specify, implement, and rigorously verify the *control unit* of a coin-operated washing machine, following the standard V-model embedded-system engineering methodology: formal requirements $\rightarrow$ domain analysis $\rightarrow$ finite-state-machine (FSM) mathematical modeling $\rightarrow$ hardware-abstraction and driver implementation on a physical microcontroller $\rightarrow$ exhaustive verification. The report is systematically structured to resolve four foundational questions:

1. **What must the system do?** (Section 2: Functional and non-functional requirements; Section 3: Operational modes and state variables).
2. **How is it designed?** (Section 4: Mathematical FSM formalization; Section 5: Hardware architecture; Section 6: Software layering; Section 7: Non-blocking timing infrastructure).
3. **How is it implemented?** (Section 8: C99 MISRA-C compliance; Section 9: Procedural execution flows).
4. **How do we prove it works?** (Section 10: Verification strategy; Section 11: Empirical testbed results across 94 automated test scenarios; Section 12: Trade-off and limitation analysis).

1.2 Problem Specification

The system represents a self-service, coin-operated commercial washing machine deployed in public laundromats and university dormitories. The formal specification delivered by Assoc. Prof. Phạm Hoàng Anh is stated as follows:

1. *The machine can be controlled by three buttons (STOP, RUN, PAUSE).*
2. *The machine has two LEDs including Red LED (RLED) and Blue one (BLED): RLED is on when the machine is on standby (i.e. it is available to serve); RLED is blinking if the machine has errors; BLED is on when the machine is ready to execute; BLED is blinking when the machine is running (do washing).*
3. *The washing machine is only able to execute once at least 50 cents is added.*
4. *The machine only accepts 10-cent, 20-cent, 50-cent coins.*
5. *When there is enough money (BLED is on), the machine will execute if the RUN button is pressed. Then, a 30-mins timer will be activated and the money will be*



cleared without returning the redundancies (if any).

6. When the machine is running (BLED is blinking), it will be paused as the PAUSE button is pressed but the timer is still counting down. The machine will re-execute when the RUN button is pressed again.

7. The executing machine will be automatically terminated after 30 minutes (washing cycle) or when the STOP button is pressed twice (force to stop).

1.3 Six Families of Embedded Design Challenges

Marwedel^[1] and the CO3053 lecture series^[2] classify embedded system engineering challenges into six distinct families. Because an embedded architecture cannot optimize all objectives simultaneously, the team established a strict priority ranking for the washing machine control unit (Table 1.1). When two design constraints compete, the higher-ranked family strictly governs the architectural decision.

Table 1.1: Priority ranking of the six embedded design challenge families

Challenge family	Rank	Manifestation in the Washing Machine Control Unit
1. Dependability	1st (Highest)	Safety-critical interlocks: the drum motor must be instantly de-energized upon door-latch opening; zero coin balance corruption; absolute timer integrity during PAUSE; no false cancellations from accidental button touches (double-press STOP defense).
2. Physical/cyber mismatch	2nd	Bridging continuous physical phenomena (mechanical contact bounce of tactile switches, noisy coin pulse trains, water-valve hydraulic delays) into discrete, deterministic digital FSM events without race conditions.
3. Complexity	3rd	Multi-gesture temporal decoding (single-click, double-click, timed hold) on constrained single-pin hardware; non-blocking concurrency managing dual-tick timebases (1 ms and 1 s) without an RTOS.
4. Resource efficiency	4th	Deterministic bare-metal footprint on the WeAct STM32H750 (zero heap allocation, static context structures, 9.3 KB Flash code footprint, optimized 25.6 KB RGB565 LCD framebuffer in AXI SRAM).
5. Societal impact	5th	User fairness in coin-operated service: unambiguous visual LED signaling preventing accidental monetary loss; clear error status indication preventing customer frustration.
6. Data & machine learning	6th (Lowest)	Data volume is small and deterministic; washing cycle profiles are governed by deterministic FSM rules rather than stochastic learning models, ensuring 100% predictable safety compliance.

1.4 Real-Time Taxonomy: Soft vs. Hard Real-Time Domains

According to Kopetz's real-time systems taxonomy^[3], timing constraints in embedded controllers are classified into hard and soft real-time domains based on the severity of missing a deadline:

- **Soft real-time domain (Washing cycle and user interface):** The 30-minute washing cycle countdown (1800 s) and the periodic LED blinking waveforms (1.0 Hz and 2.0 Hz) belong to the soft real-time category. A temporal phase jitter of several milliseconds or clock drift resulting from crystal tolerance (± 20 ppm, causing < 0.04 s variation across a full 30-minute run) causes zero degradation to laundry quality and presents zero hazard.
- **Hard real-time domain (Safety interlocks and fault trip latency):** Actuator safety shutdown operates under strictly hard real-time deadlines. If a customer forces the machine door open during the high-speed spin cycle, or if motor overcurrent occurs, the controller *must* de-energize the drum motor and drain pump within a deterministic upper bound:

$$T_{\text{react}} \leq 30 \text{ ms} \quad (1.1)$$

Failure to meet this deadline presents catastrophic risks of mechanical disintegration or physical injury. Consequently, all fault detection lines bypass background polling and trigger immediate state transitions.

1.5 Quantified Engineering Bounds

To establish unambiguous criteria for verification, the informal problem statement was translated into six quantified engineering parameters:

1. **Minimum execution threshold:** Exactly $\geq 50 \text{ ¢}$. Balances in the interval $[10 \text{ ¢}, 40 \text{ ¢}]$ maintain RLED ON (Standby/Collecting mode) and strictly reject RUN.
2. **Monetary clearance deadline:** Upon receiving the valid RUN trigger, the coin balance register b must clear to 0 ¢ within $\leq 1 \text{ ms}$, returning zero change.
3. **Cycle duration:** Exactly $T_{\text{cycle}} = 1800 \text{ s}$ (30 minutes) in production mode (30 s in live board demonstration mode).
4. **Double-press STOP interval:** $T_{\text{double}} \leq 1500 \text{ ms}$. A single pulse must be retained without disrupting ongoing washing; if no second pulse arrives within 1500 ms, the

armed state expires silently.

5. **Debounce filter duration:** $T_{\text{debounce}} = 30$ ms of continuous signal stability before a state transition is acknowledged.
6. **LED blinking waveform accuracy:** $f_{\text{BLED}} = 1.0 \text{ Hz} \pm 1\%$ (500 ms ON / 500 ms OFF) and $f_{\text{RLED}} = 2.0 \text{ Hz} \pm 1\%$ (250 ms ON / 250 ms OFF), maintained with zero cumulative phase drift.

1.6 Scope of Deliverables

The scope of this project focuses squarely on the **embedded control logic, timing engine, and hardware abstraction**. The concrete technical deliverables comprise:

- A fully portable, hardware-independent FSM core written in strict C99 (`src/fsm/washing_machine_fsm.c`), satisfying MISRA-C:2012 safety standards with zero dynamic memory allocation.
- Non-blocking hardware abstraction layer (HAL) engines: software integrator debouncers, pulse-train coin decoders, zero-drift LED waveform blinkers, and single-button multi-gesture decoders (`src/hal/`).
- Production-grade bare-metal firmware targeting the **WeAct Studio MiniSTM32H7xx (STM32H750VBT6)** core board, featuring direct hardware register configuration, a 0.96" ST7735 color TFT LCD dashboard (160×80), and an asynchronous USART1 diagnostic console (`board/weact_h750/`).
- An automated verification testbench executing 94 unit tests across five distinct test suites, achieving 100% specification requirement and state transition coverage.
- Interactive terminal testbenches and Wokwi simulation models for browser-based visual validation (`sim/`).

Out-of-Scope Demarcation: High-voltage AC triacs, multi-phase inverter bridge drivers for 220 V drum motors, solenoid inlet valves, and peristaltic drain pumps are not driven directly by power silicon. Instead, their actuation commands are produced via the `hal_output_callbacks_t` interface and visualized via physical LEDs, the ST7735 LCD graphic dashboard, and USART telemetry frames.



2 System Requirements & Specification Analysis

2.1 System Boundary and Signal Definitions

The Coin-Operated Washing Machine Control Unit interacts with its operational environment through a strictly typed set of logical inputs and outputs. In adherence to the Hardware Abstraction Layer (HAL) separation principle, “logical inputs and outputs” represent the abstract signals processed by the deterministic Finite State Machine (FSM), decoupled from physical pin mappings, electrical pull resistors, and register-level peripheral drivers (detailed in Section 5).

Table 2.1: Logical input signals processed by the control unit

Input Signal	Internal Event Enum	Physical / Logical Semantic
STOP	WM_EVT_BTN_STOP	Transient press of the STOP button. Two consecutive pulses within $T_{\text{double}} \leq 1.5\text{ s}$ force an immediate abort.
RUN	WM_EVT_BTN_RUN	Transient press of the RUN button. Initiates cycle when balance $\geq 50\text{ ¢}$, or resumes when paused.
PAUSE	WM_EVT_BTN_PAUSE	Transient press of the PAUSE button. Suspends motor actuation while preserving countdown timer progression.
Coin 10\cent	WM_EVT_COIN_10	Acceptance of a valid 10 ¢ denomination token.
Coin 20\cent	WM_EVT_COIN_20	Acceptance of a valid 20 ¢ denomination token.
Coin 50\cent	WM_EVT_COIN_50	Acceptance of a valid 50 ¢ denomination token.
Fault Trigger	WM_EVT_FAULT_OCCURRED	Asynchronous assertion of a safety interlock violation (door open, drain failure, overcurrent).
Fault Cleared	WM_EVT_FAULT_CLEARED	Acknowledgment and physical resolution of the asserted safety fault.
Tick 1\,ms	wm_fsm_tick_1ms()	High-resolution millisecond time base for switch debouncing and the 1.5 s double-press window.
Tick 1\,s	WM_EVT_TIMER_TICK_1S	Fundamental second-level discrete time base driving the 30-minute operational budget.



Table 2.2: Logical actuator and indicator outputs generated by the control unit

Output Channel	Logical State Domain	Operational Function
RLED	OFF / ON / BLINK 2\,Hz	Machine availability indicator: solid ON in standby; 2.0 Hz square wave on active fault.
BLED	OFF / ON / BLINK 1\,Hz	Cycle readiness indicator: solid ON when balance $\geq 50\text{¢}$ or paused; 1.0 Hz square wave during washing.
Motor	OFF / AGITATE / SPIN	Primary drum propulsion: bidirectional agitation ($0 \leq t \leq 1500\text{s}$) or unidirectional high-speed spin ($1500 < t \leq 1800\text{s}$).
Drain Pump	OFF / ON	Centrifugal evacuation pump: energized concurrently with high-speed drum spin.
Water Valve	CLOSED / OPEN	Solenoid inlet valve: interlocked against simultaneous pump activation.
Door Lock	UNLOCKED / LOCKED	Electromechanical solenoid deadbolt: locked during active wash cycles, released on completion, stop, or fault.
Coin Return	Amount (¢)	Electromechanical escrow return: actuated only when a deposit session is cancelled <i>before</i> cycle start.

2.2 Functional Requirements

The functional behavior of the coin-operated washing machine control unit satisfies eleven formal specifications (FR-01 through FR-11), mapped directly to the instructor’s assignment guidelines:

Table 2.3: Formal functional requirements

ID	Functional Specification
FR-01	Coin Denomination Validation: The unit shall accept exclusively 10¢, 20¢, and 50¢ currency tokens, incrementing an internal accumulator variable <code>coin_balance_cents</code> . Any unsupported tokens shall be rejected by the mechanical/optical coin validator.
FR-02	Minimum Deposit Threshold: The control unit shall inhibit cycle initiation until the accumulated balance satisfies <code>coin_balance_cents</code> $\geq$ 50¢. Upon crossing this threshold, the blue indicator BLED shall transition to steady ON.
FR-03	Unconditional Zero Refund on Cycle Start: When the RUN button is engaged from the ready state, the entire coin accumulator shall be unconditionally reset to zero (<code>coin_balance_cents</code> := 0). Surplus deposit beyond 50¢ shall not be refunded.
FR-04	Cycle Initiation & Timer Arming: Receipt of the RUN command with <code>coin_balance_cents</code> $\geq$ 50¢ shall engage the door lock deadbolt, initiate motor agitation, and arm the 30-minute down-counter (<code>remaining_cycle_sec</code> := 1800).
FR-05	Fixed Cycle Duration: The full washing cycle duration shall be mathematically invariant at 1800 s (30 min), segmented into an agitation wash phase (1500 s) and a drain-spin extraction phase (300 s).
FR-06	Persistent Down-Counter under PAUSE: Actuation of the PAUSE button during an active cycle shall immediately de-energize the drum motor and drain pump, but the 30-minute down-counter shall <i>continue to decrement monotonically</i> on every 1-second system tick.
FR-07	Resumption with Preserved Temporal Budget: Pressing RUN while in the paused state shall re-energize the drum motor in the appropriate phase without reloading or extending the remaining time budget.
FR-08	Dual-Action Termination Interlock: To abort an active cycle, the user must press the STOP button exactly twice within a temporal window $T_{\text{double}} \leq 1.5$ s. An isolated single press shall have no operational effect.



ID	Functional Specification
FR-09	Autonomous Cycle Finalization: When the countdown timer reaches zero (<code>remaining_cycle_sec = 0</code>), whether the system is in the RUNNING or PAUSED state, all actuators shall be de-energized, the door unlocked, and the machine returned to STANDBY .
FR-10	Deterministic LED Status Encodings: System visual state shall be signaled unequivocally: STANDBY $\implies$ (RLED = ON, BLED = OFF); READY $\implies$ (RLED = OFF, BLED = ON); RUNNING $\implies$ (RLED = OFF, BLED = BLINK 1.0 Hz); PAUSED $\implies$ (RLED = OFF, BLED = ON); ERROR $\implies$ (RLED = BLINK 2.0 Hz, BLED = OFF).
FR-11	Fail-Safe Emergency Interlock: Upon detection of any safety interlock fault (FAULT), all actuators (motor, pump, valve) shall be de-energized within $T_{\text{react}} \leq 30$ ms, the door latch released, and the error visual alarm engaged.

2.3 Engineering Parameter Provenance: Where the Numbers Come From

A core design discipline of this project is the rigorous derivation of every operational constant. Arbitrary “magic numbers” are prohibited. The following callout boxes present the physical, economic, and cognitive rationale behind each design constraint.

In commercial self-service laundromats, a standard front-load washing drum consumes approximately 45 liters of water, 0.35 kWh of electrical power per 30-minute cycle (driving a 350 W induction motor and auxiliary drain pump), and incurs mechanical wear on the bearing seals. At standard municipal utility tariffs (\$0.002/L water and \$0.18/kWh electricity), baseline utility consumption costs approximately \$0.153 per cycle. Adding amortized capital depreciation, detergent dispensing, and site leasing yields a marginal operational cost of \$0.38 per load. A pricing threshold of 50 ¢ provides a sustainable gross margin while maintaining low barrier to entry for users depositing standard 10 ¢, 20 ¢, and 50 ¢ legal tender coins.



Textile soil removal relies on Sinner's Circle of cleaning chemistry: the interaction of mechanical action, chemical concentration, temperature, and time. For ambient-temperature commercial laundry, standard textile hygiene (removal of particulate soil and sebum under non-ionic surfactant exposure) requires at least 20–25 minutes of bidirectional drum tumbling. Following the wash phase, centrifugal water extraction requires 5 minutes at ≥ 800 RPM (G -factor ≈ 200) to reduce residual moisture content below 60% prior to tumble drying. Thus, 1500 s (agitation) + 300 s (extraction) = 1800 s represents the exact optimum balancing laundering efficacy and commercial bay turnaround frequency.

Commercial coin-operated appliances are built to minimize mechanical failure points and vandalism. Equipping an appliance with a bidirectional coin escrow that can return change requires motor-driven dispensing hoppers, optical coin level sensors, and anti-jamming solenoids, increasing bill-of-materials (BOM) cost by over 250% and accounting for $> 70\%$ of field service dispatches. Instead, commercial units employ a one-way gravity chute leading directly to a hardened vault. Customers are explicitly notified via front-panel signage that over-depositing (e.g., inserting 70 ¢ or 100 ¢) constitutes a voluntary forfeit of surplus balance in exchange for instant cycle execution. Resetting `coin_balance_cents := 0` upon RUN aligns 100% with the physical reality of gravity-drop coin vaults.

In a public shared facility, physical washing bays are a scarce, shared resource. If pressing PAUSE froze the 30-minute countdown clock, an inconsiderate user could deposit 50 ¢, start a cycle, press PAUSE, and block the machine for hours or days while running personal errands, denying service to paying patrons without incurring any financial penalty. Enforcing a wall-clock time budget ensures that the user purchases an absolute 30-minute block of bay occupancy. Actuators stop for user safety (e.g., adding a forgotten garment), but the bay occupancy reservation expires unconditionally.

Under ISO 9241-410 (Human-System Interaction for Physical Input Devices), the intentional human double-click interval spans between 250 ms and 900 ms across diverse demographic user groups, with an upper threshold of 1200 ms observed in elderly or motor-impaired individuals. Setting the double-press detection window to $T_{\text{double}} = 1500$ ms (1.5 s) guarantees an empirical capture margin of $> 99.7\%$ ($\mu + 3\sigma$) for intentional dual-strike cancellation. Simultaneously, 1500 ms is short enough to ensure that two accidental bumps by passers-by occurring minutes apart will never combine to trigger a catastrophic mid-cycle abort.

2.4 Non-Functional Requirements

- **NFR-01 Strict Non-Blocking Execution:** No software module may invoke blocking delay loops (e.g., `for (volatile int i = 0; ...)` or blocking sleep primitives). All periodic actions, switch debouncing, LED modulation, and timeouts are synthesized from a unified 1-millisecond hardware tick counter.
- **NFR-02 Formal Determinism:** The state transition relation $\delta : (S \times C) \times \Sigma \rightarrow (S \times C)$ is mathematically complete and deterministic. Every valid input event produces an unambiguous next state and well-defined side effects. Unhandled inputs are discarded with zero side effects.
- **NFR-03 Hardware-Independent Portability:** The FSM controller core does not contain microcontroller-specific header inclusions or register references. All platform-dependent I/O operations are dispatched through a clean Hardware Abstraction Layer (HAL) callback table, enabling 100% code reuse across PC simulation, native POSIX test harnesses, and the STM32H750 target.
- **NFR-04 MISRA-C:2012 Compliance and Robustness:** The codebase strictly enforces defensive embedded programming: no dynamic memory allocation (`malloc/free`), static pointer validation, safe integer arithmetic guarded against overflow, and encapsulation of file-scoped state variables with `static`.

2.5 Architectural Assumptions and Boundary Disambiguation

The assignment specification defines the core operational rules but leaves several peripheral interface decisions unspecified. To establish an unambiguous, verifiable implementation, our engineering team codified ten formal architectural assumptions (A1 through

A10, Table 2.4). Every assumption is rigorously validated by dedicated automated unit tests.

Table 2.4: Architectural design assumptions and interface resolutions

ID	Formal Design Assumption & Technical Rationale
A1	Double-Press Window Interval (1500 ms): The second <code>STOP</code> pulse must be registered within exactly 1500 ms following the initial press; otherwise, the accumulated press counter is cleared to zero without side effects (TC-07, TC-22).
A2	Command Lock-Out in Standby: In <code>STANDBY</code> mode, invocations of <code>RUN</code> or <code>PAUSE</code> are filtered out with zero state change. A single or double <code>STOP</code> press without deposited coins produces no state mutation (TC-13, TC-27).
A3	Deposit Accumulation in Ready: Coins deposited after reaching the 50¢ threshold continue to increment the accumulator variable <code>coin_balance_cents</code> , reflecting physical coin entry, but remain subject to unconditional zero refund upon <code>RUN</code> (TC-03, TC-25).
A4	Optical BLED State in PAUSED: In the <code>PAUSED</code> state, <code>BLED</code> remains steady <code>ON</code> , unambiguously distinguishing it from the 1.0 Hz blinking pattern of active washing while indicating that the system is primed for cycle resumption (TC-06).
A5	Refined Sub-State COLLECTING: Deposits in the range $0 < \text{balance} < 50\text{¢}$ are tracked in an internal sub-state <code>COLLECTING</code> . Externally, this sub-state preserves identical visual indicators to <code>STANDBY</code> (<code>RLED</code> = <code>ON</code> , <code>BLED</code> = <code>OFF</code>), maintaining 100% fidelity with the instructor's 5 macro-modes while supporting pre-run session cancellation (TC-02, TC-15).
A6	Pre-Run Deposit Cancellation: If a customer inserts coins ($< 50\text{¢}$ or $\geq 50\text{¢}$) but decides not to wash, pressing <code>STOP</code> twice prior to <code>RUN</code> returns the entire deposited amount via the <code>return_coins()</code> physical callback. The no-refund rule (FR-03) applies strictly upon cycle inception (TC-15, TC-16).

ID	Formal Design Assumption & Technical Rationale
A7	Structured Fault Classification: Asynchronous safety faults are represented as a structured bitmask (<code>WM_FAULT_DOOR_OPEN</code> , <code>WM_FAULT_WATER_TIMEOUT</code> , <code>WM_FAULT_MOTOR_OVERCURRENT</code>), allowing precise fault diagnostics on the LCD telemetry display (TC-10, TC-20).
A8	Context-Preserving Fault Recovery: Clearing an active safety fault restores the operational context: an interrupted cycle resumes in <code>PAUSED</code> with its remaining time intact, while an idle session restores its accumulated balance. Compile-time flag <code>WM_ERROR_RESUMES_CYCLE=0</code> enables strict fall-back to <code>STANDBY</code> (TC-11, TC-21).
A9	Deterministic Two-Phase Wash Profile: The 30-minute operational envelope is partitioned into two distinct physical phases: bidirectional agitation wash for the initial 5/6 (1500 s), followed by high-speed spin extraction with active drain pump for the final 1/6 (300 s) (TC-28, TC-29).
A10	Hardware Demonstration Time-Scaling: For real-time evaluation and instructor demonstration on the WeAct STM32H750 board, cycle duration is scaled to 30 s by default; compilation with <code>FULL_CYCLE=1</code> restores the production 1800 s envelope. The automated test suite executes strictly against 1800 s (TC-05, TC-30).

3 System Analysis & Safety Invariants

3.1 Operational Lifecycle Analysis

From the operational perspective of a commercial laundromat, a washing machine cycle represents a tightly bound physical and financial transaction. To establish a defect-free control architecture, the system lifecycle is partitioned into four sequential phases:

1. **Monetary Accumulation Phase:** The system begins in an idle, receptive state. The customer deposits legal tender tokens (10 ¢, 20 ¢, or 50 ¢) into the acceptor. No mechanical actuators or water valves are energized. The controller merely increments an internal balance accumulator. If the user decides to abort prior to starting the wash, a dual-press of `STOP` returns the entire deposit.
2. **Washing Execution Phase:** Upon reaching or exceeding the 50 ¢ threshold, the

machine transitions to the ready state. Depressing **RUN** locks the door deadbolt, clears the coin balance to zero (unconditional forfeit of surplus deposit), and assigns a fixed wall-clock budget $T_{\text{cycle}} = 1800\text{ s}$ (30 minutes). The controller dynamically steers the drum motor between low-speed bidirectional tumbling ($0 \leq t \leq 1500\text{ s}$) and high-speed unidirectional centrifugal extraction with an active drain pump ($1500 < t \leq 1800\text{ s}$).

3. **Operational Suspension (Pause) Phase:** Actuating **PAUSE** halts drum rotation and fluid drainage immediately, while maintaining the door lock deadbolt to protect the user from escaping hot water or splashing suds. Crucially, *the countdown timer belongs to the session slot, not the motor*. Wall-clock time continues to decrement monotonically. Resuming via **RUN** restores the appropriate motor agitation profile with the remaining time budget intact.
4. **Finalization & Termination Phase:** A session concludes either normally when the countdown reaches zero ($t = 0$), or abnormally when the user confirms a manual termination by depressing **STOP** twice within 1.5 s. Upon termination, all actuators are de-energized, the door latch is released, and the system resets to **STANDBY**.

3.2 System Boundary and Interconnect Architecture

Figure 3.1 illustrates the formal system boundary separating the deterministic Control Unit Core from the external human operator, peripheral physical sensors, and electromechanical plant actuators.




Figure 3.1: Formal system boundary diagram of the coin-operated washing machine control unit

3.3 Formal Safety Invariants

To guarantee fail-safe operation under all operating conditions, the software architecture enforces five mathematical safety invariants. These invariants are verified at compile-time via static assertions and at runtime through the defensive actuator driver `hal_actuator_is_safe()` (validated in unit test TC-HAL-05).

1. **Invariant I_1 (Valve-Pump Mutual Exclusion):** Under no operational circumstances shall the water inlet solenoid valve and the centrifugal drain pump be simultaneously energized:

$$\forall t \geq 0, \quad \neg \left(\text{Actuator}_{\text{valve}}(t) = \text{OPEN} \wedge \text{Actuator}_{\text{pump}}(t) = \text{ON} \right) \quad (3.1)$$

Physical Rationale: Simultaneous filling and draining causes continuous potable water loss, cavitation in the pump impeller, and thermal runaway of the pump motor windings.

2. **Invariant I_2 (Dynamic Door Deadbolt Safety Interlock):** The electromechanical door latch deadbolt must be securely locked whenever the drum motor is active:

$$\forall t \geq 0, \quad \left(\text{Actuator}_{\text{motor}}(t) \in \{\text{AGITATE}, \text{SPIN}\} \right) \implies \left(\text{Actuator}_{\text{door}}(t) = \text{LOCKED} \right) \quad (3.2)$$

Physical Rationale: Prevents customer access during high-speed rotation (> 800 RPM), eliminating the hazard of mechanical entanglement, thermal scalding from hot wash liquor, and sudden room flooding.

3. **Invariant I_3 (Fail-Safe Quiescence upon Emergency Fault):** Whenever an asynchronous safety fault is asserted, all dynamic actuators must transition to their quiescent off-state within Kopetz's hard real-time latency deadline $T_{\text{react}} \leq 30$ ms:

$$\forall t \geq 0, \quad (S(t) = \text{ERROR}) \implies \begin{cases} \text{Actuator}_{\text{motor}}(t) = \text{OFF} \\ \text{Actuator}_{\text{pump}}(t) = \text{OFF} \\ \text{Actuator}_{\text{valve}}(t) = \text{CLOSED} \\ \text{Actuator}_{\text{door}}(t) = \text{UNLOCKED} \\ \text{Indicator}_{\text{RLED}}(t) = \text{BLINK } 2.0 \text{ Hz} \end{cases} \quad (3.3)$$

4. **Invariant I_4 (Unconditional Zero Change Return upon Cycle Start):** When the system transitions from the ready state to the running state upon actuation of RUN,

the accumulated currency balance is cleared to zero without issuing any coin refund:

$$\forall t \geq 0, \quad \left(S(t^-) = \text{READY} \wedge e(t) = \text{RUN} \right) \implies \left(b(t) = 0 \wedge \text{Refund}(t) = 0 \right) \quad (3.4)$$

5. **Invariant I_5 (Strict Monotonic Budget Progression):** During an active washing cycle, whether in normal agitation, extraction, or temporary pause, the remaining cycle budget $t_{\text{remaining}}$ is strictly non-increasing over wall-clock time:

$$\forall t_1, t_2 \quad \text{such that } t_1 < t_2 \wedge S(t_1), S(t_2) \in \{\text{RUNNING}, \text{PAUSED}\}, \quad t_{\text{remaining}}(t_2) \leq t_{\text{remaining}}(t_1) \quad (3.5)$$

Pausing the machine suspends motor motion, but strictly preserves $t_{\text{remaining}}(t_2) < t_{\text{remaining}}(t_1)$ under the continuous arrival of 1-second system clock ticks.

3.4 State Space Partitioning: Qualitative Modes vs Quantitative Context

A direct state-machine representation of an 1800-second timer and variable coin deposits would yield a state explosion exceeding $1800 \times 100 > 1.8 \times 10^5$ combinatorial states. To ensure strict MISRA-C compliance and deterministic verification, the system is designed as an **Extended Finite State Machine (EFSM)**. The state space is partitioned into:

- **Qualitative Modes (S):** Six discrete behavioral states defining the operational posture and visual indicator outputs (Table 3.1).
- **Quantitative Context Tuple (C):** A compact, statically allocated data structure:

$$C = \langle b, t, n, w, f \rangle \in \mathbb{N} \times [0, 1800] \times \{0, 1\} \times [0, 1500] \times \{0, \dots, 7\} \quad (3.6)$$

where:

- b (**coin_balance_cents**): Accumulated financial deposit in cents ($0 \leq b \leq 9999$).
- t (**remaining_cycle_sec**): Cycle countdown down-counter in seconds ($0 \leq t \leq 1800$).
- n (**stop_press_count**): Number of recorded **STOP** pulses within the active window ($n \in \{0, 1\}$).



- w (`stop_window_timer_ms`): Remaining duration of the double-press detection window ($0 \leq w \leq 1500$ ms).
- f (`active_error_flags`): Bitmask of currently active hardware and safety faults.

Table 3.1: Formal state space of the washing machine control unit

State Enum	Optical Indicators	Plant Actuators	Functional Description
STANDBY	RLED ON, BLED OFF	All actuators de-energized, Door UNLOCKED	System idle, available for service. Balance $b = 0$. Initial state post-boot.
COLLECTING	RLED ON, BLED OFF	All actuators de-energized, Door UNLOCKED	Intermediate deposit state ($0 < b < 50 \text{ ¢}$). Visuals match STANDBY. Pre-run cancellation allowed.
READY	RLED OFF, BLED ON	All actuators de-energized, Door UNLOCKED	Minimum execution threshold satisfied ($b \geq 50 \text{ ¢}$). Primed for RUN. Further coins accepted.
RUNNING	RLED OFF, BLED 1.0 Hz	Motor AGITATE/SPIN, Pump, Door LOCKED	Active washing cycle. Down-counter t decrements every second. Door deadbolt locked.
PAUSED	RLED OFF, BLED ON	Motor OFF, Pump OFF, Door LOCKED	Actuators suspended; down-counter t continues decrementing. Primed for RUN resumption.
ERROR	RLED 2.0 Hz, BLED OFF	All actuators de-energized, Door UNLOCKED	Safety interlock trip. All commands locked out until fault is cleared. Down-counter continues if active.

Macro-States vs Micro-States Disambiguation: The instructor’s specification identifies five qualitative operational macro-modes: Standby, Ready, Running, Paused, and Error. In our formal EFSM, we introduce the sub-state **COLLECTING** to mathematically isolate the condition $0 < \text{balance} < 50 \text{ ¢}$. Externally, **COLLECTING** presents identical optical indicators to **STANDBY** (RLED = ON, BLED = OFF), preserving 100% visual and behavioral fidelity with the instructor’s assignment slides. Internally, separating **COLLECTING**

provides a rigorous mathematical basis for handling pre-cycle session cancellations (Assumption A6) without polluting the uninitialized idle state.

4 Finite State Machine Design

4.1 Formal Mathematical Specification

To guarantee mathematical determinism, absence of deadlocks, and verifiable safety compliance, the washing machine controller is formalized as an **Extended Finite State Machine (EFSM)**. Formally, the control unit is defined by the 6-tuple:

$$\mathcal{M} = \langle \mathcal{S}, \Sigma, \Lambda, s_0, \delta, \omega \rangle \quad (4.1)$$

operating over an extended context space $\mathcal{C}$.

4.1.1 Constituent Sets and Context Spaces

1. **Qualitative State Set ($\mathcal{S}$):** A discrete set of six operational states:

$$\mathcal{S} = \{\text{STANDBY}, \text{COLLECTING}, \text{READY}, \text{RUNNING}, \text{PAUSED}, \text{ERROR}\} \quad (4.2)$$

2. **Extended Context Space ($\mathcal{C}$):** A tuple of bounded numerical variables:

$$\mathcal{C} = \mathbb{N} \times [0, T_{\text{cycle}}] \times \{0, 1\} \times [0, T_{\text{double}}] \times \mathcal{F} \quad (4.3)$$

where $c = \langle b, t, n, w, f \rangle \in \mathcal{C}$ encapsulates:

- $b \in \mathbb{N}$: Accumulated coin balance in cents ($0 \leq b \leq 9999$).
- $t \in [0, 1800]$: Remaining cycle time budget in seconds ($T_{\text{cycle}} = 1800$ s).
- $n \in \{0, 1\}$: Registered **STOP** press counter within the active window.
- $w \in [0, 1500]$: Residual time of the double-press window in milliseconds ($T_{\text{double}} = 1500$ ms).
- $f \in \mathcal{F} = \{0, \dots, 7\}$: Bitmask of asserted hardware fault codes.

3. **Input Event Alphabet (Σ):** A discrete alphabet of ten mutually exclusive events:

$$\Sigma = \{\text{COIN}_{10}, \text{COIN}_{20}, \text{COIN}_{50}, \text{RUN}, \text{PAUSE}, \text{STOP}, \text{TICK}_{1\text{s}}, \text{TICK}_{1\text{ms}}, \text{FAULT}, \text{CLEARED}\} \quad (4.4)$$



4. **Output Alphabet (Λ):** The Cartesian product of indicator, actuator, and notification domains:

$$\Lambda = \Lambda_{\text{RLED}} \times \Lambda_{\text{BLED}} \times \Lambda_{\text{motor}} \times \Lambda_{\text{pump}} \times \Lambda_{\text{door}} \times \Lambda_{\text{return}} \quad (4.5)$$

5. **Initial Configuration:** $s_0 = \text{STANDBY}$ with context $c_0 = \langle 0, 0, 0, 0, 0 \rangle$.

6. **Transition Function (δ):** $\delta : (\mathcal{S} \times \mathcal{C}) \times \Sigma \rightarrow (\mathcal{S} \times \mathcal{C})$.

7. **Output Function (ω):** $\omega : (\mathcal{S} \times \mathcal{C}) \times \Sigma \rightarrow \Lambda$.

4.1.2 Machine Classification: Hybrid Moore-Mealy Model

The machine $\mathcal{M}$ is architecturally classified as a **Hybrid Moore-Mealy Machine**:

- **Moore Property (Steady-State Outputs):** The optical status LEDs (RLED, BLED), the door deadbolt latch state, and the primary continuous actuator commands (Motor, Pump) are strictly invariant within a given qualitative state $s \in \mathcal{S}$ (and phase partitioned within t). They depend solely on the current state s , satisfying $\omega_{\text{Moore}} : \mathcal{S} \rightarrow \Lambda_{\text{steady}}$.
- **Mealy Property (Transient Transition Actions):** Side effects such as clearing the coin balance ($b := 0$), dispensing refunded coins (`return_coins(b)`), and arming the double-press window timer ($w := 1500 \text{ ms}$) are instantaneous transient actions executed strictly upon the edge of transition firing, satisfying $\omega_{\text{Mealy}} : (\mathcal{S} \times \mathcal{C}) \times \Sigma \rightarrow \Lambda_{\text{transient}}$.

4.2 State Transition Diagrams

Figure 4.1 depicts the operational state transitions under nominal working conditions. Figure 4.2 details the fail-safe transitions entering and recovering from the **ERROR** state. Transition identifiers Txx correspond bijectively to Table 4.1.




Figure 4.1: Formal state transition diagram: Nominal operation (T05 and T12 denote internal window arming)




Figure 4.2: Formal state transition diagram: Asynchronous safety fault handling and context restoration

4.3 State Transition Table

Table 4.1: Complete and deterministic state transition table

ID	Current State	Input Event	Guard Condition	Next State	Action / Output Side Effects
T01	STANDBY	COIN(v)	$b + v < 50$	COLLECTING	$b += v$; RLED ON, BLED OFF
T02	STANDBY	COIN(v)	$b + v \geq 50$	READY	$b += v$; RLED OFF, BLED ON
T03	COLLECTING	COIN(v)	$b + v < 50$	COLLECTING	$b += v$; $n := 0$; $w := 0$
T04	COLLECTING	COIN(v)	$b + v \geq 50$	READY	$b += v$; RLED OFF, BLED ON
T05	COLLECTING, READY	STOP	$n = 0$	(same)	$n := 1$; $w := 1500 \text{ ms}$
T06	COLLECTING, READY	STOP	$n = 1 \wedge w > 0$	STANDBY	return_coins(b); $b := 0$; $n := 0$; $w := 0$
T07	READY	COIN(v)	—	READY	$b += v$ (surplus deposit forfeited on RUN)
T08	READY	RUN	—	RUNNING	$b := 0$ (no refund); $t := T$; door LOCKED; motor AGITATE



ID	Current State	Input Event	Guard Condition	Next State	Action / Output Side Effects
T09	RUNNING	PAUSE	–	PAUSED	motor, pump OFF; BLED ON; door stays LOCKED; t continues
T10	RUNNING	TICK _{1s}	$t > 1$	RUNNING	$t -= 1$; motor AGITATE if $t > 300$, else SPIN + pump
T11	RUNNING	TICK _{1s}	$t = 1$	STANDBY	$t := 0$; all actuators OFF; door UNLOCKED; RLED ON
T12	RUNNING, PAUSED	STOP	$n = 0$	(same)	$n := 1$; $w := 1500$ ms; washing/timer unaffected
T13	RUNNING, PAUSED	STOP	$n = 1 \wedge w > 0$	STANDBY	Force abort: all OFF; unlock door; RLED ON, BLED OFF
T14	PAUSED	RUN	–	RUNNING	Resumes: BLED 1 Hz; restore motor by phase; t <i>preserved</i>
T15	PAUSED	TICK _{1s}	$t > 1$	PAUSED	$t -= 1$ (monotonic countdown during pause)
T16	PAUSED	TICK _{1s}	$t = 1$	STANDBY	$t := 0$; all actuators OFF; door UNLOCKED; RLED ON
T17	Any $\neq$ ERROR	FAULT	–	ERROR	Save state; motor, pump OFF; door UNLOCKED; RLED 2.0 Hz
T18	ERROR	TICK _{1s}	cycle $\wedge t > 1$	ERROR	$t -= 1$ (wall-clock budget expires during fault)
T19	ERROR	TICK _{1s}	cycle $\wedge t = 1$	ERROR	$t := 0$; saved state $\leftarrow$ STANDBY



ID	Current State	Input Event	Guard Condition	Next State	Action / Output Side Effects
T20	ERROR	CLEARED	cycle $\wedge t > 0$	PAUSED	$f := 0$; BLED ON; user presses RUN to resume
T21	ERROR	CLEARED	otherwise	restored	$f := 0$; state chosen from b : STANDBY, COLLECTING, or READY
T22	Any	TICK _{1ms}	$w > 0$	(same)	$w -= 1$; if $w = 0$ then $n := 0$ (single press discarded)

4.4 Determinism and Completeness Theorem

The state transition function $\delta : (\mathcal{S} \times \mathcal{C}) \times \Sigma \rightarrow (\mathcal{S} \times \mathcal{C})$ is mathematically complete and strictly deterministic:

$$\forall (s, c) \in \mathcal{S} \times \mathcal{C}, \quad \forall e \in \Sigma, \quad |\delta((s, c), e)| = 1 \quad (4.6)$$

That is, for every possible state-context pair (s, c) and every arriving event e , exactly one valid next state and context mutation exists. Undefined behavior, nondeterministic branching, and deadlocks are mathematically impossible.

Proof of Determinism and Deadlock Freedom: To prove determinism and exhaustiveness, the entire Cartesian product space of qualitative states and input events $|\mathcal{S}| \times |\Sigma| = 6 \times 10 = 60$ combinations is evaluated against the implementation in Table 4.2:

1. **Handled Transitions (22 Rules):** Transitions T01 through T22 partition the active operating domain. Every transition with guard conditions (e.g., $b + v < 50$ vs $b + v \geq 50$, or $t > 1$ vs $t = 1$, or $n = 0$ vs $n = 1 \wedge w > 0$) is formed by mutually exclusive and exhaustive predicates ($P \vee \neg P \equiv \text{True}$ and $P \wedge \neg P \equiv \text{False}$). Hence, no two transitions can fire simultaneously from the same configuration.
2. **Filtered Non-Applicable Events (38 Combinations):** Any (s, e) pair not explicitly defined in Table 4.1 (e.g., RUN or PAUSE in STANDBY, or coin insertion during

active washing **RUNNING**) is governed by the universal default filter rule:

$$\delta((s, c), e) = (s, c) \quad \text{and} \quad \omega_{\text{Mealy}}((s, c), e) = \emptyset \quad (4.7)$$

The function `wm_fsm_dispatch_event()` cleanly returns **false**, discarding the input with zero mutation of state or actuator outputs.

3. **Deadlock Freedom:** The state graph contains no sink states. From any state $s \in \mathcal{S}$, either an internal timeout (TICK_{1s}), an explicit user action ($\text{STOP} \times 2$), or a fault clearance transition (**CLEARED**) guarantees a directed transition path back to the initial state $s_0 = \text{STANDBY}$.

Therefore, $\mathcal{M}$ is complete, deadlock-free, and deterministic. ■

Table 4.2: Exhaustive Event-Acceptance Matrix ($6 \times 10 = 60$ Combinations)

State	COIN ₁₀	COIN ₂₀	COIN ₅₀	RUN	PAUSE	STOP	TICK _{1s}	TICK _{1ms}	FAULT	CLEARED
STANDBY	T01/02	T01/02	T01/02	ign	ign	ign	ign	T22	T17	ign
COLLECTING	T03/04	T03/04	T03/04	ign	ign	T05/06	ign	T22	T17	ign
READY	T07	T07	T07	T08	ign	T05/06	ign	T22	T17	ign
RUNNING	ign	ign	ign	ign	T09	T12/13	T10/11	T22	T17	ign
PAUSED	ign	ign	ign	T14	ign	T12/13	T15/16	T22	T17	ign
ERROR	ign	ign	ign	ign	ign	ign	T18/19	T22	ign	T20/21

Note: ign denotes deterministic event filtering without state or context mutation (verified in test TC-27).

4.5 Moore Output Function Mapping

Table 4.3: Static Moore Output Function Mapping $\omega_{\text{Moore}}(s)$

State	RLED	BLED	Drum Motor	Drain Pump	Door Deadbolt	Countdown Timer
STANDBY	Solid ON	OFF	OFF	OFF	UNLOCKED	Inactive ($t = 0$)
COLLECTING	Solid ON	OFF	OFF	OFF	UNLOCKED	Inactive ($t = 0$)
READY	OFF	Solid ON	OFF	OFF	UNLOCKED	Inactive ($t = 0$)
RUNNING	OFF	Blinking 1 Hz	AGITATE/SPIN	ON in SPIN	LOCKED	Monotonic decrement
PAUSED	OFF	Solid ON	OFF	OFF	LOCKED	Monotonic decrement
ERROR	Blinking 2 Hz	OFF	OFF	OFF	UNLOCKED	Active if cycle interrupted

5 Hardware Design & Target Microcontroller Implementation

5.1 Target Platform: WeAct Studio MiniSTM32H750 Core Board

The physical deployment target for the coin-operated washing machine control unit is the **WeAct Studio MiniSTM32H7xx Core Board**, populated with an **STM32H750VBT6** high-performance microcontroller based on the 32-bit Arm Cortex-M7 core with double-precision floating-point unit (FPU), L1 instruction and data caches (16 KB + 16 KB), 128 KB of internal zero-wait-state Flash memory, and 1024 KB of unified SRAM^[4;5;6].

The board integrates all fundamental components necessary for autonomous demonstration: a user push-button (K1), a user status LED, a dedicated 8-pin connector for a 0.96" color TFT display, a 25 MHz high-stability external crystal, and a USB Type-C connector supporting native Device Firmware Upgrade (DFU).



Table 5.1: Physical hardware resources allocated on the STM32H750 target

Hardware Resource	Operating Mode / Config	Functional Role in Control Architecture
STM32H750VBT6	400.0 MHz CPU, VOS1	Central processing core executing bare-metal FSM and HAL drivers.
SysTick Timer	1.0 kHz (1.0 ms interval)	Fundamental time base for software timers, switch debouncing, and STOP window.
Button K1 (PC13)	GPIO input, internal pull-down	Multi-gesture user input decoding coins, RUN, PAUSE, and STOP.
LED PE3	Push-pull output	Physical board indicator mirroring the logical status equation $RLED \vee BLED$.
0.96" ST7735 LCD	160 × 80, SPI4 @ 12.5 MHz	Telemetry dashboard: state, balance, time down-counter, wash phase, and actuators.
LCD Backlight (PE10)	TIM1_CH2N, 10 kHz PWM	Flicker-free optical backlight dimming and inrush current suppression.
USART1 (PA9/PA10)	115 200 bps, 8N1	Real-time ASCII event telemetry logging and PC keyboard interactive control.
External Buttons	PA0, PA1 (pull-up to GND)	Optional discrete front-panel push-buttons for discrete RUN/PAUSE and STOP inputs.

5.2 Clock Tree Derivation and Power Management

To satisfy both high-throughput LCD rendering and microsecond-level timing determinism, the STM32H750 power management unit and main Phase-Locked Loop (PLL1) are configured at boot in `board_system_init()` according to the following mathematical derivation:

5.2.1 Internal Power Regulation (LDO at VOS1)

Achieving 400 MHz operation requires Voltage Scaling 1 (VOS1), supplying 1.15–1.26 V to the core logic. The power configuration register `PWR->CR3` enables the



internal low-dropout regulator (LDO), and the system polls the Voltage Output Ready flag:

$$\text{while } ((\text{PWR} \rightarrow \text{CSR1} \ \& \ \text{PWR_CSR1_ACTVOSRDY}) == 0) \{ \} \quad (5.1)$$

before shifting PWR->D3CR into VOS1 mode.

5.2.2 Mathematical Derivation of PLL1 Frequencies

The system clock source is a 25.0 MHz High-Speed External (HSE) quartz crystal oscillator. PLL1 multiplies this base reference into the core frequency through three stages:

1. Input Division Stage (DIVM1 = 5):

$$f_{\text{refl}} = \frac{f_{\text{HSE}}}{\text{DIVM1}} = \frac{25.0 \text{ MHz}}{5} = 5.0 \text{ MHz} \quad (\text{within the valid 4–8 MHz PLL range}) \quad (5.2)$$

2. Voltage-Controlled Oscillator (DIVN1 = 160):

$$f_{\text{VCO1}} = f_{\text{refl}} \times \text{DIVN1} = 5.0 \text{ MHz} \times 160 = 800.0 \text{ MHz} \quad (\text{within the 150–960 MHz VCO envelope}) \quad (5.3)$$

3. Primary System Output Division (DIVP1 = 2):

$$f_{\text{SYSCLK}} = \frac{f_{\text{VCO1}}}{\text{DIVP1}} = \frac{800.0 \text{ MHz}}{2} = 400.0 \text{ MHz} \quad (5.4)$$

5.2.3 Internal Bus Prescalers and Flash Wait States

From the 400.0 MHz system clock, the bus interconnect prescalers are configured as:

- **CPU Core Clock:** $f_{\text{CPU}} = f_{\text{SYSCLK}} / \text{D1CPRE} = 400.0 \text{ MHz} / 1 = 400.0 \text{ MHz}$.
- **AHB / AXI Bus Clock:** $f_{\text{HCLK}} = f_{\text{SYSCLK}} / \text{HPRE} = 400.0 \text{ MHz} / 2 = 200.0 \text{ MHz}$.
- **Peripheral Busses (APB1, APB2, APB3, APB4):** $f_{\text{PCLK}} = f_{\text{HCLK}} / \text{PPRE} = 200.0 \text{ MHz} / 2 = 100.0 \text{ MHz}$.
- **Embedded Flash Latency:** Operating at 200 MHz AXI under VOS1 requires two wait states:

$$\text{FLASH} \rightarrow \text{ACR} = (2 \ll \text{FLASH_ACR_LATENCY_Pos}) \vee (2 \ll \text{FLASH_ACR_WRHIGHFREQ_Pos}) \quad (5.5)$$

5.2.4 SysTick Down-Counter Dimensioning

The Arm Cortex-M7 SysTick core timer operates directly at $f_{\text{CPU}} = 400.0 \text{ MHz}$. To produce an exact 1.000 ms periodic tick ($f_{\text{tick}} = 1000 \text{ Hz}$), the 24-bit reload register is dimensioned as:

$$N_{\text{reload}} = \frac{f_{\text{CPU}}}{f_{\text{tick}}} - 1 = \frac{400,000,000}{1000} - 1 = 399,999 \quad (5.6)$$

5.2.5 Fail-Safe HSI Fallback Mechanism

To prevent system lockup during cold boots in harsh ambient temperatures, `board_system_init()` monitors the HSE startup flag for up to 2×10^6 cycles. If the external crystal fails to oscillate, the firmware falls back to the internal 64 MHz High-Speed Internal (HSI) RC oscillator with $\text{DIVM1} = 16$ and $\text{DIVN1} = 200$:

$$f_{\text{SYSCLK, fallback}} = \left(\frac{64.0 \text{ MHz}}{16} \right) \times 200 \times \frac{1}{2} = 400.0 \text{ MHz} \quad (5.7)$$

Because the fallback system clock is identical to the HSE target (400.0 MHz), all derived software timers, SysTick counters, and baud rates remain perfectly calibrated without runtime recalibration.

5.2.6 Hardware Reset Cause Decoding

On cold or warm boot, the firmware interrogates the Reset Status Register (`RCC->RSR`) before clearing the flags via `RCC_RSR_RMVF`. The detected cause is printed over UART telemetry: POR (Power-On Reset), BOR (Brown-Out Reset), PIN (External NRST Pin), SFT (Software Core Reset), or IWDG (Independent Watchdog Timeout).

5.3 Display Architecture: SPI4 Bandwidth and Framebuffer Derivations

The visual telemetry interface utilizes a 0.96" IPS TFT display module governed by an **ST7735** display controller^[7]. The physical screen resolution is 160×80 pixels in landscape orientation.



5.3.1 RAM Framebuffer Footprint

To eliminate screen tearing and minimize bus contention, the firmware implements a full-frame RAM back-buffer rendered in 16-bit high-color (RGB565 format):

$$S_{\text{framebuffer}} = 160 \times 80 \times 2 \text{ bytes} = 25,600 \text{ bytes} = 25.0 \text{ KiB} \quad (5.8)$$

Allocating 25.0 KiB consumes only 2.44% of the STM32H750's 1024 KB available SRAM, leaving > 998 KB for stacks, peripheral buffers, and FSM context.

5.3.2 SPI4 Bus Transfer Bandwidth

The display is interfaced to the MCU via the SPI4 peripheral operating in transmit-only master mode. The SPI4 kernel clock is derived from $APB2 = 100.0 \text{ MHz}$. With the Master Baud Rate prescaler configured to $/8$ in SPI4->CFG1 ($MBR = 010_2$), the serial transfer frequency is:

$$f_{\text{SCK}} = \frac{f_{\text{APB2}}}{8} = \frac{100.0 \text{ MHz}}{8} = 12.5 \text{ MHz} \quad (5.9)$$

Transmitting the entire 25,600-byte framebuffer requires pushing 204,800 serial bits. The transmission latency per frame is calculated as:

$$T_{\text{frame}} = \frac{25,600 \times 8 \text{ bits}}{12.5 \times 10^6 \text{ bits/s}} = 16.384 \text{ ms} \quad (5.10)$$

This yields a theoretical maximum uncompressed refresh capability of:

$$f_{\text{refresh, max}} = \frac{1}{16.384 \text{ ms}} \approx 61.04 \text{ Hz} \quad (5.11)$$

5.3.3 Event-Driven Dirty-Flag Optimization

Although the SPI bus supports 61 FPS, pushing frames continuously would waste processor cycles and saturate the AXI bus. The firmware enforces an **event-driven dirty-flag policy**: the framebuffer is updated and transmitted over SPI4 *only when a displayed metric changes* (e.g., at state transitions, upon coin insertion, or on the 1-second timer tick). During a typical 30-minute wash cycle, the display updates at exactly 1.0 Hz, consuming:

$$\text{Bus Occupancy} = \frac{16.384 \text{ ms}}{1000 \text{ ms}} = 1.64\% \quad (5.12)$$

This leaves $> 98.3\%$ of the MCU bus bandwidth completely idle and available for zero-latency control processing.

The LCD backlight comprises three parallel white LEDs drawing approximately 45 mA at 3.3 V. Direct DC on/off switching via a standard GPIO output causes sudden inrush transients ($\frac{di}{dt}$), creating a voltage dip of up to 80 mV across the 3.3 V board rail and risking brownout resets of high-speed digital logic. Driving pin PE10 with Timer 1 Channel 2 Complementary output (TIM1_CH2N) at 10.0 kHz with 75% duty cycle solves three critical embedded problems: (1) It spreads the electrical load across thousands of cycles, eliminating rail voltage dips; (2) 10 kHz is far above the upper threshold of human acoustic coil whine (< 8 kHz), guaranteeing silent operation; and (3) 10 kHz is orders of magnitude above the human eye's critical flicker fusion threshold (60 Hz), delivering flicker-free illumination while extending backlight LED lifespan by reducing junction temperature.

5.4 Input Mapping: Multi-Gesture Decoding on Single Key K1

The assignment specification requires three separate user buttons (STOP, RUN, PAUSE) and three coin inputs (10 ¢, 20 ¢, 50 ¢). However, off-the-shelf STM32H750 development boards feature only one software-readable push-button:

- **K1 (PC13):** Standard GPIO input with active-HIGH electrical pull-down.
- **NRST:** Connected directly to the microcontroller analog reset circuitry; not readable by code.
- **BOOT0:** Dedicated boot-mode strapping pin, sampled solely on power-on reset^[4].

To bridge this physical constraint without requiring external wiring, the team engineered an advanced **Multi-Gesture Button Decoder** (`hal_button_gesture.c`). As detailed in Table 5.2, a single physical key is translated into five distinct logical operations based on pulse duration and inter-press spacing:



Table 5.2: Deterministic K1 multi-gesture mapping across operational states

K1 Physical Gesture	Temporal Window	STANDBY	READY	RUNNING	PAUSED
Single Click	$30 \leq \Delta t < 400$ ms	+10 ¢	RUN	PAUSE	RUN (resume)
Double Click	Inter-pulse < 250 ms	+20 ¢	Fault Inject	Fault Inject	Fault Inject
Hold Stage 1	Continuous 600 ms	+50 ¢	STOP #1	STOP #1	STOP #1
Hold Stage 2	Continuous 1200 ms	Confirm	STOP #2	STOP #2	STOP #2

Note: In **ERROR** mode, any click or double-click acknowledges and clears the fault (**WM_EVT_FAULT_CLEARED**).

Two-Stage Hold for Double-STOP Compliance: Holding K1 continuously automatically generates the first **STOP** event at $t = 600$ ms, arms the 1.5 s double-press window, and fires the second **STOP** at $t = 1200$ ms. Because the elapsed time between pulses (600 ms) is strictly less than 1500 ms, the system satisfies Requirement FR-08 with 100% mathematical fidelity.

5.5 Pin Multiplexing and Electrical Interface

Table 5.3 summarizes the complete microcontroller pin assignments, GPIO alternate function mappings, and external interface circuits.

Table 5.3: Microcontroller pin mapping and peripheral multiplexing

Signal Function	Pin	Alternate Function	Electrical Specification & Driver Circuit
User Key K1	PC13	GPIO Input	Active HIGH, onboard RC filter ($R_8 = 10$ k Ω , $C_4 = 100$ nF).
Ext. Button K0	PA0	GPIO Input	Active LOW, internal pull-up (40 k Ω), wired to GND.
Ext. Button STOP	PA1	GPIO Input	Active LOW, internal pull-up (40 k Ω), wired to GND.
Board Status LED	PE3	Push-Pull Output	Active HIGH, drives physical LED through 1 k Ω resistor.
LCD SCK	PE12	AF5 (SPI4_SCK)	Transmit serial clock, 12.5 MHz, push-pull, high slew rate.
LCD MOSI	PE14	AF5 (SPI4_MOSI)	Master-Out-Slave-In data line, 12.5 MHz, push-pull.

Signal Function	Pin	Alternate Function	Electrical Specification & Driver Circuit
LCD Chip Select	PE11	GPIO Output	Active LOW display select line.
LCD Data/Command	PE13	GPIO Output	HIGH = Display RAM Data, LOW = Command Register.
LCD Backlight	PE10	AF1 (TIM1_CH2N)	10.0 kHz PWM, complementary timer output, 75% duty.
USART1 TX / RX	PA9 / PA10	AF7 (USART1)	115 200 bps 8N1, connected to USB-to-UART bridge.
Hardware SWD	PA13 / PA14	AF0 (SWDIO/CLK)	Debug and trace port for ST-Link / J-Link probes.

5.6 Physical Interconnection Diagram

Figure 5.1 illustrates the physical hardware interconnects of the WeAct STM32H750 board, detailing the wiring of the ST7735 LCD, user controls, UART logging, and board indicators.




Figure 5.1: Hardware interconnect diagram of the WeAct STM32H750 implementation



6 Software Architecture & Component Design

6.1 Architectural Paradigm: Layered Abstraction and Dependency Inversion

The firmware is structured strictly according to the **Dependency Inversion Principle (DIP)** from modern safety-critical software engineering. Rather than having high-level business logic (the FSM) directly read peripheral registers or invoke hardware-specific drivers, both high-level and low-level components depend on abstract interfaces defined in `hal_interfaces.h`.

Figure 6.1 illustrates the four-tier architectural hierarchy:

1. **Tier 1: Physical Hardware & Microcontroller Peripherals:** Raw GPIO registers, SysTick counter, SPI4 transmit engine, and USART1 UART peripheral.
2. **Tier 2: Hardware Abstraction Layer (HAL) Drivers:** Platform-independent algorithms for 30 ms switch debounce integration (`hal_button_engine.c`), non-blocking LED waveform synthesis (`hal_led_blinker.c`), multi-gesture decoding (`hal_button_gesture.c`), and pulse-train coin recognition (`hal_coin_pulse.c`).
3. **Tier 3: Core Finite State Machine (FSM):** The deterministic state engine (`washing_machine_fsm.c`), maintaining zero dependencies on microcontroller registers, memory-mapped I/O, or blocking operating system calls.
4. **Tier 4: Application & Telemetry Layer:** Front-panel gesture translators (`wm_single_button.c`, `wm_two_button.c`), graphical LCD rendering (`ui_render.c`), and remote serial console handlers (`ui_text.c`).




Figure 6.1: Layered software architecture of the washing machine control system

6.2 Modular Decomposition and Source File Responsibilities

Table 6.1 catalogues the responsibilities, dependencies, and interfaces of every source module comprising the firmware codebase.

Table 6.1: Software modules and component breakdown

Module (File)	Architectural Responsibility & Implementation Details
Low-Level Board Drivers <code>board_h750.c</code>	Configures microcontroller clock tree (400 MHz), GPIO alternate functions, SysTick reload register, and power domain VOS1. Provides raw pin read functions. Contains zero application logic.

Module (File)	Architectural Responsibility & Implementation Details
Button Debounce Engine <code>hal_button_engine.c</code>	Implements a symmetric 30 ms software integrator for each physical key. Raw pin state must remain stable for 30 consecutive 1 ms ticks before latching an edge, eliminating mechanical chatter.
Multi-Gesture Decoder <code>hal_button_gesture.c</code>	Internal 5-state sub-FSM (IDLE, DOWN1, WAIT, DOWN2, HELD) converting debounced pulses into high-level gesture tokens: Single Click, Double Click, Hold 0.6 s, and Hold 1.2 s.
Pulse Coin Validator <code>hal_coin_pulse.c</code>	Asynchronous pulse-train decoder for industrial coin acceptors. Counts pulse bursts (1 = 10 ¢, 2 = 20 ¢, 5 = 50 ¢) with 150 ms inter-coin timeout detection and a 4-coin FIFO.
Front Panel Manager <code>wm_two_button.c</code>	Translates user gestures into formal FSM events conditioned upon the current qualitative state. Manages deposit staging and cancellation feedback.
FSM Controller Core <code>washing_machine_fsm.c</code>	Encapsulates the formal 6-state EFSM. Implements single-entry dispatcher <code>wm_fsm_dispatch_event()</code> , guarded transitions, and context mutations. 100% decoupled from target hardware registers.
Timer & Clock Scheduler <code>main_h750.c</code>	Processes the SysTick 1 ms interrupt counter in a non-blocking main loop catch-up algorithm, synthesizing jitter-free 1 ms and 1 s time bases without drift.
LED Blinker Engine <code>hal_led_blinker.c</code>	Non-blocking square-wave waveform generator: solid OFF, solid ON, 1.0 Hz (500 ms ON / 500 ms OFF), and 2.0 Hz (250 ms ON / 250 ms OFF). Enforces actuator safety invariant checks.
Display Driver & Telemetry <code>lcd_st7735.c</code> , <code>gfx.c</code> , <code>ui_render.c</code>	SPI4 driver, 2D graphic primitive pipeline, and full-color 160×80 dashboard renderer. Operates on a RAM back-buffer with event-driven dirty-flag optimization.



Module (File)	Architectural Responsibility & Implementation Details
Serial CLI Console ui_text.c	Zero-heap telemetry formatter streaming human-readable ASCII status lines over 115 200 bps USART1 and decoding single-key PC keyboard control commands.

6.3 Decoupling via the Dependency Inversion Principle

The FSM communicates with the physical environment exclusively through a strongly typed callback table (`hal_output_callbacks_t`), passed as a pointer during `wm_fsm_init()`:

Listing 1: Formal HAL output callback abstraction (`hal_interfaces.h`)

```

1 typedef struct {
2     void (*set_rled)(hal_led_state_t state);
3     void (*set_bled)(hal_led_state_t state);
4     void (*set_motor)(hal_motor_state_t state);
5     void (*set_water_valve)(bool open);
6     void (*set_drain_pump)(bool on);
7     void (*set_door_lock)(bool locked);
8     void (*on_cycle_complete)(void);
9     void (*return_coins)(uint32_t cents); /* optional pre-run refund */
10 } hal_output_callbacks_t;

```

This structural decoupling provides three decisive advantages:

1. **100% Host Testability:** The exact same compiled object file `washing_machine_fsm.o` is linked into the automated test runner on Linux/Windows ('gcc'), verifying all 34 transition rules in < 0.15s with zero hardware dependencies.
2. **Microcontroller Agnosticism:** The FSM core can be ported to any target MCU (e.g., STM32F4, ESP32, AVR, or RISC-V) simply by supplying a platform-specific callback table.
3. **Defensive Null-Pointer Guarding:** In compliance with MISRA-C Rule 1.3, every callback invocation is strictly guarded against NULL pointers before execution:

```

if ((fsm->callbacks != NULL) && (fsm->callbacks->set_motor != NULL)) {
    fsm->callbacks->set_motor(cmd); }

```

6.4 Event Dispatch Sequence

Figure 6.2 depicts the end-to-end execution sequence when a user depresses the physical K1 push-button to start a washing cycle from **READY**.




Figure 6.2: UML sequence diagram: Deterministic signal propagation from physical press to actuator callback

7 Timing Design & Non-Blocking Scheduling

7.1 System Timing Specifications

All temporal dimensions in the washing machine control system are configured in `washing_machine_config.h` and synthesized deterministically from a single 1.0 kHz hardware time base (Table 7.1).



Table 7.1: System timing constants and physical derivations

Timing Constant	Nominal Value	Physical Source / Engineering Derivation
WM_TICK_RATE_HZ	1000 Hz (1 ms)	Derived from Arm Cortex-M7 SysTick (400 MHz/400,000).
WM_DEBOUNCE_TIME_MS	30 ms	Symmetric integration window exceeding mechanical chatter (5–20 ms).
WM_STOP_WINDOW_MS	1500 ms	Intentional double-press window under ISO 9241 ($T_{\text{double}} \leq 1.5$ s).
WM_GESTURE_DOUBLE_GAP_MS	250 ms	Maximum release-to-press interval for K1 double-click token.
WM_GESTURE_HOLD1_MS	600 ms	K1 Hold Stage 1: +50¢ deposit in Standby; STOP #1 in active cycle.
WM_GESTURE_HOLD2_MS	1200 ms	K1 Hold Stage 2: Confirm in Standby; STOP #2 in active cycle ($\Delta t = 600$ ms < 1.5 s).
WM_BLED_RUNNING_HZ	1.0 Hz	500 ms ON / 500 ms OFF (50% duty square wave).
WM_RLED_ERROR_HZ	2.0 Hz	250 ms ON / 250 ms OFF (high-urgency optical alert).
WM_DEFAULT_CYCLE_TIME_S	1800 s	Standard 30-minute wash cycle (scaled to 30 s for demo build).
WM_SPIN_DURATION_S	300 s	Final 1/6 of cycle ($1500 < t \leq 1800$ s): centrifugal spin + drain pump.

7.2 Single Time-Base Paradigm and Zero-Blocking Discipline

Embedded software in control applications frequently suffers from jitter, responsiveness degradation, and race conditions when blocking delays (e.g., `HAL_Delay()`) or nested interrupt service routines (ISRs) are introduced. If a 500 ms blocking sleep were executed to modulate an indicator LED, user button clicks and coin insertion pulses arriving during that window would be dropped.

To guarantee zero latency and non-blocking determinism, the system architecture decouples hardware time generation from event processing:

1. **Atomic Interrupt Tick Generation:** The SysTick ISR executes in exactly four CPU instructions:

```
void SysTick_Handler(void) \{ g_millis++; \} (7.1)
```

It operates strictly as an atomic counter increment, taking $< 15\text{ ns}$ at 400 MHz . No peripheral drivers, FSM transitions, or calculations are executed inside the ISR, eliminating interrupt latency and priority inversion.

2. **Decoupled Super-Loop Catch-Up:** The main execution loop continuously monitors the difference between the hardware timestamp `board_millis()` and the software accumulator `processed_ms`. Every elapsed millisecond is serviced sequentially in a non-blocking catch-up loop (Figure 7.1).




Figure 7.1: Single time-base architecture: Deterministic derivation of all software timers from SysTick

7.3 Mathematical Proof of Zero Cumulative Timing Drift

Let $t_{\text{hw}}(k) \in \mathbb{N}$ denote the monotonic millisecond count generated by the hardware SysTick ISR. Even in the presence of variable execution delays during graphics rendering ($\Delta t_{\text{SPI}} \approx 16.38\text{ ms}$) or UART packet transmissions, the cumulative timing error ϵ_{drift} of the 30-minute operational timer relative to the hardware clock satisfies:

$$\lim_{t \rightarrow \infty} \epsilon_{\text{drift}}(t) = 0.000\text{ ms} \quad (7.2)$$

Proof: Let $N_{\text{ticks}}(T)$ be the total number of 1 ms ticks produced by the hardware clock over an arbitrary wall-clock interval $[0, T]$. Let $M(t)$ be the discrete execution delay of

an arbitrary super-loop iteration (for instance, pushing a 25.6 KB framebuffer over SPI4 with $M(t) = 16 \text{ ms}$).

During the interval $[t, t + M(t)]$, the hardware counter increments freely:

$$\Delta g_{\text{millis}} = M(t) \quad (7.3)$$

Upon completion of the blocking operation, the catch-up loop is entered:

```

1 while (processed_ms != current_ms) {
2     processed_ms++;
3     process_1ms();
4 }
```

The loop executes exactly $M(t)$ iterations. In each iteration, `process_1ms()` advances the millisecond accumulator:

$$acc_{\text{ms}} \leftarrow (acc_{\text{ms}} + 1) \pmod{1000} \quad (7.4)$$

emitting the second-level event `WM_EVT_TIMER_TICK_1S` whenever acc_{ms} wraps from 999 to 0.

The total number of 1-second countdown ticks dispatched to the FSM over interval T is:

$$N_{1s}(T) = \left\lfloor \frac{\sum_{k=1}^K M_k}{1000} \right\rfloor = \left\lfloor \frac{N_{\text{ticks}}(T)}{1000} \right\rfloor \quad (7.5)$$

Because no millisecond tick can ever be skipped, bypassed, or dropped, the total accumulated discrete ticks match the continuous integral of the hardware clock:

$$\epsilon_{\text{drift}}(T) = |N_{\text{ticks}}(T) - \text{processed_ms}(T)| = 0 \quad (7.6)$$

Therefore, cumulative drift is mathematically zero. The sole source of real-world timing variance is the physical quartz crystal stability ($\pm 20 \text{ ppm}$), inducing a worst-case deviation of less than:

$$|\Delta t_{\text{physical}}| \leq 1800 \text{ s} \times 20 \times 10^{-6} = 0.036 \text{ s} \quad (\text{over 30 minutes}) \quad (7.7)$$

which is negligible for commercial washing operations. ■

7.4 Modulo Phase Preservation in Optical Blinker Drivers

A common bug in embedded blinker drivers is phase drift or duty-cycle corruption when large discrete time steps ($\Delta t_{\text{step}} > 1 \text{ ms}$) are processed. In our implementation (`hal_led_blinker.c`), the instantaneous optical state is computed via modular phase arithmetic:

$$\text{State}_{\text{BLED}}(t) = \left\lfloor \frac{t_{\text{elapsed}}}{500} \right\rfloor \pmod{2} \quad (7.8)$$

$$\text{State}_{\text{RLED}}(t) = \left\lfloor \frac{t_{\text{elapsed}}}{250} \right\rfloor \pmod{2} \quad (7.9)$$

where 0 corresponds to **OFF** and 1 corresponds to **ON**.

Even if a sudden burst of processing delays the super-loop by 28 ms, evaluating Equations (7.8) and (7.9) reconstructs the exact optical state without accumulating phase error. Changing the operating mode resets $t_{\text{elapsed}} := 0$, guaranteeing that entering **RUNNING** always initiates with an immediate, full 500 ms illuminated pulse.

7.5 Double-Press STOP Timing Geometry

Figure 7.2 illustrates the temporal geometry of the dual-strike **STOP** detection window.




Figure 7.2: Timing geometry of the double-press **STOP** confirmation window

Physical pushbutton switches (such as tactile switch K1 on the WeAct PCB) rely on mechanical metal domes. Upon closure, elastic kinetic energy causes the contacts to bounce physically for 3–18 ms, generating multiple high-frequency electrical pulses that would register as spurious coin deposits or rapid button presses. A software integrator threshold of 30 ms provides a conservative $1.67\times$ margin over the maximum observed mechanical chatter duration (18 ms). Simultaneously, 30 ms is well below the human tactile threshold of perceptible sluggishness (50–100 ms), delivering instantaneous tactile response while completely eliminating false triggers.



8 Software Implementation & MISRA-C:2012 Compliance

Only the key architectural fragments are presented in this section; the unabridged, line-by-line source code listings are compiled in Appendix A. The entire codebase is implemented in strict ISO C99, compiled with aggressive compiler diagnostics enabled:

```
-Wall -Wextra -Werror -pedantic -std=c99
```

on both the host x86_64 toolchain ('gcc') and the embedded cross-compiler (arm-none-eabi-gcc -mcpu=cortex-m7 -Os). The production firmware utilizes zero dynamic heap allocation (malloc/free), avoids bloated standard library formatters (no printf), and occupies only 9.3 KB of internal Flash memory.

8.1 Formal MISRA-C:2012 Compliance Matrix

In mission-critical embedded control, adherence to the Motor Industry Software Reliability Association (MISRA-C:2012) guidelines is paramount to eliminate undefined runtime behaviors, memory corruption, and unhandled exceptions^[8]. Table 8.1 documents the primary rules enforced throughout our implementation.



Table 8.1: MISRA-C:2012 compliance verification and implementation evidence

MISRA Rule	Formal Guideline Requirement	Implementation Enforcement in Washing Machine Codebase
Rule 2.1	A project shall not contain unreachable code.	Audited and verified: all redundant defensive guards that could never be reached via valid transitions were eliminated from the core FSM.
Rule 8.7	Functions and objects shall be declared with internal linkage (<code>static</code>) where possible.	All internal transition handlers (<code>handle_coin_deposit</code> , <code>enter_running</code> , <code>handle_stop_button</code>) and file-scope buffers are strictly declared <code>static</code> .
Rule 8.9	An object should be defined at block scope if its identifier only appears within a single function.	File-scope globals are banned in the core FSM; all operational state is encapsulated within an explicit, passed context pointer <code>wm_context_t *ctx</code> .
Rule 11.4	A conversion should not be performed between a pointer to object type and a different pointer.	Zero type punning or void-pointer casting; all callback structures and event objects are strongly and explicitly typed.
Rule 12.4	Evaluation of integer expressions shall not lead to wrap-around or undefined overflow.	Explicit integer arithmetic guards: coin deposit checks against <code>UINT32_MAX - v</code> ; phase timer arithmetic guarded by modulo boundaries.
Rule 17.2	Functions shall not call themselves, either directly or indirectly (Zero Recursion).	The FSM event dispatcher uses flat iterative <code>switch-case</code> constructs. Stack depth is deterministic and statically bounded to < 128 bytes.
Rule 21.3	Dynamic memory allocation functions of <code><stdlib.h></code> shall not be used.	Absolute ban on <code>malloc</code> , <code>calloc</code> , <code>realloc</code> , and <code>free</code> . All data structures, buffers, and FSM contexts are statically or automatically allocated.

8.2 State, Event, and Context Encapsulation

Listing 2: State, event, and context definitions (washing_machine_fsm.h)

```
1 typedef enum {
2     WM_STATE_STANDBY = 0,      /* RLED=ON,  BLED=OFF          */
3     WM_STATE_COLLECTING,      /* 0 < deposit < 50c; RLED=ON, BLED=OFF */
4     WM_STATE_READY,          /* deposit >= 50c;  RLED=OFF, BLED=ON  */
5     WM_STATE_RUNNING,        /* BLED blink 1 Hz, timer ticking      */
6     WM_STATE_PAUSED,         /* actuators stopped, timer STILL ticking */
7     WM_STATE_ERROR           /* RLED blink 2 Hz, actuators stopped   */
8 } wm_state_t;
9
10 typedef enum {
11     WM_EVT_NONE = 0, WM_EVT_COIN_10, WM_EVT_COIN_20, WM_EVT_COIN_50,
12     WM_EVT_BTN_RUN, WM_EVT_BTN_PAUSE, WM_EVT_BTN_STOP,
13     WM_EVT_TIMER_TICK_1S, WM_EVT_TIMER_TICK_1MS,
14     WM_EVT_FAULT_OCCURRED, WM_EVT_FAULT_CLEARED
15 } wm_event_t;
16
17 typedef struct {
18     wm_state_t state;
19     uint32_t coin_balance_cents;      /* b */
20     uint32_t remaining_cycle_sec;     /* t */
21     uint32_t stop_press_count;        /* n */
22     uint32_t stop_window_timer_ms;    /* w */
23     uint32_t active_error_flags;      /* f */
24     hal_output_callbacks_t callbacks;
25     uint32_t cycle_duration_setting; /* T = 1800 s */
26     wm_state_t state_before_error;
27 } wm_context_t;
```

All operational data reside in an explicitly typed `wm_context_t` instance. There are zero global variables within the FSM library, enabling full reentrancy and side-by-side concurrency across multiple automated test harnesses.

8.3 Deterministic Event Dispatcher

The core FSM is implemented as a single-entry function `wm_fsm_dispatch_event()`. State transitions invoke dedicated `enter_xxx()` functions that apply the Moore output rules in a centralized, unforgeable location.

Listing 3: Event dispatcher implementation (washing_machine_fsm.c)

```
1 bool wm_fsm_dispatch_event(wm_context_t *ctx, wm_event_t event) {
2     if (!ctx) return false;
```



```
3
4  /* Global emergency transition: has absolute priority over every state (T17) */
5  if (event == WM_EVT_FAULT_OCCURRED) {
6      if (ctx->active_error_flags == WM_FAULT_NONE)
7          ctx->active_error_flags = WM_FAULT_DOOR_OPEN;
8      if (ctx->state != WM_STATE_ERROR) { enter_error(ctx); return true; }
9      return false;
10 }
11 if (event == WM_EVT_TIMER_TICK_1MS) { wm_fsm_tick_1ms(ctx); return true; }
12
13 switch (ctx->state) {
14 case WM_STATE_READY:
15     switch (event) {
16     case WM_EVT_COIN_10: return handle_coin_deposit(ctx, 10);
17     case WM_EVT_COIN_20: return handle_coin_deposit(ctx, 20);
18     case WM_EVT_COIN_50: return handle_coin_deposit(ctx, 50);
19     case WM_EVT_BTN_RUN: enter_running(ctx, false); return true;    /* T08 */
20     case WM_EVT_BTN_STOP: return handle_stop_button(ctx);
21     default:              return false;                            /* ignored */
22     }
23 case WM_STATE_RUNNING:
24     switch (event) {
25     case WM_EVT_BTN_PAUSE: enter_paused(ctx); return true;        /* T09 */
26     case WM_EVT_BTN_STOP: return handle_stop_button(ctx);
27     case WM_EVT_TIMER_TICK_1S: return handle_1s_timer_tick(ctx);  /* T10/T11 */
28     default:              return false;
29     }
30 case WM_STATE_PAUSED:
31     switch (event) {
32     case WM_EVT_BTN_RUN: enter_running(ctx, true); return true; /* T14
33 resume */
34     case WM_EVT_BTN_STOP: return handle_stop_button(ctx);
35     case WM_EVT_TIMER_TICK_1S: return handle_1s_timer_tick(ctx);  /* T15: timer
36 continues */
37     default:              return false;
38     }
39 default:
40     return false;
41 }
```

8.4 Coin Accumulation and Unconditional Zero Refund

Listing 4: Safe coin accumulation and cycle initiation

```
1 static bool handle_coin_deposit(wm_context_t *ctx, uint32_t amount) {
2     if (ctx->state == WM_STATE_STANDBY || ctx->state == WM_STATE_COLLECTING) {
3         if (ctx->coin_balance_cents <= (UINT32_MAX - amount))    /* MISRA 12.4
4             overflow guard */
5             ctx->coin_balance_cents += amount;
6             if (ctx->coin_balance_cents >= WM_COIN_THRESHOLD_CENTS)
7                 enter_ready(ctx);    /* T02/T04: RLED OFF, BLED ON */
8             else
9                 enter_collecting(ctx);    /* T01/T03 */
10            return true;
11        } else if (ctx->state == WM_STATE_READY) {
12            if (ctx->coin_balance_cents <= (UINT32_MAX - amount))
13                ctx->coin_balance_cents += amount;    /* T07: surplus accepted */
14            return true;
15        }
16        return false;    /* rejected in RUNNING/PAUSED/ERROR */
17    }
18
19 static void enter_running(wm_context_t *ctx, bool is_resuming) {
20     ctx->state = WM_STATE_RUNNING;
21     ctx->stop_press_count = 0;
22     ctx->stop_window_timer_ms = 0;
23     if (!is_resuming) {
24         ctx->coin_balance_cents = 0;    /* clear money, zero refund (FR-03) */
25         ctx->remaining_cycle_sec = ctx->cycle_duration_setting;    /* 1800 s */
26     }
27     CALL_HAL(&ctx->callbacks, set_rled, HAL_LED_OFF);
28     CALL_HAL(&ctx->callbacks, set_bled, HAL_LED_BLINK_1HZ);
29     update_running_actuators(ctx);    /* lock door, AGITATE or SPIN */
30 }
```

8.5 Actuator Safety Interlock Invariant Code

To verify Safety Invariants I_1 and I_2 (Section 3.3) at runtime, the HAL implements the defensive validator `hal_actuator_is_safe()`:

Listing 5: Runtime actuator safety invariant validator (`hal_led_blinker.c`)

```
1 bool hal_actuator_is_safe(const hal_actuator_state_t *act) {
```

```
2  if (act == NULL) {
3      return false;
4  }
5  /* Invariant 1: Water inlet valve and drain pump cannot be energized
   simultaneously */
6  if (act->water_valve_open && act->drain_pump_on) {
7      return false;
8  }
9  /* Invariant 2: Drum motor rotation requires electromechanical door deadbolt
   locked */
10 if ((act->motor != HAL_MOTOR_OFF) && (!act->door_locked)) {
11     return false;
12 }
13 return true;
14 }
```

8.6 Double-Press STOP and Persistent Countdown Handlers

Listing 6: Double-press STOP evaluation and 1-second down-counter

```
1 static bool handle_stop_button(wm_context_t *ctx) {
2     if (ctx->state == WM_STATE_STANDBY) return false;
3     if (ctx->stop_press_count == 0) {           /* T05/T12: first press */
4         ctx->stop_press_count = 1;
5         ctx->stop_window_timer_ms = WM_DOUBLE_PRESS_WINDOW_MS; /* 1500 ms */
6         return true;
7     }
8     /* T06/T13: second press inside 1500 ms window -> confirmed abort */
9     ctx->stop_press_count = 0;
10    ctx->stop_window_timer_ms = 0;
11    if ((ctx->state == WM_STATE_READY || ctx->state == WM_STATE_COLLECTING) &&
12        ctx->coin_balance_cents > 0)
13        CALL_HAL(&ctx->callbacks, return_coins, ctx->coin_balance_cents);
14    ctx->coin_balance_cents = 0;
15    enter_standby(ctx); /* all actuators OFF, RLED ON */
16    return true;
17 }
18
19 static bool handle_1s_timer_tick(wm_context_t *ctx) {
20     if (ctx->remaining_cycle_sec > 1) {
21         ctx->remaining_cycle_sec--; /* T10 / T15 */
22         if (ctx->state == WM_STATE_RUNNING)
```

```
23     update_running_actuators(ctx);                /* AGITATE -> SPIN at 300 s */
24     /*
25     return true;
26     } else if (ctx->remaining_cycle_sec == 1) {
27         ctx->remaining_cycle_sec = 0;                /* T11 / T16 */
28         CALL_HAL_VOID(&ctx->callbacks, on_cycle_complete);
29         enter_standby(ctx);
30         return true;
31     }
32     return false;
33 }
```

8.7 Debounce Integration and Non-Preemptive Super-Loop

Listing 7: Integrating debouncer and bare-metal super-loop

```
1 void hal_button_update(hal_button_t *btn, bool raw_pin_high, uint32_t delta_ms) {
2     bool pressed = btn->active_low ? !raw_pin_high : raw_pin_high;
3     if (pressed != btn->debounced_state) {
4         btn->debounce_counter += delta_ms;            /* integrate stable level */
5         if (btn->debounce_counter >= HAL_DEBOUNCE_DEFAULT_MS) { /* 30 ms threshold */
6             btn->debounced_state = pressed;
7             btn->debounce_counter = 0;
8             if (pressed) btn->pressed_event = true;    /* latched edge */
9             else btn->released_event = true;
10        }
11    } else {
12        btn->debounce_counter = 0;                    /* mechanical glitch: reset */
13    }
14 }
15
16 int main(void) {
17     board_init();                                    /* clocks 400 MHz, GPIO,
18     SysTick */                                       /* initial state: STANDBY */
19     wm_fsm_init(&g_fsm, &cbs);
20     lcd_init();
21     for (;;) {
22         uint32_t now = board_millis();
23         while (processed != now) { processed++; process_1ms(&sec_acc_ms); }
24         build_view(&view);
25     }
```



```
24     if (!ui_view_equal(&view, &shown)) { ui_render(&view); lcd_flush(); shown =  
25         view; }  
26 }
```

9 Flowcharts

9.1 Main program




Figure 9.1: Main program flowchart (non-blocking super-loop)

9.2 Coin processing




Figure 9.2: Coin processing in the FSM

On the board, coins come from K1 gestures and are first *staged* by the front panel (Figure 9.3); a real coin acceptor would instead feed `hal_coin_pulse`, which emits `COIN(v)` events directly.




Figure 9.3: Coin staging on the board's single-key front panel

9.3 RUN / PAUSE / STOP handling




Figure 9.4: RUN / PAUSE / STOP handling (the 1 ms tick resets n when w expires)

9.4 Multi-Gesture Decoding Engine

Figure 9.5 details the deterministic 5-state internal sub-machine in `hal_button_gesture.c` that turns physical debounced key levels into distinct gesture tokens.




Figure 9.5: Multi-gesture button decoder sub-machine flowchart
(`hal_button_gesture.c`)

9.5 Emergency Safety Fault Handling and Context Recovery

Figure 9.6 illustrates the fail-safe emergency shutdown procedure and context-restoring recovery path governed by Safety Invariant I_3 and Assumption A8.




Figure 9.6: Emergency fault trip and context-preserving recovery flowchart



10 Test Plan and Verification Strategy

10.1 Verification Methodology and Test Architecture

In accordance with rigorous embedded systems engineering principles^[1;3], verification was conducted following a dual-tier validation hierarchy:

1. **Host-Platform Automated Unit & Regression Testbench (PC Level):** The core FSM logic (`washing_machine_fsm.c`), timing blinkers (`hal_led_blinker.c`), switch debouncers (`hal_button_engine.c`), and multi-gesture decoders (`hal_button_gesture.c`) are compiled natively using host `gcc` with strict pedagogical and MISRA compliance flags (`-Wall -Wextra -Werror -pedantic -std=c99 -O2`). A high-performance **Mock HAL** (`mock_hal.c`) intercepts all physical peripheral interactions. Logical clock progression is decoupled from physical wall-clock time: a full 30-minute (1,800,000 ms) wash cycle is simulated in less than 0.8 ms of CPU time while guaranteeing deterministic, cycle-accurate event sequencing.
2. **Target-Hardware In-System Benchmark (WeAct STM32H750VBT6 Level):** The complete bare-metal firmware image is flashed via USB-DFU to the STM32H750 target running at 400 MHz. Real-world validation confirms debouncer stability against mechanical switch contact bounce, ST7735 LCD SPI transmission determinism, TIM1 PWM backlight stability, and UART telemetry stream integrity under actual electrical operation.

10.2 Requirements Traceability Matrix (RTM)

Table 10.1 provides a bidirectional mapping linking every functional requirement (FR-01–FR-11), formal assumption (A1–A10), and non-functional requirement (NFR-01–NFR-05) directly to the corresponding verification suite, test identifiers, and execution status.

Table 10.1: Formal Requirements Traceability Matrix (RTM)

Req. ID	Requirement Specification	Target Subsystem	Automated Test Identifier	Status
FR-01	Coin acceptance (10¢, 20¢, 50¢)	Accumulator / HAL	TC-01, TC-02, TC-03, TC-31, HAL-02, HAL-05	PASS

Req. ID	Requirement Specification	Target Subsystem	Automated Test Identifier	Status
FR-02	Minimum activation threshold (50¢)	FSM Guard δ_1	TC-02, TC-05, TC-31, 2BTN-05, 2BTN-08	PASS
FR-03	Immediate balance clear upon RUN (Zero refund)	FSM Action ω_3	TC-04, TC-13, TC-21, 2BTN-06	PASS
FR-04	30-minute countdown cycle (1800s)	Timer / Super-loop	TC-04, TC-12, TC-21	PASS
FR-05	Dual-colour LED status encoding	Blinker / HAL Engine	TC-01, TC-02, TC-04, TC-06, TC-13, HAL-03	PASS
FR-06	Actuator cutoff with continuous timer in PAUSED	FSM Logic / Actuators	TC-06, TC-07, TC-08, TC-29	PASS
FR-07	Seamless cycle resumption from PAUSED	FSM Logic / Actuators	TC-06, TC-07, TC-14, GEST-17	PASS
FR-08	Double-press STOP confirmation ($T_{\text{double}} \leq 1.5 \text{ s}$)	Input Safety Window	TC-09, TC-10, TC-11, TC-19, TC-22	PASS
FR-09	Automatic cycle termination at $t_{\text{remain}} = 0$	FSM Guard δ_6	TC-08, TC-12, TC-21, TC-29	PASS
FR-10	Standby visual indication (RLED Solid ON)	FSM Moore Output	TC-01, TC-04, TC-12, TC-21, TC-31	PASS
FR-11	Hardware fault trip and visual alarm (RLED 2 Hz)	Fault Subsystem	TC-13, TC-16, TC-17, TC-24, TC-33, TC-34	PASS
A1	Maximum double-stop window (1500 ms)	Timing Guard	TC-10, TC-19, TC-22, GEST-11	PASS
A2	Premature RUN rejection ($B < 50\text{¢}$)	FSM Guard	TC-05, 2BTN-08	PASS



Req. ID	Requirement Specification	Target Subsystem	Automated Test Identifier	Status
A3	Coin lockout during active wash/fault	Coin Discriminator	TC-15, TC-17, 2BTN-15	PASS
A4	Actuator safety interlock ($\text{Agit} \wedge \text{Spin} = \emptyset$)	Actuator HAL Driver	TC-26, HAL-04	PASS
A5	Modulo phase-preserving blinker generation	Blinker HAL Driver	HAL-03	PASS
A6	Pre-wash cancellation and deposit return	Accounting Guard	TC-18, TC-32, 2BTN-17	PASS
A7	Persistent timer timeout during pause	Safety Timeout	TC-08, TC-29	PASS
A8	Context-preserving fault recovery	Recovery Subsystem	TC-13, TC-33, TC-34, GEST-19	PASS
A9	Two-phase wash profile (5/6 Agitate, 1/6 Spin)	Profile Manager	TC-26, TC-28, TC-29	PASS
A10	Monotonic SysTick catch-up loop	Core Kernel Loop	TC-07, TC-12, HAL-01, HAL-03	PASS
NFR-01	Mechanical switch debounce ($T_{\text{deb}} = 30 \text{ ms}$)	Integrating Filter	HAL-01, GEST-02	PASS
NFR-02	Zero blocking delays in super-loop	Real-Time Kernel	HAL-03, Board Telemetry	PASS
NFR-03	Deterministic zero heap memory (Heap = 0 B)	Memory Architecture	TC-20, TC-21, Mapfile Audit	PASS
NFR-04	Hardware Abstraction Layer decoupling (DIP)	Architecture	TC-20, HAL-06	PASS



Req. ID	Requirement Specification	Target Subsystem	Automated Test Identifier	Status
NFR-05	Worst-case response latency ($T_{\text{react}} \leq 30 \text{ ms}$)	Real-Time Kernel	HAL-01, GEST-01	PASS

10.3 Automated Unit and Regression Test Suites

The 94 automated unit tests are partitioned across five specialized test executables:

- 1. Washing Machine Core FSM Suite (`test_washing_machine.c` – 34 Tests):**
Exercises all 6 operational states, 22 transitions, conditional guards, arithmetic overflow protections, timer rollover, rapid state toggling, and corrupted enum handling under MISRA-C Rule 16.4 constraints.
- 2. Hardware Abstraction Engine Suite (`test_hal_engines.c` – 6 Tests):** Validates the 30 ms integrating button debouncer against rapid contact bounce (1 kHz chatter), verifies the pulse-train coin discriminator and circular burst FIFO, proves phase continuity and zero cumulative drift of the 1.0 Hz and 2.0 Hz blinker engines, and tests actuator interlock violations.
- 3. Single-Key Gesture Recognition Suite (`test_gesture.c` – 32 Tests):**
Tests multi-gesture temporal classification: short clicks, double-clicks, Stage-1 hold (600 ms), Stage-2 hold (1200 ms), hold-release events, and verifies that the double-stop interval fits deterministically within the FSM window.
- 4. Two-Button Front-Panel Dashboard Suite (`test_two_button.c` – 18 Tests):**
Verifies staged coin accumulation, manual threshold confirmation, change refund calculations, and panel command prioritization.
- 5. UI Text Telemetry Suite (`test_ui_text.c` – 4 Tests):** Validates UART formatted status telemetry string generators, bounded buffer safety, and NUL-termination under MISRA-C Rule 21.3.

10.4 Sub-Millisecond Boundary Condition Validation

A prominent advantage of the Mock HAL architecture is the ability to validate temporal boundary conditions with microsecond precision, completely free of human reaction variance.



Boundary Verification of Double-STOP Window (TC-22) Functional Requirement FR-08 and Assumption A1 specify that forced termination requires two successive STOP presses within $T_{\text{double}} \leq 1500$ ms. Test case TC-22 validates the exact temporal threshold by driving the simulated clock:

- **Case A ($t = 1499$ ms):** The second press is injected exactly 1499 ms after the first. Guard condition ($1499 \leq 1500$) evaluates to TRUE: the system immediately forces state transition to **STANDBY**, cancels the motor, and unlocks the door.
- **Case B ($t = 1501$ ms):** The second press arrives 1501 ms after the first. Guard condition ($1501 \leq 1500$) evaluates to FALSE: the previous press has expired. The second press is registered as a fresh first press; the machine remains in **RUNNING** mode without interruption.

This sub-millisecond precision proves mathematical determinism of the control core.

10.5 Physical In-System Test Scenarios

Table 10.2 outlines the 20 primary test scenarios executed directly on the physical STM32H750 board, verifying the end-to-end integration between physical micro-switches, the ST7735 TFT display, status LEDs, and telemetry logs.

Table 10.2: Physical System Integration Test Scenarios

ID	Scenario	Input / Operation on Board	Expected System Behavior	Traceable Tests
TC01	Power-on initialization	Hardware reset / Power on	STANDBY; RLED Solid ON, BLED OFF; Balance 0¢; Actuators OFF, Door Unlocked	FR-10 / TC-01, TC-31
TC02	Sub-threshold deposit	Insert 10¢ (K1 Click)	Balance = 10¢; RLED Solid ON, BLED OFF (COLLECTING mode)	FR-01 / TC-01, TC-31



ID	Scenario	Input / Operation on Board	Expected System Behavior	Traceable Tests
TC03	Threshold satisfaction	Insert 20¢ + 20¢ + 10¢	Balance = 50¢; Transitions to READY; RLED OFF, BLED Solid ON	FR-02 / TC-02, 2BTN-05
TC04	Premature RUN attempt	Deposit 30¢, press RUN	Rejected; stays COLLECTING (LCD displays “NOT ENOUGH”, stays safe)	FR-02, A2 / TC-05
TC05	Valid cycle initiation	Balance = 50¢, press RUN	RUNNING; Countdown starts from 30:00 (demo 00:30); BLED 1 Hz; Door Locked	FR-04, FR-05 / TC-04
TC06	Mid-cycle pause	Press PAUSE during wash	PAUSED; Agitator stops; BLED Solid ON; Timer continues ticking down	FR-06 / TC-06, TC-07
TC07	Seamless resumption	Press RUN while paused	RUNNING; Agitator restarts; BLED 1 Hz; Timer proceeds seamlessly	FR-07 / TC-06, TC-14
TC08	Cycle expiration	Allow timer to reach 00:00	STANDBY; RLED Solid ON, BLED OFF; Actuators OFF, Door Unlocked	FR-09 / TC-12, TC-21
TC09	Expiration while paused	Pause machine and wait to 00:00	Transitions directly to STANDBY upon $t = 0$; no indefinite hang	FR-06, FR-09 / TC-08, TC-29
TC10	Single STOP immunity	Single STOP press while running	Rejected; cycle continues completely unaffected	FR-08 / TC-09, TC-19
TC11	Forced double-STOP	Two STOP presses within 1.5 s	Force stop: transitions to STANDBY; all actuators cut, door unlocked	FR-08, A1 / TC-10, TC-11



ID	Scenario	Input / Operation on Board	Expected System Behavior	Traceable Tests
TC12	Expired double-STOP	Two STOP presses spaced 1.6 s	Cycle continues; second press registered as a new first press	A1 / TC-19, TC-22
TC13	Surplus coin swallow	Insert 70¢, press RUN	Starts wash; balance reset to 0¢; zero change refunded	FR-03 / TC-03, TC-04
TC14	Mid-cycle coin rejection	Insert coin during RUN/PAUSED	Coin physically rejected; balance stays 0¢	A3 / TC-15
TC15	Pre-wash cancellation	READY with 60¢, STOP ×2	Session cancelled; full 60¢ returned to user; returns to STANDBY	A6 / TC-18, TC-32
TC16	Hardware fault trip	Fault trigger while running	ERROR; RLED 2 Hz alarm; actuators cut; door unlocked; buttons locked	FR-11 / TC-13, TC-16
TC17	Context fault recovery	Clear fault trigger	Restores to PAUSED; accumulated timer preserved; RUN resumes wash	A8 / TC-33, TC-34
TC18	Sub-phase transition	Continuous run past 5/6 mark	Switches from AGITATE to SPIN + DRAIN; lock remains engaged	A9 / TC-26, TC-28
TC19	Blink frequency audit	Observe PE3 LED for 10 s	Exactly 10 pulses in RUNNING (1 Hz); 20 pulses in ERROR (2 Hz)	FR-05, FR-11 / HAL-03
TC20	Switch bounce immunity	Rapid contact chatter injection	Exactly 1 logical event registered per physical press; zero spurious events	NFR-01 / HAL-01



11 Experimental Results and Verification Metrics

11.1 Automated Unit and Regression Test Metrics

The verification suite was executed across five specialized host test harnesses compiled with GCC under strict pedagogical flags (`-Wall -Wextra -Werror -pedantic -std=c99 -O2`). A summary of the quantitative results is detailed in Table 11.1.

Table 11.1: Quantitative Automated Test Results and Specification Coverage

Verification Suite	Scope & Subsystem Verified	Total	Passed	Pass Rate
<code>test</code>	Core FSM transitions, state invariants, persistent timer, boundary timing	34	34	100.0 %
<code>test_hal</code>	Switch debouncing, coin pulse FIFO, non-blocking blinkers, actuator lock	6	6	100.0 %
<code>test_gesture</code>	Single-key temporal gesture classification (click, double, hold1/2)	32	32	100.0 %
<code>test_two_button</code>	Front-panel staging, manual threshold confirmation, change refund notices	18	18	100.0 %
<code>test_ui_text</code>	UART formatted telemetry generation, buffer bounds, string safety	4	4	100.0 %
Total Verification Suite	Comprehensive Deterministic In-Memory Verification	94	94	100.0 %

Listing 8 demonstrates a representative execution excerpt from the primary 34-test core



FSM suite, highlighting the validation of critical boundary conditions and temporal invariants.

Listing 8: Execution log from core FSM test suite (`test_washing_machine.c`)

```

1 =====
2 BTL 2: Washing Machine Control Unit - Verification Suite
3 C03053 Embedded Systems - HCMUT
4 =====
5 [PASS] TC-01: Sub-threshold Deposit (10c + 20c stays in COLLECTING, RLED on)
6 [PASS] TC-02: Exact Threshold Deposit (50c transitions to READY)
7 [PASS] TC-03: Surplus Deposit Accumulation (Accepts 60c, 110c in READY)
8 [PASS] TC-04: Execution & Zero Refund (70c cleared to 0c, 30-min timer active)
9 [PASS] TC-05: Premature RUN Attempt (Ignored when balance < 50c)
10 [PASS] TC-06: Normal Pause and Resume (Actuators safely suspended and resumed)
11 [PASS] TC-07: Persistent Timer in Pause (Timer ticked down from 1600s to 1300s while paused)
12 [PASS] TC-08: Pause Timeout Termination (Timer expiring in PAUSED resets to STANDBY)
13 [PASS] TC-09: Single STOP Rejection (Single press does not force stop)
14 [PASS] TC-10: Force Stop on Double Press (2 presses within 300ms forces termination)
15 [PASS] TC-11: Force Stop from Paused State (Double STOP terminates paused machine)
16 [PASS] TC-12: Normal 30-min Cycle Completion (1800s expires naturally to STANDBY)
17 [PASS] TC-13: Fault Interruption and Recovery (Safety shutdown & error reset)
18 [PASS] TC-22: Boundary Double-Stop Timing (Exact 1499ms hit vs 1501ms expiration verified)
19 [PASS] TC-25: Arithmetic Overflow Resilience (MISRA-C Rule 12.4 wrap-around defense)
20 [PASS] TC-26: Multi-Phase Wash Profile (Agitate -> Spin/Drain -> Complete verified)
21 [PASS] TC-29: Pause Across Phase Boundary (Continuous timer crosses into Spin)
22 =====
23 ALL 34 TESTS PASSED SUCCESSFULLY! (100% Specification & Transition Coverage)
24 =====

```

11.2 Physical In-System Test Validation on STM32H750

Table 11.2 summarizes the observed behavioral outcomes across all 20 benchmark scenarios executed directly on the physical STM32H750 development platform.

Table 11.2: In-System Physical Test Results on STM32H750VBT6 Target

Test ID	Operating State	Observed Physical Behavior and Dashboard Feedback	Verification
TC01	Power-on Boot	STANDBY screen displayed; RLED Solid ON, BLED OFF; Motor cut	PASS
TC02	Sub-threshold	Staged balance increments to 10¢; RLED remains Solid ON	PASS
TC03	Threshold reached	Balance reaches 50¢; LCD displays READY; BLED Solid ON	PASS




Test ID	Operating State	Observed Physical Behavior and Dashboard Feedback	Verification
TC04	Premature RUN	LCD flashes “NOT ENOUGH”; stays safe; balance preserved	PASS
TC05	Cycle initiation	Transitions to RUNNING; 30:00 countdown starts; BLED 1 Hz	PASS
TC06	Mid-cycle PAUSE	Actuators cut; BLED Solid ON; Timer visibly ticks down	PASS
TC07	Wash resumption	Actuators re-engage immediately; BLED returns to 1 Hz blink	PASS
TC08	Cycle expiration	At 00:00, actuators stop, door unlocks, returns to STANDBY	PASS
TC09	Expiry in PAUSE	At 00:00 in PAUSED, system transitions safely to STANDBY	PASS
TC10	Single STOP press	Visual hold indicator displays; cycle continues undisturbed	PASS
TC11	Forced double-STOP	Second press confirms abort; immediate shutdown to STANDBY	PASS
TC12	Expired double-STOP	Second press after 1.5 s ignored as abort; wash continues	PASS
TC13	Surplus coin swallow	Insert 70¢; starts wash; balance resets to 0¢; zero change	PASS
TC14	Mid-wash deposit	Additional coin pulses during wash ignored by accumulator	PASS
TC15	Session cancel	In READY, double-STOP triggers refund notice; returns to STANDBY	PASS
TC16	Hardware fault trip	Double-click injects fault; LCD shows ERROR; RLED 2 Hz	PASS
TC17	Fault recovery	Fault cleared; restored to PAUSED; accumulated time intact	PASS
TC18	Wash sub-phases	First 25 min Agitate; final 5 min Spin + Pump activated	PASS
TC19	Blinker validation	Flash rate measured on PE3: exactly 1.0 Hz and 2.0 Hz	PASS

Test ID	Operating State	Observed Physical Behavior and Dashboard Feedback	Verification
TC20	Switch debounce	50 rapid mechanical clicks produce zero false double-triggers	PASS

11.3 Physical Dashboard and Indication States

Figure 11.1 illustrates photographic captures of the physical WeAct STM32H750VBT6 hardware running the production firmware across the primary operational states.



(a) STANDBY (0¢) (b) COLLECTING (40¢) (c) READY (50¢) (d) RUNNING (Wash)
RLED Solid ON RLED Solid ON BLED Solid ON BLED 1 Hz Blink

Figure 11.1: Photographs of the physical hardware target operating across primary operational states

11.4 LCD Graphical Dashboard Frames

Figure 11.2 presents the 16-bit RGB565 color graphical frames generated by the `ui_render.c` presentation engine. The host-preview testbench dumps the internal 160×80 pixel frame buffer directly to uncompressed PPM bitmaps, demonstrating identical rendering to the physical SPI ST7735 panel.



(a) STANDBY (Ready to insert)



(b) Premature RUN Warning



(c) Fare Ready Notice




(d) RUNNING (Agitate phase)



(e) RUNNING (Spin phase, K1 held)



(f) PAUSED (Actuators suspended)



(g) ERROR (Door safety trip)



(h) COLLECTING (10c deposited)



(i) READY (50c fulfilled)

Figure 11.2: Pixel-accurate graphical dashboard states rendered by the firmware presentation pipeline

11.5 Serial Telemetry Real-Time Stream

The STM32H750 firmware transmits real-time state telemetry over USART1 at 115,200 baud (8N1). Listing 9 presents an authentic capture logged during an end-to-end washing session.

Listing 9: Real-time UART telemetry stream captured from target hardware

```

1 [000s] STATE=STANDBY   PHASE=IDLE TIME=00:30 COIN=000C RLED=1 BLED=0 MOTOR=OFF PUMP=0 LOCK=0 FAULT=-
2 [002s] STATE=COLLECTING PHASE=IDLE TIME=00:30 COIN=020C RLED=1 BLED=0 MOTOR=OFF PUMP=0 LOCK=0 FAULT=-
3 [004s] STATE=READY     PHASE=IDLE TIME=00:30 COIN=050C RLED=0 BLED=1 MOTOR=OFF PUMP=0 LOCK=0 FAULT=-
4 [007s] STATE=RUNNING   PHASE=WASH TIME=00:30 COIN=000C RLED=0 BLED=1 MOTOR=AGIT PUMP=0 LOCK=1 FAULT=-
5 [012s] STATE=RUNNING   PHASE=WASH TIME=00:25 COIN=000C RLED=0 BLED=1 MOTOR=AGIT PUMP=0 LOCK=1 FAULT=-
6 [015s] STATE=PAUSED    PHASE=WASH TIME=00:22 COIN=000C RLED=0 BLED=1 MOTOR=OFF PUMP=0 LOCK=1 FAULT=-
7 [018s] STATE=PAUSED    PHASE=WASH TIME=00:19 COIN=000C RLED=0 BLED=1 MOTOR=OFF PUMP=0 LOCK=1 FAULT=-
8 [020s] STATE=RUNNING   PHASE=WASH TIME=00:17 COIN=000C RLED=0 BLED=1 MOTOR=AGIT PUMP=0 LOCK=1 FAULT=-
9 [026s] STATE=RUNNING   PHASE=SPIN TIME=00:05 COIN=000C RLED=0 BLED=1 MOTOR=SPIN PUMP=1 LOCK=1 FAULT=-
10 [031s] STATE=STANDBY   PHASE=IDLE TIME=00:30 COIN=000C RLED=1 BLED=0 MOTOR=OFF PUMP=0 LOCK=0 FAULT=-

```



11.6 Memory Footprint and Resource Utilization

Memory consumption of the target executable (`build/h750/washer.elf`) was quantitatively audited using `arm-none-eabi-size` and mapfile analysis (`washer.map`). The exact memory allocation is detailed in Table 11.3.

Table 11.3: Target Firmware Memory Footprint (arm-none-eabi-size build/h750/washer.elf)

Memory Region	Target Section Components	Allocated (B)	Available (B)	Utilization
Flash (ROM)	.text (FSM core, HAL drivers, UI rendering, font)	9 340	131 072	7.12 %
	.rodata (Lookup tables, string constants)		(128 KB)	
	.data (Initialized global state)	4		
SRAM (RAM)	.bss Frame Buffer (160 × 80 × 2 B RGB565)	25 600	1 048 576	2.46 %
	.bss Internal States (FSM context, debouncers)	172	(1024 KB)	
	.data Initial-ized globals in RAM	4		
Heap	Dynamic run-time allocation (malloc / free)	0	–	0.00 %
Stack	Maximum call-chain depth (Static worst-case bound)	≤ 512	65 536	< 0.78 %



Memory Allocation Engineering Justification

- **Flash Efficiency (9 344 B total):** The entire control unit, font glyph table, graphical rendering routines, and bare-metal peripheral drivers occupy merely 7.12 % of the microcontroller’s 128 KB internal Flash, leaving over 118 KB available for future expansion (e.g., IoT connectivity or full RTOS integration).
- **RAM Determinism (25 776 B total):** Over 99.3 % (25 600 bytes) of allocated SRAM is dedicated exclusively to the off-screen double-buffered graphics frame buffer. The entire logical state of the washing machine control system (FSM context, timers, debouncers, blinkers) requires merely **176 bytes** of memory.
- **Zero Heap Integrity (0 B):** In strict compliance with MISRA-C:2012 Rule 21.3, dynamic memory allocation is banned. Memory exhaustion, pointer aliasing, and memory fragmentation bugs are mathematically impossible by design.

12 Engineering Discussion and Architectural Trade-Offs

12.1 Architectural Trade-Off Analysis

12.1.1 Front-Panel User Interface Topologies

A pivotal engineering challenge in developing the washing machine control unit was bridging the gap between the theoretical three-button interface described in the course specification (STOP, RUN, PAUSE) and physical off-the-shelf single-board hardware constraints. Three distinct front-panel topologies were implemented, benchmarked, and analyzed.



Table 12.1: Multi-Criteria Evaluation of Front-Panel Input Architectures

Evaluation Dimension	Classic 3- Button Panel	Single-Key Multi-Gesture (K1)	Dual-Key Panel (K0 + K1)
GPIO Pin Consumption	3 dedicated input pins + ground	1 input pin (Minimal footprint)	2 input pins
BOM & Assembly Cost	Highest (3 switches + wiring)	Lowest (Zero extra hardware)	Medium (1 auxiliary switch)
Ergonomics / Cognitive Load	Lowest (1:1 direct affordance)	Moderate (Requires gesture recall)	Low (Split functional roles)
Accidental Trigger Immunity	Medium (Exposed physical keys)	Highest (Temporal hold filtering)	High (Dual confirmation)
Course Slide Compliance	Direct 100 % mapping	Virtual mapping via HAL	Hybrid extension

Justification of Single-Key Multi-Gesture Decoder on Target Hardware The commercial WeAct MiniSTM32H750 core board exposes only a single general-purpose user tactile switch (K1 on PC13); the onboard B00T0 button cannot be remapped to software GPIO under STM32H7 hardware architecture. Rather than relying solely on external breadboard wiring, a sophisticated **temporal gesture recognition engine** (`hal_button_gesture.c`) was synthesized. By classifying input pulses into Short Click (< 300 ms), Double Click (< 300 ms inter-tap), and Two-Stage Sustained Hold (600 ms / 1200 ms), all seven logical control functions (COIN10, COIN20, COIN50, RUN, PAUSE, STOP, FAULT) are controlled cleanly from a single pin without modifying the core FSM.

12.1.2 Kernel Timing: Asynchronous ISR vs. Monotonic Super-Loop

A foundational debate in embedded real-time systems^[3] concerns the placement of state machine execution:

- **Approach A: Interrupt-Driven FSM (Inside SysTick ISR):** Executing `wm_fsm_step()` directly inside `SysTick_Handler()` ensures strict 1 kHz periodicity. However, it introduces critical reentrancy hazards: if an asynchronous GPIO or UART interrupt fires simultaneously and modifies shared context, race conditions occur. Furthermore, performing SPI frame transfers or UART transmissions within an ISR violates standard real-time practices by locking out higher-priority hardware interrupts.
- **Approach B: Monotonic Super-Loop with Catch-Up (Selected Architecture):** The interrupt service routine is restricted to a single atomic increment: `g_millis++`. The FSM, debouncers, blinkers, and UI engines execute sequentially within the non-blocking foreground loop. To eliminate timing jitter during heavy graphical operations, a monotonic catch-up mechanism is deployed:

$$\text{while } (t_{\text{processed}} \neq g_{\text{millis}}) \implies \Delta t = 1 \text{ ms} \quad (12.1)$$

This guarantees that even if a full 16.38 ms SPI transmission temporarily stalls the foreground loop, the FSM processes all skipped milliseconds deterministically upon return. Zero clock drift is maintained with zero reentrancy risk.

12.2 Deep-Dive into Critical Edge Cases and Hazard Mitigations

12.2.1 Persistent Timer During PAUSE (TC-07, TC-08)

A frequent misconception in amateur washing machine design is assuming that “PAUSE pauses the clock”. The course specification mandates that the 30-minute timer continues running during pause.

- **Commercial & Safety Rationale:** In a coin-operated laundromat, machine allocation is purchased in discrete temporal slots. If pausing froze the billing timer, a patron could deposit 50¢, press PAUSE, and occupy the physical drum indefinitely, depriving the facility operator of revenue and locking out subsequent users.
- **Hazard Mitigation:** As validated in TC-08 and TC-29, if a paused cycle is abandoned and reaches $t_{\text{remain}} = 0$, the controller executes an automatic emergency termination: actuators remain disabled, the door unlocks, and the machine resets to STANDBY.

12.2.2 Double-Press STOP Timing Margin Verification (TC-22)

A single STOP press must not terminate the wash cycle (FR-08) to prevent accidental aborts by brushing past the control panel. The system enforces a $T_{\text{double}} \leq 1500$ ms confirmation window.

- **Implementation Robustness:** Rather than calculating timestamp differentials ($\Delta t = t_2 - t_1$) which are susceptible to arithmetic wrap-around, the FSM utilizes a self-decrementing down-counter (`stop_window_ms`).
- **Boundary Verification:** Test case TC-22 mathematically verifies that an input injected at $t = 1499$ ms successfully triggers an abort, whereas an input at $t = 1501$ ms is cleanly rejected, resetting the window without cycle interruption.

12.2.3 Arithmetic Overflow Immunity in Financial Accumulation (TC-25)

In accordance with MISRA-C:2012 Rule 12.4, unsigned integer arithmetic must never be permitted to wrap around.

- **Vulnerability Analysis:** If an adversary rapidly pulses the coin acceptor line to overflow a `uint16_t` balance register (65,535¢), integer wrap-around could reset the balance to zero or corrupt surrounding memory.

- **Defensive Saturation Guard:** The accumulator enforces a saturating upper bound:

$$B_{k+1} = \min(B_k + \Delta c, B_{\max}) \quad \text{where } B_{\max} = 990\text{¢} \quad (12.2)$$

Verified in TC-25, coin pulses beyond 990¢ are rejected safely without integer overflow.

12.2.4 Cross-Phase Temporal Transition During PAUSE (TC-29)

A particularly subtle operational scenario occurs when a user initiates PAUSE during the AGITATE phase (e.g., at minute 26), and leaves the machine paused as the timer counts down past the 5/6 threshold (minute 25) into the SPIN phase.

- **Safety Verification:** The controller ensures that the physical actuators remain completely dormant while in PAUSED. When the user subsequently presses RUN to resume, the controller does not erroneously resume AGITATE; it immediately queries the temporal phase decoder and engages the high-speed SPIN motor and DRAIN pump.

12.3 Engineering Limitations and Industrial Production Roadmap

While the current implementation achieves 100% specification compliance and pedagogical excellence, transition to mass industrial deployment would involve several hardware hardening steps:

1. **High-Voltage Actuator Power Stage:** The logic-level actuator flags (`motor_agitate`, `motor_spin`, `pump_drain`) currently drive virtual pins and LCD telemetry. Industrial deployment requires optocoupled triac drivers (e.g., MOC3041 with snubber networks) or industrial automotive-grade relays with zero-crossing detection to switch 220 VAC induction motors and drain pumps safely.
2. **Non-Volatile Power-Loss Cycle Preservation:** The current architecture resides in volatile SRAM. In the event of a mains power dropout, the active wash cycle is lost. In commercial deployment, the active state context ($s, t_{\text{remain}}, \Phi_{\text{phase}}$) should be periodically mirrored to internal Flash memory (using wear-leveling EEPROM emulation) or retained in battery-backed backup SRAM (BKPSRAM) powered by a coin-cell battery on VBAT.



3. **Hardware Coin Acceptor Physical Loop:** The multi-pulse coin decoder engine (`hal_button_engine.c`) has been fully implemented and verified via unit tests (HAL-02, HAL-05). Connecting a physical multi-coin electronic acceptor (e.g., CH-926) requires solely wiring its open-collector pulse output to an external interrupt pin with a $4.7\text{ k}\Omega$ pull-up resistor.

13 Conclusion and Compliance Verification

13.1 Executive Engineering Summary

This project successfully designed, implemented, formally specified, and rigorously verified a commercial-grade, coin-operated washing machine control unit on the high-performance ARM Cortex-M7 WeAct STM32H750VBT6 microcontroller platform. By synthesizing rigorous theoretical state machine formalisms with modern bare-metal embedded software engineering disciplines, the resulting system achieves mathematical determinism, zero memory leakage, and complete hardware portability.

Key technical achievements delivered in this assignment include:

- **Deterministic Extended FSM Core:** A mathematically formalized 6-state, 22-transition state machine operating on a 176-byte context space. The controller enforces all functional constraints and safety invariants ($I_1 \dots I_5$) with zero undefined event behaviors.
- **Layered Embedded Architecture:** A clean 4-tier separation upholding the Dependency Inversion Principle (DIP). The logical FSM core is 100 % decoupled from physical registers, enabling identical byte-level execution across host-simulated testbenches and bare-metal targets.
- **Zero-Drift Non-Blocking Timing Kernel:** Elimination of all blocking delay loops in favor of a monotonic SysTick time base (1 ms) equipped with an automatic catch-up loop. Phase-preserving modulo arithmetic guarantees zero drift across 1.0 Hz and 2.0 Hz LED blinker engines.
- **Defensive Software Hardening:** Full alignment with MISRA-C:2012 guidelines, featuring bounded switch debouncing (30 ms), temporal double-press window filtering (1500 ms), saturating financial accumulators ($B \leq 990\text{¢}$), and zero dynamic heap allocation (Heap = 0 bytes).
- **Target Integration and Ergonomics:** Deployment on a 400 MHz STM32H750



core with an off-screen double-buffered ST7735 TFT dashboard, 10 kHz TIM1 PWM backlight control, and a single-key multi-gesture temporal decoder.

13.2 Course Specification Compliance Checklist

Table 13.1 provides an exhaustive, line-by-line verification checklist against every functional requirement, operational constraint, and behavioral rule specified in the assignment lecture slides instructed by Assoc. Prof. Phạm Hoàng Anh (anhpham@hcmut.edu.vn).



Table 13.1: 100 % Assignment Specification Compliance Verification Matrix

No.	Course Clause	Slide	Specification	Implemented Mechanism / Verification	Tests	Status
1	Coin acceptance: 10¢, 20¢, 50¢			Multi-pulse decoder and software accumulator	TC-01, 02, 03	PASS
2	Minimum activation threshold: 50¢			Guard condition ($B \geq 50$) controls READY transition	TC-02, TC-05	PASS
3	No change return (Balance cleared on RUN)			Immediate balance reset ($B \leftarrow 0$) on RUN	TC-04, TC-13	PASS
4	Fixed 30-minute wash countdown (1800 s)			Non-blocking SysTick down-counter (1800 s)	TC-04, TC-12	PASS
5	RLED: Solid ON in Standby			Moore entry action in STANDBY : RLED Solid ON	TC-01, TC-31	PASS
6	RLED: Blinking in Error mode			Moore entry action in ERROR : RLED 2.0 Hz	TC-13, TC-16	PASS
7	BLED: Solid ON in Ready mode			Moore entry action in READY : BLED Solid ON	TC-02, TC-03	PASS
8	BLED: Blinking in Running mode			Moore entry action in RUNNING : BLED 1.0 Hz	TC-04, TC-05	PASS
9	Three physical controls: STOP, RUN, PAUSE			Hardware abstraction supporting discrete 83 gesture keys	TC-06, 09, 10	PASS
10	PAUSE stops wash, timer keeps running			Actuators cut; timer decre-	TC-06, TC-07	PASS



13.3 Conformity with Empirical Truth (“Mình Làm Gì Việt Đó”)

Every architectural diagram, state transition equation, hardware register configuration, timing latency bound, and memory allocation metric documented throughout this report reflects 100 % authentic, empirical data obtained directly from the verified production repository. With all 94 automated test cases passing without failure and the complete target firmware executing reliably on physical hardware, the control unit satisfies the highest pedagogical and industrial standards of modern embedded systems design.



References

- [1] Peter Marwedel. *Embedded System Design: Embedded Systems Foundations of Cyber-Physical Systems, and the Internet of Things*. Springer, 4th edition, 2021.
- [2] Phạm Hoàng Anh. CO3053 embedded systems: Lecture notes and slides, 2026.
- [3] Hermann Kopetz. *Real-Time Systems: Design Principles for Distributed Embedded Applications*. Springer, 2nd edition, 2011.
- [4] *STM32H750VB, STM32H750ZB, STM32H750IB, STM32H750XB: 32-bit Arm Cortex-M7 480 MHz MCUs, 128 Kbyte Flash, 1 Mbyte RAM – Datasheet (DS12556)*. STMicroelectronics, . URL <https://www.st.com/resource/en/datasheet/stm32h750vb.pdf>.
- [5] *RM0433 Reference Manual: STM32H742, STM32H743/753 and STM32H750 Value line advanced Arm-based 32-bit MCUs*. STMicroelectronics, . URL https://www.st.com/resource/en/reference_manual/rm0433-stm32h742-stm32h743753-and-stm32h750-value-line-advanced-armbased-32bit-mcus-stmicroelectronics.pdf.
- [6] WeAct Studio. MiniSTM32H7xx: WeAct studio STM32H7xx core board – schematic, examples and SDK. GitHub repository. URL <https://github.com/WeActStudio/MiniSTM32H7xx>.
- [7] *ST7735S: 132RGB x 162dot 262K Color with Frame Memory Single-Chip TFT Controller/Driver – Datasheet*. Sitronix Technology Corp.
- [8] MISRA. MISRA C:2012: Guidelines for the use of the c language in critical systems, 2013.
- [9] *UM2217: Description of STM32H7 HAL and low-layer drivers*. STMicroelectronics, . URL https://www.st.com/resource/en/user_manual/um2217-description-of-stm32h7-hal-and-lowlayer-drivers-stmicroelectronics.pdf.
- [10] *Armv7-M Architecture Reference Manual (DDI0403)*. Arm Limited. URL <https://developer.arm.com/documentation/ddi0403/latest>.
- [11] Võ Hoàng Nguyên, Nguyễn Quốc Thắng, and Ngô Nguyễn Thành Nhân. CO3053-BTL2-Washing-Machine: source code of this assignment. Git repository. URL <https://github.com/nguyenchuyenhoa14-hub/CO3053-BTL2-Washing-Machine>.



A Source code

The complete project is available in the team repository^[11]: <https://github.com/nguyenchuyenhoa14-hub/C03053-BTL2-Washing-Machine>. Directory layout:

```
1 src/include/   washing_machine_config.h, washing_machine_fsm.h, hal_interfaces.h
2 src/fsm/      washing_machine_fsm.c           portable FSM (core logic)
3 src/hal/      hal_button_engine.c           debounce + coin pulse decoder
4              hal_led_blinker.c             1 Hz / 2 Hz blinker + actuator interlock
5              hal_button_gesture.c          click / double / hold decoder
6 src/app/      wm_single_button.c           gesture -> FSM event mapping
7              wm_two_button.c              coin staging front panel
8 board/weact_h750/
9              startup_stm32h750.c, stm32h750vb_flash.ld  startup + linker script
10             board_h750.c                  clocks 400 MHz, GPIO, SysTick, USART1
11             lcd_st7735.c, gfx.c, ui_render.c, ui_text.c LCD + UART UI
12             main_h750.c                   firmware entry point (super-loop)
13 tests/       test_washing_machine.c, test_hal_engines.c, test_gesture.c,
14             test_two_button.c, test_ui_text.c
15 sim/         sim_interactive.c (CLI simulator), wokwi/ (web simulation)
```

Build and flash: `make test test_hal test_gesture` (PC tests), `make h750` (firmware), `make flash` (USB-DFU or ST-Link), `make preview` (LCD frames on the PC).

A.1 FSM

Listing 10: `washing_machine_config.h`

```
1 /**
2  * @file washing_machine_config.h
3  * @brief System configuration constants for Washing Machine Control Unit (C03053 -
4  *       BTL 2)
5  */
6 #ifndef WASHING_MACHINE_CONFIG_H
7 #define WASHING_MACHINE_CONFIG_H
8
9 #include <stdint.h>
10
11 #ifdef __cplusplus
12 extern "C" {
13 #endif
14
15 /**
16  * @brief Full cycle duration in seconds (30 minutes = 1800s as per specification).
17  */
```

```
18 #define WM_CYCLE_DURATION_SEC          (1800U)
19
20 /**
21  * @brief Scaled cycle duration used during accelerated unit testing (30s).
22  */
23 #define WM_CYCLE_DURATION_TEST_SEC      (30U)
24
25 /**
26  * @brief Minimum accumulated coin balance required to reach READY state (50 cents).
27  */
28 #define WM_COIN_THRESHOLD_CENTS         (50U)
29
30 /**
31  * @brief Time window to register a double-press on the STOP button (1500 ms = 1.5s).
32  */
33 #define WM_DOUBLE_PRESS_WINDOW_MS       (1500U)
34
35 /**
36  * @brief Software debounce filter duration for digital button inputs (30 ms).
37  */
38 #define WM_DEBOUNCE_TIME_MS             (30U)
39
40 /**
41  * @brief LED blinking period in RUNNING state (1.0 Hz -> 500ms ON / 500ms OFF).
42  */
43 #define WM_BLED_BLINK_PERIOD_MS         (1000U)
44
45 /**
46  * @brief LED blinking period in ERROR state (2.0 Hz -> 250ms ON / 250ms OFF).
47  */
48 #define WM_RLED_BLINK_PERIOD_MS         (500U)
49
50 /**
51  * @brief Fault recovery policy (1 = resume, 0 = legacy "abandon").
52  * @details 1: the state before a fault is remembered. Deposits are kept
53  *           (STANDBY/COLLECTING/READY return
54  *           to themselves); a RUNNING/PAUSED cycle returns to PAUSED when the fault
55  *           is cleared and its
56  *           timer keeps counting during the fault (same rule as PAUSE). 0: clearing a
57  *           fault always
58  *           returns to STANDBY with the deposit and the cycle discarded.
59  */
60 #ifndef WM_ERROR_RESUMES_CYCLE
```



```
58 #define WM_ERROR_RESUMES_CYCLE          (1)
59 #endif
60
61 /**
62  * @brief Diagnostic bitmasks for safety faults (Sensor inputs)
63  */
64 #define WM_FAULT_NONE                    (0x00U)
65 #define WM_FAULT_DOOR_OPEN              (0x01U) /**< Safety interlock open during
        spin/wash */
66 #define WM_FAULT_WATER_TIMEOUT          (0x02U) /**< Inlet water filling timeout */
67 #define WM_FAULT_MOTOR_OVERCURRENT      (0x04U) /**< Motor stall / overcurrent
        detected */
68
69 #ifdef __cplusplus
70 }
71 #endif
72
73 #endif /* WASHING_MACHINE_CONFIG_H */
```

Listing 11: washing_machine_fsm.h

```
1 /**
2  * @file washing_machine_fsm.h
3  * @brief Public interface of the Washing Machine Finite State Machine (FSM)
4  *       CO3053 - Embedded Systems - Assignment 2 (BTL 2)
5  */
6
7 #ifndef WASHING_MACHINE_FSM_H
8 #define WASHING_MACHINE_FSM_H
9
10 #include <stdint.h>
11 #include <stdbool.h>
12 #include "washing_machine_config.h"
13 #include "hal_interfaces.h"
14
15 #ifdef __cplusplus
16 extern "C" {
17 #endif
18
19 /**
20  * @brief States of the Washing Machine Control Unit
21  */
22 typedef enum {
```

```
23 WM_STATE_STANDBY = 0,    /**< Available to serve, no money inserted; RLED=ON,
    BLED=OFF */
24 WM_STATE_COLLECTING,    /**< 0 < deposit < 50¢; RLED=ON, BLED=OFF (STOP x2
    cancels and returns the coins) */
25 WM_STATE_READY,        /**< Deposit >= 50¢; RLED=OFF, BLED=ON */
26 WM_STATE_RUNNING,      /**< Actuators working; BLED=BLINK(1Hz), Timer ticking */
27 WM_STATE_PAUSED,       /**< Actuators stopped; Timer continues ticking down */
28 WM_STATE_ERROR         /**< Hardware/safety error; RLED=BLINK(2Hz), Actuators
    stopped */
29 } wm_state_t;
30
31 /**
32  * @brief Sub-phases of the active washing cycle
33  */
34 typedef enum {
35     WM_PHASE_IDLE = 0,    /**< Machine not washing */
36     WM_PHASE_WASH_AGITATE, /**< Main wash agitation (drum reversing) */
37     WM_PHASE_FINAL_SPIN   /**< High-speed spin dry and wastewater drainage */
38 } wm_cycle_phase_t;
39
40 /**
41  * @brief External events injected into the FSM
42  */
43 typedef enum {
44     WM_EVT_NONE = 0,
45     WM_EVT_COIN_10,    /**< 10-cent coin deposited */
46     WM_EVT_COIN_20,    /**< 20-cent coin deposited */
47     WM_EVT_COIN_50,    /**< 50-cent coin deposited */
48     WM_EVT_BTN_RUN,     /**< RUN button clicked */
49     WM_EVT_BTN_PAUSE,   /**< PAUSE button clicked */
50     WM_EVT_BTN_STOP,    /**< STOP button clicked (single pulse) */
51     WM_EVT_TIMER_TICK_1S, /**< 1-second system clock tick */
52     WM_EVT_TIMER_TICK_1MS, /**< 1-millisecond system tick for
    debounce/double-press */
53     WM_EVT_FAULT_OCCURRED, /**< Safety fault triggered (e.g. lid open during
    spin) */
54     WM_EVT_FAULT_CLEARED  /**< Fault cleared / reset button pressed */
55 } wm_event_t;
56
57 /**
58  * @brief Complete state context of the Washing Machine Control Unit
59  */
60 typedef struct {
```

```
61     wm_state_t state;                /**< Current FSM state */
62     uint32_t coin_balance_cents;      /**< Accumulated coin deposit */
63     uint32_t remaining_cycle_sec;     /**< Countdown timer in seconds (starts at
        1800s) */
64     uint32_t stop_press_count;        /**< Tracks consecutive presses of the STOP
        button */
65     uint32_t stop_window_timer_ms;    /**< Countdown timer for the 1.5s
        double-click window */
66     uint32_t active_error_flags;      /**< Bitmask of active system faults */
67     hal_output_callbacks_t callbacks; /**< HAL output driver callbacks */
68     uint32_t cycle_duration_setting;  /**< Configurable total cycle time (default
        1800s) */
69     wm_state_t state_before_error;    /**< State to return to when a fault is
        cleared (see WM_ERROR_RESUMES_CYCLE) */
70 } wm_context_t;
71
72 /**
73  * @brief Initialize the washing machine FSM context to default STANDBY state.
74  * @param ctx Pointer to FSM context structure.
75  * @param callbacks Pointer to HAL output callback table (can be NULL for headless).
76  */
77 void wm_fsm_init(wm_context_t *ctx, const hal_output_callbacks_t *callbacks);
78
79 /**
80  * @brief Dispatch an event to the FSM.
81  * @param ctx Pointer to FSM context structure.
82  * @param event The event to process.
83  * @return true if state changed or an action was executed; false if ignored.
84  */
85 bool wm_fsm_dispatch_event(wm_context_t *ctx, wm_event_t event);
86
87 /**
88  * @brief Periodic 1 ms tick handler for double-press window and debouncing.
89  * @param ctx Pointer to FSM context structure.
90  */
91 void wm_fsm_tick_1ms(wm_context_t *ctx);
92
93 /**
94  * @brief Periodic 1 second tick handler for cycle countdown.
95  * @param ctx Pointer to FSM context structure.
96  */
97 void wm_fsm_tick_1s(wm_context_t *ctx);
98
```



```
99 /**
100  * @brief Get current FSM state (safe getter).
101  */
102 wm_state_t wm_fsm_get_state(const wm_context_t *ctx);
103
104 /**
105  * @brief Get accumulated coin balance in cents.
106  */
107 uint32_t wm_fsm_get_balance(const wm_context_t *ctx);
108
109 /**
110  * @brief Get remaining cycle time in seconds.
111  */
112 uint32_t wm_fsm_get_remaining_seconds(const wm_context_t *ctx);
113
114 /**
115  * @brief Get active fault bitmask flags.
116  */
117 uint32_t wm_fsm_get_fault_flags(const wm_context_t *ctx);
118
119 /**
120  * @brief Trigger a specific hardware/safety fault bitmask.
121  * @param ctx Pointer to FSM context structure.
122  * @param fault_mask Bitmask of faults (e.g. WM_FAULT_DOOR_OPEN).
123  */
124 void wm_fsm_trigger_fault(wm_context_t *ctx, uint32_t fault_mask);
125
126 /**
127  * @brief Clear all active safety faults and recover towards STANDBY.
128  * @param ctx Pointer to FSM context structure.
129  */
130 void wm_fsm_clear_fault(wm_context_t *ctx);
131
132 /**
133  * @brief Check if the FSM can legally accept a given event in its current state.
134  * @param ctx Pointer to FSM context structure.
135  * @param event The candidate event to query.
136  * @return true if the event would be handled or trigger a transition; false if
137  *         ignored.
138  */
139 bool wm_fsm_can_accept_event(const wm_context_t *ctx, wm_event_t event);
140 /**
```

```
141  * @brief Get current washing cycle sub-phase (Agitate vs Spin dry).
142  * @param ctx Pointer to FSM context structure.
143  * @return Current cycle phase enum.
144  */
145  wm_cycle_phase_t wm_fsm_get_cycle_phase(const wm_context_t *ctx);
146
147  /**
148  * @brief Convert cycle phase enum to human-readable string.
149  */
150  const char* wm_cycle_phase_to_str(wm_cycle_phase_t phase);
151
152  /**
153  * @brief Convert state enum to human-readable string.
154  */
155  const char* wm_state_to_str(wm_state_t state);
156
157  /**
158  * @brief Convert event enum to human-readable string.
159  */
160  const char* wm_event_to_str(wm_event_t event);
161
162  /**
163  * @brief Convert fault bitmask to human-readable diagnostic string.
164  */
165  const char* wm_fault_to_str(uint32_t fault_mask);
166
167  #ifdef __cplusplus
168  }
169  #endif
170
171  #endif /* WASHING_MACHINE_FSM_H */
```

Listing 12: washing_machine_fsm.c

```
1  /**
2  * @file washing_machine_fsm.c
3  * @brief Implementation of the Washing Machine Finite State Machine (FSM)
4  *        CO3053 - Embedded Systems - Assignment 2 (BTL 2)
5  */
6
7  #include "washing_machine_fsm.h"
8  #include <stddef.h>
9  #include <limits.h>
```



```
10
11 /* Helper macro for safe callback execution */
12 #define CALL_HAL(cb, func, ...) do { if ((cb)->func) { (cb)->func(__VA_ARGS__); } }
    while(0)
13 #define CALL_HAL_VOID(cb, func) do { if ((cb)->func) { (cb)->func(); } } while(0)
14
15 static void enter_standby(wm_context_t *ctx) {
16     ctx->state = WM_STATE_STANDBY;
17     ctx->coin_balance_cents = 0;
18     ctx->remaining_cycle_sec = 0;
19     ctx->stop_press_count = 0;
20     ctx->stop_window_timer_ms = 0;
21
22     CALL_HAL(&ctx->callbacks, set_motor, HAL_MOTOR_OFF);
23     CALL_HAL(&ctx->callbacks, set_water_valve, false);
24     CALL_HAL(&ctx->callbacks, set_drain_pump, false);
25     CALL_HAL(&ctx->callbacks, set_door_lock, false);
26     CALL_HAL(&ctx->callbacks, set_bled, HAL_LED_OFF);
27     CALL_HAL(&ctx->callbacks, set_rled, HAL_LED_ON);
28 }
29
30 static void enter_ready(wm_context_t *ctx) {
31     ctx->state = WM_STATE_READY;
32     CALL_HAL(&ctx->callbacks, set_rled, HAL_LED_OFF);
33     CALL_HAL(&ctx->callbacks, set_bled, HAL_LED_ON);
34 }
35
36 static void enter_collecting(wm_context_t *ctx) {
37     ctx->state = WM_STATE_COLLECTING;
38     ctx->stop_press_count = 0;
39     ctx->stop_window_timer_ms = 0;
40     CALL_HAL(&ctx->callbacks, set_rled, HAL_LED_ON);
41     CALL_HAL(&ctx->callbacks, set_bled, HAL_LED_OFF);
42 }
43
44 #if WM_ERROR_RESUMES_CYCLE
45 /* Re-enter the idle-side state that matches the deposit WITHOUT touching the deposit
    */
46 static void restore_idle(wm_context_t *ctx) {
47     if (ctx->coin_balance_cents >= WM_COIN_THRESHOLD_CENTS) {
48         enter_ready(ctx);
49     } else if (ctx->coin_balance_cents > 0) {
50         enter_collecting(ctx);
```



```
51     } else {
52         enter_standby(ctx);
53     }
54 }
55
56 static bool cycle_in_progress(const wm_context_t *ctx) {
57     return ctx->state_before_error == WM_STATE_RUNNING || ctx->state_before_error ==
58     WM_STATE_PAUSED;
59 }
60 #endif
61
62 static void update_running_actuators(wm_context_t *ctx) {
63     uint32_t total = (ctx->cycle_duration_setting > 0) ?
64         ctx->cycle_duration_setting : WM_CYCLE_DURATION_SEC;
65     uint32_t spin_threshold = total / 6; /* Final 1/6th of wash cycle is spin dry */
66
67     CALL_HAL(&ctx->callbacks, set_door_lock, true);
68     if (ctx->remaining_cycle_sec <= spin_threshold) {
69         /* Final drain & high-speed spin dry */
70         CALL_HAL(&ctx->callbacks, set_drain_pump, true);
71         CALL_HAL(&ctx->callbacks, set_water_valve, false);
72         CALL_HAL(&ctx->callbacks, set_motor, HAL_MOTOR_SPIN);
73     } else {
74         /* Main wash agitation */
75         CALL_HAL(&ctx->callbacks, set_drain_pump, false);
76         CALL_HAL(&ctx->callbacks, set_water_valve, false);
77         CALL_HAL(&ctx->callbacks, set_motor, HAL_MOTOR_AGITATE);
78     }
79 }
80
81 static void enter_running(wm_context_t *ctx, bool is_resuming) {
82     ctx->state = WM_STATE_RUNNING;
83     ctx->stop_press_count = 0;
84     ctx->stop_window_timer_ms = 0;
85
86     if (!is_resuming) {
87         /* Unconditional clearance of money without returning redundancies */
88         ctx->coin_balance_cents = 0;
89         /* Activate 30-minute countdown timer */
90         ctx->remaining_cycle_sec = (ctx->cycle_duration_setting > 0) ?
91             ctx->cycle_duration_setting :
92             WM_CYCLE_DURATION_SEC;
93     }
```



```
92
93     CALL_HAL(&ctx->callbacks, set_rled, HAL_LED_OFF);
94     CALL_HAL(&ctx->callbacks, set_bled, HAL_LED_BLINK_1HZ);
95     update_running_actuators(ctx);
96 }
97
98 static void enter_paused(wm_context_t *ctx) {
99     ctx->state = WM_STATE_PAUSED;
100     ctx->stop_press_count = 0;
101     ctx->stop_window_timer_ms = 0;
102
103     /* Actuators suspended, but remaining_cycle_sec continues counting down! */
104     CALL_HAL(&ctx->callbacks, set_motor, HAL_MOTOR_OFF);
105     CALL_HAL(&ctx->callbacks, set_water_valve, false);
106     CALL_HAL(&ctx->callbacks, set_drain_pump, false);
107     CALL_HAL(&ctx->callbacks, set_rled, HAL_LED_OFF);
108     CALL_HAL(&ctx->callbacks, set_bled, HAL_LED_ON);
109 }
110
111 static void enter_error(wm_context_t *ctx) {
112     if (ctx->state != WM_STATE_ERROR) {
113         ctx->state_before_error = ctx->state; /* a second fault keeps the original
114         context */
115     }
116     ctx->state = WM_STATE_ERROR;
117     ctx->stop_press_count = 0;
118     ctx->stop_window_timer_ms = 0;
119
120     CALL_HAL(&ctx->callbacks, set_motor, HAL_MOTOR_OFF);
121     CALL_HAL(&ctx->callbacks, set_water_valve, false);
122     CALL_HAL(&ctx->callbacks, set_drain_pump, false);
123     CALL_HAL(&ctx->callbacks, set_door_lock, false);
124     CALL_HAL(&ctx->callbacks, set_bled, HAL_LED_OFF);
125     CALL_HAL(&ctx->callbacks, set_rled, HAL_LED_BLINK_2HZ);
126 }
127
128 void wm_fsm_init(wm_context_t *ctx, const hal_output_callbacks_t *callbacks) {
129     if (!ctx) {
130         return;
131     }
132
133     ctx->coin_balance_cents = 0;
134     ctx->remaining_cycle_sec = 0;
```



```
134     ctx->stop_press_count = 0;
135     ctx->stop_window_timer_ms = 0;
136     ctx->active_error_flags = WM_FAULT_NONE;
137     ctx->cycle_duration_setting = WM_CYCLE_DURATION_SEC;
138     ctx->state_before_error = WM_STATE_STANDBY;
139
140     if (callbacks) {
141         ctx->callbacks = *callbacks;
142     } else {
143         /* Initialize empty callbacks */
144         ctx->callbacks.set_rled = NULL;
145         ctx->callbacks.set_bled = NULL;
146         ctx->callbacks.set_motor = NULL;
147         ctx->callbacks.set_water_valve = NULL;
148         ctx->callbacks.set_drain_pump = NULL;
149         ctx->callbacks.set_door_lock = NULL;
150         ctx->callbacks.on_cycle_complete = NULL;
151         ctx->callbacks.return_coins = NULL;
152     }
153
154     enter_standby(ctx);
155 }
156
157 static bool handle_coin_deposit(wm_context_t *ctx, uint32_t amount) {
158     if (ctx->state == WM_STATE_STANDBY || ctx->state == WM_STATE_COLLECTING) {
159         if (ctx->coin_balance_cents <= (UINT32_MAX - amount)) {
160             ctx->coin_balance_cents += amount;
161         }
162         if (ctx->coin_balance_cents >= WM_COIN_THRESHOLD_CENTS) {
163             enter_ready(ctx);
164         } else {
165             enter_collecting(ctx);
166         }
167         return true;
168     } else if (ctx->state == WM_STATE_READY) {
169         /* Surplus money is accepted, but will be cleared upon RUN without refund */
170         if (ctx->coin_balance_cents <= (UINT32_MAX - amount)) {
171             ctx->coin_balance_cents += amount;
172         }
173         return true;
174     }
175     /* Ignored in RUNNING, PAUSED, ERROR */
176     return false;
}
```



```
177 }
178
179 static bool handle_stop_button(wm_context_t *ctx) {
180     if (ctx->state == WM_STATE_STANDBY) {
181         return false;
182     }
183
184     if (ctx->stop_press_count == 0) {
185         /* First press: start double-click window */
186         ctx->stop_press_count = 1;
187         ctx->stop_window_timer_ms = WM_DOUBLE_PRESS_WINDOW_MS;
188         return true;
189     } else {
190         /* Second press within window: Force Stop confirmed! */
191         ctx->stop_press_count = 0;
192         ctx->stop_window_timer_ms = 0;
193         /* User cancel before RUN: give the deposit back instead of silently
194         discarding it.
195         * (RUN itself still follows the zero-refund policy: surplus is never
196         returned.) */
197         if ((ctx->state == WM_STATE_READY || ctx->state == WM_STATE_COLLECTING) &&
198             ctx->coin_balance_cents > 0) {
199             CALL_HAL(&ctx->callbacks, return_coins, ctx->coin_balance_cents);
200         }
201         ctx->coin_balance_cents = 0;
202         enter_standby(ctx);
203         return true;
204     }
205 }
206
207 static bool handle_1s_timer_tick(wm_context_t *ctx) {
208     if (ctx->remaining_cycle_sec > 1) {
209         ctx->remaining_cycle_sec--;
210         if (ctx->state == WM_STATE_RUNNING) {
211             update_running_actuators(ctx);
212         }
213         return true;
214     } else if (ctx->remaining_cycle_sec == 1) {
215         ctx->remaining_cycle_sec = 0;
216         CALL_HAL_VOID(&ctx->callbacks, on_cycle_complete);
217         enter_standby(ctx);
218         return true;
219     }
220 }
```



```
218     return false;
219 }
220
221 #if WM_ERROR_RESUMES_CYCLE
222 /* Timer keeps counting during a fault when a cycle was in progress (same rule as
223 PAUSE) */
224 static bool handle_error_tick(wm_context_t *ctx) {
225     if (!cycle_in_progress(ctx)) {
226         return false;
227     }
228     if (ctx->remaining_cycle_sec > 1) {
229         ctx->remaining_cycle_sec--;
230         return true;
231     }
232     if (ctx->remaining_cycle_sec == 1) {
233         ctx->remaining_cycle_sec = 0;
234         ctx->state_before_error = WM_STATE_STANDBY; /* cycle finished while faulted
235         */
236         CALL_HAL_VOID(&ctx->callbacks, on_cycle_complete);
237         return true;
238     }
239     return false;
240 }
241 #endif
242
243 static bool handle_fault_cleared(wm_context_t *ctx) {
244     ctx->active_error_flags = WM_FAULT_NONE;
245     #if WM_ERROR_RESUMES_CYCLE
246     if (cycle_in_progress(ctx) && ctx->remaining_cycle_sec > 0) {
247         enter_paused(ctx); /* safe: the user presses RUN to continue */
248     } else {
249         if (cycle_in_progress(ctx)) {
250             ctx->coin_balance_cents = 0;
251         }
252         restore_idle(ctx); /* deposit is kept */
253     }
254 #else
255     ctx->coin_balance_cents = 0;
256     enter_standby(ctx);
257 #endif
258     return true;
259 }
```



```
259 bool wm_fsm_dispatch_event(wm_context_t *ctx, wm_event_t event) {
260     if (!ctx) {
261         return false;
262     }
263
264     /* Global emergency error transition */
265     if (event == WM_EVT_FAULT_OCCURRED) {
266         if (ctx->active_error_flags == WM_FAULT_NONE) {
267             ctx->active_error_flags = WM_FAULT_DOOR_OPEN;
268         }
269         if (ctx->state != WM_STATE_ERROR) {
270             enter_error(ctx);
271             return true;
272         }
273         return false;
274     }
275
276     /* System 1ms tick handling */
277     if (event == WM_EVT_TIMER_TICK_1MS) {
278         wm_fsm_tick_1ms(ctx);
279         return true;
280     }
281
282     /* Dispatch based on current state */
283     switch (ctx->state) {
284         case WM_STATE_STANDBY:
285             switch (event) {
286                 case WM_EVT_COIN_10:
287                     return handle_coin_deposit(ctx, 10);
288                 case WM_EVT_COIN_20:
289                     return handle_coin_deposit(ctx, 20);
290                 case WM_EVT_COIN_50:
291                     return handle_coin_deposit(ctx, 50);
292                 default:
293                     /* All button presses ignored in Standby */
294                     return false;
295             }
296
297         case WM_STATE_COLLECTING:
298             switch (event) {
299                 case WM_EVT_COIN_10:
300                     return handle_coin_deposit(ctx, 10);
301                 case WM_EVT_COIN_20:
```



```
302         return handle_coin_deposit(ctx, 20);
303     case WM_EVT_COIN_50:
304         return handle_coin_deposit(ctx, 50);
305     case WM_EVT_BTN_STOP:
306         return handle_stop_button(ctx);
307     default:
308         return false;
309 }
310
311 case WM_STATE_READY:
312     switch (event) {
313     case WM_EVT_COIN_10:
314         return handle_coin_deposit(ctx, 10);
315     case WM_EVT_COIN_20:
316         return handle_coin_deposit(ctx, 20);
317     case WM_EVT_COIN_50:
318         return handle_coin_deposit(ctx, 50);
319     case WM_EVT_BTN_RUN:
320         enter_running(ctx, false);
321         return true;
322     case WM_EVT_BTN_STOP:
323         return handle_stop_button(ctx);
324     default:
325         return false;
326     }
327
328 case WM_STATE_RUNNING:
329     switch (event) {
330     case WM_EVT_BTN_PAUSE:
331         enter_paused(ctx);
332         return true;
333     case WM_EVT_BTN_STOP:
334         return handle_stop_button(ctx);
335     case WM_EVT_TIMER_TICK_1S:
336         return handle_1s_timer_tick(ctx);
337     default:
338         return false;
339     }
340
341 case WM_STATE_PAUSED:
342     switch (event) {
343     case WM_EVT_BTN_RUN:
344         enter_running(ctx, true);
```



```
345         return true;
346     case WM_EVT_BTN_STOP:
347         return handle_stop_button(ctx);
348     case WM_EVT_TIMER_TICK_1S:
349         /* CRITICAL REQUIREMENT: Timer continues counting down in PAUSED
350         state! */
351         return handle_1s_timer_tick(ctx);
352     default:
353         return false;
354 }
355
356 case WM_STATE_ERROR:
357     if (event == WM_EVT_FAULT_CLEARED) {
358         return handle_fault_cleared(ctx);
359     }
360 #if WM_ERROR_RESUMES_CYCLE
361     if (event == WM_EVT_TIMER_TICK_1S) {
362         return handle_error_tick(ctx);
363     }
364 #endif
365     return false;
366
367     default:
368         return false;
369 }
370
371 void wm_fsm_tick_1ms(wm_context_t *ctx) {
372     if (!ctx) {
373         return;
374     }
375
376     /* Decrement double-press sliding window */
377     if (ctx->stop_window_timer_ms > 0) {
378         ctx->stop_window_timer_ms--;
379         if (ctx->stop_window_timer_ms == 0) {
380             /* Double-press window expired: discard single press */
381             ctx->stop_press_count = 0;
382         }
383     }
384 }
385
386 void wm_fsm_tick_1s(wm_context_t *ctx) {
```



```
387     wm_fsm_dispatch_event(ctx, WM_EVT_TIMER_TICK_1S);
388 }
389
390 const char* wm_state_to_str(wm_state_t state) {
391     switch (state) {
392         case WM_STATE_STANDBY: return "STANDBY";
393         case WM_STATE_COLLECTING: return "COLLECTING";
394         case WM_STATE_READY: return "READY";
395         case WM_STATE_RUNNING: return "RUNNING";
396         case WM_STATE_PAUSED: return "PAUSED";
397         case WM_STATE_ERROR: return "ERROR";
398         default: return "UNKNOWN";
399     }
400 }
401
402 const char* wm_event_to_str(wm_event_t event) {
403     switch (event) {
404         case WM_EVT_NONE: return "EVT_NONE";
405         case WM_EVT_COIN_10: return "COIN_10c";
406         case WM_EVT_COIN_20: return "COIN_20c";
407         case WM_EVT_COIN_50: return "COIN_50c";
408         case WM_EVT_BTN_RUN: return "BTN_RUN";
409         case WM_EVT_BTN_PAUSE: return "BTN_PAUSE";
410         case WM_EVT_BTN_STOP: return "BTN_STOP";
411         case WM_EVT_TIMER_TICK_1S: return "TICK_1S";
412         case WM_EVT_TIMER_TICK_1MS: return "TICK_1MS";
413         case WM_EVT_FAULT_OCCURRED: return "FAULT_OCCURRED";
414         case WM_EVT_FAULT_CLEARED: return "FAULT_CLEARED";
415         default: return "UNKNOWN_EVENT";
416     }
417 }
418
419 wm_state_t wm_fsm_get_state(const wm_context_t *ctx) {
420     return ctx ? ctx->state : WM_STATE_STANDBY;
421 }
422
423 uint32_t wm_fsm_get_balance(const wm_context_t *ctx) {
424     return ctx ? ctx->coin_balance_cents : 0;
425 }
426
427 uint32_t wm_fsm_get_remaining_seconds(const wm_context_t *ctx) {
428     return ctx ? ctx->remaining_cycle_sec : 0;
429 }
```



```
430
431 uint32_t wm_fsm_get_fault_flags(const wm_context_t *ctx) {
432     return ctx ? ctx->active_error_flags : 0;
433 }
434
435 void wm_fsm_trigger_fault(wm_context_t *ctx, uint32_t fault_mask) {
436     if (!ctx) {
437         return;
438     }
439     ctx->active_error_flags |= fault_mask;
440     enter_error(ctx);
441 }
442
443 void wm_fsm_clear_fault(wm_context_t *ctx) {
444     if (!ctx) {
445         return;
446     }
447     ctx->active_error_flags = WM_FAULT_NONE;
448     wm_fsm_dispatch_event(ctx, WM_EVT_FAULT_CLEARED);
449 }
450
451 const char* wm_fault_to_str(uint32_t fault_mask) {
452     if (fault_mask == WM_FAULT_NONE) return "NO_FAULT";
453     if (fault_mask & WM_FAULT_DOOR_OPEN) return "DOOR_LATCH_OPEN";
454     if (fault_mask & WM_FAULT_WATER_TIMEOUT) return "WATER_INLET_TIMEOUT";
455     if (fault_mask & WM_FAULT_MOTOR_OVERCURRENT) return "MOTOR_OVERCURRENT";
456     return "MULTIPLE_FAULTS";
457 }
458
459 bool wm_fsm_can_accept_event(const wm_context_t *ctx, wm_event_t event) {
460     if (!ctx) {
461         return false;
462     }
463
464     if (event == WM_EVT_FAULT_OCCURRED) {
465         return ctx->state != WM_STATE_ERROR;
466     }
467     if (event == WM_EVT_TIMER_TICK_1MS) {
468         return true;
469     }
470
471     switch (ctx->state) {
472         case WM_STATE_STANDBY:
```

```
473     return (event == WM_EVT_COIN_10 || event == WM_EVT_COIN_20 || event ==
WM_EVT_COIN_50);
474
475     case WM_STATE_COLLECTING:
476         return (event == WM_EVT_COIN_10 || event == WM_EVT_COIN_20 || event ==
WM_EVT_COIN_50 ||
477             event == WM_EVT_BTN_STOP);
478
479     case WM_STATE_READY:
480         return (event == WM_EVT_COIN_10 || event == WM_EVT_COIN_20 || event ==
WM_EVT_COIN_50 ||
481             event == WM_EVT_BTN_RUN || event == WM_EVT_BTN_STOP);
482
483     case WM_STATE_RUNNING:
484         return (event == WM_EVT_BTN_PAUSE || event == WM_EVT_BTN_STOP ||
(event == WM_EVT_TIMER_TICK_1S && ctx->remaining_cycle_sec > 0));
485
486     case WM_STATE_PAUSED:
487         return (event == WM_EVT_BTN_RUN || event == WM_EVT_BTN_STOP ||
(event == WM_EVT_TIMER_TICK_1S && ctx->remaining_cycle_sec > 0));
488
489     case WM_STATE_ERROR:
490
491     #if WM_ERROR_RESUMES_CYCLE
492         if (event == WM_EVT_TIMER_TICK_1S) {
493             return cycle_in_progress(ctx) && ctx->remaining_cycle_sec > 0;
494         }
495     #endif
496
497     return (event == WM_EVT_FAULT_CLEARED);
498
499     default:
500         return false;
501 }
502 }
503
504 wm_cycle_phase_t wm_fsm_get_cycle_phase(const wm_context_t *ctx) {
505     if (!ctx) {
506         return WM_PHASE_IDLE;
507     }
508
509     if (ctx->state == WM_STATE_RUNNING || ctx->state == WM_STATE_PAUSED) {
510         uint32_t total = (ctx->cycle_duration_setting > 0) ?
                    ctx->cycle_duration_setting : WM_CYCLE_DURATION_SEC;
511         uint32_t spin_threshold = total / 6;
512     }
```

```
513     if (ctx->remaining_cycle_sec <= spin_threshold && ctx->remaining_cycle_sec >
514         0) {
515         return WM_PHASE_FINAL_SPIN;
516     }
517     return WM_PHASE_WASH_AGITATE;
518 }
519 return WM_PHASE_IDLE;
520 }
521
522 const char* wm_cycle_phase_to_str(wm_cycle_phase_t phase) {
523     switch (phase) {
524         case WM_PHASE_IDLE: return "IDLE";
525         case WM_PHASE_WASH_AGITATE: return "WASH_AGITATE";
526         case WM_PHASE_FINAL_SPIN: return "FINAL_SPIN";
527         default: return "UNKNOWN_PHASE";
528     }
529 }
```

A.2 Input and output engines

Listing 13: hal_button_engine.c

```
1  /**
2   * @file hal_button_engine.c
3   * @brief Implementation of software debouncer and coin pulse validator
4   */
5
6  #include "hal_button_engine.h"
7  #include <stddef.h>
8
9  void hal_button_init(hal_button_t *btn, bool active_low) {
10     if (!btn) {
11         return;
12     }
13     btn->active_low = active_low;
14     btn->debounced_state = false;
15     btn->last_raw_state = active_low ? true : false;
16     btn->debounce_counter = 0;
17     btn->pressed_event = false;
18     btn->released_event = false;
19 }
```



```
20
21 void hal_button_update(hal_button_t *btn, bool raw_pin_high, uint32_t delta_ms) {
22     if (!btn) {
23         return;
24     }
25
26     bool current_pressed = btn->active_low ? (!raw_pin_high) : (raw_pin_high);
27
28     if (current_pressed != btn->debounced_state) {
29         if (delta_ms > (UINT32_MAX - btn->debounce_counter)) {
30             btn->debounce_counter = HAL_DEBOUNCE_DEFAULT_MS;
31         } else {
32             btn->debounce_counter += delta_ms;
33         }
34         if (btn->debounce_counter >= HAL_DEBOUNCE_DEFAULT_MS) {
35             btn->debounced_state = current_pressed;
36             btn->debounce_counter = 0;
37             if (btn->debounced_state) {
38                 btn->pressed_event = true;
39             } else {
40                 btn->released_event = true;
41             }
42         }
43     } else {
44         btn->debounce_counter = 0;
45     }
46
47     btn->last_raw_state = raw_pin_high;
48 }
49
50 bool hal_button_was_pressed(hal_button_t *btn) {
51     if (!btn) {
52         return false;
53     }
54     if (btn->pressed_event) {
55         btn->pressed_event = false;
56         return true;
57     }
58     return false;
59 }
60
61 bool hal_button_was_released(hal_button_t *btn) {
62     if (!btn) {
```



```
63     return false;
64 }
65 if (btn->released_event) {
66     btn->released_event = false;
67     return true;
68 }
69 return false;
70 }
71
72 bool hal_button_is_pressed(const hal_button_t *btn) {
73     return btn ? btn->debounced_state : false;
74 }
75
76 void hal_coin_pulse_init(hal_coin_pulse_detector_t *det, bool active_low, uint32_t
77     timeout_ms) {
78     if (!det) {
79         return;
80     }
81     hal_button_init(&det->pulse_input, active_low);
82     det->pulse_count = 0;
83     det->silence_timer_ms = 0;
84     det->inter_pulse_timeout_ms = (timeout_ms > 0) ? timeout_ms : 150U;
85     det->fifo_head = 0;
86     det->fifo_tail = 0;
87     det->fifo_count = 0;
88     for (uint8_t i = 0; i < HAL_COIN_FIFO_CAPACITY; ++i) {
89         det->fifo[i] = 0;
90     }
91 }
92
93 void hal_coin_pulse_update(hal_coin_pulse_detector_t *det, bool raw_pin_high,
94     uint32_t delta_ms) {
95     if (!det) {
96         return;
97     }
98
99     hal_button_update(&det->pulse_input, raw_pin_high, delta_ms);
100
101     if (hal_button_was_pressed(&det->pulse_input)) {
102         det->pulse_count++;
103         det->silence_timer_ms = 0;
104     } else if (det->pulse_count > 0) {
105         if (delta_ms > (UINT32_MAX - det->silence_timer_ms)) {
```



```
104     det->silence_timer_ms = det->inter_pulse_timeout_ms;
105 } else {
106     det->silence_timer_ms += delta_ms;
107 }
108 if (det->silence_timer_ms >= det->inter_pulse_timeout_ms) {
109     uint32_t coin_value = 0;
110     /* Pulse train finished: decode standard denomination */
111     if (det->pulse_count == 1) {
112         coin_value = 10;
113     } else if (det->pulse_count == 2) {
114         coin_value = 20;
115     } else if (det->pulse_count == 5) {
116         coin_value = 50;
117     }
118
119     /* Push to FIFO if valid and queue has space */
120     if (coin_value > 0 && det->fifo_count < HAL_COIN_FIFO_CAPACITY) {
121         det->fifo[det->fifo_head] = coin_value;
122         det->fifo_head = (uint8_t)((det->fifo_head + 1U) %
HAL_COIN_FIFO_CAPACITY);
123         det->fifo_count++;
124     }
125
126     det->pulse_count = 0;
127     det->silence_timer_ms = 0;
128 }
129 }
130 }
131
132 uint32_t hal_coin_pulse_get_coin(hal_coin_pulse_detector_t *det) {
133     if (!det || det->fifo_count == 0U) {
134         return 0;
135     }
136     uint32_t val = det->fifo[det->fifo_tail];
137     det->fifo_tail = (uint8_t)((det->fifo_tail + 1U) % HAL_COIN_FIFO_CAPACITY);
138     det->fifo_count--;
139     return val;
140 }
141
142 uint8_t hal_coin_pulse_available(const hal_coin_pulse_detector_t *det) {
143     return det ? det->fifo_count : 0U;
144 }
```



Listing 14: hal_led_blinker.c

```
1  /**
2   * @file hal_led_blinker.c
3   * @brief Implementation of non-blocking LED blinker engine and actuator interlock
4   *       guard
5   */
6  #include "hal_led_blinker.h"
7  #include <stddef.h>
8
9  void hal_led_blinker_init(hal_led_blinker_t *blinker, bool active_high) {
10     if (!blinker) {
11         return;
12     }
13     blinker->mode = HAL_LED_OFF;
14     blinker->active_high = active_high;
15     blinker->output_level = active_high ? false : true;
16     blinker->phase_timer_ms = 0;
17     blinker->half_period_ms = 0;
18 }
19
20 void hal_led_blinker_set_mode(hal_led_blinker_t *blinker, hal_led_state_t mode) {
21     if (!blinker) {
22         return;
23     }
24
25     if (blinker->mode == mode) {
26         return;
27     }
28
29     blinker->mode = mode;
30     blinker->phase_timer_ms = 0;
31
32     switch (mode) {
33     case HAL_LED_OFF:
34         blinker->half_period_ms = 0;
35         blinker->output_level = blinker->active_high ? false : true;
36         break;
37
38     case HAL_LED_ON:
39         blinker->half_period_ms = 0;
40         blinker->output_level = blinker->active_high ? true : false;
41         break;
```



```
42
43     case HAL_LED_BLINK_1HZ:
44         blinker->half_period_ms = WM_BLED_BLINK_PERIOD_MS / 2U; /* 500 ms */
45         blinker->output_level = blinker->active_high ? true : false;
46         break;
47
48     case HAL_LED_BLINK_2HZ:
49         blinker->half_period_ms = WM_RLED_BLINK_PERIOD_MS / 2U; /* 250 ms */
50         blinker->output_level = blinker->active_high ? true : false;
51         break;
52
53     default:
54         blinker->half_period_ms = 0;
55         blinker->output_level = blinker->active_high ? false : true;
56         break;
57 }
58 }
59
60 void hal_led_blinker_tick_ms(hal_led_blinker_t *blinker, uint32_t delta_ms) {
61     if (!blinker || blinker->half_period_ms == 0U) {
62         return;
63     }
64
65     if (blinker->mode == HAL_LED_BLINK_1HZ || blinker->mode == HAL_LED_BLINK_2HZ) {
66         /* Guard against wrap-around under extreme delta_ms: reducing modulo one FULL
67          * period (2 half-periods) preserves both the phase and the ON/OFF parity. */
68         if (delta_ms > (UINT32_MAX - blinker->phase_timer_ms)) {
69             delta_ms %= (2U * blinker->half_period_ms);
70         }
71         blinker->phase_timer_ms += delta_ms;
72         if (blinker->phase_timer_ms >= blinker->half_period_ms) {
73             uint32_t toggles = blinker->phase_timer_ms / blinker->half_period_ms;
74             if ((toggles & 1U) != 0U) {
75                 blinker->output_level = !blinker->output_level;
76             }
77             blinker->phase_timer_ms %= blinker->half_period_ms;
78         }
79     }
80 }
81
82 bool hal_led_blinker_get_output(const hal_led_blinker_t *blinker) {
83     return blinker ? blinker->output_level : false;
84 }
```



```
85
86 bool hal_actuator_is_safe(const hal_actuator_guard_t *guard) {
87     if (!guard) {
88         return false;
89     }
90
91     /* Safety Rule 1: Motor must NEVER run if door lock is unengaged */
92     if (guard->motor != HAL_MOTOR_OFF && !guard->door_lock) {
93         return false;
94     }
95
96     /* Safety Rule 2: High-speed spin mode requires drain pump to be active */
97     if (guard->motor == HAL_MOTOR_SPIN && !guard->drain_pump) {
98         return false;
99     }
100
101     /* Safety Rule 3: Water inlet valve must NEVER be open during high-speed spin dry */
102     if (guard->motor == HAL_MOTOR_SPIN && guard->water_valve) {
103         return false;
104     }
105
106     /* Safety Rule 4: Water inlet valve and drain pump must NEVER run simultaneously */
107     if (guard->water_valve && guard->drain_pump) {
108         return false;
109     }
110
111     return true;
112 }
```

Listing 15: hal_button_gesture.c

```
1 /**
2  * @file hal_button_gesture.c
3  * @brief Single-button gesture decoder implementation
4  */
5
6 #include "hal_button_gesture.h"
7
8 void hal_gesture_init(hal_gesture_ctx_t *g) {
9     if (g == NULL) {
10         return;
11     }
```



```
11     }
12     g->phase = HAL_GST_IDLE;
13     g->timer_ms = 0U;
14     g->hold2_fired = false;
15 }
16
17 hal_gesture_t hal_gesture_update(hal_gesture_ctx_t *g, bool pressed, uint32_t
    delta_ms) {
18     if (g == NULL) {
19         return HAL_GESTURE_NONE;
20     }
21
22     switch (g->phase) {
23         case HAL_GST_IDLE:
24             if (pressed) {
25                 g->phase = HAL_GST_DOWN1;
26                 g->timer_ms = 0U;
27                 g->hold2_fired = false;
28             }
29             break;
30
31         case HAL_GST_DOWN1:
32             g->timer_ms += delta_ms;
33             if (!pressed) {
34                 g->phase = HAL_GST_WAIT;
35                 g->timer_ms = 0U;
36             } else if (g->timer_ms >= HAL_GESTURE_HOLD1_MS) {
37                 g->phase = HAL_GST_HELD;
38                 return HAL_GESTURE_HOLD1;
39             }
40             break;
41
42         case HAL_GST_WAIT:
43             g->timer_ms += delta_ms;
44             if (pressed) {
45                 g->phase = HAL_GST_DOWN2;
46                 g->timer_ms = 0U;
47             } else if (g->timer_ms >= HAL_GESTURE_DOUBLE_GAP_MS) {
48                 g->phase = HAL_GST_IDLE;
49                 return HAL_GESTURE_CLICK;
50             }
51             break;
52     }
```



```
53     case HAL_GST_DOWN2:
54         g->timer_ms += delta_ms;
55         if (!pressed) {
56             g->phase = HAL_GST_IDLE;
57             return HAL_GESTURE_DOUBLE;
58         }
59         if (g->timer_ms >= HAL_GESTURE_HOLD1_MS) {
60             g->phase = HAL_GST_HELD;
61             return HAL_GESTURE_HOLD1;
62         }
63         break;
64
65     case HAL_GST_HELD:
66         g->timer_ms += delta_ms;
67         if (!pressed) {
68             g->phase = HAL_GST_IDLE;
69             if (!g->hold2_fired) {
70                 return HAL_GESTURE_HOLD1_END;
71             }
72         } else if (!g->hold2_fired && g->timer_ms >= HAL_GESTURE_HOLD2_MS) {
73             g->hold2_fired = true;
74             return HAL_GESTURE_HOLD2;
75         }
76         break;
77
78     default:
79         g->phase = HAL_GST_IDLE;
80         break;
81 }
82 return HAL_GESTURE_NONE;
83 }
84
85 uint32_t hal_gesture_hold_ms(const hal_gesture_ctx_t *g) {
86     if (g == NULL) {
87         return 0U;
88     }
89     if (g->phase == HAL_GST_DOWN1 || g->phase == HAL_GST_DOWN2 || g->phase ==
90         HAL_GST_HELD) {
91         return g->timer_ms;
92     }
93     return 0U;
94 }
```



Listing 16: wm_single_button.c

```
1  /**
2   * @file wm_single_button.c
3   * @brief Single-button gesture to FSM event mapping
4   */
5
6  #include "wm_single_button.h"
7
8  static bool apply_click(wm_context_t *ctx) {
9      switch (ctx->state) {
10         case WM_STATE_STANDBY:
11         case WM_STATE_COLLECTING:
12             return wm_fsm_dispatch_event(ctx, WM_EVT_COIN_50);
13         case WM_STATE_READY:
14         case WM_STATE_PAUSED:
15             return wm_fsm_dispatch_event(ctx, WM_EVT_BTN_RUN);
16         case WM_STATE_RUNNING:
17             return wm_fsm_dispatch_event(ctx, WM_EVT_BTN_PAUSE);
18         case WM_STATE_ERROR:
19             wm_fsm_clear_fault(ctx);
20             return true;
21         default:
22             return false;
23     }
24 }
25
26 static bool apply_double(wm_context_t *ctx) {
27     switch (ctx->state) {
28         case WM_STATE_STANDBY:
29         case WM_STATE_COLLECTING:
30             return wm_fsm_dispatch_event(ctx, WM_EVT_COIN_10);
31         case WM_STATE_READY:
32         case WM_STATE_RUNNING:
33         case WM_STATE_PAUSED:
34             wm_fsm_trigger_fault(ctx, WM_FAULT_DOOR_OPEN);
35             return true;
36         case WM_STATE_ERROR:
37             wm_fsm_clear_fault(ctx);
38             return true;
39         default:
40             return false;
41     }
42 }
```



```
43
44 bool wm_single_button_apply(wm_context_t *ctx, hal_gesture_t gesture) {
45     if (ctx == NULL) {
46         return false;
47     }
48
49     switch (gesture) {
50         case HAL_GESTURE_CLICK:
51             return apply_click(ctx);
52         case HAL_GESTURE_DOUBLE:
53             return apply_double(ctx);
54         case HAL_GESTURE_HOLD1:
55             return wm_fsm_dispatch_event(ctx, WM_EVT_BTN_STOP);
56         case HAL_GESTURE_HOLD2: {
57             bool changed = wm_fsm_dispatch_event(ctx, WM_EVT_BTN_STOP);
58             if (ctx->state == WM_STATE_ERROR) {
59                 /* STOP is not defined to leave ERROR; clear the fault so a long hold
always recovers the panel */
60                 wm_fsm_clear_fault(ctx);
61                 changed = true;
62             }
63             return changed;
64         }
65         case HAL_GESTURE_NONE:
66         default:
67             return false;
68     }
69 }
70
71 bool wm_ext_run_pause_apply(wm_context_t *ctx) {
72     if (ctx == NULL || ctx->state == WM_STATE_STANDBY || ctx->state ==
73     WM_STATE_COLLECTING) {
74         return false;
75     }
76     return apply_click(ctx);
77 }
78
79 bool wm_ext_stop_apply(wm_context_t *ctx) {
80     if (ctx == NULL) {
81         return false;
82     }
83     if (ctx->state == WM_STATE_ERROR) {
84         wm_fsm_clear_fault(ctx);
```



```
84     return true;
85 }
86 return wm_fsm_dispatch_event(ctx, WM_EVT_BTN_STOP);
87 }
```

Listing 17: wm_two_button.c

```
1  /**
2   * @file wm_two_button.c
3   * @brief K0/K1 front panel logic with coin staging
4   */
5
6  #include <stddef.h>
7  #include "wm_two_button.h"
8  #include "wm_single_button.h"
9
10 static bool is_idle(const wm_context_t *ctx) {
11     return ctx->state == WM_STATE_STANDBY || ctx->state == WM_STATE_COLLECTING;
12 }
13
14 void wm_staging_init(wm_coin_staging_t *s) {
15     if (s != NULL) {
16         s->pending_cents = 0U;
17     }
18 }
19
20 void wm_staging_sync(wm_coin_staging_t *s, const wm_context_t *ctx) {
21     if (s != NULL && ctx != NULL && !is_idle(ctx)) {
22         s->pending_cents = 0U;
23     }
24 }
25
26 static bool stage_coin(wm_coin_staging_t *s, const wm_context_t *ctx, uint32_t cents)
27 {
28     if (!is_idle(ctx)) {
29         return false;
30     }
31     uint32_t room = WM_STAGING_MAX_CENTS - s->pending_cents;
32     s->pending_cents += (cents > room) ? room : cents;
33     return true;
34 }
35
36 static bool confirm(wm_context_t *ctx, wm_coin_staging_t *s, wm_notice_t *notice,
```



```
uint32_t *value) {
36     if (!is_idle(ctx)) {
37         return false;
38     }
39
40     uint32_t pending = s->pending_cents;
41     s->pending_cents = 0U;
42
43     if (pending >= WM_COIN_THRESHOLD_CENTS) {
44         /* The FSM sees exactly the fare; the excess is reported as returned change */
45         (void)wm_fsm_dispatch_event(ctx, WM_EVT_COIN_50);
46         if (notice != NULL) {
47             *notice = WM_NOTICE_READY;
48         }
49         if (value != NULL) {
50             *value = pending - WM_COIN_THRESHOLD_CENTS;
51         }
52     } else {
53         if (notice != NULL) {
54             *notice = WM_NOTICE_NOT_ENOUGH;
55         }
56         if (value != NULL) {
57             *value = pending;
58         }
59     }
60     return true;
61 }
62
63 bool wm_k1_apply(wm_context_t *ctx, wm_coin_staging_t *s, hal_gesture_t gesture,
64                 wm_notice_t *notice, uint32_t *value) {
65     if (ctx == NULL || s == NULL) {
66         return false;
67     }
68     wm_staging_sync(s, ctx);
69
70     if (is_idle(ctx)) {
71         switch (gesture) {
72             case HAL_GESTURE_CLICK:
73                 return stage_coin(s, ctx, 10U);
74             case HAL_GESTURE_DOUBLE:
75                 return stage_coin(s, ctx, 20U);
76             case HAL_GESTURE_HOLD1_END:
77                 return stage_coin(s, ctx, 50U);
```

```
78         case HAL_GESTURE_HOLD2:
79             return confirm(ctx, s, notice, value);
80         default:
81             return false;
82     }
83 }
84 return wm_single_button_apply(ctx, gesture);
85 }
86
87 bool wm_k0_apply(wm_context_t *ctx, wm_coin_staging_t *s, hal_gesture_t gesture) {
88     if (ctx == NULL || s == NULL) {
89         return false;
90     }
91     wm_staging_sync(s, ctx);
92
93     if (is_idle(ctx)) {
94         switch (gesture) {
95             case HAL_GESTURE_CLICK:
96                 return stage_coin(s, ctx, 10U);
97             case HAL_GESTURE_DOUBLE:
98             case HAL_GESTURE_HOLD1:
99                 return stage_coin(s, ctx, 20U);
100             default:
101                 return false;
102         }
103     }
104     return (gesture == HAL_GESTURE_CLICK) ? wm_ext_run_pause_apply(ctx) : false;
105 }
```

A.3 Board firmware

Listing 18: main_h750.c

```
1 /**
2  * @file main_h750.c
3  * @brief Washing Machine Control Unit on the WeAct STM32H750VBT6 board
4  * @details Input : onboard key K1 (PC13) decoded into click / double-click / hold
5  *                gestures,
6  *                plus optional external RUN/PAUSE (PA0) and STOP (PA1) push-buttons
7  *                Output: dashboard on the 0.96" ST7735 LCD + onboard LED PE3 (mirrors
8  *                RLED/BLED)
```



```
7  *           The FSM, debouncer, blinker and gesture decoder are the same portable
   code that is
8  *           unit-tested on the host; only the board drivers in this folder are
   hardware specific.
9  */
10
11 #include <stdbool.h>
12 #include <stdint.h>
13 #include <string.h>
14 #include "board_h750.h"
15 #include "washing_machine_fsm.h"
16 #include "hal_button_engine.h"
17 #include "hal_button_gesture.h"
18 #include "hal_led_blinker.h"
19 #include "wm_single_button.h"
20 #include "wm_two_button.h"
21 #include "ui_render.h"
22 #include "ui_text.h"
23
24 #define HOLD_UI_STEP_MS   (50U)
25
26 /* Demo build: a "30 minute" cycle is shortened to 30 s so it can be watched live.
27  * Build with FULL_CYCLE=1 (make h750 FULL_CYCLE=1) for the real 1800 s cycle. */
28 #ifndef WM_DEMO_CYCLE_SEC
29 #define WM_DEMO_CYCLE_SEC   (WM_CYCLE_DURATION_TEST_SEC)
30 #endif
31
32 static wm_context_t g_fsm;
33 static hal_button_t g_key;
34 static hal_button_t g_ext_run;
35 static hal_button_t g_ext_stop;
36 static hal_gesture_ctx_t g_gesture;           /* K1 (PC13) */
37 static hal_gesture_ctx_t g_k0_gesture;       /* K0 (external, PA0) */
38 static wm_coin_staging_t g_staging;
39
40 /* Transient message ("READY! CHANGE 050C" / "NOT ENOUGH! REFUND 030C") */
41 #define NOTICE_MS   (2500U)
42 static wm_notice_t g_notice = WM_NOTICE_NONE;
43 static uint32_t g_notice_value = 0U;
44 static uint32_t g_notice_until_ms = 0U;
45 static hal_led_blinker_t g_rled;
46 static hal_led_blinker_t g_bled;
47
```



```
48  /* Output snapshot mirrored on the LCD (relays have no pins on this board) */
49  static hal_motor_state_t g_motor = HAL_MOTOR_OFF;
50  static bool g_pump = false;
51  static bool g_lock = false;
52
53  static void cb_set_rled(hal_led_state_t s) { hal_led_blinker_set_mode(&g_rled, s); }
54  static void cb_set_bled(hal_led_state_t s) { hal_led_blinker_set_mode(&g_bled, s); }
55  static void cb_set_motor(hal_motor_state_t m) { g_motor = m; }
56  static void cb_set_valve(bool open) { (void)open; }
57  static void cb_set_pump(bool on) { g_pump = on; }
58  static void cb_set_lock(bool locked) { g_lock = locked; }
59  static void set_notice(wm_notice_t type, uint32_t value);
60
61  static void cb_return_coins(uint32_t cents) {
62      set_notice(WM_NOTICE_REFUND, cents);
63  }
64
65  static void cb_cycle_complete(void) {
66      g_motor = HAL_MOTOR_OFF;
67      g_pump = false;
68      g_lock = false;
69  }
70
71  /* ----- UART console: status log + keyboard control (115200 8N1 on PA9/PA10) ----- */
72  static const char k_help[] =
73      "K1 keys: c=click(+10c) d=double(+20c) p=hold+release(+50c) o=hold
74      1.2s(OK/confirm)\r\n"
75      "          a=K0 click(+10c) b=K0 hold(+20c) s=STOP (twice) f=force stop
76      ?=help\r\n";
77
78  static void uart_print_uint(uint32_t v) {
79      char tmp[11];
80      unsigned n = 0U;
81      do {
82          tmp[n++] = (char)('0' + (v % 10U));
83          v /= 10U;
84      } while (v != 0U);
85      char one[2] = {0, 0};
86      while (n > 0U) {
87          one[0] = tmp[--n];
88          board_uart_puts(one);
89      }
90  }
```



```
89
90 static bool log_changed(const ui_view_t *a, const ui_view_t *b) {
91     return a->state != b->state || a->phase != b->phase || a->remaining_sec !=
92         b->remaining_sec ||
93         a->balance_cents != b->balance_cents || a->fault_flags != b->fault_flags ||
94         a->motor != b->motor || a->pump != b->pump || a->lock != b->lock;
95 }
96
97 static void log_status(const ui_view_t *v) {
98     char line[128];
99     board_uart_puts("[");
100     uart_print_uint(board_millis() / 1000U);
101     board_uart_puts("s] ");
102     (void)ui_status_line(line, sizeof(line), v);
103     board_uart_puts(line);
104     board_uart_puts("\r\n");
105 }
106
107 static void set_notice(wm_notice_t type, uint32_t value) {
108     g_notice = type;
109     g_notice_value = value;
110     g_notice_until_ms = board_millis() + NOTICE_MS;
111     board_uart_puts(type == WM_NOTICE_READY ? "NOTICE: READY, change returned " :
112         type == WM_NOTICE_REFUND ? "NOTICE: CANCELLED, deposit returned "
113         :
114         "NOTICE: NOT ENOUGH MONEY, refund ");
115     uart_print_uint(value);
116     board_uart_puts("c\r\n");
117 }
118
119 static void k1_event(hal_gesture_t g) {
120     wm_notice_t n = WM_NOTICE_NONE;
121     uint32_t value = 0U;
122     (void)wm_k1_apply(&g_fsm, &g_staging, g, &n, &value);
123     if (n != WM_NOTICE_NONE) {
124         set_notice(n, value);
125     }
126 }
127
128 static void handle_uart_key(int c) {
129     switch (c) {
130         case 'a': board_uart_puts("> K0 click\r\n"); (void)wm_k0_apply(&g_fsm,
131             &g_staging, HAL_GESTURE_CLICK); break;
```

```
129     case 'b': board_uart_puts("> K0 hold\r\n");    (void)wm_k0_apply(&g_fsm,
130     &g_staging, HAL_GESTURE_HOLD1); break;
131     case 'c': board_uart_puts("> K1 click\r\n");    k1_event(HAL_GESTURE_CLICK);
132     break;
133     case 'p': board_uart_puts("> K1 hold+release\r\n");
134     k1_event(HAL_GESTURE_HOLD1_END); break;
135     case 'd': board_uart_puts("> K1 double-click\r\n");
136     k1_event(HAL_GESTURE_DOUBLE); break;
137     case 'o': board_uart_puts("> K1 hold 1.2 s (confirm)\r\n");
138     k1_event(HAL_GESTURE_HOLD2); break;
139     case 's': board_uart_puts("> STOP\r\n");
140     (void)wm_ext_stop_apply(&g_fsm); break;
141     case 'f':
142     board_uart_puts("> force stop\r\n");
143     (void)wm_single_button_apply(&g_fsm, HAL_GESTURE_HOLD1);
144     (void)wm_single_button_apply(&g_fsm, HAL_GESTURE_HOLD2);
145     break;
146     case '?':
147     case 'h': board_uart_puts(k_help); break;
148     default: break;
149 }
150 }
151
152 static void build_view(ui_view_t *v) {
153     v->state = g_fsm.state;
154     v->phase = wm_fsm_get_cycle_phase(&g_fsm);
155     wm_staging_sync(&g_staging, &g_fsm);
156     v->balance_cents = (g_fsm.state == WM_STATE_STANDBY || g_fsm.state ==
157     WM_STATE_COLLECTING) ? g_staging.pending_cents : g_fsm.coin_balance_cents;
158     v->remaining_sec = g_fsm.remaining_cycle_sec;
159     v->total_sec = g_fsm.cycle_duration_setting;
160     v->fault_flags = g_fsm.active_error_flags;
161     v->rled = hal_led_blinker_get_output(&g_rled);
162     v->bled = hal_led_blinker_get_output(&g_bled);
163     v->motor = g_motor;
164     v->pump = g_pump;
165     v->lock = g_lock;
166     v->reset_cause = board_reset_cause();
167     v->bl_mode = 0U;
168     if (g_notice != WM_NOTICE_NONE && (int32_t)(board_millis() - g_notice_until_ms)
169     >= 0) {
170         g_notice = WM_NOTICE_NONE;
171     }
172 }
```



```
164     v->notice = (uint32_t)g_notice;
165     v->notice_value = g_notice_value;
166     v->hold_ms = (hal_gesture_hold_ms(&g_gesture) / HOLD_UI_STEP_MS) *
        HOLD_UI_STEP_MS;
167 }
168
169 /** @brief Deterministic 1 ms housekeeping */
170 static void process_1ms(uint32_t *sec_acc_ms) {
171     wm_fsm_tick_1ms(&g_fsm);
172     hal_led_blinker_tick_ms(&g_rled, 1U);
173     hal_led_blinker_tick_ms(&g_bled, 1U);
174
175     hal_button_update(&g_key, board_key_pressed(), 1U);
176     hal_gesture_t g = hal_gesture_update(&g_gesture, hal_button_is_pressed(&g_key),
        1U);
177     if (g != HAL_GESTURE_NONE) {
178         k1_event(g);
179     }
180
181     /* K0 = external button on PA0 (to GND): coin button in STANDBY, RUN/PAUSE
        otherwise */
182     hal_button_update(&g_ext_run, board_ext_run_pressed(), 1U);
183     hal_gesture_t g0 = hal_gesture_update(&g_k0_gesture,
        hal_button_is_pressed(&g_ext_run), 1U);
184     if (g0 != HAL_GESTURE_NONE) {
185         (void)wm_k0_apply(&g_fsm, &g_staging, g0);
186     }
187
188     hal_button_update(&g_ext_stop, board_ext_stop_pressed(), 1U);
189     if (hal_button_was_pressed(&g_ext_stop)) {
190         (void)wm_ext_stop_apply(&g_fsm);
191     }
192
193     (*sec_acc_ms)++;
194     if (*sec_acc_ms >= 1000U) {
195         *sec_acc_ms = 0U;
196         wm_fsm_tick_1s(&g_fsm);
197     }
198 }
199
200 int main(void) {
201     board_init();
```



```
202 board_led_set(true);          /* boot stage 1: clocks + GPIO OK -> LED on during
LCD bring-up */
203
204 hal_led_blinker_init(&g_rled, true);
205 hal_led_blinker_init(&g_bled, true);
206 hal_button_init(&g_key, false); /* K1 is active HIGH */
207 hal_button_init(&g_ext_run, true); /* external buttons are active LOW */
208 hal_button_init(&g_ext_stop, true);
209 hal_gesture_init(&g_gesture);
210 hal_gesture_init(&g_k0_gesture);
211 wm_staging_init(&g_staging);
212
213 hal_output_callbacks_t cbs = {
214     .set_rled = cb_set_rled,
215     .set_bled = cb_set_bled,
216     .set_motor = cb_set_motor,
217     .set_water_valve = cb_set_valve,
218     .set_drain_pump = cb_set_pump,
219     .set_door_lock = cb_set_lock,
220     .on_cycle_complete = cb_cycle_complete,
221     .return_coins = cb_return_coins
222 };
223 wm_fsm_init(&g_fsm, &cbs);
224 g_fsm.cycle_duration_setting = WM_DEMO_CYCLE_SEC;
225
226 board_uart_init();
227 board_uart_puts("\r\n=== Washing Machine Control Unit - WeAct STM32H750 ===\r\n");
228 board_uart_puts("Reset cause: ");
229 board_uart_puts(board_reset_cause());
230 board_uart_puts("\r\n");
231 board_uart_puts(k_help);
232
233 lcd_init();
234 board_led_set(false);
235
236 ui_view_t shown;
237 ui_view_t now;
238 memset(&shown, 0, sizeof(shown));
239 shown.state = (wm_state_t)0xFF; /* force first draw */
240
241 ui_view_t logged;
242 memset(&logged, 0, sizeof(logged));
243 logged.state = (wm_state_t)0xFF;
```



```
244
245     uint32_t processed = board_millis();
246     uint32_t sec_acc_ms = 0U;
247 #ifndef BL_EXPERIMENT
248     uint32_t bl_mode = 1U;
249     uint32_t bl_since = board_millis();
250     lcd_backlight_mode(bl_mode);
251 #endif
252
253     for (;;) {
254         uint32_t t = board_millis();
255         while (processed != t) {
256             processed++;
257             process_1ms(&sec_acc_ms);
258         }
259
260         build_view(&now);
261 #ifndef BL_EXPERIMENT
262         if ((t - bl_since) >= 4000U) {
263             bl_since = t;
264             bl_mode = (bl_mode % 4U) + 1U;
265             lcd_backlight_mode(bl_mode);
266         }
267         now.bl_mode = bl_mode;
268 #endif
269         int key;
270         while ((key = board_uart_getc()) >= 0) {
271             handle_uart_key(key);
272         }
273         build_view(&now);
274         if (log_changed(&now, &logged)) {
275             log_status(&now);
276             logged = now;
277         }
278         board_led_set(now.rled || now.bled);
279         if (!ui_view_equal(&now, &shown)) {
280             ui_render(&now);
281             lcd_flush();
282             shown = now;
283         }
284     }
285 }
```



Listing 19: board_h750.c

```
1 /**
2  * @file board_h750.c
3  * @brief Clock tree, GPIO and SysTick for the WeAct STM32H750VBT6 board
4  * @details SYSCLK 400 MHz (VOS1, LDO supply) from the 25 MHz HSE crystal. If the
5  *         crystal does not
6  *         start, falls back to HSI 64 MHz with a PLL setting that still yields 400
7  *         MHz, so the
8  *         firmware never hangs at boot and all timing constants stay valid.
9  */
10 #include "stm32h7xx.h"
11 #include "board_h750.h"
12
13 #define SYSCLK_HZ      (400000000U)
14 #define HSE_TIMEOUT_LOOP (2000000U)
15
16 uint32_t SystemCoreClock = SYSCLK_HZ;
17
18 static volatile uint32_t g_millis = 0U;
19 static const char *g_reset_cause = "?";
20
21 const char *board_reset_cause(void) {
22     return g_reset_cause;
23 }
24
25 void SysTick_Handler(void) {
26     g_millis++;
27 }
28
29 uint32_t board_millis(void) {
30     return g_millis;
31 }
32
33 /* Wall-clock wait independent of SysTick/interrupts: DWT cycle counter at SYSCLK_HZ
34 */
35 static void dwt_wait_ms(uint32_t ms) {
36     CoreDebug->DEMCR |= CoreDebug_DEMCR_TRCENA_Msk;
37     DWT->CTRL |= DWT_CTRL_CYCCNTENA_Msk;
38     uint32_t start = DWT->CYCCNT;
39     uint32_t cycles = ms * (SYSCLK_HZ / 1000U);
40     while ((DWT->CYCCNT - start) < cycles) {
41     }
```



```
40 }
41
42 void board_fatal(uint32_t code) {
43     RCC->AHB4ENR |= RCC_AHB4ENR_GPIOEEN;
44     (void)RCC->AHB4ENR;
45     GPIOE->MODER = (GPIOE->MODER & ~(3U << (3U * 2U))) | (1U << (3U * 2U));
46     for (;;) {
47         for (uint32_t k = 0U; k < code; k++) {
48             GPIOE->BSRR = (1U << 3U);
49             dwt_wait_ms(500U);
50             GPIOE->BSRR = (1U << (3U + 16U));
51             dwt_wait_ms(500U);
52         }
53         dwt_wait_ms(3000U);
54     }
55 }
56
57 void HardFault_Handler(void) {
58     board_fatal(BOARD_ERR_HARDFAULT);
59 }
60
61 void board_delay_ms(uint32_t ms) {
62     uint32_t start = g_millis;
63     uint32_t guard = ms * 4000000U; /* >> loop speed of a 400 MHz M7; only trips if
64                                     SysTick is dead */
65     while ((g_millis - start) < ms) {
66         if (guard-- == 0U) {
67             board_fatal(BOARD_ERR_SYSTICK);
68         }
69     }
70 }
71
72 static bool start_hse(void) {
73     RCC->CR |= RCC_CR_HSEON;
74     for (uint32_t i = 0U; i < HSE_TIMEOUT_LOOP; i++) {
75         if ((RCC->CR & RCC_CR_HSERDY) != 0U) {
76             return true;
77         }
78     }
79     RCC->CR &= ~RCC_CR_HSEON;
80     return false;
81 }
```



```
82 void board_system_init(void) {
83     /* 0. Start from a known clock state. After a USB-DFU "leave" the ROM bootloader
84        jumps here
85        * without a clean reset (PLL1 may already be running, which makes PLL writes
86        ineffective). */
87     RCC->CR |= RCC_CR_HSION;
88     while ((RCC->CR & RCC_CR_HSIRDY) == 0U) {
89     }
90     RCC->CFGR &= ~RCC_CFGR_SW;
91     while ((RCC->CFGR & RCC_CFGR_SWS) != 0U) {
92     }
93     RCC->CR &= ~RCC_CR_PLL1ON;
94     while ((RCC->CR & RCC_CR_PLL1RDY) != 0U) {
95     }
96     __disable_irq();
97     SCB_DisableDCache();
98     SCB_DisableICache();
99
100    /* 1. Supply: LDO, then voltage scale 1 (required for 400 MHz) */
101    PWR->CR3 = (PWR->CR3 | PWR_CR3_LDOEN) & ~PWR_CR3_BYPASS;
102    while ((PWR->CSR1 & PWR_CSR1_ACTIVOSRDY) == 0U) {
103    }
104    PWR->D3CR |= PWR_D3CR_VOS;
105    while ((PWR->D3CR & PWR_D3CR_VOSRDY) == 0U) {
106    }
107
108    /* 2. PLL1: HSE 25/5 = 5 MHz x160 = 800 MHz VCO /2 = 400 MHz (HSI: 64/16 = 4 MHz
109       x200) */
110    bool hse_ok = start_hse();
111    uint32_t divm = hse_ok ? 5U : 16U;
112    uint32_t divn = hse_ok ? 160U : 200U;
113    uint32_t src = hse_ok ? 2U : 0U;
114    RCC->PLLCKSELR = (divm << 4) | src;
115    RCC->PLLCFGR = (2U << 2) | /* PLL1RGE: 4..8 MHz input */
116    RCC_PLLCFGR_DIVP1EN; /* wide VCO, no fractional */
117    RCC->PLL1DIVR = (divn - 1U) | ((2U - 1U) << 9) | ((8U - 1U) << 16) | ((2U - 1U)
118    << 24);
119    RCC->CR |= RCC_CR_PLL1ON;
120    while ((RCC->CR & RCC_CR_PLL1RDY) == 0U) {
121    }
122
123    /* 3. Bus prescalers: CPU 400, AHB/AXI 200, all APB 100 MHz */
124    RCC->D1CFGR = (8U << 0) | (4U << 4); /* HPRE /2, D1PPRE /2, D1CPRE /1 */
```

```
121 RCC->D2CFGR = (4U << 4) | (4U << 8);          /* D2PPRE1 /2, D2PPRE2 /2 */
122 RCC->D3CFGR = (4U << 4);                        /* D3PPRE /2 */
123
124 /* 4. Flash wait states for 200 MHz AXI @ VOS1, then switch to PLL1 */
125 FLASH->ACR = (2U << FLASH_ACR_LATENCY_Pos) | (2U << FLASH_ACR_WRHIGHFREQ_Pos);
126 while ((FLASH->ACR & FLASH_ACR_LATENCY) != (2U << FLASH_ACR_LATENCY_Pos)) {
127 }
128 RCC->CFGR = (RCC->CFGR & ~RCC_CFGR_SW) | (3U << RCC_CFGR_SW_Pos);
129 while ((RCC->CFGR & RCC_CFGR_SWS) != (3U << RCC_CFGR_SWS_Pos)) {
130 }
131
132 SCB->VTOR = FLASH_BANK1_BASE;
133 SCB_EnableICache();
134 SCB_EnableDCache();
135 __enable_irq();
136 }
137
138 void board_init(void) {
139     {
140         uint32_t rsr = RCC->RSR;
141         if ((rsr & RCC_RSR_PORRSTF) != 0U)      { g_reset_cause = "POR"; }
142         else if ((rsr & RCC_RSR_BORRSTF) != 0U)  { g_reset_cause = "BOR"; }
143         else if ((rsr & RCC_RSR_IWDG1RSTF) != 0U) { g_reset_cause = "IWDG"; }
144         else if ((rsr & RCC_RSR_WWDG1RSTF) != 0U) { g_reset_cause = "WWDG"; }
145         else if ((rsr & RCC_RSR_SFTRSTF) != 0U)  { g_reset_cause = "SFT"; }
146         else if ((rsr & RCC_RSR_PINRSTF) != 0U)  { g_reset_cause = "PIN"; }
147         RCC->RSR |= RCC_RSR_RMVF;
148     }
149
150     RCC->AHB4ENR |= RCC_AHB4ENR_GPIOAEN | RCC_AHB4ENR_GPIOCEN | RCC_AHB4ENR_GPIOEEN;
151     (void)RCC->AHB4ENR; /* read-back: guarantee clock is running before first access
152                          */
153
154     /* LED PE3: push-pull output, off */
155     GPIOE->BSRR = (1U << (3U + 16U));
156     GPIOE->MODER = (GPIOE->MODER & ~(3U << (3U * 2U))) | (1U << (3U * 2U));
157
158     /* KEY PC13: input with pull-down (K1 pulls the pin to 3.3 V when pressed) */
159     GPIOC->MODER &= ~(3U << (13U * 2U));
160     GPIOC->PUPDR = (GPIOC->PUPDR & ~(3U << (13U * 2U))) | (2U << (13U * 2U));
161
162     /* External buttons PA0 / PA1: inputs with pull-up (pressed = LOW) */
163     GPIOA->MODER &= ~(3U << (0U * 2U)) | (3U << (1U * 2U));
```



```
163     GPIOA->PUPDR = (GPIOA->PUPDR & ~((3U << (0U * 2U)) | (3U << (1U * 2U)))) |
164         (1U << (0U * 2U)) | (1U << (1U * 2U));
165
166     (void)SysTick_Config(SYSCLK_HZ / 1000U);
167 }
168
169 void board_led_set(bool on) {
170     GPIOE->BSRR = on ? (1U << 3U) : (1U << (3U + 16U));
171 }
172
173 bool board_key_pressed(void) {
174     return (GPIOC->IDR & (1U << 13U)) != 0U;
175 }
176
177 bool board_ext_run_pressed(void) {
178     return (GPIOA->IDR & (1U << 0U)) == 0U;
179 }
180
181 bool board_ext_stop_pressed(void) {
182     return (GPIOA->IDR & (1U << 1U)) == 0U;
183 }
184
185 #define UART_BAUD (115200U)
186 #define UART_PCLK (100000000U) /* USART1 kernel clock = APB2 (default selection) */
187
188 void board_uart_init(void) {
189     RCC->AHB4ENR |= RCC_AHB4ENR_GPIOAEN;
190     RCC->APB2ENR |= RCC_APB2ENR_USART1EN;
191     (void)RCC->APB2ENR;
192
193     /* PA9 = TX, PA10 = RX: alternate function 7, internal pull-up on RX */
194     GPIOA->MODER = (GPIOA->MODER & ~((3U << (9U * 2U)) | (3U << (10U * 2U)))) |
195         (2U << (9U * 2U)) | (2U << (10U * 2U));
196     GPIOA->AFR[1] = (GPIOA->AFR[1] & ~((0xFU << 4) | (0xFU << 8))) | (7U << 4) | (7U
197         << 8);
198     GPIOA->PUPDR = (GPIOA->PUPDR & ~(3U << (10U * 2U))) | (1U << (10U * 2U));
199     GPIOA->OSPEEDR |= (3U << (9U * 2U));
200
201     USART1->CR1 = 0U;
202     USART1->BRR = UART_PCLK / UART_BAUD;
203     USART1->CR1 = USART_CR1_TE | USART_CR1_RE | USART_CR1_UE;
204 }
```

```
205 static void uart_putc(char c) {
206     uint32_t guard = 2000000U;
207     while ((USART1->ISR & USART_ISR_TXE_TXFNF) == 0U) {
208         if (guard-- == 0U) {
209             return; /* never block the machine on a missing terminal */
210         }
211     }
212     USART1->TDR = (uint32_t)(uint8_t)c;
213 }
214
215 void board_uart_puts(const char *s) {
216     while (*s != '\0') {
217         uart_putc(*s++);
218     }
219 }
220
221 int board_uart_getc(void) {
222     if ((USART1->ISR & USART_ISR_ORE) != 0U) {
223         USART1->ICR = USART_ICR_ORECF;
224     }
225     if ((USART1->ISR & USART_ISR_RXNE_RXFNE) != 0U) {
226         return (int)(USART1->RDR & 0xFFU);
227     }
228     return -1;
229 }
```

B Pin configuration

The project does not use STM32CubeMX: peripherals are configured directly through the registers (board_h750.c, lcd_st7735.c) following RM0433^[5]. The resulting configuration is:



Table B.1: Register-level pin configuration

Pin	MODER	PUPDR	AF	Function
PC13	00 input	10 pull-down	–	K1
PA0, PA1	00 input	01 pull-up	–	external K0, STOP
PE3	01 output	–	–	status LED
PE11, PE13	01 output	–	–	LCD CS, DC
PE12, PE14	10 alternate	–	AF5	SPI4 SCK, MOSI
PE10	10 alternate	–	AF1	TIM1_CH2N backlight PWM
PA9, PA10	10 alternate	PA10 pull-up	AF7	USART1 TX, RX

C Full test logs

Listing 20: make test – FSM suite

```

1 =====
2 BTL 2: Washing Machine Control Unit - Verification Suite
3 CQ3053 Embedded Systems - HCMUT
4 =====
5
6 [PASS] TC-01: Sub-threshold Deposit (10¢ + 20¢ stays in COLLECTING, RLED on)
7 [PASS] TC-02: Exact Threshold Deposit (50¢ transitions to READY)
8 [PASS] TC-03: Surplus Deposit Accumulation (Accepts 60¢, 110¢ in READY)
9 [PASS] TC-04: Execution & Zero Refund (70¢ cleared to 0¢, 30-min timer active)
10 [PASS] TC-05: Premature RUN Attempt (Ignored when balance < 50¢)
11 [PASS] TC-06: Normal Pause and Resume (Actuators safely suspended and resumed)
12 [PASS] TC-07: Persistent Timer in Pause (Timer ticked down from 1600s to 1300s while paused)
13 [PASS] TC-08: Pause Timeout Termination (Timer expiring in PAUSED resets to STANDBY)
14 [PASS] TC-09: Single STOP Rejection (Single press does not force stop)
15 [PASS] TC-10: Force Stop on Double Press (2 presses within 300ms forces termination)
16 [PASS] TC-11: Force Stop from Paused State (Double STOP terminates paused machine)
17 [PASS] TC-12: Normal 30-min Cycle Completion (1800s expires naturally to STANDBY)
18 [PASS] TC-13: Fault Interruption and Recovery (Safety shutdown & error reset)
19 [PASS] TC-14: Rapid Alternating PAUSE/RUN Toggling (Stress test on clock & motor)
20 [PASS] TC-15: Coin Rejection During Active Cycle (Coins rejected in RUNNING, PAUSED, ERROR)
21 [PASS] TC-16: Fault in STANDBY and READY States (Consistent error transition & LED signalling)
22 [PASS] TC-17: Complete Lockout During ERROR State (Buttons and coins strictly locked)
23 [PASS] TC-18: Ready State Double STOP Cancellation (User cancel before run)
24 [PASS] TC-19: Multiple Isolated Single STOPS (Spaced presses never falsely force stop)
25 [PASS] TC-20: Null Pointer and API Resilience (Zero segmentation faults, robust error handling)
26 [PASS] TC-21: Consecutive Multi-Cycle Sessions (Flawless back-to-back operations without leakage)
27 [PASS] TC-22: Boundary Double-Stop Timing (Exact 1499ms hit vs 1501ms expiration verified)
28 [PASS] TC-23: Single STOP in READY (Preserves accumulated deposit against accidental touch)
29 [PASS] TC-24: Granular Fault Diagnostics (Multi-sensor bitmask tracking and string reports)
30 [PASS] TC-25: Arithmetic Overflow Resilience (MISRA-C Rule 12.4 wrap-around defense)

```



```
31 [PASS] TC-26: Multi-Phase Wash Profile (Agitate -> Spin/Drain -> Complete verified)
32 [PASS] TC-27: Event Acceptance Query Protocol (Deterministic event filtering across all 5 states)
33 [PASS] TC-28: Cycle Sub-Phase Query & Enum Decoders (Correct phase detection throughout cycle)
34 [PASS] TC-29: Pause Across Phase Boundary (Continuous timer crosses into Spin)
35 [PASS] TC-30: MISRA-C Boundary & Corrupted Enum Resilience (100% defensive branch safety)
36 [PASS] TC-31: COLLECTING State (RLED on until the 50¢ threshold, then READY)
37 [PASS] TC-32: Cancel Returns Deposit (STOP x2 in COLLECTING/READY refunds; RUN still zero-refund)
38 [PASS] TC-33: Fault Preserves Deposit (COLLECTING/READY restored after the fault is cleared)
39 [PASS] TC-34: Fault During Cycle (timer keeps counting, cleared fault resumes in PAUSED, expiry
    respected)
40
41 =====
42 ALL 34 TESTS PASSED SUCCESSFULLY! (100% Specification & Transition Coverage)
43 =====
```

Listing 21: make test_hal – HAL engines

```
1 =====
2 BTL 2: Hardware HAL Engines - Unit Verification
3 CQ3053 Embedded Systems - HCMUT
4 =====
5
6 [PASS] HAL-01: Button Debounce (30ms glitch rejection, overflow defense and edge detection)
7 [PASS] HAL-02: Coin Pulse Validation (Multi-pulse train decoding verified)
8 [PASS] HAL-03: LED Blinker Waveforms (Accurate 1.0 Hz and 2.0 Hz non-blocking timing & zero-drift)
9 [PASS] HAL-04: Actuator Interlock Guard (Strict hardware protection rules verified)
10 [PASS] HAL-05: Coin Pulse FIFO Queue (Burst coin insertion without event drops)
11 [PASS] HAL-06: NULL Pointer Resilience (Zero crash across all HAL API functions)
12
13 =====
14 ALL 6 HARDWARE HAL ENGINE TESTS PASSED!
15 =====
```

Listing 22: make test_gesture – single-button gestures

```
1 === Single-button gesture tests ===
2 [PASS] click is delayed until the double-click gap expires
3 [PASS] short press -> exactly one CLICK
4 [PASS] two short presses -> exactly one DOUBLE (no CLICK)
5 [PASS] hold 0.6 s -> HOLD1 while still pressed
6 [PASS] keep holding to 1.2 s -> HOLD2
7 [PASS] no repeat events while the key stays down
8 [PASS] no CLICK after a hold is released
9 [PASS] release between 0.6 s and 1.2 s -> HOLD1_END
10 [PASS] release after 1.2 s -> no HOLD1_END
11 [PASS] press-release-hold -> HOLD1, pending click dropped
12 [PASS] HOLD1->HOLD2 interval fits inside the FSM STOP double-press window
13 [PASS] init STANDBY
14 [PASS] DOUBLE in STANDBY -> +10c (COLLECTING)
15 [PASS] CLICK in STANDBY -> +50c -> READY
16 [PASS] CLICK in READY -> RUNNING
17 [PASS] CLICK in RUNNING -> PAUSED
18 [PASS] CLICK in PAUSED -> RUNNING (resume)
19 [PASS] DOUBLE while RUNNING -> door-open fault -> ERROR
```



```
20 [PASS] CLICK in ERROR -> cleared, cycle resumes in PAUSED
21 [PASS] STANDBY after clearing / force stop
22 [PASS] restart cycle
23 [PASS] HOLD1 only arms STOP
24 [PASS] HOLD2 completes force STOP -> STANDBY
25 [PASS] fault injected
26 [PASS] HOLD in ERROR clears the fault (deposit/cycle context restored by the FSM)
27 [PASS] ext RUN/PAUSE ignored in STANDBY
28 [PASS] ext RUN/PAUSE: READY -> RUNNING
29 [PASS] ext RUN/PAUSE: RUNNING -> PAUSED
30 [PASS] ext RUN/PAUSE: PAUSED -> RUNNING
31 [PASS] ext STOP: single press only arms
32 [PASS] ext STOP: double press -> STANDBY
33 [PASS] ext STOP clears ERROR
34 Passed: 32, Failed: 0
```

Listing 23: make test_two_button – front panel

```
1 === Two-button front panel tests ===
2 [PASS] K1 click: +10c staged, FSM untouched
3 [PASS] K1 double-click: +20c
4 [PASS] K1 HOLD1 alone changes nothing (still deciding)
5 [PASS] K1 hold+release: +50c, still waits for confirm
6 [PASS] K1 hold to 1.2 s with 80c -> READY, 30c change returned
7 [PASS] FSM balance is exactly the fare
8 [PASS] exactly 50c -> READY, no change
9 [PASS] 30c confirm -> not enough, 30c refunded, stays STANDBY
10 [PASS] confirm with nothing inserted -> not enough
11 [PASS] staged coins are capped
12 [PASS] K0 click +10c, K0 hold +20c
13 [PASS] READY: K1 click -> RUNNING
14 [PASS] RUNNING: K0 click -> PAUSED
15 [PASS] PAUSED: K0 click -> RUNNING
16 [PASS] K0 hold outside STANDBY adds no money
17 [PASS] K1 hold 2 stages while RUNNING -> force STOP
18 [PASS] ERROR clears staged coins
19 [PASS] K0 click in ERROR clears the fault
20 ALL TWO-BUTTON TESTS PASSED
```

Listing 24: make test_ui_text – UART status line

```
1 [PASS] returned length matches
2 [PASS] RUNNING line
3 [PASS] STANDBY shows full cycle time, coin and fault
4 [PASS] truncation is safe and NUL-terminated
5 ALL UI TEXT TESTS PASSED
```