Nguyen Anh Tuan

TRƯỜNG ĐẠI HỌC
SƯ PHẠM KỸ THUẬT TP. HỒ CHÍ MINH
HCMC University of Technology and Education
HCMUTE

HỆ THỐNG THI TRẮC NGHIỆM TRỰC TUYẾN

TRUNG TÂM CÔNG NGHỆ THÔNG TIN

Call Us: (+84 - 8) 38968641 - (+84 - 8) 38961333 Email: ic@hcmute.edu.vn

Bắt đầu vào lúc Thứ hai, 5 Tháng sáu 2017, 1:13 PM
State Finished
Kết thúc lúc Thứ hai, 5 Tháng sáu 2017, 2:23 PM
Thời gian thực hiện 1 giờ 10 phút

Câu hỏi 1
Hoàn thành
Đạt điểm 0,50

Which are correct action for SCASW string operation if DF is reset (=0)

Select one or more:
- [ ] decrease DI by 2
- [ ] compare value in AL register with memory location pointed by ES:[DI]
- [x] increase DI by 2
- [x] compare value in AL register with memory location pointed by DS:[SI]

Câu hỏi 2
Hoàn thành
Đạt điểm 0,50

the instruction, CMP to compare source and destination operands by _____

Select one:
- ( ) adding
- ( ) dividing
- (•) comparing
- ( ) subtracting

studeersnel
messages.pdf_cover_qr_code_label
messages.downloaded_by

Câu hỏi 3

Hoàn thành

Đạt điểm 1,00

What is the correct value of SI, AL (in hex) at watch point:

```
01:             MOV SI, 300h
02:             MOV AL, 10h
03:             MOV CX, 7
04: Loop_label:
05:             MOV [SI], AL
06:             ADD AL,10h
07:             INC  SI
08:             LOOP Loop_label
```

watch point:

SI 307h ▾

AL = 70 ▾

Câu hỏi 4

Hoàn thành

Đạt điểm 1,50

Given a row of memory image in debug

072C:FFF0 00 00 00 01 00 00 2C 07 - 07 01 2C 07 17 72 00 00

SS=072C, SP=FFF8, DS = 072C

Assume the stack now stores two (2) 16-bit parameters and one (1) 16-bit return address in following order: stack top (return address) >> parameter #1 >> parameter #2.

The following sequence of instructions are executed. What is the correct values at watch points?

```
MOV BP, SP
```

watch point #1 (BP):

```
MOV AX, [BP+2]
```

watch point #2 (AX):

```
ADD AX, [BP+4]
```

watch point #3 (AX):

```
MOV DI, 120
MOV [DI], AX
```

watch point #1: BP = FFF8 ▾

watch point #2: AX = 072C ▾

watch point #3: AX = 7943 ▾

studeersnel

messages.pdf_cover_qr_code_label

messages.downloaded_by



Câu hỏi 5

Hoàn thành

Đạt điểm 1,00

In computer, how does the processor serve multiple interrupt request from devices?

Select one:

- Device with higher priority will use interrupt enable flag
- The processor can not process multiple interrupt requests
- Each device are assigned an interrupt priority, the device with higher priority will be served.
- Each device are assigned an interrupt priority, the device with lower priority will be served.

Câu hỏi 6

Hoàn thành

Đạt điểm 1,20

Given a code snippet:

```
if (a>=0 && a <=9)
   x = a + 30h;
else if (a >=10 && a <=15)
   x = a + 55;
```

The logic of the above code snippet in assembly is (with missing lines):

```
01:      CMP DL, 0
02:      ---------- ; possibly missing code
03:      CMP DL, 9
04:      ---------- ; possibly missing code
05:      ADD DL, 30h
06:      ---------- ; possibly missing code
a_label:
08:      CMP DL, 0Fh
09:      ---------- ; possibly missing code
10:      ADD DL, 55
x_label:
12:      MOV AL, DL
...
```

Choose correct missing instructions in the above sequence of instructions

04: JA a_label ▾

06: JMP x_label ▾

09: JA x_label ▾

02: JB x_label ▾

studeersnel

messages.pdf_cover_qr_code_label

messages.downloaded_by



Câu hỏi 7

Hoàn thành

Đạt điểm 0,50

In multiplication instruction, when the value of source operand is 12 (decimal), the other operand is loaded in AX. Which registers can be used to load source operand?

Select one or more:

- [x] DL
- [ ] DX
- [x] CL
- [ ] AX
- [ ] BX

Câu hỏi 8

Hoàn thành

Đạt điểm 1,00

The following sequence of instructions are executed. What is the correct value of AX, DX at watch point?

```
MOV DL,FF
MOV AL,42
IMUL  DL
```

watch point:

AX = FFBE ▾

DX = 00FF ▾

studeersnel

messages.pdf_cover_qr_code_label
messages.downloaded_by

Câu hỏi 9

Hoàn thành

Đạt điểm 1,00

Memory dump at 1D20:0200 as below:

1D20:0200 00 20 10 5D 55 47 00 90 - 00 10 20 30 40 50 60 70

Given value of registers:

DS = 1D20, ES = 1D20,

DI = 20A, SI = 208,

BX = 202, AX = 0103, CX = 0003

and flag bit DF = 1

What is the correct value of AX, SI, DI registers after the instruction REP LODSW is executed?

AX = 4755h

DI = 020Ch

SI = 020Ah

Câu hỏi 10

Hoàn thành

Đạt điểm 0,50

The instruction that subtracts 1 from the contents of the specified register/memory location is

Select one:

- SUB
- DEC
- INC
- SBB

Câu hỏi 11

Hoàn thành

Đạt điểm 0,50

To test one bit in a byte value which can be destructive. use _____ instruction.

Select one:

- OR
- AND
- TEST
- NOT

studeersnel

messages.pdf_cover_qr_code_label
messages.downloaded_by

Câu hỏi 12

Không trả lời

Đạt điểm 1,00

Part of memory shown in figure



What is the value of AH follow the execution of this code:

MOV BX, 1D4D

MOV AX, [BX]

Answer:

Câu hỏi 13

Hoàn thành

Đạt điểm 1,50

Which are correct about the Pointer registers of IA-32 processors:

Select one or more:

- [x] Stack Pointer (ESP): the 32 bit pointer to the top of stack
- [x] Base Pointer (EBP): The 32 bit pointer refers to stack memory
- [ ] Base Pointer (BP): The 16 bit pointer refers to stack memory
- [ ] Instruction Pointer (IP): the 16 bit register points to the next instruction to be execute
- [ ] Stack Pointer (SP): the 16 bit pointer to the top of stack
- [x] Instruction Pointer (EIP): the 32 bit register points to the next instruction to be execute

studeersnel

messages.pdf_cover_qr_code_label
messages.downloaded_by



Câu hỏi 14

Không trả lời

Đạt điểm 1,00

Memory dump at 1D20:0200 shown as below:

1D20:0200 00 20 10 5D 55 47 00 90 - 00 10 20 30 40 50 60 70

Given value of registers:

DS = 1D20, ES = 1D20, DI = 20A

The following sequence of instructions is being executed:

```
MOV SI,208h
MOV AX,0040h
MOV CX,000Ah
CLD
REPNZ SCASB
```

watch point:

. . . . .

What is the correct value of AX, SI, DI registers at watch point?

DI = Chọn...

SI = Chọn...

AX = Chọn...

Câu hỏi 15

Hoàn thành

Đạt điểm 1,00

The following sequence of instructions are executed. What is the correct value of flag bits at watch point?

```
MOV DL,19
MOV AL,F6
IMUL  DL
```

watch point:

OF = set

CF = set

studeersnel

messages.pdf_cover_qr_code_label
messages.downloaded_by

Câu hỏi 16

Hoàn thành

Đạt điểm 0,50

Which are correct input for XLAT instruction

Select one or more:

- [ ] look-up index must be loaded into DL
- [ ] DS:[SI] pointed to look-up table
- [x] DS:[BX] pointed to look-up table
- [ ] look-up index must be loaded into AL

Câu hỏi 17

Hoàn thành

Đạt điểm 1,20

Convert 39887.5625 to IEEE 32-bit floating point format (1 sign+ 8 exponent + 23 mantissa) in hex

Answer: 471C3390

Câu hỏi 18

Hoàn thành

Đạt điểm 1,00

The following sequence of instructions are executed. What is the correct value of flag bits at watch point?

```
MOV AL, 78
MOV BL, 2
MUL  BL
```

watch point:

Carry flag (CF) = set

Overflow flag (OF) = set

Câu hỏi 19

Hoàn thành

Đạt điểm 0,50

Which are correct action for LODSW string operation if DF is reset (=0)

Select one or more:

- [x] decrease DI by 2
- [ ] Load 16-bit value at memory location pointed by DS:[SI] into AX
- [x] Load 16-bit value at memory location pointed by ES:[DI] into AX
- [ ] increase SI by 2

studeersnel

messages.pdf_cover_qr_code_label
messages.downloaded_by



Câu hỏi 20

Hoàn thành

Đạt điểm 1,00

Major structural components of the CPU include:

Select one or more:

- [x] Arithmetic and Logic Unit
- [ ] Instruction Pointer (PC)
- [ ] Instruction Register
- [x] Interconnections
- [x] Registers
- [x] Control Unit

Câu hỏi 21

Hoàn thành

Đạt điểm 1,00

Basic functions that a computer can perform including:

Select one or more:

- [x] Data processing
- [x] Data movement
- [x] Control
- [ ] Direct memory access
- [x] Data storage
- [ ] Interrupt

Câu hỏi 22

Hoàn thành

Đạt điểm 1,00

Enter debug command to fill 250 bytes in the memory segment FED5 in computer memory starting from 100 with value AD

Answer: F FED5:[0100]

Câu hỏi 23

Hoàn thành

Đạt điểm 0,50

The instruction, MOV AX, 1234h is an example of

Select one:

- register addressing mode
- Immediate addressing mode
- based index addressing mode
- direct addressing mode

studeersnel

messages.pdf_cover_qr_code_label
messages.downloaded_by



Câu hỏi 24

Không trả lời

Đạt điểm 1,00

Part of computer memory are shown in figure.



What is the value of AX register after instruction **MOV AX, 1D49** executed

Answer:

Câu hỏi 25

Hoàn thành

Đạt điểm 1,00

The following sequence of instructions are executed. What is the correct value of EAX, EBX, EDX at watch point?

```
MOV EAX,00002000
MOV EBX,00100000
MUL  EBX
```

watch point:

EDX = 00000002

EAX = 00000000

EBX = 00100000

studeersnel

messages.pdf_cover_qr_code_label
messages.downloaded_by

Câu hỏi 26

Hoàn thành

Đạt điểm 1,20

Given a code snippet to look for a value (from AL) in memory buffer Buff

```
Buff      DB   11,22,33,44,55
          .................
01:       LEA  DI, Buff
02:       ------------ ; possibly missing code
03:       MOV AL,33
04:       MOV CX,5
a_label:
05:       ------------ ; possibly missing code
06:       CMP Byte Ptr [DI],AL
07:       ------------ ; possibly missing code
08:       LOOPNZ a_label
...
```

Choose correct missing instructions in the above sequence of instructions

05: Empty ▾

02: Empty ▾

07: INC DI ▾

Câu hỏi 27

Hoàn thành

Đạt điểm 0,50

In multiplication instruction, the result is taken from AX means the source operand is _____ bit

Select one:

- 4
- 8
- 16
- None of the choices are correct

studeersnel

messages.pdf_cover_qr_code_label
messages.downloaded_by



Câu hỏi 28

Không trả lời

Đạt điểm 1,20

Given an assembly code copying the memory buffer Buff1 to Buff2:

```
        PUSH DS
        POP   ES
        LEA   SI, Buff1
        LEA   DI, Buff2
        MOV  CX,20
        ;--- Start of block
cp_loop:
        MOV  AL, Byte Ptr [SI]
        MOV  Byte Ptr ES:[DI], AL
        INC   SI
        INC   DI
        LOOP cp_loop
        ; ---End of block
```

Choose equivalent string operations in place of block code from ---Start of block to ---End of block

Select one or more:

- CLD
  ```
  cp_loop:
      MOVSB
      LOOP cp_loop
  ```
- CLD
  ```
  REP MOVSB
  ```
- CLD
  ```
  cp_loop:
      REP MOVSB
      LOOP cp_loop
  ```
- STD
  ```
  cp_loop:
      MOVSB
      LOOP cp_loop
  ```

Câu hỏi 29

Hoàn thành

Đạt điểm 0,50

the instruction, JMP C008:2000h is an example of

Select one or more:

- intersegment jump
- intrasegment mode
- near jump
- far jump

studeersnel

messages.pdf_cover_qr_code_label
messages.downloaded_by



Câu hỏi 30

Hoàn thành

Đạt điểm 1,00

The following sequence of instructions are executed. What is the correct value of AX and DX (in hex) at watch point?

```
MOV AX,FFF6h
MOV CX,1000h
IMUL  CX
```

watch point:

DX= FFFF ▾

AX= 6000 ▾

studeersnel

messages.pdf_cover_qr_code_label
messages.downloaded_by



Câu hỏi 31

Hoàn thành

Đạt điểm 1,20

Given a code snippet:

```
int ax, bx;
...
if (ax >= bx)
   ax -=bx;
else
   bx -=ax;
```

What is the equivalent logic sequence of instructions in Assembly

Select one:

-
```
cmp ax,bx
 ja  a_label
 sub ax,bx
 jmp x_label
a_label:
 sub bx,ax
x_label:
```

-
```
cmp ax,bx
 jl  a_label
 sub ax,bx
 jmp x_label
a_label:
 sub bx,ax
x_label:
```

-
```
cmp ax,bx
 jbe a_label
 sub ax,bx
 jmp x_label
a_label:
 sub bx,ax
x_label:
```

-
```
 cmp ax,bx
 jge  a_label
 sub ax,bx
 jmp x_label
a_label:
 sub bx,ax
x_label:
```

studeersnel

messages.pdf_cover_qr_code_label
messages.downloaded_by



Câu hỏi 32

Hoàn thành

Đạt điểm 1,00

Which are valid based indexed addressing?

Select one or more:

- [x] [BX][SI]
- [ ] [BP][SI]
- [ ] [DX][DI]
- [ ] [SP][SI]

Câu hỏi 33

Hoàn thành

Đạt điểm 1,00

Which statements are correct for HDDs?

Select one or more:

- [ ] Bits are store randomly on disk surfaces
- [x] Head, Track, Cylinder are key parameters for access data on hard disk
- [x] Head, Track, Sector are key parameters for access data on hard disk
- [ ] Bits are stored on tracks

Câu hỏi 34

Hoàn thành

Đạt điểm 1,00

What are components of Von Neumann, namely IAS computer?

Select one or more:

- [x] I/O Equipments
- [x] CPU
- [ ] Punched card reader
- [ ] Monitor
- [x] Memory
- [x] Bus

studeersnel

messages.pdf_cover_qr_code_label
messages.downloaded_by



Câu hỏi 35

Không trả lời

Đạt điểm 1,20

Consider the following assembly instruction sequence

```
        XOR BX, BX
        CMP DL, 5
        JLE   a_label
        CMP DL,17h
        JGE  a_label
        MOV BX, 10h
a_label:
        INC BX
```

watch point:

...

Choose correct value of BX register at watch point for different value of DL?

DL=0Ah Chọn...

DL=0FFh Chọn...

DL=17h Chọn...

DL=10 Chọn...

Câu hỏi 36

Hoàn thành

Đạt điểm 1,00

Given a row of memory image in debug

0AE8:0120 13 96 D0 E0 D0 E0 A2 1E - 99 80 3E 20 99 00 75 24

Initially, AX=BX=CX=DX=0, SI=128

What are value of AX,DX after execution of the following instructions?

```
MOV EDX, [SI]
MOV EAX, [SI+4]
```

EDX = 203E8099

EAX = 24750099

studeersnel

messages.pdf_cover_qr_code_label
messages.downloaded_by



Câu hỏi 37

Hoàn thành

Đạt điểm 0,50

To set one or more bits in a byte value, use _____ instruction.

Select one:

- OR
- NOT
- AND
- XOR

Câu hỏi 38

Hoàn thành

Đạt điểm 0,50

The instruction that loads effective address is

Select one:

- LEA
- LDS
- LES
- LAHF

Câu hỏi 39

Hoàn thành

Đạt điểm 0,50

After each execution of POP instruction, the stack pointer is

Select one:

- increment by 2
- decrement by 1
- increment by 1
- decrement by 2

Câu hỏi 40

Hoàn thành

Đạt điểm 1,00

Physical address of a memory location is 5FE2E. This memory address located by DI register which now has value of 993E. Compute the memory address of data segment register

Answer: 564f

Câu hỏi 41

Hoàn thành

Đạt điểm 1,20

Write mask byte (in hex) to clear the lower 4 bit of a byte value with AND instruction.

Answer: F0

studeersnel

messages.pdf_cover_qr_code_label
messages.downloaded_by

Câu hỏi 42

Hoàn thành

Đạt điểm 1,20

Convert the 32-bit floating point number 44363C00 (in hex) to decimal.

Answer: 728,9375

Câu hỏi 43

Không trả lời

Đạt điểm 1,00

The following sequence of instructions are executed. What is the correct value of flag bits at watch point?

```
MOV AL,-5
ADD  AL,132
ADD  AL,1
```

watch point:

Sign flag (SF) Chọn...

Overflow flag (OF) = Chọn...

Carry flag (CF) = Chọn...

Zero flag (OF) = Chọn...

Câu hỏi 44

Hoàn thành

Đạt điểm 1,00

Select correct match for AL and carry flag at watch point #1:

```
MOV BL, 8C
MOV AL, 7E
ADD AL, BL
```

watch point #1:

.....

Carry flag 6A

AL 0A

studeersnel

messages.pdf_cover_qr_code_label
messages.downloaded_by



Câu hỏi 45

Hoàn thành

Đạt điểm 1,00

Choose correct features for SRAM and DRAM

SRAM: Faster access time, cost more per bit, smaller size

DRAM: Slower access time, cheaper cost per bit, can manufacture with larger size

VỀ CHÚNG TÔI

Trường Đại học Sư phạm Kỹ thuật TP HCM sẽ trở thành trung tâm đào tạo, nghiên cứu khoa học, đổi mới sáng tạo và khởi nghiệp hàng đầu Việt Nam, ngang tầm với các trường đại học uy tín trong khu vực và thế giới.
Read More »

THÔNG TIN

Tin tức - Sự kiện

Tuyển sinh

Thông báo

Học bổng- việc làm

LIÊN HỆ CHÚNG TÔI

1 Võ Văn Ngân, Phường Linh Chiểu, Quận Thủ Đức, Thành phố Hồ Chí Minh
Phone: (+84 - 8) 38968641 - (+84 - 8) 38961333
E-mail: ic@hcmute.edu.vn

Follow us

Copyright © 2016, HCMC University Of Technology and Education. All Rights Reserved. Powered by IT
studeersnel
messages.pdf_cover_qr_code_label
messages.downloaded_by