Prova 1

①



$x_{1_0} = a_1 \quad \dot{x}_{1_0} = v_{1_0} \quad x_{2_0} = a_2 \quad \dot{x}_{2_0} = v_{2_0}$

Equazioni di Lagrange $\rightarrow$ non ci sono forze attive

$\frac{d}{dt}\left(\frac{\partial T}{\partial \dot{q}_i}\right) - \frac{\partial T}{\partial q_i} + \frac{\partial U}{\partial q_i} + \frac{\partial D}{\partial \dot{q}_i} = Q_i$

- $T = T_1 + T_2 \qquad T_1 = \frac{1}{2} m_1 \dot{y}_1^2 \quad (m_1 \ddot{w})$

$\dot{y}_1 = \dot{w} + \frac{d}{dt}\left(\begin{matrix} l\cos\theta_1 \\ l\sin\theta_1 \end{matrix}\right) = \begin{pmatrix} \dot{w} - l\dot{\theta}_1\sin\theta_1 \\ l\dot{\theta}_1\cos\theta_1 \end{pmatrix} \Rightarrow \dot{y}_1^2 = \dot{w}^2 + l^2\dot{\theta}_1^2\cos^2\theta_1 - 2l\dot{w}\dot{\theta}_1\sin\theta_1$

$T_1 = \frac{1}{2} m_1 \left(\dot{w}^2 + l^2\dot{\theta}_1^2\cos^2\theta_1 - 2l\dot{w}\dot{\theta}_1\sin\theta_1 \right) \qquad \dot{w}^2 \rightarrow \frac{1}{2} m_1 \dot{w}^2$

$T_2 = \frac{1}{2} m_2 \dot{w}^2$

$T_2 = \frac{1}{2} m_2 \dot{w}^2$

- $U = U_1 + U_2$

$U_1 = -m_1 g l \cos\theta_1 \qquad U_2 = -m_2 g \left(l\cos\theta_1 + \frac{l}{2}\cos\theta_2 \right) = -mgl\left(\cos\theta_1 + \frac{1}{2}\cos\theta_2\right)$

$U_{1_0} = -\frac{1}{2} m \cdot g l \cdot 1 \qquad = -\frac{1}{2} k \left(\frac{l}{2}(\cos\theta_1 - 1) - \frac{l}{2}(\cos\theta_2 - 1) \right)^2 = -\frac{kl^2}{8}\left(\cos\theta_1 - \cos\theta_2\right)^2$

$U_2 = -mgl\left(\cos\theta_1 + \frac{1}{2}\cos\theta_2\right) + \frac{kl^2}{8}\left(\cos\theta_1 - \cos\theta_2\right)^2$

$\Rightarrow U = -mgl\left(\cos\theta_1 + \frac{1}{2}\cos\theta_2\right) + \frac{kl^2}{8}\left(\cos\theta_1 - \cos\theta_2\right)^2$

$\Rightarrow U = \frac{k}{2}\left(\frac{l}{2}\right)^2 \left(\cos\theta_1 - \cos\theta_2\right)^2 - mgl\left(\cos\theta_1 + \frac{1}{2}\cos\theta_2\right)$

$\frac{k}{2}\left(\frac{l}{2}\right)^2 = \frac{kl^2}{8}$

$\delta(\cos\theta_1 - \cos\theta_2) = \frac{\partial}{\partial\theta_1}(\cos\theta_1 - \cos\theta_2)\delta\theta_1 + \frac{\partial}{\partial\theta_2}(\cos\theta_1 - \cos\theta_2)\delta\theta_2 = -\sin\theta_1\delta\theta_1 + \sin\theta_2\delta\theta_2$

$\delta U = \frac{kl^2}{8}\left(\cos\theta_1 - \cos\theta_2\right)\left(-\sin\theta_1\delta\theta_1 + \sin\theta_2\delta\theta_2\right) + mgl\sin\theta_1\delta\theta_1 + \frac{1}{2}mgl\sin\theta_2\delta\theta_2$

$\delta U = \left[\frac{kl^2}{8}\left(\cos\theta_1 - \cos\theta_2\right)\left(-\sin\theta_1\right) + mgl\sin\theta_1\right]\delta\theta_1 + \left[\frac{kl^2}{8}\left(\cos\theta_1 - \cos\theta_2\right)\sin\theta_2 + \frac{1}{2}mgl\sin\theta_2\right]\delta\theta_2$

$\delta U = \left[\frac{kl^2}{8}\left(\cos\theta_2 - \cos\theta_1\right)\sin\theta_1 + mgl\sin\theta_1\right]\delta\theta_1 + \left[\frac{kl^2}{8}\left(\cos\theta_1 - \cos\theta_2\right)\sin\theta_2 + \frac{1}{2}mgl\sin\theta_2\right]\delta\theta_2$

$\delta U = Q_1\delta\theta_1 + Q_2\delta\theta_2$

$Q_1 = \frac{kl^2}{8}\left(\cos\theta_2 - \cos\theta_1\right)\sin\theta_1 + mgl\sin\theta_1$

$Q_2 = \frac{kl^2}{8}\left(\cos\theta_1 - \cos\theta_2\right)\sin\theta_2 + \frac{1}{2}mgl\sin\theta_2$

- Calcolo delle D_i

$\frac{\partial L}{\partial \dot{\theta}_i} = \frac{\partial T}{\partial \dot{\theta}_i} + \frac{\partial U}{\partial \dot{\theta}_i} = \frac{\partial T}{\partial \dot{\theta}_i}$ poiché $\frac{\partial U}{\partial \dot{\theta}_i} = 0$

$\frac{\partial L}{\partial \dot{\theta}_i} = \frac{\partial T_1}{\partial \dot{\theta}_i} + \frac{\partial T_2}{\partial \dot{\theta}_i}$ poiché $\frac{\partial T_2}{\partial \dot{\theta}_i} = 0$

$\frac{\partial T_1}{\partial \dot{\theta}_i} = \frac{\partial T_1}{\partial \dot{\theta}_1} + \frac{\partial T_1}{\partial \dot{\theta}_2}$ poiché $\frac{\partial T_1}{\partial \dot{\theta}_3} = 0$

$T_1 = \frac{1}{2} m_1 \dot{y}_1^2 = \frac{1}{2} m_1 \left(\dot{w}^2 + l^2\dot{\theta}_1^2\cos^2\theta_1 - 2l\dot{w}\dot{\theta}_1\sin\theta_1 \right)$

$\frac{\partial T_1}{\partial \dot{\theta}_1} = \frac{1}{2} m_1 \left(2l^2\dot{\theta}_1\cos^2\theta_1 - 2l\dot{w}\sin\theta_1 \right) = m_1 l^2\dot{\theta}_1\cos^2\theta_1 - m_1 l\dot{w}\sin\theta_1$

$\frac{\partial T_1}{\partial \dot{\theta}_2} = 0$

$\frac{\partial T_2}{\partial \dot{\theta}_1} = 0 \qquad \frac{\partial T_2}{\partial \dot{\theta}_2} = \frac{1}{2} m_2 \left(\frac{l}{2} \right)^2 2\dot{\theta}_2 = \frac{1}{4} m_2 l^2 \dot{\theta}_2$

$\Rightarrow \frac{\partial L}{\partial \dot{\theta}_1} = m_1 l^2\dot{\theta}_1\cos^2\theta_1 - m_1 l\dot{w}\sin\theta_1 \qquad \frac{\partial L}{\partial \dot{\theta}_2} = \frac{1}{4} m_2 l^2 \dot{\theta}_2$

$\Rightarrow D_1 = -\frac{\partial L}{\partial \dot{\theta}_1} = -m_1 l^2\dot{\theta}_1\cos^2\theta_1 + m_1 l\dot{w}\sin\theta_1 \qquad D_2 = -\frac{\partial L}{\partial \dot{\theta}_2} = -\frac{1}{4} m_2 l^2 \dot{\theta}_2$

- Equazioni

$\begin{cases} m_1 l^2\ddot{\theta}_1 + \frac{kl^2}{8}\left(\cos\theta_1 - \cos\theta_2\right)\sin\theta_1 + mgl\sin\theta_1 = -m_1 l^2\dot{\theta}_1^2\cos\theta_1\sin\theta_1 + m_1 l\ddot{w}\sin\theta_1 \\ m_2 l^2\ddot{\theta}_2 + \frac{kl^2}{8}\left(\cos\theta_2 - \cos\theta_1\right)\sin\theta_2 + \frac{1}{2}mgl\sin\theta_2 = -\frac{1}{4} m_2 l^2\dot{\theta}_2^2 \end{cases}$

$\Rightarrow \begin{cases} m_1 l^2\ddot{\theta}_1 + \frac{kl^2}{8}\left(\cos\theta_1 - \cos\theta_2\right)\sin\theta_1 + mgl\sin\theta_1 - m_1 l\ddot{w}\sin\theta_1 = -m_1 l^2\dot{\theta}_1^2\cos\theta_1\sin\theta_1 \\ m_2 l^2\ddot{\theta}_2 + \frac{kl^2}{8}\left(\cos\theta_2 - \cos\theta_1\right)\sin\theta_2 + \frac{1}{2}mgl\sin\theta_2 = -\frac{1}{4} m_2 l^2\dot{\theta}_2^2 \end{cases}$

$\begin{cases} \ddot{x}_1 = \ddot{\theta}_1 \\ \ddot{x}_2 = -\frac{1}{2}\ddot{\theta}_2 - \left(\cos\theta_1\ddot{\theta}_1 - \left(\sin\theta_1\right)\dot{\theta}_1^2\right) = -\frac{1}{2}\ddot{\theta}_2 + \sin\theta_1\dot{\theta}_1^2 - \cos\theta_1\ddot{\theta}_1 \\ \dot{x}_1 = \dot{\theta}_1 \\ \dot{x}_2 = -\frac{1}{2}\dot{\theta}_2 - \left(\cos\theta_1\dot{\theta}_1 - \left(\sin\theta_1\right)\dot{\theta}_1^2\right) = -\frac{1}{2}\dot{\theta}_2 + \sin\theta_1\dot{\theta}_1^2 - \cos\theta_1\dot{\theta}_1 \end{cases}$

②



$x = \begin{pmatrix} x_1 \\ x_2 \end{pmatrix}$

$M\ddot{x} + Kx = 0 \qquad \Rightarrow \begin{cases} \ddot{x}_1 = \dots \\ \ddot{x}_2 = \dots \end{cases}$

$-x_1 - C\dot{x}_2 - \frac{k_2}{k_1}x_2 = 0$

$A = \begin{bmatrix} 0 & I \\ -\frac{K}{M} & -\frac{C}{M} \end{bmatrix} = \begin{bmatrix} 0 & I \\ -K & -C \end{bmatrix} \qquad B = \begin{bmatrix} 0 \\ I \end{bmatrix}$

$y(t) = x_1 \qquad \Rightarrow \qquad C = \begin{bmatrix} 1 & 0 \end{bmatrix} \qquad D = 0$

- Luogo $R = 100 \quad C = 0$ esce

Calcolo $y(t)$ a partire da $x_{1_0} = \begin{pmatrix} 1 \\ 0 \end{pmatrix}$

$A = \begin{bmatrix} 0 & 1 \\ -\frac{k_1+k_2}{m} & 0 \end{bmatrix} = \begin{bmatrix} 0 & 1 \\ -100 & 0 \end{bmatrix} \qquad B = \begin{bmatrix} 0 \\ 1 \end{bmatrix}$

$y(t) = C\,e^{At}\,x_{1_0} + C\int_0^{t} e^{A(t-\tau)}\,B\,u(\tau)\,d\tau$

$e^{At} = \mathcal{L}^{-1}\left\{(sI - A)^{-1}\right\}$

$sI - A = \begin{bmatrix} s & -1 \\ 100 & s \end{bmatrix} \qquad \det(sI - A) = s^2 + 100 \neq 0 \qquad s_{1,2} = \pm 10j$

$\Rightarrow \omega_n = 10 \qquad e^{At}$

$\psi_n(t)$ è nulla perché $\psi_n = Kx\,\ddot{e}^{\lambda t} + Kx = 0$

Multiamo a 2 membri

$\begin{cases} \psi_n(0) \\ \dot{\psi}_n(0) \end{cases}$

$\psi_n(0) = Kx_1 + Kx_2 + \dots \qquad \psi_n = \frac{-k_1}{c} - \frac{k_2}{c} = \frac{-k_1}{\omega_n m} - \frac{k_2}{\omega_n m}$

$\dot{\psi}_n(0) = \frac{-k_1}{c}\dot{x}_1 - \frac{k_2}{c}\dot{x}_2 + \dots = 0$

$\psi_n(0) = \frac{d}{dt}\left(Kx\,\ddot{e}^{\lambda t} + Kx\right) = 0$

$\Rightarrow \begin{cases} Kx_1 + Kx_2 + \dots = 0 \\ -Kx_1 + \dots = 0 \end{cases} \Rightarrow \begin{cases} Kx_1 = -Kx_2 \\ Kx_1 = \dots \end{cases} \qquad \Rightarrow \quad \psi_n(0) = -Kx_2 - Kx_2 = -2Kx_2$

- Modulo e argomento della risposta armonica -

$(sI - A)^{-1} = \begin{bmatrix} \frac{s}{s^2+100} & \frac{1}{s^2+100} \\ \frac{-100}{s^2+100} & \frac{s}{s^2+100} \end{bmatrix} \qquad C \cdot (\dots) = \begin{bmatrix} \frac{s}{s^2+100} & \frac{1}{s^2+100} \end{bmatrix} \qquad Q = \begin{bmatrix} 1 \\ 0 \end{bmatrix}$

$G(s) = C\,(sI - A)^{-1}\,B \qquad \Rightarrow \quad C = 1 \cdot \begin{bmatrix} \frac{s}{s^2+100} & \frac{1}{s^2+100} \end{bmatrix} \begin{bmatrix} 0 \\ 1 \end{bmatrix}$

$\Rightarrow \quad C = 1 \cdot \begin{bmatrix} \frac{s}{s^2+100} & \frac{1}{s^2+100} \end{bmatrix} \begin{bmatrix} 0 \\ 1 \end{bmatrix} = \frac{1}{s^2+100} \qquad G(s) = \frac{100}{s^2+100} = \frac{100}{(s+10j)(s-10j)}$

$\omega_n = 10 \Rightarrow \frac{100}{-\omega_n^2 + 100} = \frac{100}{0} \rightarrow \infty$ $\quad \xi = 0$

modulo $\left|\frac{100}{-\omega_n^2 + 100}\right| = \frac{|100|^{\xi=0}}{|-\omega_n^2 + 100|} = \frac{100}{\sqrt{\omega_n^4}} = \frac{100}{\omega_n^2} = 1$

$\arg\left(\frac{100}{-\omega_n^2 + 100}\right) = \arg(100) - \arg\left(-\omega_n^2 + 100\right) = \arg(1) - \arg\left(-\omega_n^2 + 100\right) = \arg(1) - \arg(-1) = 0 - \pi = -\pi$

$\arg(a \cdot b) = \arg(a) + \arg(b)$ $\quad \arg(-1) = \pi$

$\arg(\text{num.}/\text{den.}) = \arg(\text{num.}) - \arg(\text{den.})$ $\quad$ determinazione principale

$\Rightarrow G(j\omega_n) = 1 \cdot e^{-j\pi} = \cos(-\pi) + j\sin(-\pi) = -1 + 0j = \text{Re}\left\{\frac{1}{0}\right\}$

③ Scrivere sotto $G(s) = \frac{K}{s(s+1)(s+5)}$ $\quad$ Chiedo di rappresentare

- Calcolo modulo e argomento di K a bassa banda per la Bode

L'equazione caratteristica di un sistema a ciclo aperto (in generale) è $1 + G(s)H(s) = 0$

$1 + \frac{K}{s(s+1)(s+5)} = 0 \qquad s(s+1)(s+5) + K = 0$

$s^3 + 6s^2 + 5s + K = 0$

Criterio di Routh

3	1	5
2	6	K
1	$\frac{30-K}{6}$	0
0	K	

$K_{1_R} = \frac{-6}{-1+5} = \frac{6}{4} = \frac{3}{2}$ $\quad \det\begin{vmatrix} 1 & 5 \\ 6 & K \end{vmatrix} = 0 \Rightarrow -\frac{1}{6}(K - 30) = 0$

$K_{2_R} = \frac{-6}{5-1} = -\frac{6}{4} = -\frac{3}{2}$ $\quad \det\begin{vmatrix} 1 & 5 \\ 6 & K \end{vmatrix} = \frac{1}{-1+5}\det\begin{vmatrix} 1 & 5 \\ 6 & K \end{vmatrix} = \frac{1}{-1+5}(K - 30)$

$K_{3_R} = \frac{-6}{5-(-1)} = -1$ $\quad$ non va

Approssimo il sistema con la Bode, dopo aver calcolato una grandezza utile per capire in quale caso

$\Rightarrow \begin{cases} \frac{K}{5} < \frac{30}{6} \\ K > 0 \\ -1 < 0 \end{cases} \Rightarrow \begin{cases} K < 30 \\ K > 0 \end{cases} \Rightarrow \boxed{0 < K < 30}$

Per trovare il più conveniente percorso a 0 o ∞ uso τ

$\frac{K}{5}(1+\tau s) = 0 \Rightarrow \tau = \frac{1}{5}$ $\quad$ so di scrivere la mia coppia a più piccola tra $\frac{1}{5}$ e $\frac{1}{1}$

$\Rightarrow$ parto da $\frac{1}{5}$ (il minimo) da sopra la pendenza cresce di -1 e poi -1 (a $\frac{1}{1}$ diventa -2)

$\Rightarrow$ parto da -1 e poi -2 $\quad$ ω_c ?


$\Rightarrow$ modulo $K \Rightarrow$ ω_c ?

$\Rightarrow$ modulo $K \Rightarrow$ ω_c ?

$\Rightarrow$ modulo $K \Rightarrow \omega_c = 5 \cdot \sqrt{5-1}$

poi $\quad \omega_{c_{BF}} = 3\sqrt{5-1}$

④



$\begin{cases} \dot{x} = Ax + Bu \\ y = Cx + Du \end{cases} \qquad \begin{cases} \dot{x} = \dots \\ y = \dots \end{cases}$

Nella $\dot{x}(t)$, $x_0(t)$ ingresso $u(t)$ $\quad$ Determinare A, B, C, D

$\text{Re}\{\lambda\} < 0 \qquad x_1 = x_{1_0} \quad x_2 = x_{2_0} \quad x_3 = x_{3_0}$

$\text{Re}\{\lambda\} - x(t) = B\,x_1 + C\,x_2 \qquad \dot{x}(t) = x\,\dot{x}_0$

$\dot{x}_1 = \dot{x}_{1_0} = B\,\dot{x}_1 + C\,\dot{x}_2 \quad \Rightarrow \dot{x}_1 = \frac{-x_{1_0}}{\tau_{1_0}} + \frac{x_{2_0}}{\tau_{2_0}} = \frac{-x_1}{\tau_1} + \frac{x_2}{\tau_2}$

$\dot{x}_2 = \dot{x}_{2_0} = -x_{2_0} \Rightarrow \dot{x}_2 = -\frac{x_2}{\tau_2}$

$\dot{x}_3 = \dot{x}_{3_0} = -x_{3_0} \Rightarrow \dot{x}_3 = -\frac{x_3}{\tau_3}$

$f(t) - f(t_0) = B\,x_1 + C\,x_2 \qquad f(t) - f_0 = B\,x_1 + C\,x_2$

$\Rightarrow \dot{x}_0 = \frac{dx_0}{dt} = \frac{B}{\tau_1}x_1 + \frac{C}{\tau_2}x_2 \qquad \dot{x}_0 = \frac{-x_1}{\tau_1} + \frac{x_2}{\tau_2} + \frac{x_3}{\tau_3}$

$\dot{x}_1 = \frac{dx_1}{dt} = -\frac{x_1}{\tau_1} + \frac{x_{1_0}}{\tau_1} \qquad \dot{x}_2 = \frac{dx_2}{dt} = -\frac{x_2}{\tau_2} + \frac{x_{2_0}}{\tau_2}$

$\dot{x}_3 = \frac{dx_3}{dt} = -\frac{x_3}{\tau_3} + \frac{x_{3_0}}{\tau_3}$

$A = \begin{bmatrix} -\frac{1}{\tau_1} & 0 & 0 \\ \frac{1}{\tau_1} & -\frac{1}{\tau_2} & 0 \\ 0 & \frac{1}{\tau_2} & -\frac{1}{\tau_3} \end{bmatrix} \qquad B = \begin{bmatrix} \frac{1}{\tau_1} \\ 0 \\ 0 \end{bmatrix}$

$y(t) = x_3 \qquad C = \begin{bmatrix} 0 & 0 & 1 \end{bmatrix} \qquad D = \begin{bmatrix} 0 \end{bmatrix}$


$\dot{x}(t) = x_3$

- Calcolo in stato di equilibrio con ingresso $u = 1$ e $x_3 = 100$

$\begin{cases} \dot{x}_1 = 0 \\ \dot{x}_2 = 0 \\ \dot{x}_3 = 0 \end{cases} \Rightarrow \begin{cases} -\frac{1}{\tau_1}x_1 - \frac{1}{\tau_1}x_{1_0} = 0 \\ \frac{1}{\tau_1}x_1 - \frac{1}{\tau_2}x_2 = 0 \\ \frac{1}{\tau_2}x_2 - \frac{1}{\tau_3}x_3 = 0 \end{cases} \Rightarrow \begin{cases} -\frac{1}{\tau_1}x_1 - \frac{1}{\tau_1}x_{1_0} = 0 \\ x_1 = x_2 \\ x_1 = \frac{\tau_2}{\tau_3}x_3 \end{cases}$

$\begin{cases} x_1 = x_3 \\ x_2 = \frac{\tau_2}{\tau_3}x_3 \\ x_3 = \frac{1}{B} \end{cases} \Rightarrow \begin{cases} x_1 = \frac{\tau_2}{\tau_3} \\ x_2 = \frac{\tau_2}{\tau_3} \\ x_3 = \frac{1}{B} \end{cases}$

⑤



$C(s) = \frac{K}{s+2} \qquad G(s) = \frac{10}{(s+1)(s+5)}$

In serie $\Rightarrow \quad L(s) = G(s) \cdot C(s) = \frac{K \cdot 10}{(s+1)(s+5)(s+2)} \quad f.d.t.$

In retroazione $\Rightarrow \quad \frac{Y(s)}{R(s)} = \frac{L(s)}{1 + L(s)} = \frac{\frac{K \cdot 10}{(s+1)(s+5)(s+2)}}{1 + \frac{K \cdot 10}{(s+1)(s+5)(s+2)}} =$


$= \frac{K \cdot 10}{(s+1)(s+5)(s+2) + K \cdot 10} = \frac{K \cdot 10}{s^3 + 8s^2 + 17s + 10 + K \cdot 10}$

$= \frac{K \cdot 10}{s^3 + 8s^2 + 17s + 10 + 10K}$

$Y(s) = F(s) \cdot U(s) = \frac{K \cdot 10}{(s+1)(s+5)(s+2) + K \cdot 10} \cdot \frac{1}{s}$

$E(s) = R(s) - Y(s) = 1 - \frac{K \cdot 10}{(s+1)(s+5)(s+2) + K \cdot 10}$


- Come calcolo $\lim_{t \to \infty} e(t)$ poi il grafico va bene



Principio di sovrapposizione degli effetti $\quad Y(s) = W_1(s)\,R(s) + W_2(s)\,E(s)$

$W_1(s) = \frac{L(s)}{1 + L(s)} \qquad E(s) = \frac{1}{1 + L(s)}$

Diagramma



$E(s) = G(s) - Y(s) = \dots - Y(s)$

$A(s) = G(s) \cdot C(s) \qquad C \cdot Y(s)$

$A(s) = A_1(s) + A_2(s) = G(s) \cdot Y(s) + A_2(s)$

$Y(s) = G(s) \cdot U(s) = G(s) \cdot \left(-C(s)\,Y(s) + R(s)\right) = -G(s) \cdot C(s) \cdot Y(s) + G(s) \cdot R(s)$

Facendo $Y(s) = W_1(s)\,R(s) + W_2(s)\,E(s) = W_1(s)\,E(s)$ $\Rightarrow$ $\frac{Y(s)}{E(s)} = W_1(s)$

Abbiamo

$Y(s) = -G(s) \cdot C(s) \cdot Y(s) + G(s) \cdot R(s)$

$\Rightarrow \frac{Y(s)}{E(s)} = \frac{-G(s) \cdot C(s) \cdot Y(s)}{E(s)} + \frac{G(s) \cdot R(s)}{E(s)}$

$W_1(s) = \frac{-G(s) \cdot C(s) \cdot W_1(s) \cdot E(s)}{E(s)} + \frac{G(s) \cdot R(s)}{E(s)} = -G(s) \cdot C(s) \cdot W_1(s) + \frac{G(s) \cdot R(s)}{E(s)}$

$\Rightarrow W_1(s) = \frac{-G(s) \cdot C(s) \cdot W_1(s) \cdot E(s)}{E(s)} + \frac{G(s) \cdot R(s)}{E(s)} = -G(s) \cdot C(s) \cdot W_1(s) + \frac{G(s) \cdot R(s)}{E(s)}$

$\Rightarrow \frac{G(s) \cdot R(s)}{E(s)} = W_1(s) + G(s) \cdot C(s) \cdot W_1(s) = W_1(s)\left[1 + G(s) \cdot C(s)\right]$


$\Rightarrow \frac{G(s) \cdot R(s)}{E(s)} = W_1(s) \cdot \left[1 + G(s) \cdot C(s)\right]$

Approssimo. Un sistema è di tipo 1 se ha almeno un integratore, 2 se ha almeno due integratori, ecc.

$\frac{K}{s(s+5)} \qquad \frac{K}{s^2(s+5)}$

$\frac{K}{s(s+5)} \qquad \frac{K}{s^2(s+5)} \qquad \frac{20 - K}{5} > 0 \Rightarrow K < 20$ $\quad$ $\boxed{K < 20}$

Prova 2



Vi em regime não senoidal

$$\omega = \quad T = \quad f =$$

Sem modo A

$$i(0) = i_{L1} = \frac{V_{C1}}{R_1} = \quad v(0) = v_{C1} = i_{L1} \cdot R_1$$

$$\Rightarrow I_1 = \frac{v(0)}{R_2} - I_{L1}$$

Equações das LKC e LKT no modo A. Sem deslocamento de $\Psi(0)$: $i_{L2}(0) = i_{L3}(0) = i_{L4}(0) = 0$; $v_{C2}(0) = v_{C3}(0)$

$$\Rightarrow v_{C4}(0) = v_{C2}(0) + v_{C3}(0)$$

Substituindo nos nós LKC das LKTs

$$\frac{V_{C1}}{R_1} + \frac{I_1}{R_2} + \frac{I_{L1}}{R_3} = 0 \quad \Rightarrow v_{C1} - (R_2 I_1) = 0 \quad \Rightarrow v_{C1} = R_2 I_1$$

Somando $v(0) - I_1 R_2 + v_{C2}(0) + v_{C3}(0) = 0$

$$\Rightarrow I_{C2} = \frac{I_1}{C_2} (v_{C2}(0) + v_{C3}(0)) = \frac{I_1}{C_3} \cdot v_{C1}$$

Aplicando as LKC em v_{C4}

$$C_4 \cdot v_{C4} + \frac{I_{L4}}{R_4} + \frac{I_{L4} - I_{L3}}{R_5} \quad \forall \ t \geq 0 \quad \Rightarrow I_{L4} + \frac{I_{L4}}{R_4} - \frac{I_{L3}(s)}{R_5}$$

$$\Rightarrow I_{L4} + \frac{I_{L4}}{C_4 R_4} - \frac{I_{L3}}{C_4 R_5} = \frac{I_{L4}}{C_4 R_4} + \frac{I_{L4}}{C_4 R_5}$$

- Modelo i_{L3} no s $i_{L3} = i_{L4}$. Calculo V_o pelo de acordo com os sentidos de corrente nodais ($A \rightarrow B$)

$$\begin{bmatrix} \frac{1}{R_5} & \frac{1}{R_5} + \frac{1}{C_3 s} & -\frac{1}{C_3 s} \\ \frac{1}{R_5} & -\frac{1}{C_3 s} & \frac{1}{C_3 s} + \frac{1}{R_6} \end{bmatrix} \begin{bmatrix} V_A \\ V_B \\ V_C \end{bmatrix} = \begin{bmatrix} 0 \\ I_{L3} \\ -I_{L3} \end{bmatrix}$$

$$\Delta = \begin{vmatrix} \frac{1}{R_5} & \frac{1}{R_5} + \frac{1}{C_3 s} & -\frac{1}{C_3 s} \\ \frac{1}{R_5} & -\frac{1}{C_3 s} & \frac{1}{C_3 s} + \frac{1}{R_6} \end{vmatrix} = \frac{1}{R_5 C_3 s} + \frac{1}{R_6 C_3 s} + \frac{1}{R_5 R_6} + \frac{1}{C_3^2 s^2} - \frac{1}{C_3^2 s^2} = \frac{1}{R_5 C_3 s} + \frac{1}{R_6 C_3 s} + \frac{1}{R_5 R_6}$$

$$\Delta_1 = \begin{vmatrix} 0 & \frac{1}{R_5} + \frac{1}{C_3 s} & -\frac{1}{C_3 s} \\ I_{L3} & -\frac{1}{C_3 s} & \frac{1}{C_3 s} + \frac{1}{R_6} \\ -I_{L3} & \frac{1}{C_3 s} & \frac{1}{C_3 s} + \frac{1}{R_6} \end{vmatrix} = I_{L3} \left(\frac{1}{C_3 s} + \frac{1}{R_6} \right) + I_{L3} \left(\frac{1}{C_3 s} + \frac{1}{R_6} \right) = 2 I_{L3} \left(\frac{1}{C_3 s} + \frac{1}{R_6} \right)$$

$$\Delta_2 = \begin{vmatrix} \frac{1}{R_5} & 0 & -\frac{1}{C_3 s} \\ \frac{1}{R_5} & I_{L3} & \frac{1}{C_3 s} + \frac{1}{R_6} \end{vmatrix} = \frac{I_{L3}}{R_5} + \frac{I_{L3}}{C_3 s} + \frac{I_{L3}}{R_6} - \frac{I_{L3}}{C_3 s} = I_{L3} \left(\frac{1}{R_5} + \frac{1}{R_6} \right)$$

$$\Rightarrow \Delta^{-1} \cdot \Delta_2 = \frac{I_{L3} \left(\frac{1}{R_5} + \frac{1}{R_6} \right)}{\frac{1}{R_5 C_3 s} + \frac{1}{R_6 C_3 s} + \frac{1}{R_5 R_6}} \quad \text{e} \quad \Delta^{-1} \cdot \Delta_1 = \frac{2 I_{L3} \left(\frac{1}{C_3 s} + \frac{1}{R_6} \right)}{\frac{1}{R_5 C_3 s} + \frac{1}{R_6 C_3 s} + \frac{1}{R_5 R_6}}$$

$$\Rightarrow \begin{bmatrix} V_A \\ V_B \end{bmatrix} = \begin{bmatrix} \frac{I_{L3} \left(\frac{1}{R_5} + \frac{1}{R_6} \right)}{\frac{1}{R_5 C_3 s} + \frac{1}{R_6 C_3 s} + \frac{1}{R_5 R_6}} \\ \frac{2 I_{L3} \left(\frac{1}{C_3 s} + \frac{1}{R_6} \right)}{\frac{1}{R_5 C_3 s} + \frac{1}{R_6 C_3 s} + \frac{1}{R_5 R_6}} \end{bmatrix}$$

- Substituindo I_{L3} por I_{L4} e aplicando LKTs nas malhas temos $V_o = V_A - V_B$

$$\Rightarrow V_o = \frac{I_{L4} \left(\frac{1}{R_5} + \frac{1}{R_6} \right) - 2 I_{L4} \left(\frac{1}{C_3 s} + \frac{1}{R_6} \right)}{\frac{1}{R_5 C_3 s} + \frac{1}{R_6 C_3 s} + \frac{1}{R_5 R_6}} = \frac{I_{L4} \left(\frac{1}{R_5} + \frac{1}{R_6} - \frac{2}{C_3 s} - \frac{2}{R_6} \right)}{\frac{1}{R_5 C_3 s} + \frac{1}{R_6 C_3 s} + \frac{1}{R_5 R_6}} = \frac{I_{L4} \left(\frac{1}{R_5} - \frac{1}{R_6} - \frac{2}{C_3 s} \right)}{\frac{1}{R_5 C_3 s} + \frac{1}{R_6 C_3 s} + \frac{1}{R_5 R_6}}$$

$$\Rightarrow \frac{V_o}{I_{L4}} = \frac{\frac{1}{R_5} - \frac{1}{R_6} - \frac{2}{C_3 s}}{\frac{1}{R_5 C_3 s} + \frac{1}{R_6 C_3 s} + \frac{1}{R_5 R_6}} \quad \text{Resistência de saída do sistema}$$

Ao ser ligado a um resistor de carga

- Modelo de espaço de estados (Estados: I_{L4}, V_{C1}, V_{C2}, V_{C3}, V_{C4})

$$\dot{I}_{L4} = \quad \dot{V}_{C1} = \quad \dot{V}_{C2} = \quad \dot{V}_{C3} = \quad \dot{V}_{C4} =$$

$$\begin{bmatrix} \dot{I}_{L4} \\ \dot{V}_{C1} \\ \dot{V}_{C2} \\ \dot{V}_{C3} \\ \dot{V}_{C4} \end{bmatrix} = \begin{bmatrix} \quad & \quad & \quad & \quad & \quad \\ \quad & \quad & \quad & \quad & \quad \\ \quad & \quad & \quad & \quad & \quad \\ \quad & \quad & \quad & \quad & \quad \\ \quad & \quad & \quad & \quad & \quad \end{bmatrix} \begin{bmatrix} I_{L4} \\ V_{C1} \\ V_{C2} \\ V_{C3} \\ V_{C4} \end{bmatrix} + \begin{bmatrix} \quad \\ \quad \\ \quad \\ \quad \\ \quad \end{bmatrix} V_i$$

$$\begin{bmatrix} V_o \end{bmatrix} = \begin{bmatrix} \quad & \quad & \quad & \quad & \quad \end{bmatrix} \begin{bmatrix} I_{L4} \\ V_{C1} \\ V_{C2} \\ V_{C3} \\ V_{C4} \end{bmatrix} + \begin{bmatrix} \quad \end{bmatrix} V_i$$

Pràctica 3



NK: $\begin{cases} I_1(s) = I_2(s) + I_3(s) \\ V_1(s) = I_1(s)\left(R_1 + \frac{1}{sC_1}\right) \\ V_2(s) = I_2(s)\left(R_2 + \frac{1}{sC_2}\right) \end{cases}$

$\Rightarrow \frac{V_1}{R_1} = \frac{V_2}{R_2} + I_3 + \frac{V_1}{sC_1} \Rightarrow \frac{V_1}{R_1} - \frac{V_1}{sC_1} = \frac{V_2}{R_2} + I_3$

$\Rightarrow V_1\left(\frac{1}{R_1} - \frac{1}{sC_1}\right) = V_2\left(\frac{1}{R_2} + \frac{1}{sC_2}\right) + I_3 \Rightarrow V_1\left(\frac{sC_1 - \frac{1}{R_1}}{sC_1}\right) = V_2\left(\frac{sC_2 + \frac{1}{R_2}}{sC_2}\right) + I_3$

$\Rightarrow V_1\left(\frac{sC_1 R_1 - 1}{sC_1 R_1}\right) = V_2\left(\frac{sC_2 R_2 + 1}{sC_2 R_2}\right) + I_3 \Rightarrow V_1\left(\frac{sC_2 R_2}{sC_1 R_1 - 1}\right) = V_2\left(\frac{sC_2 R_2 + 1}{sC_1 R_1 - 1}\right) + I_3\left(\frac{sC_2 R_2}{sC_1 R_1 - 1}\right)$

$\Rightarrow V_1\left(\frac{sC_2 R_2}{sC_1 R_1 - 1}\right) = V_2\left(\frac{sC_2 R_2 + 1}{sC_1 R_1 - 1}\right) + I_3\left(\frac{sC_2 R_2}{sC_1 R_1 - 1}\right)$

$\Rightarrow \begin{bmatrix} V_1 \\ V_2 \end{bmatrix} = \begin{bmatrix} \frac{sC_2 R_2}{sC_1 R_1 - 1} & -\left(\frac{sC_2 R_2 + 1}{sC_1 R_1 - 1}\right) \\ 1 & 0 \end{bmatrix} \begin{bmatrix} V_2 \\ I_3 \end{bmatrix}$ (+ 1 SOL de tensions i 1 de pots mateu-tema 2.1.1.1. del problema) (Edwin & Isabel: $\alpha = 1$)

$\Rightarrow Y(s) = \begin{bmatrix} \frac{sC_2 R_2}{sC_1 R_1 - 1} & -\left(\frac{sC_2 R_2 + 1}{sC_1 R_1 - 1}\right) \\ 1 & 0 \end{bmatrix}$

$\Rightarrow A = \begin{bmatrix} \frac{\partial f_1}{\partial x_1} & \frac{\partial f_1}{\partial x_2} & \frac{\partial f_1}{\partial u_1} & \frac{\partial f_1}{\partial u_2} \\ \frac{\partial f_2}{\partial x_1} & \frac{\partial f_2}{\partial x_2} & \frac{\partial f_2}{\partial u_1} & \frac{\partial f_2}{\partial u_2} \\ \frac{\partial g_1}{\partial x_1} & \frac{\partial g_1}{\partial x_2} & \frac{\partial g_1}{\partial u_1} & \frac{\partial g_1}{\partial u_2} \\ \frac{\partial g_2}{\partial x_1} & \frac{\partial g_2}{\partial x_2} & \frac{\partial g_2}{\partial u_1} & \frac{\partial g_2}{\partial u_2} \end{bmatrix}$

$\frac{\partial f_1}{\partial x_1} = -\frac{1}{R_1 C_1}$ $\quad \frac{\partial f_1}{\partial x_2} = 0$ $\quad \frac{\partial f_1}{\partial u_1} = 0$ $\quad \frac{\partial f_1}{\partial u_2} = 0$

$\frac{\partial f_2}{\partial x_1} = -\frac{1}{C_1}$ $\quad \frac{\partial f_2}{\partial x_2} = \frac{1}{C_2}$ $\quad \frac{\partial f_2}{\partial u_1} = \frac{1}{R_1 C_1}$ $\quad \frac{\partial f_2}{\partial u_2} = 0$

$\frac{\partial g_1}{\partial x_1} = 1$ $\quad \frac{\partial g_1}{\partial x_2} = 0$ $\quad \frac{\partial g_1}{\partial u_1} = 0$ $\quad \frac{\partial g_1}{\partial u_2} = \frac{-1}{R_2 C_2}$

$\Rightarrow B = \begin{bmatrix} -\frac{1}{R_1 C_1} & 0 & 0 & 0 \\ -\frac{1}{C_1} & \frac{1}{C_2} & \frac{1}{R_1 C_1} & 0 \\ 1 & 0 & 0 & -\frac{1}{R_2 C_2} \\ 0 & 1 & \frac{1}{R_1 C_1} & -\frac{1}{R_2 C_2} \end{bmatrix}$ $\quad \Rightarrow C = \begin{bmatrix} \frac{1}{R_1 C_1} & 0 & 0 & 0 \\ -\frac{1}{C_1} & \frac{1}{C_2} & \frac{1}{R_1 C_1} & 0 \\ 1 & 0 & 0 & -\frac{1}{R_2 C_2} \\ 0 & 1 & \frac{1}{R_1 C_1} & -\frac{1}{R_2 C_2} \end{bmatrix}$

$D = \begin{bmatrix} 0 & 0 \\ 0 & 0 \\ 0 & 0 \\ 0 & 0 \end{bmatrix}$

$B = \begin{bmatrix} \frac{\partial f_1}{\partial u_1} & \frac{\partial f_1}{\partial u_2} \\ \frac{\partial f_2}{\partial u_1} & \frac{\partial f_2}{\partial u_2} \\ \frac{\partial g_1}{\partial u_1} & \frac{\partial g_1}{\partial u_2} \\ \frac{\partial g_2}{\partial u_1} & \frac{\partial g_2}{\partial u_2} \end{bmatrix}$ $\quad \Rightarrow \quad B = \begin{bmatrix} 0 & 0 \\ 0 & 0 \\ 1 & 0 \\ 0 & 1 \end{bmatrix}$

$Y(s) = I_{R_2}(s) = \frac{V_2(s)}{R_2}$

① $G(s) = \frac{1}{s+1}$ $\quad h(t) = L^{-1}\left\{G(s)\frac{1}{s}\right\} = L^{-1}\left\{\frac{1}{s(s+1)}\right\} = 1 - e^{-t}$ $\quad u(t) = 1$

$\lim_{t\to\infty} h(t) = \lim_{s\to 0} s \cdot G(s) \cdot U(s)$ (teorema del valor final)

$G(s) = \frac{B}{s+1} + \frac{A}{s}$ $\quad \Rightarrow \quad A = \frac{1}{s+1}\Big|_{s=0} = 1$

$h(t) = G(s)\cdot U(s) = \frac{1}{s(s+1)} \cdot \frac{1}{s} = \frac{1}{s^2(s+1)}$ $\quad \Rightarrow \quad \frac{1}{s^2(s+1)} = \frac{1}{s^2} - \frac{1}{s} + \frac{1}{s+1}$

$= \frac{(1)(s)}{(s)(s)} + \frac{(1)(s^2)}{(s^2)(s+1)} = \frac{s + 0 + s^2}{s^2(s+1)} = \frac{s(s+1)}{s^2(s+1)} = \frac{1}{s}$

$\Rightarrow \frac{A(s+1) + Bs(s+1) + Cs^2}{s^2(s+1)} = \frac{1}{s^2(s+1)}$ $\quad \Rightarrow \quad \begin{cases} A + B + C = 0 \\ A + B = 0 \\ A = 1 \end{cases}$ $\quad \Rightarrow \quad \begin{cases} A = 1 \\ B = -1 \\ C = 0 \end{cases}$

$\Rightarrow h(t) = \frac{A}{s} + \frac{B}{s^2} + \frac{C}{s+1} = \frac{1}{s} - \frac{1}{s^2} + 0$ $\quad \Rightarrow \quad h(t) = 1 - t + 0 = 1 - t$

$\lim_{t\to\infty} h(t) = \lim_{s\to 0} s \cdot G(s) \cdot U(s) = \lim_{s\to 0} s \cdot \frac{1}{s+1} \cdot \frac{1}{s} = \lim_{s\to 0} \frac{1}{s+1} = 1$

$\Rightarrow \frac{A_1 s + B_1}{(s+1)^2} + \frac{A_2}{s+1} = \frac{1}{(s+1)^2}$ $\quad \Rightarrow \quad \begin{cases} A_1 + A_2 = 0 \\ B_1 + A_2 = 1 \end{cases}$ $\quad \Rightarrow \quad \begin{cases} A_1 = -A_2 \\ B_1 = 1 - A_2 \end{cases}$ $\quad \Rightarrow \quad \begin{cases} A_1 = -1 \\ B_1 = 2 \\ A_2 = 1 \end{cases}$

$\Rightarrow Y(s) = \frac{(2s)(s)}{(s+1)^2(s)} + \frac{(1)(s^2)}{(s+1)^2(s^2)} = \frac{(2)(s)}{(s+1)^2(s)} + \frac{(1)(s^2)}{(s+1)^2(s^2)} = \frac{(2)(s)}{(s+1)^2(s)} + \frac{(1)(s^2)}{(s+1)^2(s^2)}$

$\Rightarrow y(t) = \frac{2s}{(s+1)^2} + \frac{1}{s+1}$ $\quad \Rightarrow \quad \frac{2s}{(s+1)^2} = \frac{A}{(s+1)^2} + \frac{B}{s+1}$ $\quad \Rightarrow \quad \begin{cases} A = 2 \\ B = -2 \end{cases}$ $\quad \Rightarrow \quad y(t) = \frac{2}{(s+1)^2} - \frac{2}{s+1} + \frac{1}{s+1} = \frac{2}{(s+1)^2}$

Pero, ¿cómo sabría de dónde sale la fracción (¿polos/ceros?, ¿cómo una antigua?)

② $\quad R_{eq} = \frac{R_1 \cdot \frac{1}{sC_1}}{R_1 + \frac{1}{sC_1}} = \frac{\frac{R_1}{sC_1}}{\frac{sC_1 R_1 + 1}{sC_1}} = \frac{R_1}{sC_1 R_1 + 1}$

$R_{eq} = \frac{R_1}{sC_1 R_1 + 1}$


$V_1 = I_1 \cdot R_1 \cdot \frac{1}{sC_1 R_1 + 1} = I_1 \cdot \frac{R_1}{sC_1 R_1 + 1}$ $\quad V_2 = I_2 \cdot R_2 \cdot \frac{1}{sC_2 R_2 + 1} = I_2 \cdot \frac{R_2}{sC_2 R_2 + 1}$

$R_1(sC_1 R_1 + 1) = I_1 \cdot R_1$ $\quad R_2(sC_2 R_2 + 1) = I_2 \cdot R_2$

$V_1(sC_1 R_1 + 1) = I_1 \cdot R_1$ $\quad V_2(sC_2 R_2 + 1) = I_2 \cdot R_2$

$V_1 sC_1 R_1 + V_1 = I_1 \cdot R_1$ $\quad V_2 sC_2 R_2 + V_2

Φυλλο 4



$$\Sigma_K = \frac{m\,\vec{r}}{dt}$$

$$T = \frac{1}{2}\,m\,\dot{\theta}^2 L^2 + \frac{1}{2}\,m\,\dot{\theta}^2\,\frac{L^2}{4} = \frac{1}{2}\,m\,\dot{\theta}^2\,L^2\left(1+\frac{1}{4}\right)$$

$$U_{\beta\alpha\rho} = -mg\,\frac{L}{2} \qquad U_{\alpha\rho\sigma} = \frac{1}{2}\,k_1\left(\frac{L}{2}\right)^2 + \frac{1}{2}\,k_2\left(\frac{L}{2}\right)^2$$

$$U_{\beta\alpha\sigma} = -mg\,\frac{L}{2}\,\cos\theta + \frac{1}{2}\,k_1\left(\frac{L}{2}\right)^2 + \frac{1}{2}\,k_2\left(\frac{L}{2}\right)^2$$

$$\frac{\partial U}{\partial\theta} = \frac{1}{2}\,mgL\sin\theta \qquad \frac{\partial^2 U}{\partial\theta^2} = \frac{1}{2}\,mgL\cos\theta \qquad \frac{\partial U}{\partial\dot{\theta}} = 0$$

$$\frac{\partial U}{\partial\theta} = \frac{1}{2}\,k_1\left[2\left(\frac{L}{2}\sin\theta\right)\frac{L}{2}\cos\theta\right] + \frac{1}{2}\,k_2\left[2\left(-\frac{L}{2}\sin\theta\right)\cdot\left(-\frac{L}{2}\cos\theta\right)\right]$$

$$= \frac{1}{4}\,k_1 L^2\sin\theta\cos\theta + \frac{1}{4}\,k_2 L^2\sin\theta\cos\theta = \frac{1}{4}\,(k_1+k_2)L^2\sin\theta\cos\theta$$

$$\frac{\partial}{\partial\dot{\theta}}\left(\frac{\partial T}{\partial\dot{\theta}}\right) = \frac{\partial}{\partial\dot{\theta}}\left(\frac{1}{2}\,m\dot{\theta}L^2\right) = m\ddot{\theta}\,\frac{5L^2}{4} = \frac{5}{4}\,mL^2\ddot{\theta}$$

$$\frac{\partial T}{\partial\theta} = -mg\,\frac{L}{2}\,\sin\theta\,\dot{\theta}\left(\frac{1}{2}\,m\dot{\theta}L^2\right)\cdot\frac{1}{2}\,mL^2\sin\theta\cos\theta$$

$$= -mg\,\frac{L}{2}\,\sin\theta + \frac{1}{4}\,k_1 L^2\sin\theta\cos\theta + \frac{1}{4}\,k_2 L^2\sin\theta\cos\theta$$

$$= -mg\,\frac{L}{2}\,\sin\theta + \frac{1}{4}\,(k_1+k_2)L^2\sin\theta\cos\theta$$

$$\frac{5}{4}\,mL^2\ddot{\theta} + \frac{1}{2}\,mgL\sin\theta - \frac{1}{4}\,(k_1+k_2)L^2\sin\theta\cos\theta = 0$$

Προσεγγιστικά για $\theta \ll 1$ (η γωνία είναι αρκετά μικρή)

$$\ddot{\theta} + \frac{2mgL - (k_1+k_2)L^2\cos\theta}{5mL^2}\,\sin\theta = 0$$

$$\ddot{\theta} + \frac{2mgL - (k_1+k_2)L^2}{5mL^2}\,\theta = 0$$


$$\omega_0^2 = \frac{2mgL - (k_1+k_2)L^2}{5mL^2} \qquad \omega_0 = \sqrt{\frac{2mgL - (k_1+k_2)L^2}{5mL^2}}$$

$$\theta(t) = A\cos(\omega_0 t + \varphi)$$

$$\theta(0) = \frac{\pi}{6} \;\Rightarrow\; A\cos\varphi = \frac{\pi}{6}$$

$$\dot{\theta}(0) = 0 \;\Rightarrow\; -A\omega_0\sin\varphi = 0 \;\Rightarrow\; \varphi = 0$$

$$\theta(t) = \frac{\pi}{6}\cos\left(\sqrt{\frac{2mgL - (k_1+k_2)L^2}{5mL^2}}\;t\right)$$

② 

$$\vec{w}_{1,0} = \vec{w}_{2,0} = \vec{w}_{1,0} = \vec{w}_{2,0} = \vec{w}_{1,0} = \vec{w}_{2,0} = \vec{w}_1 = \vec{w}_2 = \vec{w}_1 = \vec{w}_2 = \vec{w}_1 = \vec{w}_2 = \vec{w}_{1,0} = \vec{w}_{2,0}$$

$$\vec{w}_1 \cdot \vec{k}\vec{x}_1 = \vec{w}_{1,0}\cdot\vec{k}\vec{x}_{1,0}$$

$$\vec{w}_2\vec{k}_2\cdot\vec{x}_2 = \vec{k}_2\vec{x}_{2,0} \;\Rightarrow\; \vec{w}_2\cdot\vec{x}_2 = \frac{\vec{w}_2\vec{k}_2}{\vec{k}_2}\,\vec{x}_{2,0}$$

$$\Rightarrow \vec{w}_1\cdot\vec{k}\vec{x}_1 = \vec{w}_{1,0}\cdot\vec{k}\vec{x}_{1,0} + \vec{w}_2\cdot\vec{x}_2 = \vec{w}_{2,0}\cdot\frac{\vec{w}_2\vec{k}_2}{\vec{k}_2}\,\vec{x}_{2,0}$$


$$\vec{k}_1\cdot\vec{k}\vec{x}_1 = \vec{k}_1\vec{x}_{1,0} + \vec{k}_1\vec{x}_{2,0}$$

$$\vec{k}_2\cdot\vec{x}_2 = \vec{k}_2\vec{x}_{2,0} \qquad \vec{k}_2\cdot\vec{x}_2 - \vec{k}_2\vec{x}_{2,0} = 0 \;\Rightarrow\; \vec{w}_2 = \frac{\vec{k}_2\cdot\vec{k}_2}{\vec{k}_2}$$

$$\vec{k}_1\cdot\vec{k}\vec{x}_1 = \vec{w}_{1,0}\cdot\vec{k}\vec{x}_{1,0} + \vec{k}_1\vec{x}_{2,0} \qquad \vec{k}_2\cdot\vec{k}_2\cdot\vec{k}_2\cdot\vec{x}_2 \;\Rightarrow\; \vec{w}_2 = \frac{\vec{k}_2\cdot\vec{k}_2}{\vec{k}_2}$$

$$\vec{x}_1 = \vec{x}_{1,0} + \vec{x}_{2,0} \qquad \vec{x}_2 = \vec{x}_{2,0

Prova 5



$T_{rot} = \frac{2}{5} m r^2$

$T = \frac{1}{2} m \dot{x}^2 + \frac{1}{2} T_{rot} \dot{\theta}^2$

$O_A = < (Rx) \sin\theta \; , (Rx) \cos\theta >$ — componente $\perp$ a $\vec{OA}$ ($(Rx)\cos\theta$)

$\Rightarrow V = < (\dot{R}x)\cos\theta - \dot{\theta}, -(\dot{R}x)\sin\theta >$ — componente $\perp$ a $\vec{OA}$ ($-(\dot{R}x)\sin\theta$)

$|V|^2 = \left((\dot{R}x)\cos\theta + (R\dot{x})\sin\theta \right)^2 + \left(-(\dot{R}x)\sin\theta \right)^2$

$\Rightarrow T = \frac{m(\dot{R}x)^2}{2} + \frac{\dot{\theta}^2 m l^2}{5}$

$U = U_p + U_c$

$U_p = -mg(Rx)\cos\theta \qquad U_c = \frac{1}{2} K \cdot \left(-\frac{R}{2} x \cos\theta \right)^2$

$\Rightarrow U = -mg(Rx)\cos\theta - \frac{KR^2}{8} x^2 \cos^2\theta$

$\dot{R} = \frac{1}{2} \frac{d}{dt} \left(\frac{R}{dt} \frac{x}{\cos\theta} \right)^2 = \frac{1}{4} \frac{d}{dt} \left(\frac{R}{4} x \cos\theta \right)^2 = \frac{1}{4} \frac{R^2}{4} \frac{d}{dt} x^2 \cos^2\theta \dot{\theta}^2$

$= \frac{R R^2}{8} x \cos^2\theta \dot{\theta}^2$

$\frac{dt}{dt} \left(\frac{\partial T}{\partial \dot{\theta}} \right) - \frac{\partial}{\partial \theta} \frac{T}{\theta} = \frac{2}{5} \ddot{\theta} m l^2 \qquad \frac{\partial T}{\partial \theta} = 0 \qquad \frac{\partial U}{\partial \theta} = mg(Rx)\sin\theta - \frac{KR^2}{4} x \cos\theta \sin\theta$

$\frac{\partial R}{\partial \theta} = \frac{R R^2}{8} x \cos^2\theta \dot{\theta}$


no weights: $\Rightarrow \alpha_{CM} = 0$ (no link constraints: no constraints)

$\frac{2}{5} \ddot{\theta} m l^2 + mg(Rx)\sin\theta - \frac{KR^2}{4} x \cos\theta \cos^2\theta + \frac{R R^2}{8} x \cos^2\theta \dot{\theta} = 0$

$\ddot{\theta} = -\frac{mg(Rx)\sin\theta}{\frac{2}{5} m l^2} + \frac{KR}{\frac{2}{5} m l^2} x \cos\theta \cos\theta - \frac{R R^2}{\frac{2}{5} m l^2} x \cos^2\theta \dot{\theta}$

Secondo tentativo $x_1 = 0 \quad x_2 = \dot{\theta}$

$\begin{cases} \dot{x}_1 = 0 \\ \dot{x}_2 = -\frac{5}{2} \frac{g(Rx)}{Rl} \sin x_1 + \frac{5}{2} \frac{KR}{m l^2} \sin x_1 \cos x_1 - \frac{5}{2} \frac{R R^2}{m l^2} \cos^2 x_1 \; x_2 \end{cases}$

② 

SBAGLIATO

semplifico: $I(t), V(t)$ usando $y(t)$

LKT$_1$: $V(t) - L\dot{i}_2 - L\dot{i}_{R1} - x_1 = 0$

LKT$_2$: $x_1 - R\cdot(i_1 - i_2 - i_{R1}) = 0$ $\Rightarrow x_1 = R(i_{R1} - Cx_1 - x_2) - x_1 \Rightarrow$


LKC$_1$: $i_{R1} - C\dot{x}_1 + I(t) - (i_{R1} - C\dot{x}_1) - \frac{(Lx_2 + (x_1 - x_2))}{R} = 0$

$x_1 - x_2 - \frac{(Lx_2 + (x_1 - x_2))}{R} = 0$ $\qquad \dot{x}_1 = -\frac{x_1}{L} + \frac{x_2}{L} + Rx_2 - Rx_1$

$-\frac{L\dot{x}_2}{R} - \frac{x_2}{R} + \frac{x_1}{R} - x_2 = 0 \qquad \dot{x}_2 = -\frac{x_1}{L} + \left(\frac{1}{L} - \frac{R}{L} \right) x_2$

$V(t) - L\dot{x}_2 - K\left(-\frac{x_2}{2} \right) + \frac{x_2}{2} \frac{1}{2} R x_2 \cdot \frac{R}{2} x_2 \cdot \frac{1}{2}

Prova 6



$T = \frac{1}{2} m v^2 \qquad OG = < l \sin\theta, -l\cos\theta >$

$\bar{v} = \dot{OG} = < l\cos\theta\,\dot\theta, + l\sin\theta\,\dot\theta >$

$|\bar v|^2 = \left(\sqrt{l^2\cos^2\theta\,\dot\theta^2 + l^2\sin^2\theta\,\dot\theta^2}\right)^2 = l^2\dot\theta^2 \quad \Rightarrow T = \frac{1}{2} m l^2 \dot\theta^2$

$U = U_p + U_E \qquad U_p = -mgl\cos\theta \qquad U_{E_1} = \frac{1}{2} k_1 \left(\frac{l}{2}\sin\theta\right)^2 = \frac{1}{2} k_1 \frac{l^2}{4}\sin^2\theta$

$= \frac{k_1 l^2}{8}\sin^2\theta \qquad U_{E_2} = \frac{1}{2} k_2 \left(\frac{l}{2}\sin\theta\right)^2 = \frac{1}{2} k_2 \frac{l^2}{4}\sin^2\theta = \frac{k_2 l^2}{8}\sin^2\theta$

$U_{TOT} = -mgl\cos\theta + \frac{k_1 l^2}{8}\sin^2\theta + \frac{k_2 l^2}{8}\sin^2\theta$

$\frac{d}{dt}\left(\frac{\partial T}{\partial \dot\theta}\right) = \frac{d}{dt}\left(ml^2\dot\theta\right) = ml^2\ddot\theta \qquad \frac{\partial T}{\partial\theta} = 0$

$\frac{\partial U}{\partial\theta} = mgl\sin\theta + \frac{k_1 l^2}{4}\cdot 2\sin\theta\cos\theta + \frac{k_2 l^2}{4}\cdot 2\sin\theta\cos\theta$

$\delta L = F\cdot\delta x = F\cdot\delta(l\sin\theta) = F\cdot\frac{dl\sin\theta}{d\theta}\delta\theta = F\cdot l\cos\theta\,\delta\theta = Q_1\cdot\delta\theta$

$\Rightarrow Q_1 = F\cdot l\cos\theta$

$\Rightarrow ml^2\ddot\theta + mgl\sin\theta + \frac{k_1 l^2}{4}\sin\theta\cos\theta + \frac{k_2 l^2}{4}\sin\theta\cos\theta = F\cdot l\cos\theta$

$\ddot\theta = \frac{F\cancel{l}\cos\theta}{ml^{\cancel 2}} - \frac{mgl}{ml^2}\sin\theta - \frac{k_1}{4}\frac{l^2}{ml^2}\sin\theta\cos\theta - \frac{k_2 l^2}{4ml^2}\sin\theta\cos\theta$

Scegliendo $x_1 = \theta_1 \quad x_2 = \dot\theta_1 \quad u =$

$$\begin{cases} \dot x_1 = x_2 \\ \dot x_2 = \frac{1}{ml}\,u\cos x_1 - \frac{g}{l}\sin x_1 - \frac{k_1}{4m}\sin x_1\cos x_1 - \frac{k_2}{4m}\sin x_1\cos x_1 \end{cases}$$

(2)

$$\begin{cases} \dot x_1(t) = (u(t)+1)\sin x_1(t) \\ \dot x_2(t) = x_1(t) + x_2(t) + 2u(t) \end{cases}$$

$y(t) = x_1(t) - 3x_2^2(t) + 3u(t)$

- $u = 0 \Rightarrow \begin{cases} \dot x_1 = \sin x_1 \\ \dot x_2 = x_1 + x_2 \end{cases} \qquad \begin{cases} \dot x_1 = 0 \\ \dot x_2 = 0 \end{cases} \Rightarrow \begin{cases} \sin x_1 = 0 \\ x_2 = -x_1 \end{cases}$

$\bar x_e' = [\,0 \quad 0\,]^T \qquad \bar x_e'' = [\,\pi \quad -\pi\,]^T$

$\frac{\partial f_1}{\partial x_1} = (u(t)+1)\cdot\cos x_1 \qquad \frac{\partial f_1}{\partial x_2} = 0$

$\frac{\partial f_2}{\partial x_1} = 1 \qquad \frac{\partial f_2}{\partial x_2} = 1$

$\Rightarrow A = \begin{bmatrix} \cos x_1 & 0 \\ 1 & 1 \end{bmatrix}$

$B = \begin{bmatrix} 0 \\ 0 \end{bmatrix}$


in $\begin{bmatrix} 0 \\ 0 \end{bmatrix} \Rightarrow A = \begin{bmatrix} 1 & 0 \\ 1 & 1 \end{bmatrix}$

$C = [\,1 \quad -3\,] \qquad D = [\,0\,]$


$\Rightarrow \lambda I - A = \begin{bmatrix} \lambda-1 & 0 \\ -1 & \lambda-1 \end{bmatrix}$

$\Rightarrow (\lambda-1)(\lambda-1)+1 = \lambda^2 - \lambda - \lambda + 1 + 1 = \lambda^2 - 2\lambda + 2 \quad \Rightarrow$ instabile (grado 2 e coefficienti concordi)

(3)




(4)



$M = 1\,Kg \qquad m = 0.5\,Kg$

$c_M = 2\ J/kg\,^\circ C \qquad c_m = 1\ J/kg\,^\circ C$

$R = 0.5\ ^\circ C/W$



$x_1 = T_m \qquad x_2 = T_M$

↳ ≡



LKC A: $C_m\dot x_1 + \frac{(x_1 - x_2)}{R} = 0$

$\Rightarrow C_m\dot x_1 = -\frac{(x_1 - x_2)}{R}$

$\frac{(x_1 - x_2)}{R} - C_m\dot x_2 = 0$

$\Rightarrow C_m\dot x_2 = \frac{(x_1 - x_2)}{R}$

$\Rightarrow \begin{cases} \dot x_1 = -\frac{(x_1 - x_2)}{RC_m} \\ \dot x_2 = \frac{(x_1 - x_2)}{RC_M} \end{cases} \Rightarrow \begin{cases} \dot x_1 = -\frac{(x_1 - x_2)}{0.5} \\ \dot x_2 = \frac{(x_1 - x_2)}{1} \end{cases}$

$A = \begin{bmatrix} -2 & +2 \\ 1 & -1 \end{bmatrix} \qquad B = \begin{bmatrix} 0 \\ 0 \end{bmatrix}$

$\lambda I - A = \begin{bmatrix} \lambda+2 & -2 \\ -1 & \lambda+1 \end{bmatrix} = (\lambda+2)(\lambda+1) - 2 = \lambda^2 + \lambda + 2\lambda + 3 - 2 = \lambda^2 + 3\lambda + 1$

$\frac{-3 \pm \sqrt{9-4}}{2} \sim \begin{cases} \frac{-3-\sqrt5}{2} \\ \frac{-3+\sqrt5}{2} \end{cases} \qquad e^{\frac{-3-\sqrt5}{2}}, e^{\frac{-3+\sqrt5}{2}}$ modi del sistema

Assumendo $T_m(0) = 60^\circ C$ e $T_M(0) = 100^\circ C$

$x(t) = e^{At}x$

(5)


$\ddot y(t) - y(t) = 5\,u(t) \qquad y(0) = 0 \qquad \dot y(0) = 1 \qquad u(t) = e^{-t}\ \forall t \ge 0$

$\Rightarrow \ddot y(t) - y(t) = 5\cdot e^{-2t}$ ↓ $\frac{1}{s+2}$

$\ddot y(t) - a_1\dot y(t) - a_0 y(t)$

Prova 7 — [m] SOLUZIONI

①



$T = \frac{1}{2} m v^2 \qquad \vec{OG} = x\hat{i} + l\sin\theta\,\hat{i} - l\cos\theta\,\hat{j}$

$\vec{v} = \dot{x}\hat{i} + l\dot{\theta}\cos\theta\,\hat{i} + l\dot{\theta}\sin\theta\,\hat{j}$

$|\vec{v}|^2 = \left(\dot{x}^2 + l^2\dot{\theta}^2\cos^2\theta + 2\dot{x}l\dot{\theta}\cos\theta\right)\hat{i}\cdot\hat{i} + \left(l^2\dot{\theta}^2\sin^2\theta + 2\dot{x}l\dot{\theta}\sin\theta\right)\hat{j}\cdot\hat{j} + 2\left(-\dot{x}l\dot{\theta}\sin\theta\cos\theta + l^2\dot{\theta}^2\sin\theta\cos\theta\right)\hat{i}\cdot\hat{j}$

$= \left(\dot{x}^2 + l^2\dot{\theta}^2\right)$

$\Rightarrow T = \frac{1}{2} m\left(\dot{x}^2 + l^2\dot{\theta}^2\right)$

$U = U_P + U_K \qquad U_P = -mg(-l\cos\theta) = mgl\cos\theta$

$U_K = \frac{1}{2} k x^2 = \frac{1}{2} k (x - L_0)^2$

$U_{TOT} = mgl\cos\theta + \frac{1}{2} k (x - L_0)^2$

$\delta = \frac{1}{2} \beta \dot{\theta}^2$

$\frac{d}{dt}\left(\frac{\partial T}{\partial \dot{\theta}}\right) = \frac{d}{dt}\left(ml^2\dot{\theta}\right) = ml^2\ddot{\theta} \qquad \frac{\partial T}{\partial \theta} = 0 \qquad \frac{\partial U}{\partial \theta} = -mgl\sin\theta$

$\frac{\partial \delta}{\partial \dot{\theta}} = \beta\dot{\theta}$

$\frac{d}{dt}\left(\frac{\partial T}{\partial \dot{x}}\right) = \frac{d}{dt}\left(m\dot{x}\right) = m\ddot{x} \qquad \frac{\partial T}{\partial x} = ml\dot{\theta}^2 \qquad \frac{\partial U}{\partial x} = mg\cos\theta + k(x - L_0)$

$\frac{\partial \delta}{\partial \dot{x}} = 0$

$\exists L \quad \exists Q_i(t, \theta, \dot{\theta}) = F\sin\theta \quad \exists \delta \quad \exists F_i(t, \theta, \dot{\theta}) = F\cos\theta$

Scegliendo $q_1 = \theta \quad q_2 = x \quad \Rightarrow \quad Q_1 = F\sin\theta \qquad Q_2 = F\cos\theta$


$$\begin{cases} m\ddot{x} - ml\dot{\theta}^2 + mg\cos\theta + k(x - L_0) = F\sin\theta \\ ml^2\ddot{\theta} - mgl\sin\theta + \beta\dot{\theta}^2 = F\,l\cos\theta \end{cases}$$

$$\begin{cases} \ddot{x} = \frac{F\sin\theta}{m} + l\dot{\theta}^2 - g\cos\theta - \frac{k(x - L_0)}{m} \\ \ddot{\theta} = \frac{F\cos\theta}{ml^2} + \frac{mgl\sin\theta}{ml^2} - \frac{\beta\dot{\theta}^2}{ml^2} \end{cases}$$

$X_1 = \theta \quad X_2 = \dot{x} \quad X_3 = x \quad X_4 = \dot{\theta} \qquad \omega_0 = F \qquad \omega_2 = L_0$

$$\begin{cases} \dot{X}_1 = X_4 \\ \dot{X}_2 = \frac{1}{m}\omega_0\sin X_3 + X_1 X_4^2 - g\cos X_3 - \frac{k}{m}(X_3 - \omega_2) \\ \dot{X}_3 = X_4 \\ \dot{X}_4 = \frac{1}{ml}\omega_0\cos X_3 + \frac{g}{X_3}\sin X_3 - \frac{\beta}{ml}\frac{X_4^2}{X_3} \end{cases}$$

②



$I(t) = -R_1 V_2(t) + R_2 i_2(t)$

$R_1 > 0 \quad e \quad R_2 \geq 0$

$x_1 = L\dot{x}_1 + R_1 x_1 = V(t) \quad \Rightarrow \quad \dot{x}_1 = -R_1 x_1 + R_1 x_2^2$

$LKC_2: \; I - x_1 - C\dot{x}_2 - x_1(t) = 0 \quad \Rightarrow \quad I - x_1 - C\dot{x}_2 + R_2 x_2 - R_2 x_2^2 = 0$

$L\dot{x}_2 = x_2 - R_2 x_2$

$R = I(t)$

$$\Rightarrow \begin{cases} \dot{x}_1 = \frac{x_1}{L} - \frac{R}{L} x_2 \\ \dot{x}_2 = \frac{1}{C} - \frac{x_2}{C} + \frac{R_2}{C} x_2 - \frac{R_2}{C} x_2^2 \end{cases}$$

$V_2(t) = -R_1 x_1 + R_2 x_2^2$

$\cdot R = 0 \Rightarrow \quad R_1 = 0 \; \forall R_2 \qquad R_2 \geq 0 \; \forall R_1 \qquad I = 0$

$$\Rightarrow \begin{cases} \dot{x}_1 = 0 \\ \dot{x}_2 = 0 \end{cases} \Rightarrow \begin{cases} \frac{x_1}{L} - \frac{R}{L} x_2 = 0 \\ \frac{1}{C} - \frac{x_2}{C} + \frac{R_2}{C} x_2 - \frac{R_2}{C} x_2^2 = 0 \end{cases}$$

$$\Rightarrow \begin{cases} x_2 - R_2 x_2 = 0 \\ -x_2 + R_2 x_2 - L x_2^2 = 0 \end{cases} \Rightarrow \begin{cases} x_1 = x_2 \\ x_2 - R_2 - L x_2^2 = 0 \end{cases}$$

$$\Rightarrow \begin{cases} x_1 = x_2 \\ x_2 \left(x_2^2 - 1\right) = 0 \end{cases}$$

$$\vec{x}_1 = \begin{pmatrix} 0 \\ 0 \end{pmatrix} \quad \vec{x}_2^2 = \begin{pmatrix} 1 \\ 1 \end{pmatrix} \quad \vec{x}_3 = \begin{pmatrix} -1 \\ -1 \end{pmatrix}$$

$\vec{f}_1 = x_2 - R_2 x_2$

$\vec{f}_2 = -R_1 x_1 + R_2 x_2 - L x_2^2$

$\frac{\partial \vec{f}_1}{\partial x_1} = 0 \qquad \frac{\partial \vec{f}_1}{\partial x_2} = 1 \qquad \frac{\partial \vec{f}_2}{\partial x_1} = -1 \qquad \frac{\partial \vec{f}_2}{\partial x_2} = R_2 - 2 L x_2$

$$\Rightarrow A = \begin{bmatrix} 0 & 1 \\ -1 & R_2 - 2 L x_2 \end{bmatrix} \quad \forall R_2 \geq 0 \quad \Rightarrow \quad A = \begin{bmatrix} 0 & 1 \\ -1 & 0 \end{bmatrix} \qquad B = \begin{bmatrix} 0 \\ 0 \end{bmatrix}$$

$y_1(t) = -R_1 x_1 + R_2 x_2^2 = -R_1 x + R_2 x^2 \quad \Rightarrow \quad C = \begin{bmatrix} 0 & 0 \end{bmatrix} \qquad D = \begin{bmatrix} 0 \end{bmatrix}$

$\frac{\partial}{\partial x_1} \qquad \frac{\partial}{\partial x_2}$

[vapor acqua sonno]

$$\lambda I - A = \begin{bmatrix} \lambda & -1 \\ 1 & \lambda - R_2 + 2 L x_2 \end{bmatrix} \qquad \det(\lambda I - A) = \lambda\left(\lambda - R_2 + 2 L x_2\right) + 1 = \lambda^2 - R_2 \lambda + 2 L x_2 \lambda + 1 = \lambda^2 + \left(2 L x_2^2 - R_2\right)\lambda + 1$$

Im $\begin{bmatrix} 0 \\ 0 \end{bmatrix} \quad \Rightarrow \quad \lambda^2 - R_2 \lambda + 1 \Rightarrow$ soggetto al segno discorde $\Rightarrow$ instabile (1 sempre ≥ 1)

Im $\begin{bmatrix} 1 \\ 1 \end{bmatrix} \Rightarrow \lambda^2 + L\lambda + 1 \Rightarrow$ soggetto al segno concorde $\Rightarrow$ potenzialmente instabile (1 sempre ≥ 1)

Im $\begin{bmatrix} -1 \\ -1 \end{bmatrix} \Rightarrow \lambda^2 - 2\lambda + 5 \Rightarrow$ soggetto al segno discorde $\Rightarrow$ instabile (1 sempre ≥ 1)

③

$\dot{x}(t) = Ax(t) + Bu(t) \qquad A = \begin{bmatrix} -2 & 1 \\ 1 & -2 \end{bmatrix} \qquad B = \begin{bmatrix} 1 \\ 0 \end{bmatrix} \qquad C = \begin{bmatrix} 1 & 0 \end{bmatrix}$

$y(t) = Cx(t)$

- $X(t) = e^{At} \cdot x_0$

$e^{At} = L^{-1}\left[(sI - A)^{-1}\right] \qquad sI - A = \begin{bmatrix} \lambda+2 & -1 \\ -1 & \lambda+2 \end{bmatrix}$

$\det(sI - A) = (\lambda+2)(\lambda+2) - 1 = \lambda^2 + 2\lambda + 2\lambda + 4 - 1 = \lambda^2 + 4\lambda + 3$

$-2 \pm \sqrt{4 - 3} = -2 \pm 1 \begin{matrix} -1 \\ -3 \end{matrix} \qquad \Rightarrow \qquad (\lambda+3)(\lambda+1)$

$adj(sI - A)$

$C_{11} = \lambda + 2$

$C_{12} = -1 \quad (-1) \qquad \Rightarrow \quad C = \begin{bmatrix} \lambda+1 & 1 \\ 1 & \lambda+3 \end{bmatrix} \qquad C^T = C$

$C_{21} = -1 \quad (-1)$

$C_{22} : \lambda + 2$

$$\Rightarrow (sI - A)^{-1} = \begin{bmatrix} \frac{\lambda+2}{(\lambda+1)(\lambda+3)} & \frac{1}{(\lambda+1)(\lambda+3)} \\ \frac{1}{(\lambda+1)(\lambda+3)} & \frac{\lambda+2}{(\lambda+1)(\lambda+3)} \end{bmatrix}$$

$\frac{\lambda+2}{(\lambda+1)(\lambda+3)} = \frac{A}{\lambda+1} + \frac{B}{\lambda+3} \quad \Rightarrow \quad \forall\lambda \; A + B\lambda + 3B = \lambda + 2$

$$\Rightarrow \begin{cases} A + B = 1 \\ 3A + B = 2 \end{cases} \Rightarrow \begin{cases} A = 1 - B \\ -3 + B - 3B = 2 \end{cases} \Rightarrow \begin{cases} \cdot \\ -2B = 1 \end{cases} \Rightarrow \begin{cases} A = \frac{1}{2} \\ B = -\frac{1}{2} \end{cases}$$

$$\Rightarrow \frac{1}{2}\left(\frac{1}{\lambda+3}\right) + \frac{1}{2}\left(\frac{1}{\lambda+1}\right) \qquad L^{-1} = \frac{1}{2} e^{-3t} + \frac{1}{2} e^{-t}$$

$\frac{1}{(\lambda+3)(\lambda+1)} = \frac{A}{\lambda+3} + \frac{B}{\lambda+1} \Rightarrow \forall\lambda \; A + B\lambda + 3B = 1$

$$\Rightarrow \begin{cases} A + B = 0 \\ 3 + B - 3B = 1 \end{cases} \Rightarrow \begin{cases} A = -B \\ 0 - 3B = 1 \end{cases} \Rightarrow \begin{cases} A = \frac{1}{2} \\ B = -\frac{1}{2} \end{cases}$$

$$\Rightarrow \frac{1}{2}\left(\frac{1}{\lambda+3}\right) - \frac{1}{2}\left(\frac{1}{\lambda+1}\right) \qquad L^{-1} = \frac{1}{2} e^{-3t} - \frac{1}{2} e^{-t}$$

$$e^{At} = \begin{bmatrix} \frac{1}{2}e^{-3t} + \frac{1}{2}e^{-t} & \frac{1}{2}e^{-3t} - \frac{1}{2}e^{-t} \\ \frac{1}{2}e^{-3t} - \frac{1}{2}e^{-t} & \frac{1}{2}e^{-3t} + \frac{1}{2}e^{-t} \end{bmatrix}$$

$$X(t) = \begin{bmatrix} \frac{1}{2}e^{-3t} + \frac{1}{2}e^{-t} & \frac{1}{2}e^{-3t} - \frac{1}{2}e^{-t} \\ \frac{1}{2}e^{-3t} - \frac{1}{2}e^{-t} & \frac{1}{2}e^{-3t} + \frac{1}{2}e^{-t} \end{bmatrix} \begin{bmatrix} 1 \\ 1 \end{bmatrix}$$

$$x(t) = \begin{bmatrix} e^{At}\left(\frac{1}{3}x_1 + \frac{1}{3}x_2\right) + e^{t}\left(\frac{1}{3}x_1 - \frac{1}{3}x_2\right) \\ e^{At}\left(-\frac{1}{6}\right) + e^{t}\left(\frac{1}{6}\right) \end{bmatrix} = \begin{bmatrix} \frac{1}{6}e^{-3t} + \frac{1}{6}e^{t} \\ \frac{1}{6}e^{-3t} + \frac{1}{6}e^{t} \end{bmatrix}$$


$y(t) = C \cdot e^{At} \cdot B \qquad C = \begin{bmatrix} 1 & 0 \end{bmatrix}$

$$\begin{bmatrix} \frac{1}{2}e^{-3t} + \frac{1}{2}e^{t} & \frac{1}{2}e^{-3t} - \frac{1}{2}e^{t} \\ \frac{1}{2}e^{-3t} - \frac{1}{2}e^{t} & \frac{1}{2}e^{-3t} + \frac{1}{2}e^{t} \end{bmatrix} \begin{bmatrix} 1 \\ 0 \end{bmatrix}$$

$= \frac{1}{2}e^{-3t} + \frac{1}{2}e^{t}$

Risposta atmosmorzata. —

④



$A\,\hat{k} = q_A - q_0$

$F_k(t) - P_0 = R \cdot q \quad \Rightarrow \quad \frac{d}{dt} q_A = q_{A_0} \Rightarrow q_A = \frac{dq_A}{dt} t$

$\Rightarrow A\,\dot{\hat{k}} = q_A - \frac{dq_A}{dt}$

$\Rightarrow \dot{\hat{k}} = \frac{q_A}{A} - \frac{dq_A}{AR}$

$\cdot q_A = \bar{q} \quad \dot{k}(0) = 0 \quad \Rightarrow \quad \dot{\hat{k}} = \frac{\bar{q}_A}{A} - \frac{d\bar{q}_A}{AR} t$

$A = \left[\frac{dq_A}{dt}\right] = a$

$B = \left[\frac{1}{A}\right] = k$

$S\,X(s) - x_0 = a \qquad X(s) = k\,U(s) \qquad U(s) = \frac{\alpha}{s} - \frac{\beta}{s}$

$x(s) = \frac{x_0}{s-a} + \frac{k}{s-a} U(s)$

$\Rightarrow x(s) = \left(\frac{1}{A}\right)\left(\frac{\alpha}{s^2} - \frac{\beta}{s}\right) \frac{1}{\left(s - \frac{dq_A}{AR}\right)}$

$\Rightarrow \quad \frac{R}{s} = \frac{R}{(sR - dq_A)} \quad \Rightarrow \quad RsAR + Rdq_A + B\lambda = \bar{q}R$

$$\Rightarrow \begin{cases} RsAR + Rdq_A = 0 \\ +Rdq_A = \bar{q}R \end{cases} \Rightarrow \begin{cases} B = -\frac{Rdq_A}{dq_A} \\ K = \frac{\bar{q}R}{dq_A} \end{cases}$$

$\Rightarrow \quad \frac{\bar{q}R}{dq_A} \frac{1}{s} - \frac{Rdq_A}{dq_A} \frac{1}{sRA - dq_A} + \frac{\bar{q}R}{dq_A} \frac{1}{s} - \frac{\bar{q}Rdq_A}{dq_A} \frac{A}{sRA - dq_A}$

$= \frac{q_A}{dq_A} - \frac{q_A}{dq_A} e^{\frac{dq_A}{RA} t}$

$L(\omega) = \lim_{s \to 0} s\,x(s) = \lim_{s \to 0} s \cdot \frac{\bar{q}R}{s(sRA - dq_A)} = \frac{\bar{q}R}{dq_A}$

$\cdot q_A(t) = \qquad \dot{k}(0) = \frac{\bar{q}R}{dq_A}$

$\dot{k}(t) = e^{At} \cdot x_0 \quad \Rightarrow \quad \dot{k}(t) = e^{\frac{dq_A}{RA} t} \frac{\bar{q}R}{dq_A}$

$\frac{\bar{q}R}{dq_A} = e^{\frac{dq_A}{RA} t} \frac{\bar{q}R}{dq_A} \quad = \quad e^{\frac{dq_A}{RA} t} = \frac{1}{2} \quad \Rightarrow \quad -\frac{dq_A}{RA} t = \ln\left(\frac{1}{2}\right)$

$\Rightarrow t = \frac{\ln\left(\frac{1}{2}\right)}{\left(-\frac{dq_A}{RA}\right)}$

⑤ —

Prova 10/04/2014

1) $T_1 = \frac{1}{2} J \dot{\psi}^2 \qquad T_2 = \frac{1}{2} M_1 \dot{s}_1^2 \qquad T_3 = \frac{1}{2} M_2 \dot{s}_2^2$

$\dot{\overline{OG}} = \langle l\sin\theta + s,\ l\cos\theta \rangle \qquad \bar{v} = \dot{\overline{OG}} = \langle \dot\theta l\cos\theta + \dot s,\ -l\sin\theta \rangle$

$|\bar v|^2 = \dot\theta^2 l^2\cos^2\theta + \dot s_2^2 + 2\dot s_2\dot\theta l\cos\theta + l^2\sin^2\dot\theta^2 = \dot\theta^2 l^2 + \dot s(\dot s + 2\dot\theta l\cos\theta)$

$\Rightarrow T_4 = \frac{1}{2} m (\dot\theta^2 l^2 + \dot s_2(\dot s_2 + 2\dot\theta l\cos\theta)) + \frac{1}{2} J_4 \dot\theta^2$

$T = \frac{1}{2} J \dot\psi^2 + \frac{1}{2} M_1 \dot s_1^2 + \frac{1}{2} M_2 \dot s_2^2 + \frac{1}{2} m (\dot\theta^2 l^2 + \dot s(\dot s + 2\dot\theta l\cos\theta)) + \frac{1}{2} J_4 \dot\theta^2$

$\psi \cdot r = s_1 \quad \Rightarrow \quad \psi = \frac{s_1}{r}$

$\Rightarrow T = \frac{1}{2}\frac{J}{r^2}\dot s_1^2 + \frac{1}{2} M_1 \dot s_1^2 + \frac{1}{2} M_2 \dot s_2^2 + \frac{1}{2} m (\dot\theta^2 l^2 + \dot s_2(\dot s_2 + 2\dot\theta l\cos\theta)) + \frac{1}{2} J_4 \dot\theta^2$

$U = U_p + U_E \qquad U_p = -m\cdot g\cdot(s_2 + l\cos\theta)$

$U_E = \frac{1}{2} K\cdot(s_1 - s_2)^2 \qquad R = \frac{1}{2}\beta(\dot s_1 - \dot s_2)^2$

$U_{TOT} = -mg(s_2 + l\cos\theta) + \frac{1}{2} K(s_1 - s_2)^2$

$\frac{\partial T}{\partial \dot s_1} = \frac{J}{r^2}\dot s_1 + M_1 \dot s_1 \qquad \frac{d}{dt}\left(\frac{\partial T}{\partial \dot s_1}\right) = \frac{J}{r^2}\ddot s_1 + M_1 \ddot s_1 \qquad \frac{\partial T}{\partial s_1} = 0$

$\frac{\partial T}{\partial \dot s_2} = M_2 \dot s_2 + m\dot s_2 + m\dot\theta l\cos\theta \qquad \frac{d}{dt}\left(\frac{\partial T}{\partial \dot s_2}\right) = M_2 \ddot s_2 + m\ddot s_2 + m\ddot\theta l\cos$

$\frac{\partial T}{\partial \dot\theta} = m\dot\theta l^2 + \frac{1}{2} m \dot s_2 l\cos\theta + J_4\dot\theta \qquad \frac{d}{dt}\left(\frac{\partial T}{\partial \dot\theta}\right) = m\ddot\theta l^2 - \frac{1}{2} m \dot s_2 l\theta\,\mathrm{scm}\theta + J_4\ddot\theta$

$\frac{\partial U_{TOT}}{\partial \theta} = -mgl\sin\theta \qquad \frac{\partial U_{TOT}}{\partial s_1} = K(s_1 - s_2)$

$\frac{\partial U_{TOT}}{\partial s_2} = -mg - K(s_1 - s_2)$

$\frac{\partial R}{\partial \theta} = 0 \qquad \frac{\partial R}{\partial s_1} = \beta(\dot s_1 - \dot s_2) \qquad \frac{\partial R}{\partial s_2} = -\beta(\dot s_1 - \dot s_2)$

Forza esterna: $C \quad \Rightarrow \quad dL = F\cdot \delta r = C\cdot \delta\psi = C\cdot \delta\frac{s_1}{r}$

$C\cdot\frac{d}{d\theta}\frac{s_1}{r}\delta\theta + C\cdot\frac{d}{ds_1}\frac{s_1}{r}\delta s_1 + C\cdot\frac{d}{ds_2}\frac{s_1}{r}\cdot\delta s_2 = 0\cdot\delta\theta + \frac{C}{r}\delta s_1 + 0\,\delta s_2$

$Q_1 = \frac{C}{r} \qquad Q_2 = 0 \qquad Q_3 = 0$

$$\Rightarrow \begin{cases} m\ddot\theta l^2 - \frac{1}{2} m\dot s_2 l\theta\,\mathrm{scm}\theta + J_4\ddot\theta - mgl\sin\theta = \frac{C}{r} \\ \frac{J}{r^2}\ddot s_1 + M_1\ddot s_1 + K(s_1 - s_2) + \beta(\dot s_1 - \dot s_2) = 0 \\ M_2\ddot s_2 + m\ddot s_2 + m\ddot\theta l\cos\theta - mg - K(s_1 - s_2) - \beta(\dot s_1 - \dot s_2) = 0 \end{cases}$$

Sistemi idraulici

1) $q_1 - q_4 = A\,\dot{h}$ $\qquad x_1 = h \quad x_2 = q_1 \quad x_3 = q_4$

$p_a - p = R\,q_1 + L\,\dot{q_1}$ $\qquad p = \rho g h$

$p - p_a = R\,q_4 + L\,\dot{q_4}$

$$\begin{cases} \dot{x_1} = \dfrac{x_2}{A} - \dfrac{x_3}{A} \\ u - \rho g h = R\,q_1 + L\,\dot{q_1} \\ \rho g h = R\,q_4 + L\,\dot{q_4} \end{cases} \Rightarrow \begin{cases} \dot{x_1} = \dfrac{x_2}{A} - \dfrac{x_3}{A} \\ \dot{x_2} = \dfrac{u}{L} - \dfrac{\rho g}{L} x_1 - \dfrac{R x_2}{L} \\ \dot{x_3} = \dfrac{\rho g}{L} x_1 - \dfrac{R}{L} x_3 \end{cases}$$

$$A = \begin{bmatrix} 0 & \frac{1}{A} & -\frac{1}{A} \\ -\frac{\rho g}{L} & -\frac{R}{L} & 0 \\ \frac{\rho g}{C} & 0 & -\frac{K}{L} \end{bmatrix} \qquad B = \begin{bmatrix} 0 \\ \frac{1}{L} \\ 0 \end{bmatrix} \qquad C = \begin{bmatrix} 1 & 0 & 0 \\ 0 & 0 & 1 \end{bmatrix} \qquad D = \begin{bmatrix} 0 \\ 0 \end{bmatrix}$$

$$\begin{cases} \frac{x_2}{K} - \frac{x_3}{A} = 0 \\ \frac{2}{L} - \frac{\rho g}{L} x_1 - \frac{R x_2}{L} = 0 \\ \frac{\rho g}{L} x_1 - \frac{R}{L} x_3 = 0 \end{cases} \qquad \begin{cases} x_2 = x_3 \\ -\rho g\, x_1 - R x_3 = -L \\ x_1 = \frac{Q}{\rho g} x_3 \end{cases} \qquad \begin{cases} x_2 = x_3 \\ -R x_3 = -K \\ // \end{cases}$$

$$\begin{cases} x_2 = x_3 \\ x_3 = \frac{1}{R} \\ x_1 = \frac{1}{\rho g} \end{cases} \Rightarrow \begin{cases} \frac{1}{\rho g} \\ \frac{1}{L} \\ \frac{1}{R} \end{cases}$$

2) $x_1 = h_1 \quad x_2 = q_1 \quad x_3 = q_2 \quad x_4 = h_2$

$A_1\,\dot{h_1} = q_4 - q_1 - q_2$ $\qquad u_1 = q_4 \quad u_2 = A$

$\rho g (h_1 - d) = R\,q_1 + L\,\dot{q_1}$

$\rho g h_1 - \rho g h_2 = R\,q_2 + L\,\dot{q_2}$

$A_2\,\dot{h_2} = q_1 + q_2 - q_3$

$\rho g h_2 = R\,q_3 \Rightarrow q_3 = \dfrac{\rho g h_2}{R}$

$$\begin{cases} \dot{x_1} = \frac{u_1}{A_1} - \frac{x_2}{A_1} - \frac{x_3}{A_1} \\ \dot{x_2} = \frac{\rho g}{L}(x_1 - u_2) - \frac{R}{L} x_2 \\ \dot{x_3} = \frac{\rho g}{L} x_1 - \frac{\rho g}{L} x_4 - \frac{R}{L} x_3 \\ \dot{x_4} = \frac{x_2}{A_2} + \frac{x_3}{A_2} - \frac{\rho g}{R A_2} x_4 \end{cases} \qquad A = \begin{bmatrix} 0 & -\frac{1}{A_1} & -\frac{1}{A_1} & 0 \\ \frac{\rho g}{L} & -\frac{R}{L} & 0 & 0 \\ \frac{\rho g}{L} & 0 & -\frac{R}{L} & -\frac{\rho g}{L} \\ 0 & \frac{1}{A_2} & \frac{1}{A_2} & -\frac{\rho g}{R A_2} \end{bmatrix} \qquad B = \begin{bmatrix} \frac{1}{A_1} & 0 \\ 0 & -\frac{\rho g}{L} \\ 0 & 0 \\ 0 & 0 \end{bmatrix}$$

$y_1 = h_1 \quad y_2 = h_2$

$y_3 = q_4 = \dfrac{\rho g}{R} h_2$ $\qquad C = \begin{bmatrix} 1 & 0 & 0 & 0 \\ 0 & 0 & 0 & 1 \\ 0 & 0 & 0 & \frac{\rho g}{R} \end{bmatrix} \qquad D = \begin{bmatrix} 0 & 0 \\ 0 & 0 \\ 0 & 0 \end{bmatrix}$

3) $x_1 = q_1 \quad x_2 = h(t) \quad x_3 = s \quad x_4 = \dot{s}$

$R_i = \dfrac{F}{A_p} \qquad F - \rho g h = R\,q_1 + L\,\dot{q_1} + \rho g A$

$A_s \cdot \dot{h} = q_1 - q_2$

$q_2 = A_p\,\dot{s}$

$m\ddot{s} = F_m - K s - \rho \dot{s}$

$\rho g h - \dfrac{F_m}{A_p} = R\,q_2 + L\,\dot{q_2} \Rightarrow -F_m = -\rho g h A_p + R A_p^2 \dot{s} + L A_p \ddot{s}$

$m\ddot{s} = \rho g h A_p - R A_p^2 \dot{s} - L A_p^2 \ddot{s} - K s - \rho \dot{s}$

$\Rightarrow \ddot{s}(m + L A_p^2) = \rho g h A_p - R A_p^2 \dot{s} - K s - \rho \dot{s}$

$$\begin{cases} \dot{q_1} = \dfrac{F}{A_p L} - \dfrac{\rho g h}{L} - \dfrac{R}{L} q_1 - \dfrac{\rho g A}{L} \\ \dot{h} = \dfrac{q_1}{A_s} - \dfrac{A_p}{A_s} \dot{s} \\ \ddot{s} = \dfrac{\rho g A_p}{(m + L A_p)} - \dfrac{R A_p^2 \dot{s}}{(m + L A_p^2)} - \dfrac{K s}{(m + L A_p^2)} - \dfrac{\rho \dot{s}}{(m + L A_p^2)} \\ \dot{s} = \dot{s} \end{cases}$$

$K_1 = m + L A_p^2$

$$\Rightarrow \begin{cases} \dot{x_1} = \frac{u_1}{A_p L} - \frac{\rho g}{L} x_2 - \frac{R}{L} x_1 - \frac{\rho g}{L} u_2 \\ \dot{x_2} = \frac{x_1}{A_s} - \frac{A_p}{A_s} x_4 \\ \dot{x_3} = x_4 \\ \dot{x_4} = \frac{\rho g A_p^2}{K_1} x_2 - \frac{R A_p^2}{K_1} x_4 - \frac{K}{K_1} x_3 - \frac{A}{K_1} x_4 \end{cases}$$

$$A = \begin{bmatrix} -\frac{R}{L} & -\frac{\rho g}{L} & 0 & 0 \\ \frac{1}{A_s} & 0 & 0 & -\frac{A_p}{A_s} \\ 0 & 0 & 0 & 1 \\ 0 & \frac{\rho g A_p}{K_1} & -\frac{K}{K_1} & \frac{(R A_p^2 - \rho)}{K_1} \end{bmatrix} \qquad B = \begin{bmatrix} \frac{1}{A_p L} & -\frac{\rho g}{L} \\ 0 & 0 \\ 0 & 0 \\ 0 & 0 \end{bmatrix}$$

$u_1 = s(t) \quad u_2 = h_i(t)$ $\qquad C = \begin{bmatrix} 0 & 0 & 1 & 0 \\ 0 & 1 & 0 & 0 \end{bmatrix} \qquad D = \begin{bmatrix} 0 & 0 \\ 0 & 0 \end{bmatrix}$

4) $x_1 = h_1 \quad x_2 = h_2 \quad x_3 = q_{23} \quad x_4 = q_3$

$A_1 \cdot \dot{h_1} = q_1 - q_{12}$ $\qquad \rho g h_1 = R_1 q_{12} \Rightarrow q_{12} = \dfrac{\rho g h_1}{R_1}$

$\Rightarrow A_1\,\dot{h_1} = q_1 - \dfrac{\rho g}{R} h_1$

$A_2\,\dot{h_2} = q_{12} - q_{23} \qquad q_{23} = \dfrac{\rho g h_2}{R_3}$

$\rho g (h_2 - d_1) - \rho g h_3 = R_2 q_{23} + L_2 \dot{q_{23}} + \rho g (-q_3)$

$A_3\,\dot{h_3} = q_{23} + q_3 - q_4 \qquad q_4 = \dfrac{\rho g h_3}{R_4}$

$u_1 = q_1 \quad u_2 = q_2$


$$\begin{cases} A_1 \cdot \dot{x_1} = u_1 - \frac{\rho g}{R} x_1 \\ A_2\,\dot{x_2} = \frac{\rho g}{R_1} x_1 - \frac{\rho g}{R_3} x_2 - x_3 \\ L \cdot \dot{x_3} = \rho g\, x_2 - \rho g\, h_3 - \rho g\, x_4 - R_2 x_3 + \rho g\, u_2 \\ A_3\,\dot{x_4} = x_3 + u_2 - \frac{\rho g}{R_4} x_4 \end{cases}$$

$$\Rightarrow \begin{cases} \dot{x_1} = \frac{u_1}{A_1} - \frac{\rho g}{A_1 R} x_1 \\ \dot{x_2} = \frac{\rho g}{A_2 R_1} x_1 - \frac{\rho g}{A_2 R_3} x_2 - \frac{x_3}{A_2} \\ \dot{x_3} = \frac{\rho g}{L} x_2 - \frac{\rho g}{L} u_2 - \frac{\rho g}{L} x_4 - \frac{R_2}{L} x_3 + \frac{\rho g}{L} u_2 \\ \dot{x_4} = \frac{x_3}{A_3} + \frac{u_2}{A_3} - \frac{\rho g}{A_3 R_4} x_4 \end{cases}$$

$$A = \begin{bmatrix} -\frac{\rho g}{A_1 R_1} & 0 & 0 & 0 \\ \frac{\rho g}{A_2 R_1} & -\frac{\rho g}{A_2 R_3} & -\frac{1}{A_2} & 0 \\ 0 & \frac{\rho g}{L} & -\frac{R_2}{L} & -\frac{\rho g}{L} \\ 0 & 0 & \frac{1}{A_3} & -\frac{\rho g}{A_3 R_4} \end{bmatrix} \qquad B = \begin{bmatrix} \frac{1}{A_1} & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 \\ 0 & 0 & -\frac{\rho g}{L} & \frac{\rho g}{L} \\ 0 & \frac{1}{A_3} & 0 & 0 \end{bmatrix}$$

$$C = \begin{bmatrix} 1 & 0 & 0 & 0 \\ 0 & 0 & 0 & 1 \\ 0 & 0 & 0 & \frac{\rho g}{R_4} \end{bmatrix} \qquad D = \begin{bmatrix} 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 \end{bmatrix}$$

Prove amplificatori



$LKC_A: \quad i(t) + C\dot{x}_1 + R x_1 = 0$

$LKC_B: \quad \frac{w}{R} - i_1 - i_2 = 0$

$LKT_1: \quad R i_1 + r(t) = 0 \Rightarrow i_1 = -\frac{r(t)}{R}$

$LKT: \quad x_2 + R i_2 = 0 \Rightarrow i_2 = -\frac{x_2}{R}$

$\Rightarrow \frac{w}{R} + \frac{r(t)}{R} + \frac{x_2}{R} = 0 \Rightarrow r(t) = -(x_2 + w)$

$\Rightarrow i(t) = -k_1 \cdot (x_2 + w) + k_2 (x_2 + w)^2$

$\Rightarrow C\dot{x}_1 = k_1 (x_2 + w) - k_2 (x_2 + w)^2 - R x_1$

$\Rightarrow \dot{x}_1 = \frac{k_1}{C} (x_2 + w) - \frac{k_2}{C} (x_2 + w)^2 - \frac{R}{C} x_1$

$LKC_2: \quad i_2 - C_2 \dot{x}_2 - i_3 = 0$

$LKT_3: \quad x_2 - i_3 \cdot R - x_1 = 0 \Rightarrow i_3 = \frac{x_2}{R} - \frac{x_1}{R}$

$\Rightarrow C_2 \dot{x}_2 = -\frac{x_2}{R} + \frac{x_1}{R} - \frac{x_2}{R} \Rightarrow -\frac{2 x_2}{R} + \frac{x_1}{R}$

$\Rightarrow \dot{x}_2 = -\frac{2 x_2}{RC} + \frac{x_1}{RC}$

$$\begin{cases} \dot{x}_1 = \frac{k_1}{C} (x_2 + w) - \frac{k_2}{C} (x_2 + w)^2 - \frac{1}{RC} x_1 \\ \dot{x}_2 = -\frac{2 x_2}{RC} + \frac{x_1}{RC} \end{cases}$$

$R = 1 \quad k_1 = 4 \quad k_2 = 2$

$$\Rightarrow \begin{cases} \dot{x}_1 = \frac{4}{C} (x_2 + w) - \frac{2}{C} (x_2 + w)^2 - \frac{1}{C} x_1 \\ \dot{x}_2 = -\frac{2 x_2}{RC} + \frac{x_1}{RC} \end{cases}$$

$$\Rightarrow \begin{cases} \dot{x}_1 = 0 \Rightarrow \frac{4}{C} (x_2 + w) - \frac{2}{C} (x_2 + w)^2 - \frac{1}{C} x_1 = 0 \\ \dot{x}_2 = 0 \Rightarrow -\frac{2 x_2}{RC} + \frac{x_1}{RC} = 0 \end{cases}$$

$$\Rightarrow \begin{cases} 4 x_2 - 2 x_2^2 - x_1 = 0 \\ x_1 = 2 x_2 \end{cases} \Rightarrow \begin{cases} +2 x_2^1 - 2 x_2 = 0 \\ x_1 = 2 x_2 \end{cases} \Rightarrow \quad x_e' = \begin{Bmatrix} 0 \\ 0 \end{Bmatrix} \quad x_e'' = \begin{Bmatrix} 2 \\ 1 \end{Bmatrix}$$

$$\frac{\partial f_1}{\partial x_1} = -1 \qquad \frac{\partial f_1}{\partial x_2} = 4 - 4 x_2 \qquad \frac{\partial f_2}{\partial x_1} = 1 \qquad \frac{\partial f_2}{\partial x_2} = -2$$

$$\Rightarrow \begin{bmatrix} -1 & 4 - 4 x_2 \\ 1 & -2 \end{bmatrix} \qquad \lambda_i - M = \begin{bmatrix} \lambda + 1 & 4 x_2 - 4 \\ -1 & \lambda + 2 \end{bmatrix}$$


$$\Rightarrow (\lambda + 1)(\lambda + 2) + 4 x_2 - 4 \Rightarrow \lambda^2 + 2\lambda + \lambda + 2 + 4 x_2 - 4 = \lambda^2 + 3\lambda - 2 - 4 x_2$$

in $\begin{Bmatrix} 0 \\ 0 \end{Bmatrix} \Rightarrow \lambda^2 + 3\lambda - 2 = 0 \Rightarrow -3 \pm \sqrt{4 - 4 \cdot (-2)} \Rightarrow \frac{-3 \pm \sqrt{17}}{2}$

$\Rightarrow$ instabile

in $\begin{Bmatrix} 2 \\ 1 \end{Bmatrix} \Rightarrow \lambda^2 + 3\lambda - 0 \Rightarrow$ stabile $\Rightarrow$ schemi concordi

Esercizi sistemi 1° e 2° ordine



$R = K_1 + \frac{K_2}{s}$ $\quad G(s) = \frac{1}{s+4}$

$\hookrightarrow \frac{K_1 s + K_2}{s}$

$\Rightarrow G_R(s) = G \cdot R = \frac{K_1 s + K_2}{s(s+4)} \Rightarrow W(s) = \frac{\frac{K_1 s + K_2}{s(s+4)}}{1 + \frac{K_1 s + K_2}{s(s+4)}}$

$\Rightarrow \frac{\frac{K_1 s + K_2}{s(s+4)}}{\frac{s(s+4) + K_1 s + K_2}{s(s+4)}} \Rightarrow \frac{K_1 s + K_2}{s(s+4) + K_1 s + K_2}$

$\Rightarrow \frac{K_1 s + K_2}{s^2 + (4+K_1) s + K_2}$

$e(s) = r(s) - W \cdot r(s)$

$= \frac{1}{s^2} - W \cdot \frac{1}{s^2} = \frac{1}{s^2}(1 - W) \Rightarrow \frac{1}{s^2}\left(\frac{s(s+4) + K_1 s + K_2 - K_1 s - K_2}{s(s+4) + K_1 s + K_2}\right)$

$\Rightarrow \frac{1}{s^2}\left(\frac{s(s+4)}{s(s+4) + K_1 s + K_2}\right) = \frac{1}{s}\left(\frac{s+4}{s(s+4) + K_1 s + K_2}\right)$

$e(\infty) = \lim_{t \to \infty} e(t) = \lim_{s \to 0} s \cdot e(s) = \lim_{s \to 0} s \cdot \frac{1}{s}\left(\frac{s+4}{s(s+4) + K_1 s + K_2}\right)$


$= \frac{4}{K_2}$

L'errore a regime deve essere $0.01 \Rightarrow \frac{4}{K_2} = 0.01 \Rightarrow K_2 = 400$

$W(s) = \frac{K_1 s + K_2}{s^2 + (4+K_1) s + K_2}$

$\begin{cases} 4 + K_1 = 2 \delta \omega_n \\ \omega_n^2 = K_2 \end{cases} \Rightarrow \begin{cases} 4 + K_1 = 2 \cdot \frac{1}{2} \cdot 20 \\ \omega_n = \sqrt{K_2} = 20 \end{cases} \Rightarrow \begin{cases} K_1 = 16 \\ K_2 = 40 \end{cases}$

5 prova 3)



$R = \frac{K}{s+a}$ $\quad G(s) = \frac{s+1}{s+2}$

$G_R(s) = R \cdot G = \frac{Ks + K}{(s+a)(s+2)} \Rightarrow W(s) = \frac{G_R}{1 + G_R} = \frac{\frac{Ks+K}{(s+a)(s+2)}}{1 + \frac{Ks+K}{(s+a)(s+2)}}$

$\Rightarrow \frac{\frac{Ks+K}{(s+a)(s+2)}}{\frac{(s+a)(s+2) + Ks + K}{(s+a)(s+2)}} \Rightarrow \frac{Ks+K}{(s+a)(s+2) + Ks + K}$


$\Rightarrow \frac{Ks+K}{s^2 + 2s + as + 2a + Ks + K} \Rightarrow \frac{Ks+K}{s^2 + (2+a+K)s + 2a + K}$

$T_{d5} = 0.2 \Rightarrow 0.2 = \frac{3}{\delta \cdot \omega_n} \Rightarrow \omega_n = 6 \Rightarrow 0.2 = \frac{1}{\delta \cdot 2} = \delta = \frac{1}{2 \cdot 0.2}$

$\delta = \frac{5}{2}$

$\Rightarrow \delta = 10$

$\begin{cases} (2+a+K) = 2 \cdot \frac{5}{2} \cdot 6 \\ 2a + K = 36 \end{cases} \Rightarrow \begin{cases} 2 + a + K = 30 \\ 2a + K = 36 \end{cases} \Rightarrow \begin{cases} K = 30 - a - 2 \\ 2a + 30 - a - 2 = 36 \end{cases} \overset{6}{\Rightarrow} \begin{cases} K = 20 \\ a = 8 \end{cases}$



$R(s) = \frac{20}{s+8}$ $\quad G(s) = \frac{s+1}{s+2}$

$\frac{\left(\frac{1}{s}\right)}{\left(\frac{20}{s+8}\right)} \Rightarrow \frac{s+8}{20s}$ $\quad G_R(s) = \frac{Ks+K}{(s+a)(s+2)}$ $\quad W(s) = \frac{Ks+K}{s^2 + (2+a+K)s + 2a + K}$

$\Rightarrow W(s) = \frac{20s + 20}{s^2 + 30s + 36}$

$Y_s = W(s) \cdot \left(r(s) + \frac{d(s)}{R}\right)$

$Y_s = \frac{20s+20}{s^2 + 30s + 36} \cdot \left(\frac{1}{s} + \frac{(s+8)}{20s}\right) = \frac{20s+20}{s^2 + 30s + 36} \cdot \left(\frac{28+s}{20s}\right)$

$y(\infty) = \lim_{s \to 0} Y(s) = s \cdot \frac{20s+20}{s^2 + 30s + 36} \cdot \left(\frac{28+s}{20s}\right) \Rightarrow \frac{20 \cdot 28}{20 \cdot 36} \overset{14}{\overset{18}{\overset{7}{}}} \Rightarrow \boxed{\frac{7}{9}}$

Esercizi: risposte armoniche

1) 2) $G(s) = C \cdot e^{At} \cdot B + D$