

Exp 7: PHP Program to display digital clock with current time of the Server.

Write a PHP program to display a digital clock which displays the current time of the server.

Aim:

To Write a PHP Program to display digital clock with current time of the Server.

Program 7.php

```
<!DOCTYPE HTML>
<html>
<head>
    <meta http-equiv="refresh" content="1"/>
    <style>
        p {
            color:white;
            font-size:90px;
            position: absolute;
            top: 50%;
            left: 50%;
            transform: translate(-50%, -50%);
        }
        body{background-color:black;}
    </style>
    <p> <?php echo date(" h: i : s A");?> </p>
</head>
```

Sample Output:



10: 44 : 08 AM

The sample output shows a black rectangular box with the time '10: 44 : 08 AM' displayed in large, white, serif font.