

CSE 331: Microprocessor Interfacing and Embedded Systems

Lecture 5: **Instruction Representation**

Stored-Program Concept

- ❖ Computers built on 2 key principles:
 - 1) Instructions are represented as numbers.
 - 2) Therefore, entire programs can be stored in memory to be read or written just like numbers (data).
- ❖ Simplifies SW/HW of computer systems:
 - ❖ Memory technology for data also used for programs

Consequence #1: Everything Addressed

- ❖ Since all instructions and data are stored in memory as numbers, everything has a memory address: instructions, data words
 - ❖ both branches and jumps use these
- ❖ C pointers are just memory addresses: they can point to anything in memory
 - ❖ Unconstrained use of addresses can lead to nasty bugs; up to you in C; limits in Java
- ❖ One register keeps address of instruction being executed:
 - “Program Counter” (PC)
 - ❖ Basically a pointer to memory: Intel calls it Instruction Address Pointer, a better name

Consequence #2: Binary Compatibility

- ❖ Programs are distributed in binary form
 - ❖ Programs bound to specific instruction set
 - ❖ Different version for Macintosh and IBM PC
- ❖ New machines want to run old programs (“binaries”) as well as programs compiled to new instructions
- ❖ Leads to instruction set evolving over time
- ❖ Selection of Intel 8086 in 1981 for 1st IBM PC is major reason latest PCs still use 80x86 instruction set (Pentium 4); could still run program from 1981 PC today

Instructions as Numbers


- ❖ Most of the data that we work with is in words (32-bit blocks):
 - ❖ Each register is a word.
 - ❖ LDR and STR both access memory one word at a time.
- ❖ So how do we represent instructions?
 - ❖ Remember: Computer only understands 1s and 0s, so “ADD r0, r0, #0” is meaningless.
 - ❖ “Regular” ARM instructions are 32 bits.
 - ❖ Thumb ARM instructions are 16 bits.

Instructions as Numbers

- ❖ Divide instruction word into “fields”
- ❖ Each field tells computer something about instruction
- ❖ There is an attempt to reuse fields across instructions as much as possible.
- ❖ Simple = less complex hardware which generally leads to better performance


Data Processing Instructions

❖ Define “fields”:



- ❖ **Important:** Each field is viewed as an independent unsigned integer, not as part of a 32-bit integer.
 - ❖ Consequence: 5-bit fields can represent any number 0-31, while 6-bit fields can represent any number 0-63.

Data Processing Instructions




❖ What do these field integer values tell us?

❖ OpCode: specifies the specific data processing instruction


0000 = AND - Rd:= Op1 AND Op2
0001 = EOR - Rd:= Op1 EOR Op2
0010 = SUB - Rd:= Op1 - Op2
0011 = RSB - Rd:= Op2 - Op1
0100 = ADD - Rd:= Op1 + Op2
0101 = ADC - Rd:= Op1 + Op2 + C
0110 = SBC - Rd:= Op1 - Op2 + C - 1
0111 = RSC - Rd:= Op2 - Op1 + C - 1
1000 = TST - set condition codes on Op1 AND Op2
1001 = TEQ - set condition codes on Op1 EOR Op2
1010 = CMP - set condition codes on Op1 - Op2
1011 = CMN - set condition codes on Op1 + Op2
1100 = ORR - Rd:= Op1 OR Op2
1101 = MOV - Rd:= Op2
1110 = BIC - Rd:= Op1 AND NOT Op2
1111 = MVN - Rd:= NOT Op2

Data Processing Instructions



- ❖ What do these field integer values tell us?
 - ❖ Rd: Destination Register
 - ❖ Rn: 1st Operand Register
- ❖ Each register field is 4 bits, which means that it can specify any unsigned integer in the range 0-15. Each of these fields specifies one of the 16 registers by number.


Data Processing Instructions




❖ More fields:

- ❖ I (**Immediate**)
- ❖ 0: Operand 2 is a Register


Immediate Operand




❖ 1: Operand 2 is an Immediate




Data Processing Instructions




❖ Operand 2:



❖ Shift field:



Data Processing Instructions



❖ More fields:

- ❖ S (Set Condition Fields)
 - ❖ 0: Do not alter condition fields
 - ❖ 1: Set condition fields
 - ❖ These set the C, N, Z, V flags in the CPSR
- ❖ Cond (Condition Field)
 - ❖ Determines whether the instruction resulted is committed
 - ❖ Used with ADDEQ, ADDNE, ADDGT, etc.

Condition Field

Code	Suffix	Flags	Meaning
0000	EQ	Z set	equal
0001	NE	Z clear	not equal
0010	CS	C set	unsigned higher or same
0011	CC	C clear	unsigned lower
0100	MI	N set	negative
0101	PL	N clear	positive or zero
0110	VS	V set	overflow
0111	VC	V clear	no overflow
1000	HI	C set and Z clear	unsigned higher
1001	LS	C clear or Z set	unsigned lower or same
1010	GE	N equals V	greater or equal
1011	LT	N not equal to V	less than
1100	GT	Z clear AND (N equals V)	greater than
1101	LE	Z set OR (N not equal to V)	less than or equal
1110	AL	(ignored)	always

ARM Registers

Register	Synonym	Role in Procedure Call Standard
r0-r1	a1-a2	Argument/Result/Scratch Register
r2-r3	a3-a4	Argument/Scratch Register
r4-r8	v1-v5	Variable Register
r9	v6/sb/tr	Platform Register (static base/thread)
r10-r11	v7-v8	Variable Register
r12	ip	Intra-Procedure Call Scratch Register
r13	sp	Stack Pointer
r14	lr	Link Register
r15	pc	Program Counter

Data Processing Example

❖ ARM Instruction: `ADD r0, r1, r2`

cond = 1110 (always – unconditional)

S = 0 (not ADDS)

I = 0 (second operand not a constant)


opcode = 0100 (look up)

rd = 0 (destination *operand*)

rn = 1 (first *operand*) operand 2



shift = 0

Rm = 2



Data Processing Example

- ❖ ARM Instruction: ADD r0, r1, r2



Binary number per field representation:

hex representation: 0xE0810002

- ❖ Called a [Machine Language Instruction](#)

Data Processing Example

❖ ARM Instruction: SUBEQ a1, v7, r2, LSL #3

cond = 0000 (equal)

S = 0 (not SUBEQS)

I = 0 (second operand not a constant)

opcode = 0010 (look up)

rd = 0000 (destination *operand*: a1 = r0)


rn = 1010 (1st *operand*: v7 = r10)

operand 2

rm = 0010 (2nd *operand*: r2)





shift amount = 00011

Shift Type = 00



Data Processing Example

❖ ARM Instruction: SUBEQ a1, v7, r2, LSL #3



Data Processing Example

❖ ARM Instruction: BIC v6, a1, a2, ROR

cond = 1110 (always)

S = 0 (not BICS)

I = 0 (second operand not a constant)

opcode = 1110 (look up)

rd = 1001 (destination *operand: v6 = r9*)


rn = 0000 (1st *operand: a1 = r0*)

operand 2

rm = 0001 (2nd *operand: a2 = r1*)





rs = 0101 (shift operand: v2 = r5)

Shift Type = 11 (ROR)



Data Processing Example

❖ ARM Instruction: BIC v6, a1, a2, ROR v2



00 = logical left
01 = logical right
10 = arithmetic right
11 = rotate right

Shift amount specified in bottom byte of Rs

Data Processing Example

❖ ARM Instruction: EORGTs r6, r2, #10

cond = 1100 (greater than)

S = 1

I = 1 (second operand is a constant)

opcode = 0001 (look up)


rd = 0110 (destination *operand: r6*)

rn = 0010 (1st *operand: r2*)

operand 2



rotate = 0000

imm = 0x0A




Data Processing Example

❖ ARM Instruction: EORGTS r6, r2, #10




11 = operand 2 is an immediate value
8 7

Hex representation: 0xC232600A




Branch Instructions

- ❖ What fields do we need for Branch Instructions?
 - ❖ Opcode
 - ❖ Label
 - ❖ Condition




Branch Instructions



- ❖ Opcode
 - ❖ 101 for Branch
 - ❖ Link bit is set if BL
- ❖ Condition – same as before (EQ, LT, GT, etc.)

Branch Instructions



❖ Label

- ❖ Uses offset, i.e., how far to branch. $PC = PC + \text{offset}$.
- ❖ As opposed to absolute address of the instruction.
- ❖ 24 bits allows us to branch +/- 8 Mbytes.
- ❖ Instructions 32 bits = 4 bytes, so add implicit 00 at end.
Now can branch +/- 32 Mbytes.
- ❖ Equivalent to +/- 8 Minstructions.
- ❖ Start counting 2 instructions later (due to pipelining).

Branches: PC-Relative Addressing

- ❖ Solution to branches in a 32-bit instruction:
PC-Relative Addressing
- ❖ Let the 24-bit `offset` field be a signed two's complement integer to be *added* to the PC if we take the branch.
- ❖ Now we can branch $\pm 2^{23}$ bytes from the PC, which should be enough to cover almost any loop.
- ❖ Any ideas to further optimize this?

Branches: PC-Relative Addressing

- ❖ Note: Instructions are words, so they're word aligned (byte address is always a multiple of 4, which means it ends with 00 in binary).
 - ❖ So the number of bytes to add to the PC will always be a multiple of 4.
 - ❖ So specify the `offset` in words.
- ❖ Now, we can branch $\pm 2^{23}$ words from the PC (or $\pm 2^{25}$ bytes), so we can handle loops 4 times as large.

Branches: PC-Relative Addressing

❖ Branch Calculation:

- ❖ If we don't take the branch:

$$PC = PC + 4$$

- ❖ If we do take the branch:

$$PC = (PC + 8) + (\text{offset} * 4)$$

Why two? Pipelining starts next two following instructions before current one is finished.

Further explanation:

https://docs.google.com/document/d/14h_Njrb_xrZioHhU6ruQBmt_Xt17a_xlm0WrbMigEQeA/edit?usp=sharing

Branches: PC-Relative Addressing

❖ Branch Calculation:

❖ Observations

- ❖ `offset` field specifies the number of words to jump, which is simply the number of instructions to jump.
- ❖ `offset` field can be positive or negative.
- ❖ Due to hardware, add `immediate` to $(PC+8)$, not to PC


Branch Example

❖ ARM Instruction: here BEQ here

cond = 0000 (equal)

L = 0 (not a BL instruction)

Offset = -2 = 0xFFFFE Number of instructions to add to (or subtract from) the PC, starting at two instructions *following* the branch (PC is two instructions ahead due to pipelining)




Hex representation: 0x0AFFFFFEE

Branch Example

❖ ARM Instruction:

there ADD r0, r1, r2
 SUBEQ a1, v7, r2, LSL #3
 BIC v6, a1, a2, ROR v2
 EORGTs r6, r2, #1
here BL there



cond = 1110 (always)

L = 1 (BL instruction)

Offset = -6 110 = 0xFFFFFA

Hex representation: 0xEBFFFFFFFA


Large Offsets

- ❖ Chances are that offset is small enough to fit in the immediate field.
- ❖ How do we usually use branches?
 - ❖ Answer: `if-else`, `while`, `for`
 - ❖ Loops are generally small: typically up to 50 instructions
- ❖ Conclusion: may want to branch to anywhere in memory, but a branch often changes `PC` by a small amount
- ❖ What if too big?
- ❖ Load branch target into a register (`IP`) and `BX`

Questions on PC-addressing

- ❖ Does the value in branch field change if we move the code?
- ❖ What do we do if destination is $> 2^{23}$ instructions away from branch?
- ❖ Since its limited to $\pm 2^{23}$ instructions, doesn't this generate lots of extra ARM instructions?

Data Transfer Instructions



❖ Cond: condition field. Execute instruction when condition is met.

❖ I: immediate field. Determines type of offset.

❖ 0: if offset is an immediate


❖ 1: if offset is a register

❖ P: pre/post indexing bit.

❖ 0: post - add offset after transfer

❖ 1: pre - add offset before transfer

Data Transfer Instructions



❖ U: up/down bit.

- ❖ 0: down - subtract offset from base
- ❖ 1: up - add offset to base


❖ B: byte/word bit.

- ❖ 0: transfer word quantity
- ❖ 1: transfer byte quantity

❖ W: write-back bit.


- ❖ 0: no write-back
- ❖ 1: write address into base

Data Transfer Instructions




- ❖ L: load/store bit.
- ❖ 0: store into memory
- ❖ 1: load from memory
- ❖ Rn: base register
- ❖ Rd: source/destination register

Data Transfer Instructions




❖ Offset: source/destination register

❖ I bit = 0




❖ I bit = 1



Data Transfer Example

❖ ARM Instruction: LDR r8, [sp]



cond = 1110 (always – unconditional)

I = 0 (immediate: there is no offset, or offset = 0)

P = 1 (pre-increment: there is no offset)

U = 1 (add offset to base; there is no offset)

B = 0 (transfer word)

W = 0 (no writeback)

L = 1 (load)



rd = 8 = 1000 (destination *operand*)

rn = 13 = 1101 (base *register*)

Offset = 0 (there is no offset)

Data Transfer Example

- ❖ ARM Instruction: LDR r8, [sp]




Binary number per field representation:

hex representation: 0xE59D8000

Data Transfer Example

❖ ARM Instruction: STRB r10, [sp, #-4] !



cond = 1110 (always – unconditional)

I = 0 (offset is an immediate value)

P = 1 (pre-index – add immediate before transfer)

U = 0 (subtract offset from base)

B = 1 (transfer byte)

W = 1 (write address into base)

L = 0 (store)



rd = 10 = 1010 (destination *operand*)

rn = sp = r13 = 1101 (base *register*)

Offset = 0x004

Data Transfer Example

- ❖ ARM Instruction: LDR r8, [sp]




Binary number per field representation:

hex representation: 0xE56DA004

Data Transfer Example

❖ ARM Instruction: LDRB r2, [r1], -r3, LSR #4



cond = 1110 (always – unconditional)

I = 1 (offset is a register)

P = 0 (post-index – add immediate after transfer)

U = 0 (subtract offset from base)

B = 1 (transfer byte)

W = 0 (write address into base)


L = 1 (load)

rd = 2 = 0010 (destination *operand*)

rn = 1 = 0001 (base *register*)

Data Transfer Example

❖ ARM Instruction: LDRB r2, [r1], -r3, LSR #4




Offset:

shift:

shift amount = 4 = 00100



shift type = 01

rm = 3 = 0011



Data Transfer Example

- ❖ ARM Instruction: LDR r8, [sp]



Binary number per field representation:

hex representation: 0xE651223

Addressing Mode

https://www.youtube.com/watch?v=zgkxPdPkxa8&ab_channel=EmbeddedSystemsandDeepLearning

Pre-index

LDR r1, [r0, #4]

- $r1 \leftarrow \text{memory.word}[r0 + 4]$
- $r0$ remains unchanged

Post-index

LDR r1, [r0], #4

- $r1 \leftarrow \text{memory.word}[r0]$
- $r0 \leftarrow r0 + 4$

Pre-index with Update

LDR r1, [r0, #4]!

- $r1 \leftarrow \text{memory.word}[r0 + 4]$
- $r0 \leftarrow r0 + 4$

Addressing Mode



Summary of ARM addressing Modes

Name	Alternative Name	ARM Examples
Register to register	Register direct	MOV R0, R1
Absolute	Direct	LDR R0, MEM
Literal	Immediate	MOV R0, #15 ADD R1, R2, #12
Indexed, base	Register indirect	LDR R0, [R1]
Pre-indexed, base with displacement	Register indirect with offset	LDR R0, [R1, #4]
Pre-indexed, autoindexing	Register indirect pre-incrementing	LDR R0, [R1, #4]!
Post-indexing, autoindexed	Register indirect post-increment	LDR R0, [R1], #4
Double Reg indirect	Register indirect Register indexed	LDR R0, [R1, R2]
Double Reg indirect with scaling	Register indirect indexed with scaling	LDR R0, [R1, r2, LSL #2]
Program counter relative		LDR R0, [PC, #offset]

Instruction Format Summary

ARM Instruction Set Format

31	2827	1615	87	0	Instruction type
Cond	0 0	I	Opcode	S	Data processing / PSR Transfer
Cond	0 0 0 0	0 0	A	S	
Cond	0 0 0 0	1 0	U	A	Long Multiply (v3M / v4 only)
Cond	0 0 0 1	0 0	B	0 0	
Cond	0 0 0 1	0 0	B	W	Load/Store Byte/Word
Cond	1 0 0	P	U	S	
Cond	1 0 0	P	U	S	Halfword transfer : Immediate offset (v4 only)
Cond	0 0 0	P	U	0	
Cond	1 0 1	I	Offset		Branch
Cond	0 0 0 1	0 0 1 0	1 1 1 1	1 1 1 1	
Cond	1 1 0	P	U	N	Coprorocessor data transfer
Cond	1 1 1 0	Op1	CRn	CRd	
Cond	1 1 1 0	Op1	CRn	CRd	Coprorocessor register transfer
Cond	1 1 1 1	Op1	CRn	CRd	
Cond	1 1 1 1	SWI Number			Software interrupt

Conclusion

- ❖ Computer actually stores programs as a series of these 32-bit numbers.
- ❖ Each instruction has different number of fields that define it (opcode, registers, immediates, etc.)
- ❖ **ARM Machine Language Instruction:**
32 bits representing a single instruction