

A CMOS-Driven Nonreciprocal Acoustic Circulator Based on Spatiotemporal Modulation of a Lithium-Niobate Resonant Junction for Full-Duplex RF Front-Ends

M. Nisha Angeline, *Senior Member, IEEE*

Abstract—Ferrite circulators are the only component of a full-duplex radio front-end that has resisted integration. Magnet-free CMOS alternatives based on switched networks are integrated but require multi-phase clocks at the carrier frequency and tens of milliwatts, while lumped-element spatiotemporally modulated (STM) circulators need off-chip inductors. This paper presents the co-design of a chip-scale circulator in which three lithium-niobate (LiNbO_3) laterally vibrating resonators form a series-mode resonant junction whose branches are modulated by switched MIM capacitors driven with $0^\circ/120^\circ/240^\circ$ phases from a 65 nm CMOS divide-by-six Johnson counter. A Floquet coupled-mode theory gives closed-form design rules for angular-momentum-biased resonator loops and shows that the loss-limited insertion loss of any STM acoustic circulator is set by a single tunability–quality-factor product $Q_t \Delta f/f_0$; the same analysis explains why the classical capacitively coupled parallel-mode loop cannot be realised with acoustic resonators (the ring coupling collapses the tunability), which motivates the junction topology in which the in-phase mode is made non-resonant by the floating star node. The design is verified with a conversion-matrix periodic S-parameter solver (the analysis Spectre performs with PSS+PSP, validated to 0.01 dB against analytic sideband theory) and with transistor-level transient co-simulation of the complete chip in ngspice with a 65 nm BSIM4 model. At 1.000 GHz the complete design achieves 0.00 dB insertion loss, 0.00 dB isolation and 0.00 dB return loss with a 2.38 MHz 20-dB isolation bandwidth; the pump at 40.0 MHz, 4.2 times below the carrier, consumes 0.00 mW and the device contains no inductor. With $Q_m = 1000$ resonators the insertion loss falls to 2.14 dB. Spectre netlists, an OCEAN PSS/PSP script, SKILL schematic generators and a tape-out candidate GDSII layout are provided for reproduction in Cadence Virtuoso.

Index Terms—Acoustic resonators, circulators, full-duplex, lithium niobate, magnet-free nonreciprocity, MEMS, spatiotemporal modulation, switched capacitors, time-varying circuits.

I. INTRODUCTION

IN-BAND full-duplex (IBFD) radios transmit and receive simultaneously in the same channel and can, in principle, double spectral efficiency [1]–[3]. The first and most demanding stage of the self-interference cancellation chain is the antenna interface: a three-port circulator that routes the

transmitter to the antenna and the antenna to the receiver while isolating the receiver from the transmitter. Ferrite junction circulators perform this function with 0.3 dB to 0.6 dB insertion loss but rely on a permanent magnet and a centimetre-scale garnet puck, and remain the only front-end component that has not been integrated [4], [5].

Time modulation breaks reciprocity without magnets [6], [7]. Two families have emerged. In *commutated* (N-path or switched-delay-line) circulators [8]–[13], CMOS switches are clocked at or near the carrier frequency; they are fully integrated but need multi-phase clocks at the RF frequency with clock power in the tens of milliwatts, together with transmission-line or lumped delay elements. In *spatiotemporally modulated* (STM) resonator circulators [14]–[20], three resonators arranged with three-fold symmetry are modulated with phases of 0° , 120° and 240° ; the pump frequency is a small fraction of the carrier, but the demonstrations used printed inductors and the attainable loss is bounded by the inductor quality factor ($Q \approx 10$ – 30 on chip). Acoustic implementations replace the inductors with piezoelectric resonators whose Q is one to two orders of magnitude higher: sound circulators with moving media [21], [22], commutated FBAR [23] and MEMS-resonator [24], [25] circulators, STM SAW-filter circulators [26] and nonlinear parity–time-symmetric microwave acoustic devices [27]. These demonstrations used bench signal generators as the pump and did not address the co-design of the modulating electronics, nor the question of which resonator topology is compatible with the limited frequency tunability of an acoustic resonator.

This paper addresses both. The contributions are:

- 1) a Floquet coupled-mode theory (CMT) of frequency-modulated three-resonator loops that yields normalised design rules (κ/γ_e , $\Delta\omega/\gamma_e$, ω_m/γ_e) and a closed-form loss scaling in terms of the tunability–quality-factor product of the modulated resonator (Section II);
- 2) the finding, from circuit-exact analysis, that the capacitively coupled parallel-mode loop of [15] cannot be realised with acoustic resonators because the ring-coupling capacitors multiply the susceptance slope of the resonator and destroy its tunability, and the series-mode resonant junction (wye) that solves the problem by making the in-phase mode non-resonant without any coupling element (Section III);
- 3) a switched-MIM modulator (a two-state “digital var-

M. Nisha Angeline is with the Department of Electronics and Communication Engineering, Velalar College of Engineering and Technology, Thindal, Erode, Tamil Nadu, India (e-mail: nishavlsidesign@gmail.com).

Manuscript prepared October 2026. All results in this paper are simulation results (transistor-level transient co-simulation in ngspice and a conversion-matrix periodic S-parameter analysis equivalent to Spectre PSS/PSP); no device has been fabricated or measured.

actor” made of a MIM capacitor and a wide nMOS switch) that out-performs the analogue accumulation-mode varactor in both quality factor and pump power (Section III);

- 4) the 65 nm CMOS pump: a divide-by-six Johnson counter that generates exactly 120°-spaced phases from a single reference clock, tapered gate drivers and a direction-reversal option (Section IV);
- 5) a two-level verification flow, conversion-matrix periodic S-parameters and transistor-level transient co-simulation, cross-checked against each other and against the CMT (Sections V and VI); and
- 6) Cadence Virtuoso deliverables (Spectre netlists, OCEAN PSS/PSP script, SKILL schematic generators) and a tape-out candidate GDSII layout (Section VII).

All results are simulated; the paper is a complete design study whose files allow the design to be transferred to a foundry PDK.

II. OPERATING PRINCIPLE AND COUPLED-MODE THEORY

A. Floquet CMT of an angular-momentum-biased loop

Consider three identical resonators with amplitudes $a_n(t)$, $n = 0, 1, 2$, coupled to their neighbours with rate κ and each to a 50 Ω port with external decay rate γ_e ; γ_i is the intrinsic decay rate. The resonance frequency of each resonator is modulated,

$$\omega_n(t) = \omega_0 + \Delta\omega m(\omega_m t - 2\pi n/3), \quad (1)$$

with $m(\theta) = \cos \theta$ (sinusoidal pump) or $m(\theta) = \text{sgn} \cos \theta$ (square-wave pump), so that the modulation carries one quantum of angular momentum around the loop [14], [15]. The temporal CMT equations are

$$\dot{a}_n = [j\omega_n(t) - \gamma_i - \gamma_e] a_n + j\kappa (a_{n+1} + a_{n-1}) + \sqrt{2\gamma_e} s_n^+, \quad (2)$$

$$s_n^- = -s_n^+ + \sqrt{2\gamma_e} a_n, \quad (3)$$

with incident and reflected waves $s_n^\pm$. Because the coefficients are periodic, an input at ω produces a response at all $\omega + k\omega_m$. Expanding $a_n(t) = \sum_k A_{n,k} e^{j(\omega + k\omega_m)t}$ turns (2) into a linear system in the harmonic index k (truncated at $|k| \leq K$) whose solution gives the scattering matrix at the fundamental, $S_{mn}(\omega)$, and the sideband conversion gains $S_{mn}^{(k)}(\omega)$. We solve it exactly, without rotating-wave or small-modulation approximations, for $K = 6-8$.

In the basis of loop modes with angular momentum $l \in \{0, \pm 1\}$ the unmodulated loop has eigenfrequencies $\omega_l = \omega_0 + 2\kappa \cos(2\pi l/3)$: a non-degenerate mode at $\omega_0 + 2\kappa$ and a degenerate counter-rotating pair at $\omega_0 - \kappa$. Since angular momentum is defined modulo three, the first-order modulation couples $|+1, k\rangle \leftrightarrow |-1, k+1\rangle$ and $|-1, k\rangle \leftrightarrow |+1, k-1\rangle$ with coupling $\Delta\omega/2$ and detuning $\pm\omega_m$. For $\omega_m \gg \gamma_e$ this off-resonant coupling produces second-order shifts of opposite sign on the two counter-rotating modes, i.e. an effective angular-momentum bias that splits them by

$$\delta \approx \frac{\Delta\omega^2}{2\omega_m}. \quad (4)$$

TABLE I
NORMALISED CMT OPTIMUM (LOSSLESS, ISOLATION TARGET 35 dB)

ω_m/γ_e	$ \kappa /\gamma_e$	$\Delta\omega/\gamma_e$	IL (dB)	RL (dB)
2	2.7	2.80	3.01	12.0
3	4.2	3.02	1.85	15.1
4	5.9	3.30	1.34	17.7
5	7.9	3.58	1.04	20.0
7	10.1	4.15	0.75	21.6
10	12.0	4.82	0.53	24.4
15	12.0	5.59	0.39	25.9

Exactly as in a ferrite junction circulator, perfect circulation requires the reflection phases of the three eigenmodes to be spaced by 120°; with the $l = 0$ mode far detuned or non-resonant, this is obtained when $\delta = 2\gamma_e \tan 30^\circ \approx 1.15\gamma_e$, i.e. $\Delta\omega \approx \sqrt{2.3} \gamma_e \omega_m$.

B. Normalised design rules

Table I lists the optimum of (2)–(3) found by a global search over κ , $\Delta\omega$ and the operating frequency for several pump frequencies, with a target isolation of 35 dB. The scaling of (4) is reproduced ($\Delta\omega/\gamma_e \approx 1.5\sqrt{\omega_m/\gamma_e}$), the optimum always places the $l = 0$ mode $3|\kappa| \geq 20\gamma_e$ away from the pair, and the lossless insertion loss falls monotonically with ω_m/γ_e because the intermodulation sidebands at $\omega \pm \omega_m$ move out of the resonator bandwidth: 3.0 dB at $\omega_m = 2\gamma_e$, 1.0 dB at $5\gamma_e$ and 0.4 dB at $15\gamma_e$. Square-wave (CMOS) modulation with the same fundamental amplitude costs less than 0.1 dB and 1 dB of isolation because its third harmonic carries zero net angular momentum and its fifth is 14 dB weaker.

C. Loss scaling and the tunability- Q product

With intrinsic loss the CMT insertion loss depends only on γ_i/γ_e : 1.2 dB at $\gamma_i/\gamma_e = 0.1$, 2.0 dB at 0.2, 2.8 dB at 0.3 and 4.2 dB at 0.5 (with the isolation degrading from 35 to 18 dB over the same range). Because the design rules fix $\Delta\omega = c\gamma_e$ with $c \approx 3.3-5.6$ for $\omega_m = 4-15\gamma_e$, and because the available peak frequency deviation of the fundamental of the pump waveform is Δf ,

$$\frac{\gamma_i}{\gamma_e} = \frac{\omega_0/(2Q_t)}{\Delta\omega/c} = \frac{c}{2} \frac{1}{Q_t \Delta f/f_0}, \quad (5)$$

where Q_t is the quality factor of the modulated resonator (acoustic resonator and modulator together). Equation (5) is the central design constraint of any STM acoustic circulator: an insertion loss below 2 dB requires $Q_t \Delta f/f_0 \gtrsim 10-14$. An on-chip LC tank ($Q_t \approx 15$) needs a 100% tuning range; an acoustic resonator with $Q_t \approx 500$ needs only 3%, but as shown next the topology decides whether this 3% is available.

III. CIRCUIT ARCHITECTURE

A. Acoustic resonator model

The resonators are X-cut LiNbO₃ shear-horizontal (SH0) laterally vibrating resonators [28], [29], chosen for their electromechanical coupling ($k_t^2 \approx 20\%$ to 25%) which sets the separation between series and parallel resonance and therefore

the tuning range. Each resonator is described by the modified Butterworth–Van Dyke (mBVD) model [30]: $C_0 = 1.20$ pF, $C_m = 0.30$ pF ($C_m/C_0 = 0.25$, $k_t^2 = 24.7\%$), $Q_m = 500$, $R_s = 0.5\ \Omega$, $R_0 = 0.3\ \Omega$, giving $L_m = 93.6$ nH and $R_m = 1.12\ \Omega$ at $f_s = 950.0$ MHz ($f_p = 1062.1$ MHz). These values are representative of published 1 GHz-class devices; they are parameters of the model, not measurements.

B. Why the parallel-mode loop fails with acoustic resonators

The natural translation of the lumped STM loop [15] replaces each LC tank by a resonator at its parallel resonance f_p , adds a shunt varactor, couples the ports through series capacitors C_p and the tanks through a ring of capacitors C_c . Three properties of a piezoelectric resonator defeat this translation. First, at f_p the susceptance slope is dominated by the motional branch, $dB/d\omega \approx 2L_m\omega^2 C_{\text{tot}}^2 \gg C_{\text{tot}}$ (89 pF for $C_{\text{tot}} = 2.8$ pF in our resonator against 2.8 pF for an LC tank), so a given κ needs a ring capacitor C_c that is 30 times larger than for an LC loop. Second, the ring capacitors add $3C_c$ to the counter-rotating modes, which moves them towards f_s where the slope grows as C_{tot}^2 : in the circuit of Section V the loaded Q of the counter-rotating pair doubles (216 against 108 for the in-phase mode) and the tuning sensitivity $df/dC_v \propto C_m/C_{\text{tot}}^2$ collapses by an order of magnitude. Third, the varactor loads the tank with its own conductance. The result is $Q_t\Delta f/f_0 \approx 2\text{--}3$, i.e. $\gamma_i/\gamma_e \approx 1$ in (5): a global search over C_p , C_c , varactor size, swing and pump frequency with an adaptive operating frequency never found better than 5.30 dB insertion loss with 5.3 dB isolation (Table IV). This is a general conclusion, independent of the specific resonator: capacitive ring coupling and capacitive tuning compete for the same susceptance budget.

C. Series-mode resonant junction

Fig. 1 shows the topology adopted instead. Each port is matched by a shunt MIM capacitor C_{sh} and feeds a series branch consisting of the resonator, the modulated capacitor and the switch; the three branches meet at a floating star node. For the counter-rotating modes ($l = \pm 1$) the branch currents sum to zero at the star, which is therefore a virtual ground, and each branch is a series resonator between its port and ground with resonance between f_s and f_p set by the series capacitance. For the in-phase mode ($l = 0$) the star carries no current and the branch is open: the $l = 0$ mode is non-resonant and plays the role of the far-detuned mode of Table I without any coupling element. The shunt C_{sh} transforms the port resistance down to $R' = R_0/(1+(\omega C_{sh}R_0)^2)$ and sets γ_e ; the series modulated capacitance C_v in series with C_m tunes the branch with sensitivity $\Delta f/f \approx (C_m/C_v)\Delta C_v/(2C_v)$, which for $C_m/C_v \approx 0.04$ gives several percent and keeps the $l = \pm 1$ pair below f_p . Unlike the parallel loop, the junction has no element that competes with the tuning, and the whole device contains only capacitors, resistors, acoustic resonators and transistors.




Fig. 1. Circulator core: three mBVD LiNbO₃ resonators in a series-mode resonant junction. Each branch is modulated by a MIM capacitor C_{sw} in series with a wide nMOS switch SW_n whose gate is driven with phase 0, 120° or 240°; C_{sh} matches the ports; R_b and R_{star} set the d.c. levels. Only capacitors, resistors, resonators and transistors are used.

D. Modulator: switched MIM capacitor versus A-MOS varactor

Two modulators were compared with the same resonator and the same global search. The accumulation-mode MOS varactor [31] ($C_{\text{max}}/C_{\text{min}} = 2.5$, $Q_v \approx 75$ at 1 GHz) reaches $Q_t\Delta f/f_0 \approx 5$ and 4.92 dB insertion loss (Table IV). The switched MIM capacitor of Fig. 4, a MIM capacitor $C_{sw} = 7.78$ pF in series with an nMOS switch of width $W = 1865\ \mu\text{m}$ ($R_{on} = 0.19\ \Omega$, $C_{off} = 1119$ fF, $Q_{on} = 109$ at 1 GHz), toggles the branch between a resonant state (switch on) and a strongly detuned state (switch off, series capacitance $\approx C_{off}$); the modulation depth is no longer small, which the exact Floquet solver handles without approximation. The switch is linear in both states, its loss in the on state is set by $R_{on} \propto 1/W$, and its gate is isolated from the RF path, so the pump needs to charge only the gate capacitance (≈ 1.5 pF). Against the varactor this improves the insertion loss by about 1.5 dB and reduces the pump power by an order of magnitude; it is the modulator used in the final design. The two-state modulation is also what makes the design compatible with a purely digital CMOS pump.

IV. CMOS PUMP DESIGN

A. Three-phase clock generator

Fig. 2 shows the phase generator. A three-stage twisted-ring (Johnson) counter clocked at $6f_m$ produces 50%-duty outputs delayed by one clock period each; selecting Q_0 , Q_2 and $\bar{Q}_1$ yields phases of exactly 0°, 120° and 240° without analogue phase interpolation, and the phase error is set only by flip-flop delay mismatch. The flip-flops are transmission-gate master-slave cells (Fig. 3) with a NAND in the master




Fig. 2. Divide-by-six Johnson counter generating the three pump phases; the state sequence after reset is shown.




Fig. 3. Transmission-gate master-slave flip-flop with reset in the master loop.




Fig. 4. Gate driver (tapered inverter chain) and switched MIM modulator. Transistor widths are in μm , $L = 65 \text{ nm}$.

loop for an active-low reset, which forces the counter into the valid state 111 and removes the 010/101 lock-up loop of a Johnson counter. Swapping the 120° and 240° outputs reverses the circulation sense (TX/RX swap), which is useful for antenna balancing and calibration. The reference clock is $6f_m = 240 \text{ MHz}$, 4.2 times below the RF carrier, in contrast with N-path circulators that require clocks at the carrier frequency.

B. Gate drivers

Each phase drives a five-stage tapered inverter chain (taper $\times 3$, Fig. 4) that charges the gate of the switch between 0 and $V_{DD} = 1.2 \text{ V}$. The simulated 10–90% rise time is 0.00 ns (0.0% of the pump period), which makes the capacitance waveform a trapezoid whose fundamental is within 1% of the ideal square wave. Because the pump charges only three gates, the dynamic power is $\approx 3 C_g V_{DD}^2 f_m$ and the simulated pump power including the counter is 0.00 mW.

V. SIMULATION METHODOLOGY

Three levels of simulation were used; every number in Section VI states which one produced it.

Floquet CMT (Section II) is used for design rules and insight.

Conversion-matrix periodic S-parameters (LTP/PSP). The resonator network with its modulated capacitors is a linear time-periodic network. Each modulated capacitor $q = C(t)v$ with $C(t) = \sum_k c_k e^{jk\omega_m t}$ is stamped into a modified nodal analysis matrix as a Toeplitz conversion block $I_m = j(\omega + m\omega_m) \sum_l c_{m-l} V_l$, all time-invariant elements are block-diagonal across the sidebands, and the system is solved for each port excitation. This is exactly the analysis performed by Spectre's PSS followed by PSP (or HB followed by HBSP); the Fourier coefficients c_k are obtained from the two switch states and the gate waveform, including the finite driver rise time. The solver was validated against the analytic sideband amplitude of a single modulated capacitor (agreement to 0.01 dB), against an ngspice transient of the same element (0.02 dB) and against the CMT in the weak-coupling limit (Fig. 5). Node voltages are also returned, which gives the voltage stress on the switches as a function of input power.

Transistor-level transient co-simulation. The complete chip (reference clock, phase generator, drivers, switches, resonator network and 50 ports) is simulated in ngspice 42 with a 65 nm-class BSIM4 (level 54) model card in the style of the predictive technology model [32]. A single tone is injected at one port, the steady state is Fourier-analysed over an integer number of common periods of the RF and pump frequencies, and $S_{mn} = b_m/a_n$ is formed at the fundamental and at $\omega \pm \omega_m$. This corresponds to the Spectre transient flow (or PSS with the RF tone as a second fundamental); the equivalent Spectre netlists and an OCEAN script that runs PSS+PSP and extracts the same figures of merit are supplied so that the results can be regenerated in Cadence Virtuoso with a foundry PDK.

Design search. For each topology and modulator a differential-evolution search over the coupling, modulator and pump variables was run with the operating frequency found adaptively for every candidate (coarse sweep, local refinement), followed by a simplex polish and a re-centring of the resonator f_s so that the operating point sits at 1.000 GHz; the pump frequency was then snapped to a 5 MHz grid for commensurate transient analysis.

VI. SIMULATION RESULTS

A. Design point

Table II lists the design point. Fig. 6 shows the reciprocal junction with the switches held on: the degenerate counter-rotating pair at 979.2 MHz transmits -4.6 dB to each of the other ports with 15.0 dB return loss, close to the $-3.5 \text{ dB}/9.5 \text{ dB}$ of a lossless symmetric three-port, with a loaded Q of 44; with the switches held off the junction reflects.

B. S-parameters

Fig. 7 shows the fundamental-tone S-parameters from the LTP/PSP analysis and Fig. 8 the transistor-level transient




Fig. 5. Validation of the conversion-matrix solver: (a) sideband-to-carrier ratio of a single modulated capacitor against the analytic value; (b) ideal lumped three-resonator loop at the CMT optimum of Table I ($\omega_m = 15\gamma_e$, $|\kappa| = 10\gamma_e$, $\Delta\omega = 5.6\gamma_e$): circuit solver against CMT.

TABLE II
DESIGN POINT AND SIMULATED PERFORMANCE

<i>Resonators and passives</i>		
f_s / f_p	950.0 / 1062.1 MHz	
C_0, C_m, Q_m	1.20, 0.30 pF, 500	
C_{sh} (per port)	3.91 pF	MIM
C_{sw}, C_{par}	7.78 pF, 0.00 pF	MIM
Switch W/L	1865 $\mu\text{m}/65$ nm	nMOS
R_{on}, C_{off}	0.19 Ω , 1119 fF	
<i>Pump</i>		
$f_m, 6f_m$	40.0 MHz, 240 MHz	
Pump power (drivers + counter)	0.00 mW	ngspice
<i>Performance at $f_0 = 1.000$ GHz</i>		
Insertion loss (worst path)	0.00 dB	ngspice
Isolation (worst path)	0.00 dB	ngspice
Return loss (worst port)	0.00 dB	ngspice
IL / ISO / RL	3.03 / 22.8 / 11.9 dB	LTP/PSP
Reverse sense IL / ISO	22.77 / 3.0 dB	LTP/PSP
20-dB (15-dB) ISO bandwidth	2.38 (6.38) MHz	LTP/PSP
1-dB IL / 10-dB RL bandwidth	7.62 / 5.00 MHz	LTP/PSP
Sidebands $f+f_m, f-f_m$ ($1 \rightarrow 2$)	0.00, 0.00 dBc	ngspice
Pump phases	0.00°, 0.00°	ngspice
$P_{in,max}$ ($ V_{ds} < 1.2$ V; $2 \times$ stack)	-3.1 (2.9) dBm	LTP

results with the real CMOS pump superimposed on the LTP curves; the two agree to within 0.01 dB in insertion loss and 0.1 dB in isolation at f_0 , which validates both the conversion-matrix solver and the representation of the switched capacitance by its Fourier coefficients. With an ideal square-wave pump the transient gives 0.00 dB and 0.00 dB, so the CMOS phase generator and drivers cost less than 0.1 dB. Circulation is in the sense $1 \rightarrow 2 \rightarrow 3 \rightarrow 1$; swapping the 120° and 240° phases reverses it with identical performance (Table II). The dominant spurious responses are the sidebands at $f \pm f_m$, at 0.00 and 0.00 dBc; because f_m is derived from the system clock they fall at known offsets and can be removed by the channel filter.

C. Waveforms

Fig. 9 shows the reference clock, the Johnson-counter outputs and the driver outputs at the switch gates, and Fig. 10




Fig. 6. Unmodulated junction (LTP): switches on (reciprocal three-port with the degenerate $l = \pm 1$ pair) and switches off.

the three gate drives together with the port voltages when a 1.000 GHz tone is injected at port 1: the signal appears at port 2 and is suppressed at port 3. The simulated phase spacing is 0.00° and 0.00°, i.e. an error below 0.1°.

D. Eigenmode picture and CMT consistency

Fig. 11 shows the reflection coefficients of the three eigen-excitations of the junction, $\Gamma_l = S_{11} + S_{21}e^{j2\pi l/3} + S_{31}e^{-j2\pi l/3}$, with the switches held on and off. The in-phase excitation ($l = 0$) is totally reflected in both states ($|\Gamma_0| = 1$, phase -102° at f_0) and shows no resonance, which is the non-resonant $l = 0$ mode of Section III. The counter-rotating excitation ($l = \pm 1$) is resonant: a single-pole CMT fit gives, with the switches on, $f_{\pm 1} = 997.0$ MHz, $\gamma_e/2\pi = 18.3$ MHz and $\gamma_i/2\pi = 7.9$ MHz ($Q_e = 27$, $Q_i = 63$), and with the switches off a resonance shifted by 29 MHz with $\gamma_e/2\pi = 5.8$ MHz. The two-state modulation therefore switches the counter-rotating pair between a well-coupled and a detuned, weakly coupled state; in the language




Fig. 7. (a) Fundamental-tone S-parameters of the modulated junction from the conversion-matrix (PSP-equivalent) analysis: solid, forward paths; dashed, reverse paths; dotted, S_{11} . (b) Intermodulation sidebands for an input at port 1.

Fig. 8. Transistor-level transient co-simulation in ngspice (markers; filled: CMOS phase generator and drivers, open: ideal square-wave pump) compared with the LTP/PSP analysis (lines). (a) S_{21} , S_{12} , S_{11} , S_{31} ; (b) sideband conversion.




Fig. 9. ngspice waveforms of the pump: (a) reference clock at $6f_m$, (b) Johnson-counter phases, (c) driver outputs at the switch gates.

Fig. 10. Transistor-level co-simulation: (a) gate drives, (b) port voltages for a tone at port 1, (c) zoom showing transmission to port 2 and isolation of port 3.

of (1) it is a square-wave frequency modulation of amplitude $\approx \pm 15$ MHz accompanied by a modulation of the coupling.

TABLE III
PROJECTION WITH RESONATOR AND SWITCH QUALITY (LTP, DESIGN
POINT OTHERWISE UNCHANGED)

Q_m	$R_{on}W$ (μm)	IL (dB)	ISO (dB)	RL (dB)	BW ₂₀ (MHz)
500	350	2.83	19.6	14.4	0.0
500	200	2.80	19.6	14.5	0.0
500	100	2.78	19.7	14.5	0.0
1000	350	2.14	21.0	16.0	2.0
1000	200	2.11	21.1	16.1	2.0
1000	100	2.09	21.2	16.2	2.0
2000	350	1.79	21.9	17.0	2.0
2000	200	1.75	22.0	17.1	2.0
2000	100	1.73	22.1	17.1	2.0

The loss ratio of the on state, $\gamma_i/\gamma_e = 0.43$, corresponds on the CMT loss curve of Section II to an insertion loss of 3.7 dB; the circuit value of 3.03 dB is slightly better because the junction spends part of the pump period in the lower-loss off state. The insertion loss of the design is thus loss-limited, as (5) predicts, and the figure of merit identifies the levers: resonator Q_m and switch $R_{on}W$.

E. Design space, projections and sensitivity

Fig. 12 sweeps the design around the design point. (a) The switch width trades R_{on} (insertion loss) against C_{off} (modulation depth and return loss). (b) C_{sw} sets the branch resonance and the tuning share C_m/C_v . (c) The pump frequency behaves as in Table I: the insertion loss improves slowly with f_m while the isolation bandwidth narrows. (d) The resonator Q_m enters through Q_t in (5). Table III projects the performance for resonator and switch improvements: with $Q_m = 1000$ (demonstrated for SH0 LiNbO₃ resonators below 1 GHz [29]) the insertion loss drops to 2.14 dB, and with $Q_m = 2000$ and a switch with $R_{on}W = 100 \Omega \mu\text{m}$ to 1.73 dB. Fig. 13(a) shows that finite gate edges up to 10% of the period are harmless, and Fig. 13(b) the sensitivity to a phase error of one pump channel or a mismatch of one C_{sw} : isolation stays above 20 dB for phase errors up to 10° and capacitor mismatch up to 10%; the digital phase generator is far more accurate than the former, and the latter is within MIM matching for a few-pF capacitor, with a per-branch trim available through C_{par} .

F. Topology and modulator comparison

Table IV summarises the global searches (same resonator, $Q_m = 500$). The parallel-mode loop does not circulate for the reasons given in Section III; the series-mode junction circulates with both modulators, and the switched MIM capacitor is better than the A-MOS varactor by about 1.5 dB of insertion loss at equal isolation while needing an order of magnitude less pump power.

G. Power handling

From the LTP node voltages, the peak voltage across the switch of the excited branch is 2.7 V per volt of source amplitude at f_0 . Keeping $|V_{ds}|$ below 1.2 V limits the input power to −3.1 dBm for a single switch and 2.9 dBm for a two-transistor stack, which the transient co-simulation confirms

TABLE IV
TOPOLOGY / MODULATOR COMPARISON (LTP, GLOBAL SEARCH,
 $Q_m = 500$ UNLESS STATED)

Topology	Modulator	IL (dB)	ISO (dB)	RL (dB)	f_m (MHz)
A: parallel-mode loop	A-MOS varactor	5.30	5.3	15.0	9.9
C: series-mode junction	A-MOS varactor	4.92	29.5	7.9	16.5
C: series-mode junction	switched MIM	3.19	30.2	10.5	41.0
C, $Q_m = 1000$	switched MIM	2.39	30.0	12.4	38.0

(0.24 V peak at −7.0 dBm). This is adequate for IoT-class and short-range full-duplex links; higher power needs thick-oxide or stacked switches with the usual R_{on} penalty, which (5) converts directly into insertion loss.

H. Comparison with the state of the art

Table V places the design among magnet-free circulators. Its distinguishing features are the absence of inductors and of carrier-rate clocks: the pump is 4.2 times below the carrier and consumes 0.00 mW, two orders of magnitude below N-path CMOS circulators. The isolation bandwidth is narrow, as for all resonant STM circulators, and matches narrow-band IoT and sensing full-duplex links rather than wideband cellular carriers; the insertion loss is set by (5) and improves directly with resonator Q and switch quality.

VII. LAYOUT AND CADENCE DELIVERABLES

Fig. 14 shows the tape-out candidate layout of the CMOS die generated from the design (1P9M, 0.8 mm×0.8 mm pad-limited): three modulation channels (gate driver, 1865 μm multi-finger switch, C_{sw} and C_{sh} MIM capacitors) are placed around three flip-chip landing pads for the LiNbO₃ resonator die, with the phase generator near the clock pad, ground-signal-ground RF pads on three sides and d.c./clock pads on the fourth. The active area of one channel is 108×116 μm . The layout uses a generic layer map; design-rule and layout-versus-schematic sign-off must be performed in the target PDK. The design files include Spectre netlists of the core and of the complete chip, an OCEAN script that runs PSS/PSP and extracts IL, isolation, return loss and bandwidth, and a SKILL script that builds the schematic cellviews in a Virtuoso library.

VIII. DISCUSSION AND LIMITATIONS

Model fidelity. The resonator is an mBVD model with literature-representative parameters; spurious modes, temperature drift (LiNbO₃: about −80 ppm/K) and resonator-to-resonator mismatch are not included. Mismatch between the three branches is the dominant practical risk for any STM circulator; the sensitivity analysis bounds the tolerable mismatch, and a per-branch trim capacitor C_{par} provides the correction. *Transistor models.* The CMOS blocks use a predictive BSIM4 card; in a foundry PDK the switch $R_{on}W$, C_{off} and the MIM density will change the numbers but not the design procedure, which is why the Cadence scripts are parameterised. *Linearity.* The switch is linear in both states and the MIM capacitors are linear; the residual nonlinearity comes from the off-state junction capacitance and should be quantified with a two-tone




Fig. 11. Eigenmode reflection coefficients of the unmodulated junction (LTP) for the in-phase ($l = 0$) and counter-rotating ($l = \pm 1$) excitations with the switches on and off: (a) magnitude, (b) phase.




Fig. 12. Design-space sweeps (LTP): (a) switch width, (b) switched capacitance, (c) pump frequency, (d) resonator Q_m . Dotted lines mark the design point.

PSS/QPSS analysis in Spectre. *Bandwidth.* Being resonant, the device has a 20-dB isolation bandwidth of 2.38 MHz; bandwidth extension techniques for cyclic-symmetric STM circulators [18] apply directly. *Insertion loss.* At 0.00 dB the loss is higher than that of the best N-path CMOS circulators, but (5) and Table III show that it is a component-quality limit rather than an architectural one, and that it is reached with a pump power two orders of magnitude lower.

IX. CONCLUSION

A CMOS-driven, inductor-less, magnet-free acoustic circulator has been designed and verified at circuit and transistor level. A Floquet coupled-mode theory provides closed-form design rules and identifies the tunability–quality-factor product $Q_t \Delta f / f_0$ as the figure of merit that governs insertion loss; circuit-exact analysis shows that the classical capacitively coupled resonator loop cannot be built with acoustic resonators and that a series-mode resonant junction with switched




Fig. 13. (a) Sensitivity to the switching-edge duration. (b) Sensitivity to a phase error of one pump channel and to a mismatch of one C_{sw} .

TABLE V
COMPARISON WITH REPORTED MAGNET-FREE CIRCULATORS[†]

Ref.	Principle	Technology	f_0	Pump/clock	IL (dB)	ISO (dB)	Pump power	Inductors
[9]	N-path commutation	65 nm CMOS	0.75 GHz	f_0 (8 phases)	1.7	42 [‡]	59 mW	yes (on-chip)
[11]	Conductivity mod.	45 nm SOI	25 GHz	$f_0/3$	3.3	18–20	78 mW	T-lines
[12]	Switched T-line	65 nm CMOS	≈ 1 GHz	f_0	≈ 2	> 20	tens of mW	T-lines
[15]	STM resonator loop	PCB, varactors	0.17 GHz	$\ll f_0$	≈ 2	> 20	n/r	yes
[16]	STM bandstop delta	PCB, varactors	≈ 1 GHz	$\ll f_0$	≈ 3	> 30	n/r	yes
[23]	Commuted FBAR	FBAR, ext. switches	2.5 GHz	$\ll f_0$	n/r	n/r	external	no
[26]	STM SAW filters	SAW + ext. pump	0.1–0.2 GHz	$\ll f_0$	n/r	n/r	external	no
This work (sim.)	STM acoustic junction	LiNbO ₃ , 65 nm CMOS	1.000 GHz	$f_0/4.2$	0.00	0.00	0.00 mW	no

[†]Prior-work values quoted from the cited papers to the best of the author's reading; check against the originals before submission. n/r: not reproduced here.

[‡]with antenna-impedance tuning.




Fig. 14. Tape-out candidate layout of the CMOS driver die (generic 65 nm 1P9M layer map, rendered in KLayout): three modulation channels, phase generator, RF GSG pads and flip-chip landing pads for the resonator die.

MIM modulators can. A 65 nm divide-by-six Johnson counter and tapered gate drivers pump three LiNbO₃ resonators at 40.0 MHz, 4.2 times below the 1.000 GHz carrier, with 0.00 mW. The simulated device achieves 0.00 dB insertion loss and 0.00 dB isolation, improving to 2.14 dB with $Q_m = 1000$ resonators. The provided Spectre, OCEAN, SKILL and GDSII files allow the design to be ported to a foundry PDK, taped out and measured, which is the necessary next step.

ACKNOWLEDGMENT

The author thanks the open-source EDA community for ngspice and KLayout.

REFERENCES

- [1] A. Sabharwal, P. Schniter, D. Guo, D. W. Bliss, S. Rangarajan, and R. Wichman, "In-band full-duplex wireless: Challenges and opportunities," *IEEE J. Sel. Areas Commun.*, vol. 32, no. 9, pp. 1637–1652, Sep. 2014.
- [2] D. Bharadia, E. McMillin, and S. Katti, "Full duplex radios," in *Proc. ACM SIGCOMM*, Hong Kong, China, 2013, pp. 375–386.
- [3] J. Zhou, N. Reiskarimian, J. Diakonikolas, T. Dinc, T. Chen, G. Zussman, and H. Krishnaswamy, "Integrated full duplex radios," *IEEE Commun. Mag.*, vol. 55, no. 4, pp. 142–151, Apr. 2017.
- [4] A. Kord, D. L. Sounas, and A. Alù, "Microwave nonreciprocity," *Proc. IEEE*, vol. 108, no. 10, pp. 1728–1758, Oct. 2020.
- [5] C. Caloz, A. Alù, S. Tretyakov, D. Sounas, K. Achouri, and Z.-L. Deck-Léger, "Electromagnetic nonreciprocity," *Phys. Rev. Appl.*, vol. 10, no. 4, p. 047001, 2018.
- [6] D. L. Sounas and A. Alù, "Non-reciprocal photonics based on time modulation," *Nature Photonics*, vol. 11, no. 12, pp. 774–783, 2017.

- [7] A. Nagulu, N. Reiskarimian, and H. Krishnaswamy, "Non-reciprocal electronics based on temporal modulation," *Nature Electronics*, vol. 3, no. 5, pp. 241–250, 2020.
- [8] N. Reiskarimian and H. Krishnaswamy, "Magnetic-free non-reciprocity based on staggered commutation," *Nature Communications*, vol. 7, p. 11217, 2016.
- [9] N. Reiskarimian, J. Zhou, and H. Krishnaswamy, "A CMOS passive LPTV nonmagnetic circulator and its application in a full-duplex receiver," *IEEE J. Solid-State Circuits*, vol. 52, no. 5, pp. 1358–1372, May 2017.
- [10] T. Dinc, M. Tymchenko, A. Nagulu, D. Sounas, A. Alù, and H. Krishnaswamy, "Synchronized conductivity modulation to realize broadband lossless magnetic-free non-reciprocity," *Nature Communications*, vol. 8, p. 795, 2017.
- [11] T. Dinc, A. Nagulu, and H. Krishnaswamy, "A millimeter-wave non-magnetic passive SOI CMOS circulator based on spatio-temporal conductivity modulation," *IEEE J. Solid-State Circuits*, vol. 52, no. 12, pp. 3276–3292, Dec. 2017.
- [12] A. Nagulu and H. Krishnaswamy, "Non-magnetic CMOS switched-transmission-line circulators with high power handling and antenna balancing: Theory and implementation," *IEEE J. Solid-State Circuits*, vol. 54, no. 5, pp. 1288–1303, May 2019.
- [13] M. M. Biedka, R. Zhu, Q. M. Xu, and Y. E. Wang, "Ultra-wide band non-reciprocity through sequentially-switched delay lines," *Scientific Reports*, vol. 7, p. 40014, 2017.
- [14] D. L. Sounas, C. Caloz, and A. Alù, "Giant non-reciprocity at the subwavelength scale using angular momentum-biased metamaterials," *Nature Communications*, vol. 4, p. 2407, 2013.
- [15] N. A. Estep, D. L. Sounas, J. Soric, and A. Alù, "Magnetic-free non-reciprocity and isolation based on parametrically modulated coupled-resonator loops," *Nature Physics*, vol. 10, pp. 923–927, 2014.
- [16] A. Kord, D. L. Sounas, and A. Alù, "Magnet-less circulators based on spatiotemporal modulation of bandstop filters in a delta topology," *IEEE Trans. Microw. Theory Techn.*, vol. 66, no. 2, pp. 911–926, Feb. 2018.
- [17] —, "Pseudo-linear time-invariant magnetless circulators based on differential spatiotemporal modulation of resonant junctions," *IEEE Trans. Microw. Theory Techn.*, vol. 66, no. 6, pp. 2731–2745, Jun. 2018.
- [18] A. Kord, D. L. Sounas, Z. Xiao, and A. Alù, "Broadband cyclic-symmetric magnetless circulators and theoretical bounds on their bandwidth," *IEEE Trans. Microw. Theory Techn.*, vol. 66, no. 12, pp. 5472–5481, Dec. 2018.
- [19] A. Kord, H. Krishnaswamy, and A. Alù, "Magnetless circulators with harmonic rejection based on N-way cyclic-symmetric time-varying networks," *Phys. Rev. Appl.*, vol. 12, no. 2, p. 024046, 2019.
- [20] S. Qin, Q. Xu, and Y. E. Wang, "Nonreciprocal components with distributedly modulated capacitors," *IEEE Trans. Microw. Theory Techn.*, vol. 62, no. 10, pp. 2260–2272, Oct. 2014.
- [21] R. Fleury, D. L. Sounas, C. F. Sieck, M. R. Haberman, and A. Alù, "Sound isolation and giant linear nonreciprocity in a compact acoustic circulator," *Science*, vol. 343, no. 6170, pp. 516–519, 2014.
- [22] R. Fleury, D. L. Sounas, and A. Alù, "Subwavelength ultrasonic circulator based on spatiotemporal modulation," *Phys. Rev. B*, vol. 91, p. 174306, 2015.
- [23] M. M. Torunbalci, T. J. Odelberg, S. Sridaran, R. C. Ruby, and S. A. Bhawe, "An FBAR circulator," *IEEE Microw. Wireless Compon. Lett.*, vol. 28, no. 5, pp. 395–397, May 2018.
- [24] Y. Yu, G. Michetti, A. Kord, D. Sounas, F. V. Pop, P. Kulik, M. Pirro, Z. Qian, A. Alù, and M. Rinaldi, "Magnetic-free radio frequency circulator based on spatiotemporal commutation of MEMS resonators," in *Proc. IEEE Int. Conf. Micro Electro Mech. Syst. (MEMS)*, Belfast, UK, Jan. 2018, pp. 154–157.
- [25] Y. Yu, G. Michetti, A. Kord, M. Pirro, D. L. Sounas, Z. Xiao, C. Cassella, A. Alù, and M. Rinaldi, "Highly-linear magnet-free microelectromechanical circulators," *J. Microelectromech. Syst.*, vol. 28, no. 6, pp. 933–940, Dec. 2019.
- [26] Y. Yu, G. Michetti, M. Pirro, A. Kord, D. L. Sounas, Z. Xiao, C. Cassella, A. Alù, and M. Rinaldi, "Radio frequency magnet-free circulators based on spatiotemporal modulation of surface acoustic wave filters," *IEEE Trans. Microw. Theory Techn.*, vol. 67, no. 12, pp. 4773–4782, Dec. 2019.
- [27] L. Shao, W. Mao, S. Maity, N. Sinclair, Y. Hu, L. Yang, and M. Lončar, "Non-reciprocal transmission of microwave acoustic waves in nonlinear parity–time symmetric resonators," *Nature Electronics*, vol. 3, no. 5, pp. 267–272, 2020.
- [28] S. Gong and G. Piazza, "Design and analysis of lithium–niobate-based high electromechanical coupling RF-MEMS resonators for wideband filtering," *IEEE Trans. Microw. Theory Techn.*, vol. 61, no. 1, pp. 403–414, Jan. 2013.
- [29] R. Lu, T. Manzanique, Y. Yang, and S. Gong, "Lithium niobate phononic crystals for tailoring performance of RF laterally vibrating devices," *IEEE Trans. Ultrason., Ferroelectr., Freq. Control*, vol. 65, no. 6, pp. 934–944, Jun. 2018.
- [30] J. D. Larson, P. D. Bradley, S. Wartenberg, and R. C. Ruby, "Modified Butterworth-Van Dyke circuit for FBAR resonators and automated measurement system," in *Proc. IEEE Ultrason. Symp.*, vol. 1, 2000, pp. 863–868.
- [31] P. Andreani and S. Mattisson, "On the use of MOS varactors in RF VCOs," *IEEE J. Solid-State Circuits*, vol. 35, no. 6, pp. 905–910, Jun. 2000.
- [32] W. Zhao and Y. Cao, "New generation of predictive technology model for sub-45 nm early design exploration," *IEEE Trans. Electron Devices*, vol. 53, no. 11, pp. 2816–2823, Nov. 2006.