Reader writer problem

CASE one: TWO writer

Single semaphore WRMUTEX = 1

Writer one	Writer two
WAIT (wrmutex)	WAIT (wrmutex)
WRITE HERE	WRITE HERE
SIGNAL (wrmutex)	SIGNAL (wrmutex)

CASE 2:

ONE writer and ONE reader

TWO semaphore

WRMUTEX = 1 MUTEX=1 READERS=0

WRITER	READER
WAIT (wrmutex)	WAIT (MUTEX)
WRITE HERE	readers++
SIGNAL (wrmutex)	if (readers==1)
	WAIT (wrmutex)
	SIGNAL (mutex)
	READ HERE
	WAIT (MUTEX)
	Readers—
	If (readers==0)
	SIGNAL (wrmutex)
	SIGNAL (mutex)