

Battery Connection Direction Fault

Alarm Attribute

Alarm name	Alarm Severity	Alarm Category
Battery Connection Direction Fault	General Alarm	Inverter alarm

Possible Cause

Cause ID	Possible Cause
1	Battery Connection Direction Fault: The power cable connection of the battery is reversed.

Suggestion

- 1.Connect the power cables from the inverter to the battery master, but do not connect the other end of the cables to the inverter. Then, use a multimeter to measure the voltage at the cable terminals. If the measurement result is negative, the terminal assembly is incorrect, causing the inverter to detect a reverse battery connection.
- 2.If the measurement result is positive, update the inverter firmware to the latest version and restart the inverter.
- 3.If the issue remains, provide the completed troubleshooting results to SolaX technical support team through video or images.Including but not limited to:
 - 1) SN number of the inverter.
 - 2)The power cables connecting the inverter to the battery, with emphasis on the terminals connected to the inverter.