



United International University (UIU)
Dept. of Computer Science & Engineering (CSE)
Final-Term Exam Trimester: Spring 2026

Course Code: CSE 4325 Course Title: Microprocessors and Microcontrollers
Total Marks: 40 Duration: 2 hours

Any examinee found adopting unfair means would be expelled from the trimester/ program as per UIU disciplinary rules.

Question 1: Answer all the questions. (10 Marks)

[CO3]

Global Descriptor Table		Local Descriptor Table	
Index	Address	Index	Address
F80 H	Base: 1F308810, Limit: 23BD7H, Access: 54H, G = 1	F80 H	Base: 7A84718E, Limit: 0FAE1H, Access: F9H, G = 0
9B2 H	Base: 05E4DBB8, Limit: 3345AH, Access: 1FH, G = 0	9B2 H	Base: 2F72A2F3, Limit: 29FDBH, Access: 0DH, G = 1
D15 H	Base: 326125A3, Limit: CC32FH, Access: 8AH, G = 0	D15 H	Base: 10F3B41C, Limit: 53027H, Access: B8H, G = 0
073 H	Base: 00B2ACFE, Limit: F56A9H, Access: 27H, G = 1	073 H	Base: 99A461B6, Limit: C31ABH, Access: 62H, G = 0
585 H	Base: 411310BD, Limit: 50AEAH, Access: 53H, G = 0	585 H	Base: 56DC418, Limit: E6357H, Access: 54H, G = 1
B38 H	Base: 3CDF02F6, Limit: C5072H, Access: 49H, G = 0	B38 H	Base: 8D1C994D, Limit: 694CCH, Access: 14H, G = 1

Consider an imaginary microprocessor called Xion-32 that uses the **same Descriptor format** as the Intel 80386. The only difference is that the **G (Granularity) bit** in Xion-32 allows segment lengths to be specified in steps of **2 KB instead of 4 KB**. If the CS register contains **7C02H**, determine the following:

a.	Which descriptor table and entry will be selected?	2
b.	Ending address of the selected segment.	1
c.	Is access to the segment granted, or not?	1
d.	What is the descriptor privilege level?	1
e.	Segment type (CS/DS/SS/ES).	2
f.	Calculate the maximum virtual memory size of Xion-32 in GB (GigaByte). (Show necessary mathematical calculations.)	3

Question 2: Answer all the questions. (10 Marks)

[CO5]

a.	For the command analogWrite(x) , Sajib is using a duty cycle with a time period of 5s . He sends the high pulse for 4s and the low pulse for 1s . He is using a 7-bit DAC system . What is the value of x ?	3
b.	Which type of communication protocol (SPI or I2C) is better suited for communication involving a small number of devices? While using the I2C communication protocol, a master device, Master (index: 9H) , sends 3-byte data (char 'sPi') to a slave device (index: 5H) . Draw the corresponding sequence diagram. The ASCII codes for 'A' and 'a' are 65 and 97 respectively.	1 + 3
c.	A company wants to design a small wearable health-monitoring device that continuously measures body temperature and heart rate using sensors and sends an alert if abnormal readings are detected. The system can be built using either a Raspberry Pi or an Arduino . Which platform would be more suitable and why?	3

Question 3: Answer all the questions. (10 Marks)**[CO3]**

a.	Consider the following initial BIU fetch cycle pattern : [Fetch, Fetch, Fetch, Fetch, Fetch, Fetch, Fetch, Fetch, Fetch, Fetch] Assume during execution of one instruction, the BIU fetches three instructions into the queue. The 2nd instruction is a ' JUMP <5th instruction address> ', the 4th instruction is a memory read operation, 7th instruction is a ' MOV <address> ' instruction, 9th instruction is ' JUMP <10th instruction address> '. Draw the corresponding BIU and EU cycles.	3
b.	A program has a virtual address space of 32 KB . The system uses paging with a page size of 4 KB . Currently, 5 pages of the program are occupying primary memory. Assume that each page table entry is 8 bytes . 1) How many pages are needed for the program? 2) Calculate the total page table size for this program. 3) Calculate the percentage of pages stored in secondary storage .	1 + 1 + 2
c.	The 808x microprocessor is retrieving data from RAM . Draw the timing diagram for this operation showing the activities of Address-Data and Address-Status pins ($AD_0 - AD_{15}$, $A_{16}/S_3 - A_{19}/S_6$), $\overline{ALE}$, DEN , CLK , WR , $DT/\overline{R}$, $\overline{M}/IO$, $\overline{RD}$ in each clock cycle. [Observe the pins carefully]	3

Question 4: Answer all the questions. (10 Marks)**[CO4]****RAM Content**

Address	Content	Address	Content
0H		8H	1001 1010
1H		9H	0000 0101
2H		AH	0001 0000
3H		BH	1111 1010
4H		CH	0000 1010
5H		DH	0111 0111
6H		EH	0000 0011
7H		FH	1010 1010

Opcode Table

Mnemonic	Opcode
LDA	0011
ADD	0001
SUB	0010
OUT	1101
HLT	1011

Initially, the value of the **Accumulator Register** is 5H, and the **B Register** is 10H.

a.	Fill-up the RAM content table (0H - 7H) with the machine code of necessary instructions to show the output of the following expression (in Hexadecimal): $(-5 + 2 \times 9A - 3^2)_{16}$	3
b.	Determine the Accumulator and B register values after executing each instruction in [a].	3
c.	$CON = L_I \overline{E_I} L_A \overline{E_A} \overline{E_U} \overline{S_U} L_O L_B \overline{E_P} C_P \overline{L_M} \overline{CE}$ [Observe the pins carefully] Currently , the value of the Memory Address Register (MAR) is 9H, Accumulator Register is 5H, B Register is 10H, and Output Register is 7H. The controller sequencer accidentally generates the following three control words in three consecutive T-states (T4, T5 and T6) : i) 7EAH, ii) 4DBH, iii) 72BH Briefly describe the operation performed in each T-state . Also determine the contents of the Accumulator (AX) , B Register , and Output Register after each T-state using the RAM content table provided above . (Hint: The RAM outputs the contents of the memory location whose address is currently stored in the MAR).	4