

ISA Design

Instructionformats

	4 bits	4 bits	4 bits	4 bits
R-type	Opcode	rsd	rt	function

	4 bits	4 bits	8 bits
I-type	Opcode	rsd	immediate

	4 bits	12 bits
J-type	Opcode	address

	4 bits	4 bits	4 bits	4 bits
LS-type	Opcode	rsd	rt	immediate

Our registers

<u>Name</u>	<u>Number</u>	<u>Description</u>
#PC	0	Program counter
#out0 , #out1	1-2	Function results
#temp0,#temp1, #temp2	3-5	Temporaries
#in0, #in1, #in2	6-8	Arguments
#zero	9	Constant value zero
#S0 , #S1 , #S2 , #S3	10-13	Saved temporaries
#ra	14	Return address

#Sp	15	Stack Pointer
-----	----	---------------

Instructions

<u>Instruction</u>	<u>Description</u>	<u>Action</u>	<u>Type</u>	<u>Opcode bitfield</u>			
Seq	Skip next instruction if equal		R	0000	rsd	rt	0001
Jump		pc=pc_upper (target<<2)	J	0001	Target		
Slt	Skip next instruction if less than		R	0000	rsd	rt	0010
LW	Load word	rt=(int*)(offset+rsd)	LS	0100	rsd	rt	Immediate
SW	Store word	*(int*)(offset+rsd)=rt	LS	0101	rsd	rt	Immediate
add	Executes the add operation	rsd = rsd+ rt	R	0000	rsd	rt	0011
sub	Subtracts	rsd = rsd- rt	R	0000	rsd	rt	0100
and	And gate	rsd = rsd (and) rt	R	0000	rsd	rt	0101
or	Or gate	rsd = rsd (or) rt	R	0000	rsd	rt	0110
nor	Nor gate	rsd = rsd (nor) rt	R	0000	rsd	rt	0111
Jr	Jump to the adress in register		J	0010	Adress in register		
Mult	Performs multiplication on 2 registers	Rsd = rsd*rt	R	0000	rsd	rt	1000
Power	Performs Power operation	rsd=rsd^rt	R	0000	rsd	rt	1001

SNE	Skip if not equal		R	0000	rsd	rt	1010
Addi	Add immediate		I	0111	rsd	Immediate	
Jal	Jump and link		J	0011	Target		

Datapath

