

Can be built with one or both amplifiers.
This can use any pin compatible PAD UP chip; TDA7492, TDA7498, TDA7498L, TDA7498E
See right and datasheets for recommended filter values.
Second amplifier clock is sourced from the first amplifier. The board can also
accept a clock from another board by leaving both ROSC pins unconnected.



TDA7492 4 Ohm:
C309, C319, C342, C352 are NOT FITTED FOR 8 OHM LOAD
C307, C308, C317, C318, C340, C341, C350, C351 - Fit as 220nF
L301-L308 fit as 15uH PCV-0-153-10L

TDA7498(L) For 8 Ohm load:
C309, C319, C342, C352 are NOT FITTED
C307, C308, C317, C318, C340, C341, C350, C351 - Fit as 220nF
L301-L308 fit as 22uH PCV-0-223-10L

TDA7498E for 4 ohm load:
C307, C308, C309, C317, C318, C319,
C340, C341, C342 C350, C351, C352 – FIT ALL AS 330nF parts
L301–L308 fit as 22uH PCV-0-223-10L

VCC

R310 148

R312

R314

R313

R315

STBY

MUTE

47k

220k

3v3

C335

D301

C336

C337

2u2 10v X7R

2u2 10v X5R

2u2 10v X5R

100n 50V X7R

MMS52525B1G

GNDD

GNDD

GNDD

GNDD

Short connectors for Mute/Standby

P303 CONN_2x1

P305 CONN_2x1

1k

1k

GAIN1A/GAIN1B act as MODE select on TDA7498E
See datasheet for detailed information

3v3	P308
GAIN0A	CONN_2x1
3v3	P309
GAIN1A	CONN_2x1
3v3	P310
GAIN0B	CONN_2x1
3v3	P311
GAIN1B	CONN_2x1

Open Hardware DSP Platform – www.ohdsp.org

Title: AmpOne – Class D Amp Module

ev: 1.0

Size: A3	Date: 2017
KiCad E.D.A. eeschema 7.0.6	